



HAL
open science

Automatic Optimization of Chirp Setting Parameters In Medical Ultrasound Contrast Imaging

Amira Zaylaa, Sébastien Ménigot, Jamal Charara, Jean-Marc Girault

► **To cite this version:**

Amira Zaylaa, Sébastien Ménigot, Jamal Charara, Jean-Marc Girault. Automatic Optimization of Chirp Setting Parameters In Medical Ultrasound Contrast Imaging. *Journal of Life Sciences*, 2013, 7 (6), pp.592-598. 10.17265/1934-7391/2013.06.005 . hal-00881481

HAL Id: hal-00881481

<https://hal.science/hal-00881481>

Submitted on 21 Oct 2014

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Automatic Optimization of Chirp Setting Parameters In Medical Ultrasound Contrast Imaging

Amira Zaylaa^{1,2,3}, Sébastien Ménigot^{1,2,4}, Jamal Charara³ and Jean-Marc Girault^{1,2}

1. Department of Medical Biophysics and Imaging, Université François Rabelais de Tours UMR-S930 and ERL3106, B.P 3223, Tours, France

2. Inserm, U 930, Tours, France

3. Department of Physics and Electronics, Lebanese University, Hadath Campus, B.P. 5, Beirut, Lebanon

4. IUT Ville d'Avray, Université Paris Ouest Nanterre La Defense, B.P. 105, Avray, France

Received: February 8th, 2013 / Accepted: / Published: .

Online version : <http://www.davidpublishing.org/show.html?14253>

Abstract: Medical Ultrasound Contrast Imaging is a powerful modality undergoing successive developments in the last decade to date. Lately pulse inversion has been used in both ultrasound tissue harmonic and contrast imaging. However, there was a tradeoff between resolution and penetration. Chirp excitations partially solved the tradeoff but the chirp setting parameters were not optimized. The present work proposes for the first time combining chirp inversion with ultrasound contrast imaging, with the motivation to improve the contrast, by automatically optimizing the setting parameters of chirp excitation, it is thus an optimal command problem. Linear chirps, 5 μm diameter microbubbles and gradient ascent algorithm were simulated to optimize the chirp setting parameters. Simulations exhibited a gain of 5 dB by automatic optimization of chirp inversion relative to pulse inversion. The automatic optimization process was quite fast. Combining chirp inversion with ultrasound contrast imaging led to a maximum backscattered power permitting high contrast outcomes and optimum parameters.

Keywords: Medical Ultrasound Contrast Imaging, Chirp Inversion, Chirp Setting Parameters, Automatic Technique, Optimal Command.

1. Introduction

Ultrasound contrast imaging is an inevitable modality in medicine. It has significantly improved medical diagnosis by ameliorating the contrast after injecting a contrast agent into the patient's vascular system [1]. Several methods have been proposed in literature to improve the contrast-to-tissue ratio (CTR). These methods were classified into two major groups. The first group (i) was based on continuous encoding such as harmonic chirp imaging (HCI) [2,3]. HCI has improved resolution and increased the signal-to-noise ratio (SNR) of images. It was also capable of solving the trade-off between resolution and penetration [4, 5]. The second group (ii) was based on discrete encoding imaging methods such as pulse inversion [6], contrast pulse sequence [7] and pulse subtraction [8]. These methods were capable of efficiently extracting the harmonic frequency components out of the spectrum of backscattered signals even if any overlap existed in this

Jean-Marc Girault, Ph.D., H.D.R., research fields: Signal and Image processing and Medical Instrumentation. E-mail: jmgirault@univ-tours.fr.

spectrum.

Few years later, in order to benefit from the two aforementioned groups that contributed to the enhancement of the CTR, several scientists have proposed to merge some techniques together. For instance, chirp reversal has been proposed in harmonic contrast imaging [9] and chirp inversion in tissue harmonic imaging [10].

In this paper, we have proposed for the first time to merge chirp inversion with harmonic ultrasound contrast imaging. The reason behind this was to benefit from the advantage of not only each approach alone but also their fusion. However, our contribution was not limited to this combination. Indeed, as it has been shown recently the necessity of setting the chirp frequency parameters in an optimal way through a theoretical approach [11] and more recently, the possibility of automatically optimizing the transmitted pulse parameters, without using apriori information of the medium perfused with microbubbles [12], we

Corresponding authors: Amira Zaylaa, Ph.D. Student, research fields: Signal Processing and Ultrasound Imaging. E-mail: amira.zaylaa@inserm.fr.

Simulated medium consisted of micrometer-sized bubbles. For simplicity, and without loss of generality, in order to simulate the mean behavior of a microbubble cloud, we assumed that the response (non-linear vibration) of a cloud of N microbubbles was N times the response of a single microbubble possessing the mean properties.

Bubblesim software [15] was used in this work, in order to account for the microbubble's response when exposed to a megahertz-frequency ultrasound chirp. It is based on simulating the response by digitally solving modified Rayleigh-Plesset model (Eq. 2).

$$\ddot{R}(t)\dot{R}(t) + \frac{3}{2}\dot{R}(t)^2 + \frac{p_0+p_i(t)+p_L(t)}{\rho_L} - \frac{p_L(t)}{p_L c_L}R(t) = 0, \quad (2)$$

where R is the instantaneous radius of microbubbles, \dot{R} and \ddot{R} first and second derivative respectively, p_0 static pressure, p_i instantaneous acoustic pressure, p_L liquid pressure on the surface of the micro-bubbles, ρ_L liquid density and c_L velocity of sound in the liquid. Eq. (2) was based on modeling microbubbles by air-filled particles where the surface layer resembles that of an elastic solid.

SonoVue [16] contrast agent was simulated according to experiments in literature. The mean diameter of simulated SonoVue (Bracco Research SpA, Geneva, Switzerland) microbubbles was $5 \mu\text{m}$ [16] and the shell thickness d_{se} 1 nm [17]. The shell shear modulus G_s was 46 MPa [15] and the shear viscosity $1 \text{ Pa}\cdot\text{s}$.

2.4 Receiving Transducer, Chirp Inversion Decoding and Receiver

The first element of the reception stage (Fig. 1) was the transducer Rx, the bandwidth of Rx was 63% at -3 dB and central frequency 3.5 MHz . For illustration, the transducer's effect was taken into consideration in transmission and reception, such that, its bandwidth was 160% at -3 dB and central frequency 3 MHz . The same transducer received the echoes used for constructing the ultrasound image. The backscattered signals were decoded (Eq. 3) and a time delay was imposed on the second backscattered chirp (Fig. 1).

$$\begin{cases} r_1(t) = \text{echo}\{C_1(t - t_0)\}, \\ r_2(t - t_0) = \text{echo}\{C_2(t)\}. \end{cases} \quad (3)$$

Then the backscattered chirp $y(t)$ was computed (Eq. 4).

$$y(t) = r_1(t) + r_2(t - t_0), \quad (4)$$

The former phase is called feed forward phase.

3. Method

In this section, the automatic optimization of the chirp setting parameters that enabled to optimize the power in the ultrasound image was presented, thanks to the feedback line (dashed line in Fig. 1).

3.1 Automatic Optimization Technique

Automatic optimization was based on gradient ascent technique inspired from adaptive filtering. It is an iterative process that tracks the maximum of a cost function J [18] being the backscattered power:

$$J(\phi_k) = \int y(t, \phi_k)^2 dt, \quad (5)$$

where $\phi_k = (f_k, \beta_k)^T$ is the vector of the setting parameters to be optimized at the k^{th} iteration, T the transpose, f_k the starting frequency, β_k the modulation index and $y(t, \phi_k)$ the backscattered chirp of inversion decoding. The automatic algorithm was implemented to find the maximum of $J(\phi_k)$ at f^* and β^* according to the following equation:

$$\phi_k^* = \underset{\phi}{\text{argmax}}(J(\phi_k)), \quad (6)$$

The automatic algorithm iteratively generates the optimum value f^* and β^* from $J(\phi_k)$. The algorithm was summarized in the following points:

- Three initial values of (f, β) parameters thus far have been predefined. The algorithm launched in the forward stage for the first three iterations $k=1,2,3$;
- The output of chirp inversion processing (i.e. forward process) was fed into the optimization feedback after the third iteration i.e. $\{k \geq 4\}$;
- The cost function was measured as in Eq. (5);
- The iterative equation (Eq. (6)) was then implemented to compute steps proportional to the positive of the gradient of J at the current point. This step was responsible of setting the

maximum power that could have been attained. It is equivalent to:

$$\phi_{k+1} = \phi_k + \mu \cdot \left(\nabla_{\phi_k} J(\phi_k) \right), \quad (7)$$

where μ is the speed of convergence of f^* and β^* to the optimum value, it was initialized absolutely to 2. The choice of 2 was settled on after testing $0.1 \leq \mu \leq 3$;

- The gradient was approximated by the discrete gradient (Eq. (8)) as there is no analytical expression that describes the variation of the power as a function of the frequency parameters given below:

$$\nabla_{\phi_k} \left(J(\phi_k) \right) = \frac{J(\phi_k) - J(\phi_{k-1})}{\phi_k - \phi_{k-1}}, \quad (8)$$

- The power of $y(t, \phi_k)$ converged and (f^*, β^*) were automatically obtained.

3.2 Gain

The power gain G_{dB} was defined as the ratio of the automatically optimized chirp inversion system (i.e. the block diagram with the feedback stage Fig. 1) to the pulse inversion imaging [6] i.e. for $\beta = 0$ (as mentioned in subsection 2.1). In pulse inversion the frequency parameters were set to $f_{ref} = 2.25$ MHz and $\beta = 0$ MHz/s [19]. Therefore, the gain G_{dB} was obtained by the following equation:


$$G_{dB} = 10 \cdot \log_{10} \left(\frac{J(f^*, \beta^*)}{J(f_{ref}, 0)} \right). \quad (9)$$

4. Simulation Results and Discussion

Simulations were carried out on an ultrasound contrast agent composed of 5 μm -diameter bubbles. A linear chirp of driving pressure 100 kPa with three initial predefined central transmitted frequency 1.5, 3 and 3.5 MHz as proposed in [12] and initial second frequency parameter assigned the values 0.2, 0.4 and 0.6 MHz/s were tested using the automatic algorithm.

Fig. 2 represented the power image of the backscattered chirp $y(t)$, coded in colors, as a function of f and β . The chirp parameters f and β were ranging between 0.5 and 6.5 MHz and -2 and 2 MHz/s, respectively. The power was computed empirically i.e. point-by-point by (Eq. (5)) in logarithmic unit. The

power values were associated with colormap jet such that



high power were associated a

Fig. 2 The backscattered power (coded in colors) of the linear chirp $y(t)$ of driving pressure 100 kPa as a function of f and β with the automatic optimization trace.

dark red color and those exhibiting lowest power outcomes were associated dark blue color. This power was considered as our cost function.


From Fig. 2, it was obvious that the maximum of the cost function was obtained for β different from zero and for f different from f_{ref} . This empirically demonstrated the necessity of using chirp excitations and thus to seeking the optimal value of the two setting parameters β and f that maximizes the cost function. Nevertheless, instead of empirically testing all the (f, β) couples, we desired to achieve this optimally and automatically using a gradient ascent method.

Since the image seemed to be symmetric with respect to the line $\beta = 0$, it was sufficient to merely study the cost function for $\beta > 0$. So, we have superimposed on Fig. 2 the trajectory of the automatic technique that led to the optimum values. The bold black line elaborated the novel automatic optimization path and the circles indicated the number of iterations that was 7, after which the algorithm converged to the optimum setting parameters. Note that f_{ref} denotes the frequency value of the reference method, which is pulse inversion as mentioned in section 1.

Fig. 3 represented the variation of the power of the backscattered chirp $y(t)$ as a function of the number of

Automatic Optimization of Chirp Setting Parameters In Medical Ultrasound Contrast Imaging

iterations for chirps of driving pressure 100 kPa. In the first iteration, the power of chirp was -32.1 logarithmic power units, then as the number of iterations increased the power



increased gradually, then decreased at the

Fig. 3 Automatic optimization of the backscattered power of chirp $y(t)$ with initial driving pressure 100 kPa.

fourth iteration. Afterwards it increased until it reached its maximum of -30.8 logarithmic power units at the seventh iteration and attained a plateau until the fiftieth iteration. This variation in the power values proves the sensitivity of the cost function J to the choice of (f, β) couples. Note that the power obtained by pulse inversion was illustrated by the horizontal dashed line (Fig. 3) and the power difference was approximately 5 dB.


Fig. 4 manifested the automatic optimization of f as a function of the number of iterations. The optimum value of the first setting parameter was attained at the point of convergence of the power i.e. at the seventh iteration. The algorithm converged to 3.1 MHz. This implied that the optimal transmitted frequency was 3.1 MHz and was different from the reference frequency $f_{ref} = 2.25$ MHz in pulse inversion. The optimal frequency was 0.1 MHz above the central frequency of the transducer and 0.85 MHz above the reference frequency 2.25 MHz in pulse inversion, [12], regardless of the initial driving pressure level A_0 .

Fig. 5 exhibited the variation of the second

Setting Parameters		Gain (dB)
f^* (MHz)	β^* (MHz/s)	5
3.1	0.1	-

frequency chirp setting parameter β as a function of the number of iterations. The optimum value was 0.1

Table. 1 Automatic optimization setting parameters and



gain.

Fig. 4 Automatic optimization of the first chirp parameter f for initial driving pressure 100 kPa.




Fig. 5 Automatic optimization of the second chirp setting parameter β for initial driving pressure 100 kPa.

MHz/s, selected after the seventh iteration where the power converged to its maximum value.

Table 1 represented the optimal setting parameters in automatic chirp inversion in addition to the gain (Eq.(9)). The novel automatic technique of chirp inversion achieved a gain of 5 dB as compared to the existing pulse inversion technique.

To sum up, chirp's frequency setting parameters, transmitted frequency f and frequency modulation index β , were optimized and thought to improve the backscattered power. Results showed that the proposed

optimization method does not require apriori knowledge of the microbubble, since it requires merely the cost-function. Simulations revealed that optimization feedback in chirp inversion was crucial. A 5 dB gain was achieved by the automatic feedback as compared to pulse inversion where ($\beta = 0$). The speed of convergence of the algorithm was appreciated such that it was attained in 7 iterations knowing that there were 3 measurements required per iteration.

If the cost function was neither convex nor concave, the initial conditions of the frequency parameters should be carefully chosen. This could be fulfilled by testing various points to meet the demand. Otherwise, additional optimization technique capable of selecting the proper initial conditions should be considered.

The major practical advantage of the proposed technique is that, neither the technician nor clinician is required to tune his transducer to any frequency value. Indeed, the technique will automatically adapt itself and select the optimum setting parameters that maximize the backscattered power from the patient. The enhancement of the resolution and SNR guaranteed by the use of chirp excitations was associated with iterative power increase; this might improve the CTR of contrast ultrasound images during the whole examination even if different kinds of variations occurred.

5. Conclusion

Chirp Inversion in ultrasound contrast imaging accompanied by automatic optimization technique enhances the backscattered power. Since the technique is not limited to linear chirps, other chirp types could be investigated. However, experimental verification of the simulation is needed.

Acknowledgements

The authors are grateful to the National Council for Scientific Research in Lebanon, Lebanese University and Imaging and Brain Laboratory INSERM U930, Université François Rabelais de Tours in France for supporting this work.

References

- [1] P. J. Frinking, A. Bouakaz, J. Kirkhorn, F. J. Ten Cate and N. de Jong, Ultrasound contrast imaging: current and new potential methods. *Ultrasound in Medicine and Biology*. 26 (2000), 965-975.
- [2] J. M. G. Borsboom, C. T. Chin and N. de Jong, Nonlinear coded excitation method for ultrasound contrast imaging, *Ultrasound in Medicine and Biology*. 29 (2003) 277-287.
- [3] J. M. G. Borsboom, C. T. Chin, A. Bouakaz, M. Versluis and N. de Jong, Harmonic chirp imaging method for ultrasound contrast agent. *IEEE Transaction on Ultrasonic, Ferroelectric and Frequency Control*. 52 (2005) 241-249.
- [4] T. Misaridis and J. A. Jensen, Use of modulated excitation signals in medical ultrasound. Part I: Basic concepts and expected benefits, *IEEE Transaction on Ultrasonic, Ferroelectric and Frequency Control*. 52 (2005) 177-191.
- [5] R. Y. Chiao and X. Hao, Coded excitation for diagnostic ultrasound: a system developer's perspective, *IEEE Transaction on Ultrasonic, Ferroelectric and Frequency Control*. 52 (2005) 160-170.
- [6] D. H. Simpson, C. T. Chin and P. N. Burns, Pulse inversion Doppler: a new method for detecting nonlinear echoes from microbubble contrast agents, *IEEE Transaction on Ultrasonic, Ferroelectric and Frequency Control*. 46 (1999) 372-382.
- [7] A. G. Brock-fisher, D. M. Poland and G. P. Rafter, Means for increasing sensitivity in non-linear ultrasound imaging systems, US Patent 5 577 505, (1996).
- [8] J. M. G. Brosboom, A. Bouakaz and N. de Jong, Pulse Subtraction time delay imaging method for ultrasound contrast agent detection, *IEEE Transaction on Ultrasonic, Ferroelectric and Frequency Control*. 56 (2009) 1151-1158.
- [9] A. Bouakaz, chirp reversal ultrasound contrast imaging, EPO Patent EP1739455 (2007).
- [10] J. Song, J. H. Chang, T. K. Song and Y. Yoo, Coded tissue harmonic imaging with nonlinear chirp signals. *Ultrasonics*. 51 (2011) 516-521.
- [11] E. Barlow, A. J. Mulholland, A. Gachagan and A. Nordon, A theoretical investigation of chirp insonification of ultrasound contrast agents. *Ultrasonics*. 51 (2011) 725-733.
- [12] S. Menigot, J.-M. Girault, I. Voicu and A. Novell, Optimization of contrast to tissue ratio by frequency adaptation in pulse inversion imaging. *IEEE Transactions on Ultrasonics, Ferroelectrics and Frequency Control*. 59 (2012) 2431-2438.
- [13] J. E. Wilhjelm, Bandwidth expressions of Gaussian weighted chirp, *Electronics Letters*. 29 (1993) 2161-2162.
- [14] M. Pasovic, M. Danilouchkine, T. Faez, P. L. M. J. van Neer, C. Cachard, A. F. W. van der Steen, O. Basset and N. de Jong, Second harmonic inversion for ultrasound contrast harmonic imaging, *Physics in Medicine and Biology*. 56 (2011) 3163-3180.
- [15] L. Hoff, Acoustic Characterization of Contrast agents for Medical Ultrasound Imaging, Kluwer Academic, Boston USA, 2001, pp. 158-160.
- [16] C. Greis, Technology Overview: SonoVue (Bracco, Milan), *European Radiology*. 14 (2004) 11-15.
- [17] K. Chetty, C. A. Sennoga, J. V. Hainal, R. J. Eckersley and E. Stride, P1F-4 High speed Optical observations and Simulation Results of Lipid Based Microbubbles at Low Insonation Pressures, *Proceeding IEEE. Ultrasonics Symposium*, (2006) 1354-1357.
- [18] R. Fletcher. Conjugate Direction Methods. Numerical Methods for Unconstrained Optimization, (edited) W.

Automatic Optimization of Chirp Setting Parameters In Medical Ultrasound Contrast Imaging

Murray, Academic Press, New York, (1972).

- [19] A. Zaylaa, S. Menigot, J. M. Girault and J. Charara. Empirical Optimization of frequency parameters in chirp inversion imaging, *Proceeding Acoustics2012*, Nantes, France, 273 (2012) 2889-2893.