

**This document must be cited according to its final version
which is published in a conference proceeding as:**

J. Qian¹²³, M. Nadri¹, P.D. Morosan², P. Dufour¹

**``Closed loop optimal experiment design for on-line nonlinear
system parameter identification'',
IFAC-IEEE European Control Conference (ECC), June 24-27,
Strasbourg, France, pp. 1813-1818, 2014.**

**All open archive documents of Pascal Dufour are available at:
<http://hal.archives-ouvertes.fr/DUFOUR-PASCAL-C-3926-2008>**

**The professional web page (Fr/En) of Pascal Dufour is:
<http://www.lagep.univ-lyon1.fr/signatures/dufour.pascal>**

**The web page of this research group is:
<http://hal.archives-ouvertes.fr/SNLEP>**

1

Université de Lyon, Lyon, F-69003, France; Université Lyon 1;
CNRS UMR 5007 LAGEP (Laboratoire d'Automatique et de GEnie des Procédés),
43 bd du 11 novembre, 69100 Villeurbanne, France
Tel +33 (0) 4 72 43 18 45 - Fax +33 (0) 4 72 43 16 99
<http://www.lagep.univ-lyon1.fr/> <http://www.univ-lyon1.fr> <http://www.cnrs.fr>

2

Acssysteme
Company Acssysteme, 4 rue René Dumont, 35000 Rennes, France.
Emails: {jun.qian, [petru-daniel.morosan](mailto:petru-daniel.morosan@acssysteme.com)}@acssysteme.com

3 This PhD thesis is between the LAGEP and the french company Acssysteme which is gratefully acknowledged for the funding. The french ministry of higher education and research, for the financial support of this CIFRE PhD thesis 2011/0876, is also acknowledged.

Closed loop optimal experiment design for on-line parameter estimation

Jun QIAN^{1,2,3}, Madiha NADRI¹, Petru-Daniel MOROȘAN² and Pascal DUFOUR^{1,3}

¹Université de Lyon, Lyon F-69003, Université Lyon 1, CNRS UMR 5007, Laboratory of Process Control and Chemical Engineering (LAGEP), Villeurbanne 69100, France

²Acystème company (IT and Control engineering), Rennes, France

³Sponsors: PhD thesis CIFRE 2011/0876 between the french company Acystème and the french ministry of higher education and research: we thank for their financial support.

13th European Control Conference
24-27 June, Strasbourg, France



Table of contents

- 1 Context and motivations
- 2 Outline of the proposed approach
- 3 Proposed closed-loop optimal identification approach
 - Closed loop control structure
 - The components
 - Model Predictive Control (MPC): general framework
 - Optimal control law design
- 4 Case study: Continuous stirred tank reactor
 - The nonlinear model of CSTR
 - Simulation results
- 5 Conclusion
- 6 Contacts and discussion

Context and motivations

- 👉 All **model parameters** need to be numerically known for simulation, control or optimization of dynamic processes.

Context and motivations

- 👉 All **model parameters** need to be numerically known for simulation, control or optimization of dynamic processes.
- 👉 The optimal experiment design (**OED**) is a classic technique for **parameter estimation**. (Goodwin and Payne [1979], Ljung [1999])

Context and motivations

- All **model parameters** need to be numerically known for simulation, control or optimization of dynamic processes.
- The optimal experiment design (**OED**) is a classic technique for **parameter estimation**. (Goodwin and Payne [1979], Ljung [1999])
- The OED usually separates parameter identification from the optimal input design (**offline identification**).

Context and motivations

- All **model parameters** need to be numerically known for simulation, control or optimization of dynamic processes.
- The optimal experiment design (**OED**) is a classic technique for **parameter estimation**. (Goodwin and Payne [1979], Ljung [1999])
- The OED usually separates parameter identification from the optimal input design (**offline identification**).
- Most applications of OED are reliable on **linear** or **approximated linearized** models.

Context and motivations

- All **model parameters** need to be numerically known for simulation, control or optimization of dynamic processes.
- The optimal experiment design (**OED**) is a classic technique for **parameter estimation**. (Goodwin and Payne [1979], Ljung [1999])
- The OED usually separates parameter identification from the optimal input design (**offline identification**).
- Most applications of OED are reliable on **linear** or **approximated linearized** models.
- Recently, the coupled online OED techniques and parameter estimation has been developed for **open loop stable systems without input/output process constraint**. (Jayasankar et al. [2010], Zhu and Huang [2011])

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.
- For **linear** and **nonlinear** dynamic model based systems.

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.
- For **linear** and **nonlinear** dynamic model based systems.
- Online optimal input design which **maximize the sensitivities** of the measurements with respect to the unknown constant model parameters.

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.
- For **linear** and **nonlinear** dynamic model based systems.
- Online optimal input design which **maximize the sensitivities** of the measurements with respect to the unknown constant model parameters.


Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.
- For **linear** and **nonlinear** dynamic model based systems.
- Online optimal input design which **maximize the sensitivities** of the measurements with respect to the unknown constant model parameters.
- Combine **observer design theory** and an on-line predictive controller (**MPC**).

Outline of the proposed approach

- Our proposed approach of closed-loop OED for online parameter identification has been initially proposed in [Flila et al. \[2008\]](#) for the **mono-variable case** (SISOSP).
- Synthesize the **online OED** and **online closed-loop parameter identification**.
- For **linear** and **nonlinear** dynamic model based systems.
- Online optimal input design which **maximize the sensitivities** of the measurements with respect to the unknown constant model parameters.
- Combine **observer design theory** and an on-line predictive controller (**MPC**).
- **Input and output constraints** may be specified to keep the process in a desired operating zone.

Closed loop control structure



The components

Process

Must have:

- a dynamic behaviour;
- at least one on-line output measure $y_p(t)$;
- at least one on-line exogenous manipulable input $u(t)$.

The components

Process

Must have:

- a dynamic behaviour;
- at least one on-line output measure $y_p(t)$;
- at least one on-line exogenous manipulable input $u(t)$.

The components

Process

Must have:

- a dynamic behaviour;
- at least one on-line output measure $y_p(t)$;
- at least one on-line exogenous manipulable input $u(t)$.

The components

Model (linear or nonlinear)

$$(M) \begin{cases} \dot{x}(t) &= f(x(t), \theta, u(t)) \\ y(t) &= h(x(t), \theta, u(t)) \end{cases} \quad (1)$$

where $x \in \mathbb{R}^n$ is the state vector, $y \in \mathbb{R}^p$ is the output vector, $u \in \mathcal{U} \subset \mathbb{R}^m$ is the input vector, $\theta \in \mathbb{R}^q$ is the unknown constant parameters vector. f and h are nonlinear functions of suitable dimensions.

Assumptions

- 1 In this study, the unknown model parameters are all constant.
- 2 In the system (1), f and h are C^∞ w.r.t. their arguments.

The components

Model (linear or nonlinear)

$$(M) \begin{cases} \dot{x}(t) &= f(x(t), \theta, u(t)) \\ y(t) &= h(x(t), \theta, u(t)) \end{cases} \quad (1)$$

where $x \in \mathbb{R}^n$ is the state vector, $y \in \mathbb{R}^p$ is the output vector, $u \in \mathcal{U} \subset \mathbb{R}^m$ is the input vector, $\theta \in \mathbb{R}^q$ is the unknown constant parameters vector. f and h are nonlinear functions of suitable dimensions.

Assumptions

- 1 In this study, the unknown model parameters are all constant.
- 2 In the system (1), f and h are C^∞ w.r.t. their arguments.

The components

Observer design for augmented system

System augmented with the unknown constant model parameters.

$$(M_a) \begin{cases} \dot{x}(t) &= f(x(t), \theta(t), u(t)) \\ \dot{\theta} &= 0 \\ y(t) &= h(x(t), \theta(t), u(t)) \end{cases} \quad (2)$$

The augmented state vector $x_a = [x \ \theta]^T$ and the vector function $f_a = [f \ 0]^T$

Observer definition

A global observer for system (13) can be given by

$$(O) \begin{cases} \dot{\hat{x}}_a(t) = f_a(\hat{x}_a(t), u(t)) + g_a(t, h(\hat{x}_a(t), u(t)) - y_p(t)) \\ \text{with: } g_a(t, 0) = 0, \end{cases} \quad (3)$$

such that

i) if $\hat{x}_a(0) = x_a(0)$, then $\hat{x}_a(t) = x_a(t)$, $\forall t \geq 0$;

ii) if $\forall x_a(0), \forall \hat{x}_a(0)$, then $\lim_{t \rightarrow +\infty} \|\hat{x}_a(t) - x_a(t)\| = 0$,

where g_a is a function of the output estimation error to be designed.

The components

Observer design for augmented system

System augmented with the unknown constant model parameters.

$$(M_a) \begin{cases} \dot{x}(t) &= f(x(t), \theta(t), u(t)) \\ \dot{\theta} &= 0 \\ y(t) &= h(x(t), \theta(t), u(t)) \end{cases} \quad (2)$$

The augmented state vector $x_a = [x \ \theta]^T$ and the vector function $f_a = [f \ 0]^T$

Observer definition

A global observer for system (13) can be given by

$$(O) \begin{cases} \dot{\hat{x}}_a(t) = f_a(\hat{x}_a(t), u(t)) + g_a(t, h(\hat{x}_a(t), u(t)) - y_p(t)) \\ \text{with: } g_a(t, 0) = 0, \end{cases} \quad (3)$$

such that

- i) if $\hat{x}_a(0) = x_a(0)$, then $\hat{x}_a(t) = x_a(t)$, $\forall t \geq 0$;
- ii) if $\forall x_a(0), \forall \hat{x}_a(0)$, then $\lim_{t \rightarrow +\infty} \|\hat{x}_a(t) - x_a(t)\| = 0$,

where g_a is a function of the output estimation error to be designed.

The components

Sensitivity model

Using the definition of the sensitivity function $(\cdot)_\theta = \frac{\partial(\cdot)}{\partial\theta}$ of a variable (\cdot) with respect to the parameters θ , and the dynamical model (M) , we give the sensitivity model as follows

$$(M_\theta) \begin{cases} \dot{x}_\theta(t) &= \frac{\partial f(x(t), \theta, u(t))}{\partial x} x_\theta + \frac{\partial f(x(t), \theta, u(t))}{\partial \theta} \\ y_\theta(t) &= x_\theta(t), \end{cases} \quad (4)$$

where $x_\theta \in R^{n \times q}$ and $y_\theta \in R^{n \times q}$ are the matrices of sensitivities of the states (the outputs) with respect to the parameters.

The relative-sensitivity function

$$\begin{cases} \bar{x}_\theta(i, j) &= \frac{\theta_j}{x_i} x_\theta(i, j); & i = 1, \dots, n; j = 1, \dots, q \\ \bar{y}_\theta(i, j) &= \frac{\theta_j}{y_i} y_\theta(i, j); & i = 1, \dots, p; j = 1, \dots, q. \end{cases} \quad (5)$$

The components

Sensitivity model

Using the definition of the sensitivity function $(\cdot)_\theta = \frac{\partial(\cdot)}{\partial\theta}$ of a variable (\cdot) with respect to the parameters θ , and the dynamical model (M) , we give the sensitivity model as follows

$$(M_\theta) \begin{cases} \dot{x}_\theta(t) &= \frac{\partial f(x(t), \theta, u(t))}{\partial x} x_\theta + \frac{\partial f(x(t), \theta, u(t))}{\partial \theta} \\ y_\theta(t) &= x_\theta(t), \end{cases} \quad (4)$$

where $x_\theta \in R^{n \times q}$ and $y_\theta \in R^{n \times q}$ are the matrices of sensitivities of the states (the outputs) with respect to the parameters.

The relative-sensitivity function

$$\begin{cases} \bar{x}_\theta(i, j) &= \frac{\theta_j}{x_i} x_\theta(i, j); & i = 1, \dots, n; j = 1, \dots, q \\ \bar{y}_\theta(i, j) &= \frac{\theta_j}{y_i} y_\theta(i, j); & i = 1, \dots, p; j = 1, \dots, q. \end{cases} \quad (5)$$

Model Predictive Control (MPC): general framework

👉 Advantages:

- many theoretical papers published
- +4000 applications in the world (Qin and Badgwell [2003])

Model Predictive Control (MPC): general framework

👉 Advantages:

- many theoretical papers published
- +4000 applications in the world (Qin and Badgwell [2003])

👉 Idea:

- use the model to predict the future process behavior
- optimize any specified criteria
- take account for constrains on measures/estimations
- closed loop control approach

Optimal control law design

- Time discretization: $t = k \times T_s$ (k = current time index)
- At each k , over the prediction horizon N_p : maximize the norm of the sensitivity $\frac{\partial y_p}{\partial \theta}$ to get "rich" data for parameter identification.

Sensitivity matrix

$$\bar{y}_{\theta|k} = \begin{bmatrix} \bar{y}_{\theta}(1, 1)|_{l|k} & \bar{y}_{\theta}(1, 2)|_{l|k} & \dots & \bar{y}_{\theta}(1, q)|_{l|k} \\ \bar{y}_{\theta}(2, 1)|_{l|k} & \ddots & & \vdots \\ \vdots & & \ddots & \vdots \\ \bar{y}_{\theta}(p, 1)|_{l|k} & \dots & \dots & \bar{y}_{\theta}(p, q)|_{l|k} \end{bmatrix}. \quad (6)$$

which gives at the current instant k the prediction at a future time $l \leq k$ ($l \in [k, k + N_p]$) of the normalized outputs sensitivity \bar{y}_{θ} .

Fisher Information Matrix (FIM)

$$M_{l|k} = \|\bar{y}_{\theta|k}\|^2 \quad (7)$$

Optimal control law design

- Time discretization: $t = k \times T_s$ (k = current time index)
- At each k , over the prediction horizon N_p : maximize the norm of the sensitivity $\frac{\partial y_p}{\partial \theta}$ to get "rich" data for parameter identification.

Sensitivity matrix

$$\bar{y}_{\theta|k} = \begin{bmatrix} \bar{y}_{\theta}(1, 1)|_{l|k} & \bar{y}_{\theta}(1, 2)|_{l|k} & \dots & \bar{y}_{\theta}(1, q)|_{l|k} \\ \bar{y}_{\theta}(2, 1)|_{l|k} & \ddots & & \vdots \\ \vdots & & \ddots & \vdots \\ \bar{y}_{\theta}(p, 1)|_{l|k} & \dots & \dots & \bar{y}_{\theta}(p, q)|_{l|k} \end{bmatrix}. \quad (6)$$

which gives at the current instant k the prediction at a future time $l \leq k$ ($l \in [k, k + N_p]$) of the normalized outputs sensitivity \bar{y}_{θ} .

Fisher Information Matrix (FIM)

$$M_{l|k} = \|\bar{y}_{\theta|k}\|^2 \quad (7)$$

Optimal control law design

- Time discretization: $t = k \times T_s$ (k = current time index)
- At each k , over the prediction horizon N_p : maximize the norm of the sensitivity $\frac{\partial y_p}{\partial \theta}$ to get "rich" data for parameter identification.

Sensitivity matrix

$$\bar{y}_{\theta|k} = \begin{bmatrix} \bar{y}_{\theta}(1, 1)|_{l|k} & \bar{y}_{\theta}(1, 2)|_{l|k} & \dots & \bar{y}_{\theta}(1, q)|_{l|k} \\ \bar{y}_{\theta}(2, 1)|_{l|k} & \ddots & & \vdots \\ \vdots & & \ddots & \vdots \\ \bar{y}_{\theta}(p, 1)|_{l|k} & \dots & \dots & \bar{y}_{\theta}(p, q)|_{l|k} \end{bmatrix}. \quad (6)$$

which gives at the current instant k the prediction at a future time $l \leq k$ ($l \in [k, k + N_p]$) of the normalized outputs sensitivity \bar{y}_{θ} .

Fisher Information Matrix (FIM)

$$M_{l|k} = \|\bar{y}_{\theta|k}\|^2 \quad (7)$$

Optimal control law design

- Cost function

$$\begin{cases} F(\bar{y}_{\theta|k}, u_{|k}, y_p(k), \hat{x}_a(k)) = \frac{1}{N_p} \sum_{l=k+1}^{k+N_p} M_{l|k} \\ u_{|k} = \{u(k) \dots u(l) \dots u(k+N_p)\}, l \in [k, k+N_p]. \end{cases} \quad (8)$$

- E-optimality

$$\begin{cases} u_{|k}^* = \arg \max_{u_{|k}} \left(J(u_{|k}) = \frac{\lambda_{\min}(F)}{\lambda_{\max}(F)} \right) \\ u_{|k} = \{u(k) \dots u(l) \dots u(k+N_p)\}, l \in [k, k+N_p]. \end{cases} \quad (9)$$

- Handling specified constraints:

- Constraints on the inputs (physical limitations of the actuator):

$$u_{\min} \leq u(k) \leq u_{\max}, \forall k \quad (10)$$

Velocity constraints may also be added.

- Constraints on the estimated states and/or the measured outputs (dealing with safety, operating zone, production, ...):

$$g_{\min} \leq g(\hat{x}(k), y_p(k), u(k)) \leq g_{\max}, \forall k \quad (11)$$

Optimal control law design

- **Cost function**

$$\begin{cases} F(\bar{y}_{\theta|k}, u_{|k}, y_p(k), \hat{x}_a(k)) = \frac{1}{N_p} \sum_{l=k+1}^{k+N_p} M_{l|k} \\ u_{|k} = \{u(k) \dots u(l) \dots u(k+N_p)\}, l \in [k, k+N_p]. \end{cases} \quad (8)$$

- **E-optimality**

$$\begin{cases} u_{l|k}^* = \arg \max_{u_{|k}} \left(J(u_{|k}) = \frac{\lambda_{\min}(F)}{\lambda_{\max}(F)} \right) \\ u_{|k} = \{u(k) \dots u(l) \dots u(k+N_p)\}, l \in [k, k+N_p]. \end{cases} \quad (9)$$

- Handling specified **constraints**:

- Constraints on the inputs (**physical limitations of the actuator**):

$$u_{\min} \leq u(k) \leq u_{\max}, \forall k \quad (10)$$

Velocity constraints may also be added.

- Constraints on the estimated states and/or the measured outputs (dealing with **safety, operating zone, production, ...**):

$$g_{\min} \leq g(\hat{x}(k), y_p(k), u(k)) \leq g_{\max}, \forall k \quad (11)$$

Optimal control law design

- **Cost function**

$$\begin{cases} F(\bar{y}_{\theta|k}, u_{l|k}, y_p(k), \hat{x}_a(k)) = \frac{1}{N_p} \sum_{l=k+1}^{k+N_p} M_{l|k} \\ u_{l|k} = \{u(k) \dots u(l) \dots u(k + N_p)\}, l \in [k, k + N_p]. \end{cases} \quad (8)$$

- **E-optimality**

$$\begin{cases} u_{l|k}^* = \arg \max_{u_{l|k}} \left(J(u_{l|k}) = \frac{\lambda_{\min}(F)}{\lambda_{\max}(F)} \right) \\ u_{l|k} = \{u(k) \dots u(l) \dots u(k + N_p)\}, l \in [k, k + N_p]. \end{cases} \quad (9)$$

- Handling specified **constraints**:

- Constraints on the inputs (**physical limitations of the actuator**):

$$u_{\min} \leq u(k) \leq u_{\max}, \forall k \quad (10)$$

Velocity constraints may also be added.

- Constraints on the estimated states and/or the measured outputs (dealing with **safety, operating zone, production, ...**):

$$g_{\min} \leq g(\hat{x}(k), y_p(k), u(k)) \leq g_{\max}, \forall k \quad (11)$$

The nonlinear model of CSTR

The nonlinear dynamic model of the process is:

$$\begin{cases} \dot{c}_A(t) = \frac{q}{V}(c_A^f - c_A(t)) - k_0 \exp\left(-\left(\frac{E}{R}\right) / T(t)\right) c_A(t) \\ \dot{T}(t) = \frac{q}{V}(T_f - T(t)) + \frac{\Delta H}{\rho C_p} k_0 \exp\left(-\left(\frac{E}{R}\right) / T(t)\right) c_A + \frac{UA}{\rho V C_p}(T_c - T(t)) \end{cases} \quad (12)$$

where:

- The concentration of component A, c_A , and the reactor temperature, T , are the two states x and the two measured outputs y .
- The temperature of cooling jacket T_c is the manipulated input.
- The vector of unknown parameter θ is $[1/\rho, k_0]$.
- Input constraints: $250K \leq T_c(k) \leq 320K, \forall k$.
- Output constraints: $c_A(k) \leq 0.95 \text{ mol}/\text{m}^3$


Objective: based on (12) online identify the two unknowns parameters.
(more development details on appendix)

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality




Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality




Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality




Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality




Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality

Simulation results

- Input applied: $u(t)$
- Process output: $y_{p1}(t)$
- Parameter estimation: θ_1
- Parameter estimation: θ_2
- Criterion maximal: E-optimality



Conclusion

- 👉 The proposed approach is able to
 - + design online the optimal experiment under constraints;
 - + identify online model parameters at the same time.

Conclusion

- 👉 The **proposed approach** is able to
 - + **design online the optimal experiment** under **constraints**;
 - + **identify online model parameters** at the same time.
- 👉 The combination of an observer and a predictive control in closed loop improves the **speed** of the parameter estimation.

Conclusion

- 👉 The **proposed approach** is able to
 - + **design online** the **optimal experiment** under **constraints**;
 - + **identify online model parameters** at the same time.
- 👉 The combination of an observer and a predictive control in closed loop improves the **speed** of the parameter estimation.
- 👉 The sensitivity criteria improve the **accuracy** of parameter estimation and leads to an optimal control at the same time.

Conclusion

- 👉 The **proposed approach** is able to
 - + **design online** the **optimal experiment** under **constraints**;
 - + **identify online model parameters** at the same time.
- 👉 The combination of an observer and a predictive control in closed loop improves the **speed** of the parameter estimation.
- 👉 The sensitivity criteria improve the **accuracy** of parameter estimation and leads to an optimal control at the same time.
- 👉 The input and output **constraints** specify the physical limitations imposed by the system and ensure the efficiency of the OED.

Conclusion

- The **proposed approach** is able to
 - + **design online** the **optimal experiment** under **constraints**;
 - + **identify online model parameters** at the same time.
- The combination of an observer and a predictive control in closed loop improves the **speed** of the parameter estimation.
- The sensitivity criteria improve the **accuracy** of parameter estimation and leads to an optimal control at the same time.
- The input and output **constraints** specify the physical limitations imposed by the system and ensure the efficiency of the OED.
- The proposed approach may be **adapted and tuned** for **any user defined dynamic model**.

Contacts and discussion

Software

- MPC@CB (Model Predictive Control)
Email: MPCatCB@univ-lyon1.fr; Website: <http://mpcatcb.univ-lyon1.fr/>
- ODOE4OPE (Optimal Design Of Experiments for Online Parameter Estimation)
Email: odoe4ope@univ-lyon1.fr; Website: <http://odoe4ope.univ-lyon1.fr/>

Business contacts

- Acssysteme: Expertise in automation, signal processing, optimization, software developing, ...
Website: <http://www.acssysteme.com/en/>
- LAGEP: Laboratory of Process Control and Chemical Engineering
Website: <http://www-lagep.univ-lyon1.fr>

Authors

- Pascal DUFOUR: dufour@lagep.univ-lyon1.fr
- Madiha NADRI: nadri@lagep.univ-lyon1.fr
- Jun QIAN: jun.qian@acssysteme.com; qian@lagep.univ-lyon1.fr
- Petru-Daniel MOROȘAN: petru-daniel.morosan@acssysteme.com

Annex: CSTR

Table : CSTR: known model parameters.

Parameter (units)	Symbol	Value
Volumetric flowrate (m^3/s)	q	100
Volume of CSTR (m^3)	V	100
Heat capacity of A-B mixture (J/kgK)	C_p	0.239
Heat of reaction for A-B (J/mol)	ΔH	5×10^4
- (W/K) U : overall heat transfer coefficient (W/m^2K)	UA	5×10^4
A: Area, this value is specific for the U calculation (m^2)		
Feed concentration (mol/m^3)	C_a^f	1
Feed temperature (K)	T^f	350
Exponential factor (K), E : Activation energy in the Arrhenius equation (J/mol), R : Universal gas constant ($J/mol/K$), 8.31451	$\frac{E}{R}$	8750

Table : CSTR: target for the unknown model parameters.

Parameter (units)	Symbol	Initial Value	Target Value
Density of A-B mixture (kg/m^3)	ρ	1100	1000
Pre-exponential factor (s^{-1})	k_0	6.3×10^{10}	7.2×10^{10}

Annex: CSTR

- Augmented system:

$$(M_a) \begin{cases} \dot{x}_1(t) = \alpha_1(\alpha_2 - x_1(t)) - x_4(t)\exp\left(\frac{\alpha_3}{x_2(t)}\right)x_1(t) \\ \dot{x}_2(t) = \alpha_1(\alpha_4 - x_2(t)) + \alpha_5x_4(t)x_3(t)\exp\left(\frac{\alpha_3}{x_2(t)}\right)x_1(t) + \alpha_6x_3(t)(u(t) - x_2(t)) \\ \dot{x}_3(t) = 0 \\ \dot{x}_4(t) = 0 \\ y(t) = \begin{bmatrix} x_1(t) \\ x_2(t) \end{bmatrix} \end{cases} \quad (13)$$

- Two interconnected subsystems:

$$\begin{cases} \dot{x}_1(t) = \alpha_1(\alpha_2 - x_1(t)) - x_4(t)\exp\left(\frac{\alpha_3}{x_2(t)}\right)x_1(t) \\ \dot{x}_4(t) = 0 \\ y_1(t) = x_1(t) \end{cases} \quad (14)$$

$$\begin{cases} \dot{x}_2(t) = \alpha_1(\alpha_4 - x_2(t)) + \alpha_5x_4(t)x_3(t)\exp\left(\frac{\alpha_3}{x_2(t)}\right)x_1(t) + \alpha_6x_3(t)(u(t) - x_2(t)) \\ \dot{x}_3(t) = 0 \\ y_2(t) = x_2(t) \end{cases} \quad (15)$$

Annex: CSTR

- Form general of two subsystems:

$$\begin{cases} \dot{X}_1 = A_1(u, y_1, \alpha, X_2)X_1 + \varphi_1(u, y_1, \alpha, X_1, X_2) \\ y_1 = C_1 X_1 \end{cases} \quad (16)$$

$$\begin{cases} \dot{X}_2 = A_2(u, y_2, \alpha, X_1)X_2 + \varphi_2(u, y_2, \alpha, X_1, X_2) \\ y_2 = C_2 X_2 \end{cases} \quad (17)$$

where:

$$A_1(u, y_1, \alpha, X_2) = \begin{bmatrix} 0 & -y_1 \exp\left(\frac{\alpha_3}{X_2(1)}\right) \\ 0 & 0 \end{bmatrix}; \quad \varphi_1(u, y_1, \alpha, X_1, X_2) = \begin{bmatrix} \alpha_1 \alpha_2 - \alpha_1 y_1 \\ 0 \end{bmatrix};$$

$$A_2(u, y_2, \alpha, X_1) = \begin{bmatrix} 0 & \alpha_5 X_1(2) \exp\left(\frac{\alpha_3}{y_2}\right) X_1(1) + \alpha_6(u - y_2) \\ 0 & 0 \end{bmatrix};$$

$$\varphi_2(u, y_2, \alpha, X_1, X_2) = \begin{bmatrix} \alpha_1 \alpha_4 - \alpha_1 y_2 \\ 0 \end{bmatrix}; \quad C_2 = [1 \ 0].$$

Annex: CSTR

- Observers in cascade:

- For the subsystem (16), an observer is designed as follows:

$$\dot{Z}_1 = A_1 Z_1 + \varphi_1 - G(C_1 Z_1 - y_p(1)) \quad (18)$$

where:

- estimated state vector: $Z_1 = \begin{bmatrix} \hat{x}_1 \\ \hat{x}_4 \end{bmatrix}$;
- gain of observer: $G = \Delta^{-1} S_\theta^{-1} C_1^T$ with $\Delta = \begin{bmatrix} 1 & 0 \\ 0 & A_{12} \end{bmatrix}$ and

$$S_\theta = \begin{bmatrix} \frac{1}{\theta_{o1}} & -\frac{1}{\theta_{o1}^2} \\ -\frac{1}{\theta_{o1}^2} & \frac{1}{\theta_{o1}^3} \end{bmatrix};$$

- For the subsystem (17), we design a type of observer for the state-affine system with output injection:

$$\begin{cases} \dot{Z}_2 = A_2 Z_2 + \varphi_2 - S^{-1} C_2^T R (C_2 Z_2 - y_p(2)) \\ \dot{S} = -\theta_{o2} S - A_2^T S - S A_2^T + C_2^T R C_2 \end{cases} \quad (19)$$

where:

- estimated state vector: $Z_2 = \begin{bmatrix} \hat{x}_2 \\ \hat{x}_3 \end{bmatrix}$;
- S : matrix 2×2 S.D.P.;
- R : weight matrix 1×1 ;
- θ_{o2} : tuning parameter of observer.

Annex: CSTR

- Sensitivity model

$$(M_\theta) \left\{ \begin{array}{l}
 \dot{x}_{1\theta 1}(t) = -\alpha_1 x_{1\theta 1}(t) - \hat{\theta}_2(t) \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_{1\theta 1}(t) \\
 \quad + \hat{\theta}_2(t) x_1(t) \exp\left(\frac{\alpha_3}{x_2(t)}\right) \frac{\alpha_3}{x_2^2(t)} x_{2\theta 1}(t) \\
 \dot{x}_{1\theta 2}(t) = -\exp\left(\frac{\alpha_3}{x_2(t)}\right) x_1(t) - \alpha_1 x_{1\theta 2}(t) - \hat{\theta}_2(t) \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_{1\theta 2}(t) \\
 \quad + \hat{\theta}_2(t) x_1(t) \exp\left(\frac{\alpha_3}{x_2(t)}\right) \frac{\alpha_3}{x_2^2(t)} x_{2\theta 2}(t) \\
 \dot{x}_{2\theta 1}(t) = -\frac{\left[\alpha_5 \hat{\theta}_2(t) \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_1(t) + \alpha_6 (u(t) - x_2(t))\right]}{\hat{\theta}_1^2(t)} \\
 \quad - \left(\alpha_1 + \frac{\alpha_5 \hat{\theta}_2(t)}{\hat{\theta}_1(t)} \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_1(t) \frac{\alpha_3}{x_2^2(t)} + \frac{\alpha_6}{\hat{\theta}_1(t)}\right) x_{2\theta 1}(t) \\
 \quad + \frac{\alpha_5 \hat{\theta}_2(t)}{\hat{\theta}_1(t)} \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_{1\theta 1}(t); \\
 \dot{x}_{2\theta 2}(t) = \frac{\alpha_5}{\hat{\theta}_1(t)} \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_1(t) \\
 \quad - \left(\alpha_1 + \frac{\alpha_5 \hat{\theta}_2(t)}{\hat{\theta}_1(t)} \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_1(t) \frac{\alpha_3}{x_2^2(t)} + \frac{\alpha_6}{\hat{\theta}_1(t)}\right) x_{2\theta 2}(t) \\
 \quad + \frac{\alpha_5 \hat{\theta}_2(t)}{\hat{\theta}_1(t)} \exp\left(\frac{\alpha_3}{x_2(t)}\right) x_{1\theta 2}(t);
 \end{array} \right. \quad (20)$$