

Dynamical Continuous High Gain Observer For Sampled Measurements Systems

Cheikh A.B. Hann, Vincent van Assche, Naveena Crasta, Françoise Lamnabhi-Lagarrigue

► To cite this version:

Cheikh A.B. Hann, Vincent van Assche, Naveena Crasta, Françoise Lamnabhi-Lagarrigue. Dynamical Continuous High Gain Observer For Sampled Measurements Systems. 51th IEEE Conference on Decision and Control, Dec 2012, Maui, United States. pp.6635-6640, 10.1109/CDC.2012.6426327. hal-01061185

HAL Id: hal-01061185 https://hal.science/hal-01061185

Submitted on 11 Jul2022

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution - NonCommercial 4.0 International License

Dynamical Continuous High Gain Observer For Sampled Measurements Systems

Cheikh A.B. Hann, Vincent Van Assche, Naveena Crasta, and Françoise Lamnabhi-Lagarrigue

Abstract— This paper presents the design of an observer for a class of nonlinear Lipschitz sampled-data systems. The proposed observer uses a predictor of the output between the sampling times. This predictor is re-initialized at each sampling time. Besides, unlike the conventional high gain observer, the observer introduced herein has a dynamic observation gain. Using a Lyapunov approach, we will derive an explicit relation between the bound on maximum allowable sampling period and the parameters of the observer in order to guarantee an asymptotic convergence of the observation error.

I. INTRODUCTION

The study of observers for continuous-time systems with sampled output has attracted a lot of attention during the last decades. For linear time invariant systems, the solution is more obvious since it is possible to use the available discrete model of the continuous time system in order to design a discrete time observer [1]. For other classes of systems, the exact discrete model is generally not available. Therefore, one can resort to the use of a consistent approximation (such Euler approximation) of the exact discrete-time model, see for instance [2], [3], [4] and [5], [6] for the control design. However, this method does not take into account the behavior of the system between the sampling instants. Furthermore, it just guarantees a semi-global practical stability of the observation error.

Another approach to circumvent the need of the exact discrete model is to use a hybrid observer. This observer is formed of two parts: a prediction part that consists of 'copying' system dynamics with no correction term between the sampling instants and an update part, at the sampling times, when the error between the system and the observer output is used to correct the estimate state trajectory. Most of this kind of observers is based on the extended Kalman filter techniques. Unlike the discrete time approach, this one provides in most cases global and asymptotic stability [7], [8], [9], [10].

Recently, in [11], the authors have proposed a novel hybrid observer that consists of continuous state estimation combined with an output predictor. One can point out that only the output predictor is updated at each sampling instant. Therefore, the estimate of the state is continuous. This approach has been applied to several classes of systems such linear detectable systems and triangular globally Lipschitz nonlinear systems. The exponential convergence of the observation error has been derived by using a small gain approach.

In the present work, we present a hybrid high gain observer for a class of nonlinear triangular systems with sampled measurements. There is a large literature concerning the design of high gain observers see for instance [12], [13], [14]. In [15], [16], dynamical high gain observers for continuous time systems are designed in order to address the issue of the sensitivity to measurements error inherent to this kind of observers. The observer proposed herein includes a dynamical observation gain and uses an output predictor that is updated at each sampling time. The asymptotic convergence of the observer is derived using, as in [17], a suitable Lyapunov Krasovskii function and an explicit relation between the bound on maximum allowable sampling period (τ_{MASP}) and the parameters of the observer is given.

The paper is organized as follows: Section II gives the preliminary definitions. Section III describes the class of considered systems. A dynamical high gain observer for nonlinear triangular systems with sampled measurements is designed in Section IV, the asymptotic convergence of the observation error is proved and an explicit bound on the maximum allowable sampling period (τ_{MASP}) depending on the observer parameters is given. In Section V, an academic example is provided in order to illustrate our result.

II. NOMENCLATURE

Throughout this paper, the following mathematical notations are used. Let $\mathbf{R} = (-\infty, +\infty)$, $\mathbf{R}_{+} = (0, +\infty)$, $\mathbf{R}_{0}^{+} = [0, +\infty)$. The Euclidian norm is defined by $|\cdot|$. For $p, q, n, m \in \mathbf{N}$, $\mathbf{R}^{p \times q}$ represents the set of real matrices of order $p \times q$ and \mathbf{I}_{p} stands for the identity matrix of order $p \times p$. $D \stackrel{\text{def}}{=} \text{diag}\{d_{1}, \ldots, d_{n}\}, d_{1}, \ldots, d_{n} \in \mathbb{R}$ denotes the diagonal matrix of size n. If $P \in \mathbf{R}^{p \times p}$, P > 0 means that P is positive definite. The notation |P| represents the \mathbf{L}_{2} norm of P. If $\mathcal{X} \subset \mathbf{R}^{p \times q}$ and $\mathcal{Y} \subset \mathbf{R}^{n \times m}$, $\mathcal{C}(\mathcal{X}, \mathcal{Y})$ denotes the space of all continuous functions mapping $\mathcal{X} \to \mathcal{Y}$. $\lambda_{\min}(P)$ (resp. $\lambda_{\max}(P)$), for $P \in \mathbf{R}^{p \times p}$, is the minimal (resp. maximal) eigenvalue of P(t), $\forall t \in \mathbf{R}_{0}^{+}$. In all this study, the initial time is called $t_{0} \in \mathbf{R}_{0}^{+}$.

Cheikh A.B. Hann is with GREYC UMR CNRS 6072, 6 Boulevard du Maréchal Juin 14050 Caen Cedex cheikh.hann@unicaen.fr

Vincent Van Assche is with GREYC UMR CNRS 6072, 6 Boulevard du Maréchal Juin 14050 Caen Cedex vincent.vanassche@unicaen.fr

Naveena Crasta is with LSS, SUPELEC, 3 rue Joliot Curie, 91192 Gifsur-Yvette, France naveen.CRASTA@lss.supelec.fr

Francoise Lamnabhi-Lagarrigue is with LSS-CNRS, SUPELEC, EECI, 3 rue Joliot Curie, 91192 Gif-sur-Yvette, France lamnabhi@lss.supelec.fr

III. SYSTEM DESCRIPTION

We consider the following class of nonlinear systems described by

$$\begin{cases} \dot{x}(t) = Ax(t) + \phi(x(t), u) \\ y(t) = Cx(t) \end{cases}$$
(1)

where $x := \begin{bmatrix} x_1 & \cdots & x_n \end{bmatrix}^T \in \mathbb{R}^n$ is the state vector of the system, the input to the system $u = \begin{bmatrix} u_1 & \cdots & u_m \end{bmatrix}^T \in \Omega \subseteq \mathbb{R}^m$, with Ω a compact subset of \mathbb{R}^m . $y(t) \in \mathbf{R}$ represents the output of the system.

$$A := \begin{bmatrix} 0 & 1 & 0 & \cdots & 0 \\ 0 & 0 & 1 & \cdots & 0 \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & \cdots & 1 \\ 0 & 0 & 0 & \cdots & 0 \end{bmatrix} \in \mathbb{R}^{n \times n},$$
$$\phi(x(t), u) := \begin{bmatrix} \phi_1(x_1, u) \\ \phi_2(x_1, x_2, u) \\ \vdots \\ \phi_n(x_1, \dots, x_n, u) \end{bmatrix} \in \mathbb{R}^n,$$
$$C := \begin{bmatrix} 1 & 0 & \cdots & 0 \end{bmatrix} \in \mathbb{R}^n.$$

Furthermore, we make the following assumption.

Assumption 1: For every $i \in \{1, ..., n\}$, the triangular functions $\phi_i \colon \mathbb{R}^i \times \mathbb{R}^m \to \mathbb{R}$ are globally Lipschitz with a Lipschitz constant $L \ge 0$, that is: there exists $L \ge 0$ such that for every $x, z \in \mathbb{R}^n$ and $u \in \Omega$,

$$|\phi(x,u) - \phi(z,u)| \le L |x-z|$$
. (2)

We consider the output of the system only at the sampling time such that we have the sequence of the output $\{y_{t_k}\}_{k\geq 0}$, where $\{t_k\}_{k\geq 0}$ represents a strictly increasing sequence that models the sampling instants, such that $\lim_{k\to\infty} t_k = \infty$. Besides the sampling period, either uniform or nonuniform, is such that $0 < \tau = t_{k+1} - t_k \leq \tau_{MASP}$ for every $k \in \mathbf{N}$. The question is whether we can still preserve the convergence property of the observer when we only have the sequence $\{y_{t_k}\}_{k\geq 0}$ as output of the system.

IV. SAMPLED HIGH-GAIN OBSERVER

A. Observer structure

We consider a continuous-time adaptive high-gain observer for the system (1) without sampling given by

$$\begin{cases} \dot{x}(t) = A\hat{x}(t) + \phi(\hat{x}(t), u) \\ -\theta \Delta_{\theta}^{-1} K(C\hat{x}(t) - y(t)) \\ \hat{y}(t) = C\hat{x}(t) \\ \dot{\theta} = l(\theta) \quad \theta(t_0) > 1 \end{cases}$$
(3)

where $\hat{x} \in \mathbb{R}^n$, $\Delta_{\theta} = \text{diag} \{1, \theta^{-1}, \dots, \theta^{1-n}\}$, $K \in \mathbb{R}^n$ is such that A - KC is Hurwitz, $\theta \ge 1$, and $l : \mathbb{R} \to \mathbb{R}$ is sufficiently smooth function and is chosen such that $\theta(t) > 1$ for all $t \in \mathbf{R}_0^+$. Let us consider the following sampled-data observer with a high-gain continuous-time observer and an inter sample output predictor, that is,

$$\begin{cases} \hat{x}(t) = A\hat{x}(t) + \phi(\hat{x}(t), u) \\ -\theta \Delta_{\theta}^{-1} K(C\hat{x}(t) - w(t)) \\ \dot{w}(t) = CA\hat{x}(t) + C\phi(\hat{x}(t), u) \\ w(t_{k+1}) = y(t_{k+1}) \\ \dot{\theta} = l(\theta) \quad \theta(t_0) > 1 \end{cases}$$
(4)

for every $k \in \mathbf{N}$. The output predictor is represented by $w(t) \in \mathbf{R}$.

Let us define the state error $\tilde{x}(t) \stackrel{\text{def}}{=} \hat{x}(t) - x(t)$. The time derivative of the state error is given by $\dot{\tilde{x}}(t) = \dot{\tilde{x}}(t) - \dot{x}(t)$. Let $e_w(t)$ denote the prediction error between the predictor and the output: $e_w(t) = w(t) - y(t)$. Using (1) and (4), we obtain:

$$\tilde{\tilde{x}}(t) = \left(A - \theta \Delta_{\theta}^{-1} KC\right) \tilde{x}(t)
+ \phi\left(\hat{x}(t), u\right) - \phi\left(x(t), u\right) + \theta \Delta_{\theta}^{-1} Ke_w(t)$$
(5)

We define: $\tilde{\phi}(x(t), \hat{x}(t), u) \stackrel{\text{def}}{=} \phi(\hat{x}(t), u) - \phi(x(t), u).$ Let us introduce the change of coordinate

$$z(t) \stackrel{\text{def}}{=} \frac{1}{\theta^b} \Delta_\theta \tilde{x}(t) \tag{6}$$

for some real constant b > 1, that will be defined further. We should point out that the statement $\tilde{x}(t) = 0$ is equivalent to z(t) = 0. Thus, by deriving (6), we have:

$$\dot{z}(t) = \left(\frac{1}{\theta^b}\Delta_\theta\right)\dot{\tilde{x}}(t) + \frac{\mathrm{d}}{\mathrm{dt}}\left(\frac{1}{\theta^b}\Delta_\theta\right)\tilde{x}(t) \tag{7}$$

On one hand, we have:

$$\frac{1}{\theta^{b}} \Delta_{\theta} \dot{\tilde{x}}(t) = \Delta_{\theta} \left(A - \theta \Delta_{\theta}^{-1} KC \right) \Delta_{\theta}^{-1} z(t)
+ \frac{1}{\theta^{b}} \Delta_{\theta} \tilde{\phi}(x(t), \hat{x}(t), u) + \frac{1}{\theta^{b-1}} Ke_{w}(t)$$
(8)

We introduce these following identities:

$$\Delta_{\theta} A \Delta_{\theta}^{-1} = \theta A \qquad \text{and} \qquad C \Delta_{\theta}^{-1} = C \tag{9}$$

Using the above identities, we get:

$$\frac{1}{\theta^{b}}\Delta_{\theta}\dot{\tilde{x}}(t) = \theta \left(A - KC\right) z\left(t\right) + \frac{1}{\theta^{b}}\Delta_{\theta}\tilde{\phi}\left(x\left(t\right), \hat{x}\left(t\right), u\right) + \frac{1}{\theta^{b-1}}Ke_{w}\left(t\right)$$
(10)

On the other hand,

$$\frac{\mathrm{d}}{\mathrm{dt}} \left(\frac{1}{\theta^{b}} \Delta_{\theta}\right) \tilde{x}\left(t\right) = \frac{\mathrm{d}}{\mathrm{dt}} \mathrm{diag}\left\{\theta^{-\mathrm{b}}, \theta^{-\mathrm{b}-1}, \cdots, \theta^{-\mathrm{b}-\mathrm{n}+1}\right\}$$
(11)

$$= -\frac{\dot{\theta}}{\theta^{b+1}} \operatorname{diag} \left\{ b, b-1, \cdots, b-n+1 \right\}$$

$$\times \Delta_{\theta} \tilde{x} \left(t \right)$$

$$= -\frac{\dot{\theta}}{\theta} D\left(\frac{1}{\theta^{b}} \Delta_{\theta} \tilde{x}\left(t\right)\right)$$
(13)

where $D \stackrel{\text{def}}{=} \text{diag} \{b, b+1, \dots, b+n-1\}$. Note that $D = b \mathbf{I}_n + E$, where

$$E \stackrel{\text{def}}{=} \text{diag} \{0, 1, \dots, n-1\}$$
 (14)

From (6) and (13), we deduce that:

$$\frac{\mathrm{d}}{\mathrm{dt}} \left(\frac{1}{\theta^b} \Delta_\theta \right) \tilde{x} \left(t \right) = -\frac{\dot{\theta}}{\theta} Dz \left(t \right) \tag{15}$$

Thus we have

$$\dot{z}(t) = \theta \left(A - KC\right) z(t) + \frac{1}{\theta^{b}} \Delta_{\theta} \tilde{\phi} \left(x(t), \hat{x}(t), u\right) + \frac{1}{\theta^{b-1}} K e_{w}(t) - \frac{\dot{\theta}}{\theta} D z(t)$$
(16)

B. Technical results

Now, we shall present some useful technical results that are necessary for our next result. We recall Jensen's Inequality [18, Prop B.8, pg. 316].

Proposition 1: For any constant matrix $M \in \mathbf{R}^{m \times m}$, $M = M^T > 0$, scalar $\gamma > 0$, vector function $\omega : [0, \gamma] \to \mathbf{R}^m$ such that the integrations concerned are well defined, then

$$\left(\int_{0}^{\gamma} \omega(s) \,\mathrm{d}s\right)^{\mathrm{T}} M\left(\int_{0}^{\gamma} \omega(s) \,\mathrm{d}s\right) \leq \gamma \int_{0}^{\gamma} \omega(s)^{\mathrm{T}} M \,\omega(s) \,\mathrm{d}s.$$
(17)

Lemma 1: Consider the output of the system and the predictor as defined in (1) and (4), the prediction error $e_w(t)$ can be written as follows:

$$\left|e_{w}\left(t\right)\right|^{2} \leq \theta^{2b} \left(\theta + \sqrt{nL}\right)^{2} \tau_{MASP} \int_{t-\tau_{MASP}}^{t} \left|z\left(s\right)\right|^{2} ds$$
(18)

for every $t \in [t_k, t_{k+1})$ and $k \in \{1, ..., s-1\}$.

Proof: To prove this lemma, we first note that from (1) and (4), we have:

$$\dot{e}_w(t) = CA\tilde{x}(s) + C\tilde{\phi}(\hat{x}(s), x(s), u)$$
(19)

for $t \in [t_k, t_{k+1})$.

Therefore, by integrating the above equation between t_k and t, we get:

$$e_{w}(t) = \int_{t_{k}}^{t} CA\tilde{x}(s) + C\tilde{\phi}(\hat{x}(s), x(s), u) ds \qquad (20)$$

and then, using the change of coordinates (6) and the identities (9), we obtain:

$$|e_{w}(t)| \leq \int_{t_{k}}^{t} \left| C\Delta_{\theta} A \Delta_{\theta}^{-1} \theta^{b} z(s) + C\Delta_{\theta} \tilde{\phi}(\hat{x}(s), x(s), u) \right| ds$$

$$(21)$$

Thus, by triangle inequality and assumption 1, we can state that:

$$e_{w}(t)| \leq \int_{t_{k}}^{t} \left|\theta^{b+1} CAz(s)\right| + \left|\sqrt{n}L\theta^{b}z(s)\right| ds \quad (22)$$

As a result, we get:

$$|e_{w}(t)| \leq \theta^{b} \left(\theta + \sqrt{nL}\right) \int_{t_{k}}^{t} |z(s)| \, ds \tag{23}$$

Since we have $\tau_{MASP} \geq t_{k+1} - t_k$ for every $k \in \{1, \ldots, s-1\}$, we can assert that:

$$|e_w(t)| \le \theta^b \left(\theta + \sqrt{nL}\right) \int_{t-\tau_{MASP}}^t |z(s)| \, ds \qquad (24)$$

Invoking Jensen's inequality, we have

$$\left(\int_{t-\tau_{MASP}}^{t} |z\left(s\right)| ds\right)^{2} \leq \tau_{MASP} \int_{t-\tau_{MASP}}^{t} |z\left(s\right)|^{2} ds$$
(25)

Hence, we come to the following conclusion:

$$\left|e_{w}\left(t\right)\right|^{2} \leq \theta^{2b} \left(\theta + \sqrt{nL}\right)^{2} \tau_{MASP} \int_{t-\tau_{MASP}}^{t} \left|z\left(s\right)\right|^{2} ds$$
(26)

This completes the proof.

C. Stability Analysis

Inspired by the work of [19], let us choose the following Lyapunov function:

$$V(t, z(t)) \stackrel{\text{def}}{=} z(t)^T P z(t) + \frac{1}{\tau_{MASP}} \int_{t-\tau_{MASP}}^t \int_s^t |z(\xi)|^2 d\xi ds$$
(27)

where P is a symmetric positive definite matrix such that, for some real $q \in (0,1]$, $q\mathbf{I}_n \leq P \leq \mathbf{I}_n$. Furthermore, P satisfies the following inequality:

$$(A - KC)^{\mathrm{T}} P + P(A - KC) \le -\mu \mathbf{I}_n \qquad (28)$$

for some $\mu > 0$.

We can remark that for all $t \in \mathbf{R}_0^+$, V(t,0) = 0 and V(t, z(t)) > 0 for all $z(t) \neq 0_n$.

Let us decompose V into two functions V_1 and V_2 :

$$V_1(z(t)) \stackrel{\text{def}}{=} z(t)^T P z(t)$$
(29)

and

$$V_2(t, z(t)) \stackrel{\text{def}}{=} \frac{1}{\tau_{MASP}} \int_{t-\tau_{MASP}}^t \int_s^t |z(\xi)|^2 d\xi ds \quad (30)$$

We can assume that:

$$V(t_k, z(t_k)) = V(t_k^-, z(t_k^-)),$$
(31)

since z(t) and therefore $V_1(z(t))$ and $V_2(t, z(t))$ are continuous functions of the time t.

In order to demonstrate the asymptotic convergence of z(t) towards zero and thereby that of the observation error, it suffices now to show that $\dot{V}(t, z(t)) \leq -W(z(t))$ for $t \in [t_k, t_{k+1}) \ \forall k \in \mathbf{N}$, where $W : \mathbf{R}^n \to \mathbf{R}$ is a continuous and nonnegative definite function.

Now, let us consider $t \in [t_k, t_{k+1})$.

The time derivative of the Lyapunov function V(t, z(t)) is given by $\dot{V}(t, z(t)) = \dot{V}_1(z(t)) + \dot{V}_2(t, z(t))$, where

$$\dot{V}_{1}(z(t)) = z(t)^{T} P \dot{z}(t) + \dot{z}(t)^{T} P z(t)$$
 (32)

$$\dot{V}_{2}(t,z(t)) = |z(t)|^{2} - \frac{1}{\tau_{MASP}} \int_{t-\tau_{MASP}}^{t} |z(s)|^{2} ds \quad (33)$$

Using (16), we can compute $\dot{V}_1(z)$ so that we have:

$$\dot{V}_{1} = z(t)^{T} P$$

$$\times \left[\theta \left(A - KC \right) z(t) + \frac{1}{\theta^{b}} \Delta_{\theta} \tilde{\phi} \left(x(t), \hat{x}(t), u \right) \right.$$

$$\left. + \frac{1}{\theta^{b-1}} K e_{w}(t) - \frac{\dot{\theta}}{\theta} D z(t) \right]$$

$$\left. + \left[\theta \left(A - KC \right) z(t) + \frac{1}{\theta^{b}} \Delta_{\theta} \tilde{\phi} \left(x(t), \hat{x}(t), u \right) \right.$$

$$\left. + \frac{1}{\theta^{b-1}} K e_{w}(t) - \frac{\dot{\theta}}{\theta} D z(t) \right]^{T} P z(t)$$

$$\dot{V}_{1} = \theta z(t)^{T} \left[P \left(A - KC \right) + \left(A - KC \right)^{T} P \right] z(t)$$

$$\left. + \frac{2}{\theta^{b}} z(t)^{T} P \Delta_{\theta} \tilde{\phi} \left(x(t), \hat{x}(t), u \right)$$

$$\left. + \frac{2}{\theta^{b-1}} z(t)^{T} P K e_{w}(t) - 2 \frac{\dot{\theta}}{\theta} z(t)^{T} P D z(t) \right]$$

$$(35)$$

Using (28), we get:

$$\dot{V}_{1} \leq -\left(\theta\mu + 2b\frac{\dot{\theta}}{\theta}\right)z(t)^{T}Pz(t) + \frac{2}{\theta^{b}}z(t)^{T}P\Delta_{\theta}\tilde{\phi}(x(t),\hat{x}(t),u) + \frac{2}{\theta^{b-1}}z(t)^{T}PKe_{w}(t) - 2\frac{\dot{\theta}}{\theta}z(t)^{T}PEz(t)$$
(36)

Besides b > 1 is chosen such that it satisfies the following relation:

$$-bP \le PE + EP \le bP \tag{37}$$

from which it follows that

$$-2\frac{\dot{\theta}}{\theta}z(t)^{T}PEz(t) \le b\frac{\left|\dot{\theta}\right|}{\theta}z(t)^{T}Pz(t)$$
(38)

Therefore, we have:

$$\dot{V}_{1} \leq -\left(\theta\mu + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta}\right)z(t)^{T}Pz(t) + \frac{2}{\theta^{b}}z(t)^{T}P\Delta_{\theta}\tilde{\phi}(x(t),\hat{x}(t),u) + \frac{2}{\theta^{b-1}}z(t)^{T}PKe_{w}(t)$$

$$(39)$$

From (6) and assumption (1), we can derive that:

$$\dot{V}_{1} \leq -\left(\mu\theta + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - 2\sqrt{nL}\frac{\lambda_{\max}\left(P\right)}{\lambda_{\min}\left(P\right)}\right)V_{1} + \frac{2}{\theta^{b-1}}z\left(t\right)^{T}PKe_{w}\left(t\right)$$

$$(40)$$

Then, using Young inequality, we get:

$$\dot{V}_{1} \leq -\left(\mu\theta + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - 2\sqrt{nL}\frac{\lambda_{\max}\left(P\right)}{\lambda_{\min}\left(P\right)}\right)V_{1} + \frac{\mu\theta\lambda_{\min}\left(P\right)}{2}\left|z\left(t\right)\right|^{2} + \frac{2}{\mu\theta\lambda_{\min}\left(P\right)}\frac{\lambda_{\max}\left(P\right)^{2}}{\theta^{2b-2}}\left|K\right|^{2}\left|e_{w}\left(t\right)\right|^{2}$$

$$(41)$$

It follows that:

$$\dot{V}_{1} \leq -\left(\mu\frac{\theta}{2} + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - 2\sqrt{n}L\frac{\lambda_{\max}\left(P\right)}{\lambda_{\min}\left(P\right)}\right)V_{1} + \frac{2}{\mu\theta^{2b-1}}\frac{\lambda_{\max}\left(P\right)^{2}}{\lambda_{\min}\left(P\right)}\left|K\right|^{2}\left|e_{w}\left(t\right)\right|^{2}$$

$$(42)$$

Which, using lemma (1), leads us to

$$\dot{V}_{1} \leq -\left(\mu\frac{\theta}{2} + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - 2\sqrt{n}L\frac{\lambda_{\max}\left(P\right)}{\lambda_{\min}\left(P\right)}\right)V_{1} + \tau_{MASP}\frac{2\theta}{\mu}\frac{\lambda_{\max}\left(P\right)^{2}}{\lambda_{\min}\left(P\right)}\left|K\right|^{2}$$

$$\times \left(\theta + \sqrt{n}L\right)^{2}\int_{t-\tau_{MASP}}^{t}\left|z\left(s\right)\right|^{2}ds$$

$$(43)$$

From (43) and (33), we can deduce that:

$$\dot{V} \leq -\left(\mu\frac{\theta}{2} + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - \frac{2\sqrt{n}L\lambda_{\max}\left(P\right) + 1}{\lambda_{\min}\left(P\right)}\right)V_{1}$$
$$-\left(\frac{1}{\tau_{MASP}} - \tau_{MASP}\frac{2\theta}{\mu}\frac{\lambda_{\max}\left(P\right)^{2}}{\lambda_{\min}\left(P\right)}\left|K\right|^{2} \right.$$
$$\times \left(\theta + \sqrt{n}L\right)^{2}\right)\int_{t-\tau_{MASP}}^{t} |z\left(s\right)|^{2} ds.$$
(44)

We can choose the maximum allowable sampling period $\tau_{\rm MASP}$ such that:

$$\tau_{\scriptscriptstyle MASP} \le \frac{\sqrt{\mu \lambda_{\min}\left(P\right)}}{\sqrt{2\theta_{\max}}\lambda_{\max}\left(P\right)\left|K\right|\left(\theta_{\max} + \sqrt{n}L\right)},\qquad(45)$$

where θ_{\max} is the maximum value of θ for all $t \in \mathbf{R}_+$. Thus, we obtain:

$$\dot{V} \leq -\left(\mu\frac{\theta}{2} + 2b\frac{\dot{\theta}}{\theta} - b\frac{\left|\dot{\theta}\right|}{\theta} - \frac{2\sqrt{n}L\lambda_{\max}\left(P\right) + 1}{\lambda_{\min}\left(P\right)}\right)V_{1}$$
(46)

Following [20], let us choose $\dot{\theta}$ as:

$$\dot{\theta} = -\frac{1}{b}\theta \left[\frac{\mu}{6}\left(\theta - 1\right) - \frac{2\sqrt{n}\lambda_{\max}\left(P\right)L + 1}{\lambda_{\min}\left(P\right)}\right].$$
 (47)

Therefore, we can deduce from (45), (46), and (47) that:

$$\dot{V} \le -\frac{\mu}{2}V_1 \tag{48}$$

which completes the proof.

Remark 1: Choosing $\dot{\theta}$ as in (47), let us consider the two following cases: First, if $\dot{\theta} > 0$, we have:

$$\dot{V} \leq -\left(\mu\frac{\theta}{2} + b\frac{\dot{\theta}}{\theta} - \frac{2\sqrt{nL\lambda_{\max}(P)} + 1}{\lambda_{\min}(P)}\right)V_1 \qquad (49)$$

$$\leq -\frac{\mu}{6} \left(2\theta + 1\right) V_1 \tag{50}$$

$$\leq -\frac{\mu}{2}V_1,\tag{51}$$

since $\theta(t_0) > 1$ and θ is an increasing function of the time $(\dot{\theta} > 0)$.

Now we consider the case when $\dot{\theta} < 0$, we get:

$$\dot{V} \leq -\left(\mu\frac{\theta}{2} + 3b\frac{\dot{\theta}}{\theta} - \frac{2\sqrt{n}L\lambda_{\max}\left(P\right) + 1}{\lambda_{\min}\left(P\right)}\right)V_{1} \quad (52)$$

$$\leq -\left(\frac{\mu}{2} - \frac{4\sqrt{nL\lambda_{\max}\left(P\right)} + 2}{\lambda_{\min}\left(P\right)}\right)V_1\tag{53}$$

$$\leq -\frac{\mu}{2}V_1,\tag{54}$$

since $\frac{4\sqrt{n}L\lambda_{\max}\left(P\right)+2}{\lambda_{\min}\left(P\right)} > 0.$

Furthermore, can we remark for every value of given $\theta(t_0) \in \mathbf{R}$, the final θ remains $\theta_{\infty} := 1 + \frac{12\sqrt{n\lambda_{\max}\left(P\right)L + 6}}{12\sqrt{n\lambda_{\max}\left(P\right)L + 6}}$ Besides, $\theta_{\rm max}$ and $\mu\lambda_{\min}\left(P\right)$ θ_{\min} are such that:

$$\theta_{mn} = \begin{cases} \theta(t_0), & \text{for } \theta(t_0) \ge \theta_{\infty} \end{cases}$$
 (55)

$$\int \theta_{\infty}, \quad \text{for } \theta(t_0) < \theta_{\infty} \quad (56)$$

$$\theta_{\min} = \begin{cases} \theta_{\infty}, & \text{for } \theta(t_0) \ge \theta_{\infty} & (57) \\ \theta(t_0), & \text{for } \theta(t_0) < \theta_{\infty} & (58) \end{cases}$$

It should be noted that for $\theta(t_0) > 1$, we have $\theta(t) > 1$ for all $t > t_0$.

V. APPLICATION

Consider the nonlinear dynamical system described by

$$\dot{x}_1 = x_2 + \sin x_1$$

$$\dot{x}_2 = -x_1$$

$$y = x_1$$
(59)

where the state $x \in \mathbb{R}^2$ and output $y \in \mathbb{R}$. Note that (A, C) is observable and hence there exists $K = [k_1 \ k_2]^T \in \mathbb{R}^2$ such that

$$A - KC = \begin{bmatrix} -k_1 & 1\\ -k_2 & 0 \end{bmatrix}$$

is Hurwitz, where $A = \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix}$ and $C = \begin{bmatrix} 1 & 0 \end{bmatrix}$. The sampled data dynamical high gain observer is given

The sampled data dynamical high gain observer is given by

$$\begin{aligned} \dot{x}_1(t) &= \hat{x}_2(t) + \sin \hat{x}_1(t) - \theta k_1(\hat{x}_1(t) - w(t)) \\ \dot{x}_2(t) &= -\hat{x}_1(t) - \theta^2 k_2(\hat{x}_1(t) - w(t)), \\ \dot{w}(t) &= \hat{x}_2(t) + \sin \hat{x}_1(t) \quad t \in [t_k, t_{k+1}), \\ w(t_{i+1}) &= x_1(t_{k+1}), \\ \dot{\theta} &= -\frac{1}{b} \theta \left[\frac{\mu}{6} \left(\theta - 1 \right) - \frac{2\sqrt{n}\lambda_{\max}\left(P\right)L + 1}{\lambda_{\min}\left(P\right)} \right]. \end{aligned}$$



Fig. 1. Evolution of the state x_1 and its estimate \hat{x}_1



Fig. 2. Evolution of the state x_2 and its estimate \hat{x}_2

The simulations have been performed with the initial conditions of the system chosen as: $\begin{pmatrix} x_1(0) \\ x_2(0) \end{pmatrix} = \begin{pmatrix} 50 \\ 50 \end{pmatrix}$. Note that the Lipschitz constant L = 2. The results presented below are obtained by fixing the design parameters of the observer (4) at:

$$\hat{x}_{0} = \begin{bmatrix} 10 & -20 \end{bmatrix}^{T}, \\
K = \begin{bmatrix} 0.5 & 1.2 \end{bmatrix}^{T}, \\
w_{0} = \hat{x}_{2_{0}} + \sin(\hat{x}_{1_{0}}) = -20.5440, \\
b = 8, \\
P = \begin{bmatrix} 0.8360 & -0.1900 \\ -0.1900 & 0.7758 \end{bmatrix}$$

In order to show the convergence of the observer, the following simulations display the evolution of the system for a sampling period chosen constant and equal to $\tau = 0.005$.

VI. CONLUSION

We have presented a hybrid high gain observer with dynamical observation gain for a class of continuous nonlinear triangular sampled data systems. This observer uses an intersample output predictor. Using a Lyapunov approach, an







Fig. 4. Evolution of the dynamic observation gain

explicit relation between the maximum allowable sampling time and the parameters of the proposed observer is given in order to ensure the asymptotic convergence of the observation error towards zero. An example is also presented to illustrate this result.

ACKNOWLEDGMENT

The authors would like to thank Tarek Ahmed-Ali for his valuable suggestions and comments.

REFERENCES

- K. J. Astrom and B. Wittenmark, *Computer-controlled systems: theory* and design (2nd ed.). Upper Saddle River, NJ, USA: Prentice-Hall, Inc., 1990.
- [2] A. Assoudi, E. Yaagoubi, and H. Hammouri, "Non-linear observer based on the euler discretization," *International Journal of Control*, vol. 75, pp. 784–791, 2002.
- [3] M. Arcak and D. Nesic, "A framework for nonlinear sampled-data observer design via approximate discrete-time models and emulation," *Automatica*, vol. 40, no. 11, pp. 1931–1938, 2004. [Online]. Available: http://www.sciencedirect.com/science/article/B6V21-4D34HC4-1/2/020fd4215cda0a237da05dd08b5da24c
- [4] D. S. Laila and A. Astolfi, "Sampled-data observer design for a class of nonlinear systems with applications," in 17th International Symposium on Mathematical theory of Networks and Systems, Kyoto, Japan, 2006.

- [5] G. Besançon, H. Hammouri, and S. Benamor, "State equivalence of discrete-time nonlinear control systems to state affine form up to input/output injection," *Systems & Control Letters*, vol. 33, no. 1, pp. 1 – 10, 1998. [Online]. Available: http://www.sciencedirect.com/science/article/pii/S016769119700090X
- [6] A. Dabroom and H. Khalil, "Output feedback sampled-data control of nonlinear systems using high-gain observers," *IEEE Transactions on Automatic Control*, vol. 46, no. 11, pp. 1712–1725, nov 2001.
- [7] F. Deza, E. Busvelle, J. P. Gauthier, and D. Rakotopara, "High gain estimation for nonlinear systems," *Systems & Control Letters*, vol. 18, no. 4, pp. 295–299, 1992. [Online]. Available: http://www.sciencedirect.com/science/article/B6V4X-482B4G2-3H/2/a2fc5857015792f87c80761ac7e34369
- [8] H. Hammouri, P. Kabore, S. Othman, and J. Biston, "Failure diagnosis and nonlinear observer. application to a hydraulic process," *Journal* of the Franklin Institute, vol. 339, no. 4-5, pp. 455–478, 2002. [Online]. Available: http://www.sciencedirect.com/science/article/B6V04-46RV55X-5/2/12ae7bc918ea386361aebfcb5ec95669
- [9] M. Nadri and H. Hammouri, "Design of a continuous-discrete observer for state affine systems," *Applied Mathematics Letters*, vol. 16, no. 6, pp. 967–974, 2003.
- [10] M. Nadri, H. Hammouri, and C. Astorga, "Observer design for continuous-discrete time state affine systems up to ouput injection," *European Journal of Control*, vol. 10, pp. 252–263, 2004.
- [11] I. Karafyllis and C. Kravaris, "From continuous-time design to sampled-data design of observers," *IEEE Transactions on Automatic Control*, vol. 54, no. 9, pp. 2169–2174, sept. 2009.
- [12] J. Gauthier, H. Hammouri, and S. Othman, "A simple observer for nonlinear systems applications to bioreactors," *Automatic Control, IEEE Transactions on*, vol. 37, no. 6, pp. 875–880, jun 1992.
- [13] K. Busawon, M. Farza, and H. Hammouri, "A simple observer for a class of nonlinear systems," *Applied Mathematics Letters*, vol. 11, no. 3, pp. 27 – 31, 1998. [Online]. Available: http://www.sciencedirect.com/science/article/pii/S0893965998000299
- [14] J.-P. Gauthier and I. Kupka, *Deterministic Observation Theory and Applications*. Cambridge University Press, 2001. [Online]. Available: http://dx.doi.org/10.1017/CBO9780511546648
- [15] V. Andrieu, L. Praly, and A. Astolfi, "High gain observers with updated gain and homogeneous correction terms," *Automatica*, vol. 45, no. 2, pp. 422 – 428, 2009. [Online]. Available: http://www.sciencedirect.com/science/article/pii/S0005109808004251
- [16] M. Oueder, M. Farza, R. B. Abdennour, and M. MSaad, "A high gain observer with updated gain for a class of mimo non-triangular systems," *Systems & Control Letters*, vol. 61, no. 2, pp. 298 – 308, 2012. [Online]. Available: http://www.sciencedirect.com/science/article/pii/S0167691111002921
- [17] V. V. Assche, T. Ahmed-Ali, C. A. B. Hann, and F. Lamnabhi-Lagarrigue, "High gain observer design for nonlinear systems with time varying delayed measurements," in *18th IFAC World Congress*, 2011.
- [18] K. Gu, V. Kharitonov, and J. Chen, *Stability of time-delay systems*. Birkhauser, 2003.
- [19] E. Fridman, "A refined input delay approach to sampled-data control," *Automatica*, vol. 46, no. 2, pp. 421 – 427, 2010. [Online]. Available: http://www.sciencedirect.com/science/article/pii/S000510980900541X
- [20] P. Laurent, "Asymptotic stabilization via output feedback for lower triangular systems with output dependent incremental rate," *IEEE Transactions on Automatic Control*, vol. 48, no. 6, pp. 1103–1108, 2003.