



HAL
open science

Observers of a nonlinear neutral system modelling a musical brass instrument

Thomas Hélie, Brigitte d'Andréa-Novel, Jean-Michel Coron

► **To cite this version:**

Thomas Hélie, Brigitte d'Andréa-Novel, Jean-Michel Coron. Observers of a nonlinear neutral system modelling a musical brass instrument. IFAC Workshop on Control of Distributed Parameter Systems, Jul 2009, Toulouse, France. pp.1-1. hal-01161409

HAL Id: hal-01161409

<https://hal.science/hal-01161409>

Submitted on 8 Jun 2015

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Observers of a nonlinear neutral system modelling a musical brass instrument*

T. Hélie[†]

IRCAM & CNRS, UMR 9912: Analysis-Synthesis team.

B. d'Andréa-Novel[‡]

Mines ParisTech, Centre de Robotique.

J.-M. Coron[§]

Université Pierre et Marie Curie: Laboratoire Jacques-Louis Lions; Institut Universitaire de France.

Abstract

A model of a trumpet-like instrument is described by a nonlinear neutral system controlled by the mouth pressure. The output is the pressure at the end of the pipe. A nonlinear state observer of this system is built. Local asymptotic stability of the error estimation is proved using a Lyapunov-based analysis and illustrated by simulations.

Keywords

Nonlinear neutral system, observer, Lyapunov function, musical instrument.

1 Introduction

The control of virtual musical instruments is as difficult as that of real instruments. Inverse problem techniques can help to capture skilled musicians' gestures, by recovering parameters and inputs from a target sound [1]. This paper solves a part of the global problem, building an asymptotically stable observer of the instrument state.

2 Simple model and neutral state-space representation

The trumpet-like instrument considered here couples an ODE (a valve including the mechanics of the lips) to a PDE (acoustic pipe ended with a real passive impedance) through a static nonlinear function (Bernoulli relation on the jet). Solving the PDE, the overall system can be described by the nonlinear neutral state space representation $\dot{x}(t) = f(x(t), x_3(t - \tau), \dot{x}_3(t - \tau), v(t - \frac{\tau}{2}))$, with input $v = [p_m, \dot{p}_m]^T$, output $y = [0, 0, 1 + \lambda]x$, ($\lambda \in]-1, 1[$), state $x(t) = [\xi(t) - \xi_e, \dot{\xi}, p^+(t)]^T$, where

*This work is supported by the CONSONNES project, ANR-05-BLAN-0097-01

[†]1, pl. Igor Stravinsky, 75004 Paris, France. e-mail: thomas.helie@ircam.fr

[‡]60, bd. Saint-Michel, 75272 Paris Cedex 06, France. e-mail: brigitte.dandrea-novel@mines-paristech.fr

[§]B.C. 196, 4 place Jussieu, 75252 Paris Cedex 05, France. e-mail: coron@ann.jussieu.fr

τ , p_m , ξ ($/\xi_e$), p^+ denote respectively the delay proportional to the length of the pipe, the mouth pressure, the distance between lips ($/$ at equilibrium) and the incoming pressure at the entrance of the pipe. Moreover, $f_1(x, y, z, v) = [0, 1, 0]x$, $f_2(x, y, z, v) = -\omega^2 x_1 - \alpha x_2 + \beta_0 x_3 + \lambda \beta_0 y + \beta_m v_1$, and, if $x_1 + \xi_e > 0$, $f_3(x, y, z, v) = [v_2 - 2\lambda z + \frac{2x_2(v_1 - x_3 - \lambda y)}{x_1 + \xi_e}] [1 + \mu \frac{x_3 - \lambda y}{(x_1 + \xi_e)^2}]^{-1} + \lambda z$, and if $x_1 + \xi_e \leq 0$, $f_3(x, y, z, v) = \lambda z$ where β_0 , β_m , α , ω , λ , μ are positive coefficients depending on the lips and the pipe characteristics.

3 Observer, local robustness, and simulation results

An extended Kalman filter type observer is $\hat{x}(t) = f(\hat{x}(t), \hat{x}_3(t-\tau), \hat{x}_3(t-\tau), v(t-\frac{\tau}{2})) - \Lambda_1(y(t) - \hat{y}(t)) - \Lambda_2(y(t-\tau) - \hat{y}(t-\tau))$ where the 3×1 gain matrices Λ_1 , Λ_2 are tuned so that the linearized error equation $\dot{e}(t) = \hat{A}(t)e(t) + \hat{B}(t)e_3(t-\tau) + \hat{H}(t)\dot{e}_3(t-\tau)$ is asymptotically stable where $e = x - \hat{x}$ and $A(X, Y, Z, V) = \frac{\partial f}{\partial X}(X, Y, Z, V) + \Lambda_1[0, 0, 1 + \lambda]$, $B(X, Y, Z, V) = \frac{\partial f}{\partial Y}(X, Y, Z, V) + \Lambda_2(1 + \lambda)$ and $H(X, Y, Z, V) = \frac{\partial f}{\partial Z}(X, Y, Z, V)$ are evaluated at $(X, Y, Z, V) = (\hat{x}(t), \hat{x}_3(t-\tau), \hat{x}_3(t-\tau), v(t-\frac{\tau}{2}))$.

The tuning of Λ_1 , Λ_2 and the proof rely on the four following key points: Λ_2 can be tuned such that $\hat{B} = 0$; $\|H(t)\| \leq |\lambda| < 1$; let $\chi > 0$, then Λ_1 can be chosen such that $\hat{A}(t)$ takes the form $\hat{A} = \left(\begin{array}{cc|c} 0 & 1 & 0 \\ -\omega^2 & -\alpha & 0 \\ \hline \hat{A}_{31} & \hat{A}_{32} & -\chi \end{array} \right)$, ensuring that e_1 , e_2 are decoupled from e_3 ; $\exists \kappa > 0$, $\eta > 0$ such that, for every solution of the error equation, $e_1^2(t) + e_2^2(t) + e_3^2(t) + \int_{t-\tau}^t \dot{e}_3^2(s) ds \leq \kappa e^{-\eta t} (e_1^2(0) + e_2^2(0) + e_3^2(0) + \int_{-\tau}^0 \dot{e}_3^2(s) ds)$ (see [2] for a similar proof). Simulation results are given in Fig. 1.




Figure 1: Simulations of the system (-) and of the observer (- -) from the measured output y (-) with $\alpha = 150s^{-1}$, $\chi = 160s^{-1}$, $\tau = 2/340s$, $p_m = 1.5e4Pa$ (Heaviside shape), $\omega = 535s^{-1}$, a deviation on initial conditions $\hat{x}(0) = [1e - 3, 1e - 1, 0.2 p_m]^T$ and additional gaussian noise on the measured output with variance $\sigma = 0.01p_m$.

References

- [1] T. Hélie, C. Vergez, J. Lévine, X. Rodet, *Inversion of a physical model of a trumpet*. IEEE CDC. Phoenix, USA, 1999. p 2593-2598.
- [2] J.-M. Coron, B. d'Andréa-Novel, G. Bastin, *A strict Lyapunov function for boundary control of hyperbolic systems of conservation laws*. IEEE Trans. Auto. Ctrl., 2007. p 2-11.