



**HAL**  
open science

## Quantitative Thermoacoustic Tomography with microwaves sources \*

Hassan Akhouayri, Maïtine Bergounioux, Anabela da Silva, Peter Elbau,  
Amélie Litman, Leonidas Mindrinos

► **To cite this version:**

Hassan Akhouayri, Maïtine Bergounioux, Anabela da Silva, Peter Elbau, Amélie Litman, et al.. Quantitative Thermoacoustic Tomography with microwaves sources \*. 2016. hal-01267412v1

**HAL Id: hal-01267412**

**<https://hal.science/hal-01267412v1>**

Preprint submitted on 4 Feb 2016 (v1), last revised 4 Nov 2016 (v2)

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Quantitative Thermoacoustic Tomography with microwaves sources\*

H. Akhouayri<sup>†</sup>   M. Bergounioux<sup>‡</sup>   A. Da Silva<sup>†</sup>   P. Elbau<sup>§</sup>   A. Litman<sup>†</sup>  
L. Mindrinos<sup>§</sup>

February 4, 2016

## Abstract

We investigate a quantitative thermo-acoustic tomography process. We aim to recover the electric susceptibility and the conductivity of a medium when the sources are in the microwaves range. We focus on the case where the source signal has a slow time-varying envelope. We present the direct problem coupling equations for the electric field, the temperature variation and the pressure (to be measured via sensors). Then, we give a variational formulation of the inverse problem which takes into account the entire electromagnetic, thermal and acoustic coupled system, and perform the formal computation of the optimality system.

**Keywords.** Thermo-acoustic tomography, inverse problem, optimal control, Maxwell equations.

## 1 Introduction

In this paper we investigate a model to describe the so called thermo-acoustic tomography process as precisely as possible, in the very case where the sources are in the microwaves range [11, 15, 19, 25]. Let us briefly recall the principle of photo/thermo-acoustic tomography (we refer to [2, 20, 24] for a more complete description).

Photo-acoustic and thermo-acoustic tomographies (PAT & TAT) consist in transmitting a time-modulated electromagnetic wave (generally a pulse in the optical or near-infrared domain for PAT and in the microwave domain for TAT), whose energy is locally absorbed by the tissue absorbers, transformed into heat and then into acoustic (generally ultrasonic) waves via the thermo-expansion mechanism.

The physical model routinely used in PAT is similar to the one in TAT, apart from the fact that the reconstructions performed are based on input signals in different frequency bands. In TAT, one reconstructs refraction indices and absorption coefficients, in PAT, one reconstructs diffusion and absorption coefficients.

---

\*This work is supported by ANR (AVENTURES - ANR-12-BLAN-BS01-0001-01) and PHC AMADEUS, OEAD WTZ FR14/2013

<sup>†</sup>Aix-Marseille Université, CNRS, Centrale Marseille, Institut Fresnel UMR7249, 13013 Marseille, France

<sup>‡</sup>University of d'Orléans, Laboratory MAPMO, CNRS, UMR 7349, Fédération Denis Poisson, FR 2964, Bâtiment de Mathématiques, BP 6759, 45067 Orléans cedex 2, France, maitine.bergounioux@univ-orleans.fr

<sup>§</sup>Computational Science Center, University of Vienna, 1090 Vienna, Austria

Most of quantitative PAT methods assume that the initial pressure distribution has been reconstructed and then perform the identification of the absorption and/or diffusion coefficients. To achieve this goal one can use many measurements, for instance different lightning sources [3] or different wavelength sources [27]. Some authors assume that the Green function associated to the acoustic wave is known and perform the inversion with the pressure measurements [13, 22, 23]. Most models are based on the diffusion equation but there are some works that use the radiative transfer equation (RTE) as in [21]. The simplified model from PAT that only involves the pressure effects, does not take into account the optical inhomogeneity of the medium. It is then necessary to go one step further in the modelling of the medium, which will allow to reconstruct absorption coefficients. This has been achieved in [6] where the full coupled model has been investigated.

The aim of this paper is to focus on the TAT case to provide a complete model coupling electromagnetic source effects, heat transfer and pressure equations, for quantitative thermoacoustic tomography. Though, the equations are well known, such a model that fully describes the whole direct problem is new to our knowledge. Indeed, as in PAT, the few quantitative PAT methods currently available assume that the initial pressure distribution, i.e., the amount of absorbed radiation, has been first reconstructed and then perform the identification of the electromagnetic parameters, see for example [10]. In [4], the authors neglect the thermal effects and only handle the scalar Helmholtz equation. Furthermore, they use a linearized version to deal with the inverse problem to recover the absorption coefficient. In [5], they derive a similar approach for the vectorial Maxwell equation and reconstruct the absorption coefficient and the refractive index of the materials. In [1], only the Helmholtz equation is considered and an optimal control algorithm is proposed to recover the absorption coefficient from the local knowledge of the absorbed radiation.

In this paper, we present the direct problem, where the thermal effects are fully kept. Nevertheless, we focus on the very case where the source pulse has a slowly time varying envelope, which is the most relevant situation from a practical point of view [17, 26]. We also propose a way to solve the corresponding quantitative inverse problem using a variational formulation as in [6], thus taking into account the complete coupled model. The mathematical analysis and the numerical study of the inverse problem will be done in a forthcoming paper. The paper is organized as follows: we first set the description of the different processes, namely the electromagnetic, heating and acoustic ones. Then, we specify the mathematical model and present the equivalent minimization problem. The paper ends with the (formal) optimality conditions for the discretized system of equations.

## 2 The Thermo-Acoustic model

### 2.1 Electromagnetic propagation

To describe the propagation of the electromagnetic waves due to an illumination by a radio-frequency source, we consider the classical macroscopic Maxwell equations (in SI units) and the constitutive relations between the electric displacement  $D$ , the electric field  $E$ , the magnetic induction  $B$  and the magnetic field  $H$ . All these vectors are 3D real-valued functions of position  $x$  and time  $t$ .

### 2.1.1 Maxwell's equations

We assume that the medium is *non-magnetic, linear dielectric, isotropic* and *inhomogeneous*. Let  $\Omega \subset \mathbb{R}^3$  be a bounded domain with smooth boundary such that the exterior domain  $\mathbb{R}^3 \setminus \Omega$  is connected. The domain  $\Omega$  contains the support of the inhomogeneity we aim at recovering with the TAT technique. This domain may be possibly disconnected.

In the sequel,

- the external current density  $J^{ex}$  satisfies  $\text{supp } J^{ex}(t, \cdot) \cap \Omega = \emptyset$ , for any  $t > 0$  and is assumed to be known.
- $\chi : \mathbb{R} \times \mathbb{R}^3 \rightarrow \mathbb{R}$ ,  $(t, x) \mapsto \chi(t, x)$ , consists in a combination of the electric susceptibility  $\xi$  and the conductivity  $\sigma$  which may vary according to the medium (this will be specified in the sequel). The *exterior* part  $\chi^{ex} : \mathbb{R} \times \mathbb{R}^3 \rightarrow \mathbb{R}$  is assumed to be constant (but not necessarily equal to 0) with respect to space in the exterior domain, the so-called *background medium*. Then, we can identify  $\Omega$  as the support of  $\chi - \chi^{ex}$ . This implies that  $\hat{\chi} - \hat{\chi}^{ex}$  has (spatial) compact support as well. Here  $\hat{\chi}$  denotes the Fourier transform of  $\chi$  with respect to time (whose definition is recalled in the sequel in equation (2.2)). In addition, we assume  $\chi(t, \cdot) = 0$  and  $\chi^{ex}(t, \cdot) = 0$  for  $t < 0$ .
- $\epsilon_0, \mu_0$  are the known permittivity and permeability of vacuum, respectively. One can see examples of typical values of all the physical quantities in [subsection 2.3](#);
- $c_0 = 1/\sqrt{\epsilon_0\mu_0}$  is the speed of light in vacuum;
- as the medium is non-magnetic, we set the magnetic permeability  $\mu$  of the medium to  $\mu(t, x) = \mu_0$  for every  $(t, x) \in \mathbb{R} \times \mathbb{R}^3$ .

Let us now recall Maxwell's equations. For every  $(t, x) \in \mathbb{R} \times \mathbb{R}^3$ , the electric field  $E$ , the magnetic field  $H$  and the electric displacement  $D$  satisfy

$$\begin{aligned} \text{curl}_x E(t, x) &= -\mu_0 \frac{\partial H}{\partial t}(t, x), \\ \text{curl}_x H(t, x) &= \frac{\partial D}{\partial t}(t, x) + J(t, x). \end{aligned}$$

where we decompose the electric current density  $J$  into  $J := J^{in} + J^{ex}$ . The interior part  $J^{in}$  corresponds to the current density generated by ohmic losses while  $J^{ex}$  is due to the electromagnetic primary excitation.

As the medium is considered to be linear, isotropic, inhomogeneous and non-magnetic, we get, for every  $(t, x) \in \mathbb{R}_+ \times \mathbb{R}^3$

$$D(t, x) = \epsilon_0 \left( E(t, x) + \int_0^\infty \xi(\tau, x) E(t - \tau, x) d\tau \right) = \epsilon_0 (E + \xi *_t E)(t, x),$$

where  $*_t$  denotes the time convolution operator (indeed  $\xi(t, \cdot) = 0$  for  $t < 0$ ). This reads, in the frequency domain,

$$\hat{D}(\omega, x) = \epsilon_0 (1 + \hat{\xi}(\omega, x)) \hat{E}(\omega, x), \quad (\omega, x) \in \mathbb{R} \times \mathbb{R}^3 \quad (2.1)$$

where  $\hat{f}$  stands for the Fourier transform of a function  $f$  with respect to  $t$

$$\hat{f}(\omega, x) = \int_{-\infty}^{\infty} f(t, x) e^{i\omega t} dt, \quad (2.2)$$

and  $i^2 = -1$ . Similarly,

$$J^{in}(t, x) = \int_0^{\infty} \sigma(\tau, x) E(t - \tau, x) d\tau = (\sigma *_t E)(t, x), \quad (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3,$$

or in the frequency domain,

$$\hat{J}^{in}(\omega, x) = \hat{\sigma}(\omega, x) \hat{E}(\omega, x), \quad (\omega, x) \in \mathbb{R} \times \mathbb{R}^3. \quad (2.3)$$

Thus, the exact definition of  $\chi$  is given very easily in the frequency domain by

$$\hat{\chi}(\omega, x) = \hat{\xi}(\omega, x) + \frac{i}{\epsilon_0 \omega} \hat{\sigma}(\omega, x), \quad (\omega, x) \in \mathbb{R} \setminus \{0\} \times \mathbb{R}^3. \quad (2.4)$$

**Remark 2.1.** *We do not specify the mathematical framework by now. We assume that  $\chi$  belongs to a suitable space that allows to define  $\hat{\chi}$ . This is the case, for example if  $(\xi(\cdot, x), \sigma(\cdot, x)) \in L^2(\mathbb{R})$  and  $\sigma$  is differentiable (with respect to time).*

For any given  $\omega$ , the electromagnetic fields satisfy for any point  $x$  in  $\mathbb{R}^3$

$$\begin{aligned} \operatorname{curl}_x \hat{E}(\omega, x) &= i\omega \mu_0 \hat{H}(\omega, x), \\ \operatorname{curl}_x \hat{H}(\omega, x) &= -i\omega \epsilon_0 (1 + \hat{\chi}(\omega, x)) \hat{E}(\omega, x) + \hat{J}^{ex}(\omega, x), \end{aligned}$$

that is, for every  $(\omega, x) \in \mathbb{R} \times \mathbb{R}^3$

$$\operatorname{curl}_x \operatorname{curl}_x \hat{E}(\omega, x) - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}(\omega, x)) \hat{E}(\omega, x) = i\omega \mu_0 \hat{J}^{ex}(\omega, x). \quad (2.5)$$

If we assume that the support of all the sources  $J^{ex}$  is bounded and that the sources and the inhomogeneities are all located within a finite distance from the origin of the coordinate system, then boundary conditions at infinity are provided by the Silver-Müller radiation condition

$$\lim_{|x| \rightarrow \infty} \left( x \times \operatorname{curl}_x \hat{E} - i \frac{\omega}{c_0} \sqrt{1 + \hat{\chi}^{ex}} |x| \hat{E} \right) = 0, \quad (2.6)$$

uniformly in  $x/|x|$ . Here,  $a \times b$  denotes the  $\mathbb{R}^3$  vectorial product, while  $a \cdot b$  denotes the  $\mathbb{R}^3$  scalar product and  $|a|$  the (euclidean) associated norm of vectors  $a, b \in \mathbb{R}^3$ .

### 2.1.2 Heating function

Let us now focus on the heating function (density of absorbed power (W/m<sup>3</sup>)) caused by the electromagnetic source excitation. The total electromagnetic energy density is given by  $\mathbf{E} = \frac{1}{2}(E \cdot D + \mu_0 H \cdot H)$ . By virtue of the Maxwell equations, we get for every  $(t, x) \in \mathbb{R}_+ \times \mathbb{R}^3$

$$-\operatorname{div}_x Q(t, x) = \mu_0 \left( H \cdot \frac{\partial H}{\partial t} \right) (t, x) + \left( E \cdot \frac{\partial D}{\partial t} \right) (t, x) + (E \cdot J)(t, x),$$

where  $Q(t, x) = E(t, x) \times H(t, x)$  is the Poynting vector [14]. Therefore, considering Maxwell's equations, we obtain

$$-\operatorname{div}_x Q(t, x) = \frac{1}{2} \left( E \cdot \frac{\partial D}{\partial t} - \frac{\partial E}{\partial t} \cdot D \right) (t, x) + \frac{\partial \mathbf{E}}{\partial t} (t, x) + (E \cdot J)(t, x).$$

The absorbed power out of the electromagnetic source excitation is given by

$$\Pi(t, x) := \frac{1}{2} \left( E \cdot \frac{\partial D}{\partial t} - \frac{\partial E}{\partial t} \cdot D \right) (t, x) + (E \cdot J^{in})(t, x), \quad (2.7)$$

since the term  $\frac{\partial \mathbf{E}}{\partial t}$  describes the rate of change of the energy and the term  $J^{ex}$  only concerns the external sources.

However, the absorbed density  $\Pi_a$  has to be computed by the mean of an average on a time interval of critical length  $T_c$  sufficiently large,

$$\Pi_a(t, x) := \langle \Pi \rangle_{T_c}(t, x) = \frac{1}{T_c} \int_{t-T_c}^t \Pi(\tau, x) d\tau. \quad (2.8)$$

### 2.1.3 Slowly time-varying envelope approximation

The critical time  $T_c$  depends on the time scale coupling the different phenomena (electromagnetic, thermal and acoustic). Indeed, the acoustic and the electromagnetic waves have different wave velocities. From a numerical point of view,  $T_c$  will give the ratio between the time steps of acoustic and electromagnetic computations. This average value can be considered to be equal to the rate of the energy density deposited in the material at position  $x$ , during the total duration of one *period* or *pseudo period* of the illumination process. It can be made precise in the case where the electromagnetic signal presents a slowly time-varying envelope. This assumption makes sense when the high-frequency electromagnetic excitation signal is modulated by a pulse whose temporal width is several decades of times longer than the high-frequency oscillation period  $T_c = 2\pi/\omega_c$ . In that case, the source has a narrow bandwidth in  $W_c := [\omega_c - \Delta_c, \omega_c + \Delta_c]$ .

The excitation density current takes the form

$$J^{ex}(t, x) = \Re (j^{ex}(t, x)e^{-i\omega_c t}), \quad (2.9)$$

where  $\Re$  stands for the real part and the complex amplitude  $j^{ex}$  has a slowly varying envelope on a short period  $T_c$ . Let us recall that if  $A(t, x) = \Re (a(t, x)e^{-i\omega_c t})$  is a signal with a slowly varying envelope then

$$\left| \frac{\partial^2 a}{\partial t^2}(t, x) \right| \ll \omega_c \left| \frac{\partial a}{\partial t}(t, x) \right| \ll \omega_c^2 |a(t, x)|, \quad (t, x) \in \mathbb{R} \times \mathbb{R}^3 \quad (2.10)$$

Note that the above relation comes from

$$\frac{\partial^2 (a(t, x)e^{-i\omega_c t})}{\partial t^2} = \left[ \frac{\partial^2 a(t, x)}{\partial t^2} - 2i\omega_c \frac{\partial a(t, x)}{\partial t} - \omega_c^2 a(t, x) \right] e^{-i\omega_c t}.$$

In practice, the rate of the energy density time-averaged over the short period  $T_c$  is of interest. Before deriving the form of  $\Pi_a$  for this specific form of  $J^{ex}$ , we address the following properties:

- the electromagnetic properties of the medium, given by  $\chi$  or equivalently by  $\xi$  and  $\sigma$ , are assumed to be constant with respect to the frequency in the range  $W_c$  and depend only on the central frequency, namely,

$$\hat{\xi}(\omega, x) \simeq \hat{\xi}(\omega_c, x), \quad \hat{\sigma}(\omega, x) \simeq \hat{\sigma}(\omega_c, x), \quad \omega \in W_c.$$

- If the current density is given by equation (2.9), then the quantities  $E, D$  and  $J^{in}$  admit the same decomposition with slowly varying amplitude:

$$\begin{aligned} E(t, x) &= \Re(e(t, x)e^{-i\omega_c t}), & e(t, x) &= \frac{e^{i\omega_c t}}{\pi} \int_0^\infty \hat{E}(\omega, x)e^{-i\omega t} d\omega \\ D(t, x) &= \Re(d(t, x)e^{-i\omega_c t}), & d(t, x) &= \frac{e^{i\omega_c t}}{\pi} \int_0^\infty \hat{D}(\omega, x)e^{-i\omega t} d\omega \\ J^{in}(t, x) &= \Re(j^{in}(t, x)e^{-i\omega_c t}), & j^{in}(t, x) &= \frac{e^{i\omega_c t}}{\pi} \int_0^\infty \hat{J}^{in}(\omega, x)e^{-i\omega t} d\omega. \end{aligned}$$

This follows from the unique solvability of Maxwell's equations and the fact that  $\hat{E}, \hat{D}$  and  $\hat{J}^{in}$  are also supported in  $W_c$ . In particular,

$$d(t, x) \simeq \epsilon_0(1 + \hat{\xi}(\omega_c, x))e(t, x).$$

This comes from

$$\begin{aligned} d(t, x)e^{-i\omega_c t} &= \frac{1}{\pi} \int_0^\infty \hat{D}(\omega, x)e^{-i\omega t} d\omega \\ &= \frac{1}{\pi} \int_{W_c} \epsilon_0(1 + \hat{\xi}(\omega, x))\hat{E}(\omega, x)e^{-i\omega t} d\omega \\ &\simeq \frac{\epsilon_0}{\pi}(1 + \hat{\xi}(\omega_c, x)) \int_{W_c} \hat{E}(\omega, x)e^{-i\omega t} d\omega \\ &= \epsilon_0(1 + \hat{\xi}(\omega_c, x))e(t, x)e^{-i\omega_c t}. \end{aligned}$$

Similarly,

$$j^{in}(t, x) \simeq \hat{\sigma}(\omega_c, x)e(t, x).$$

- Let  $A(t, x) = \Re(a(t, x)e^{-i\omega_c t})$  and  $B(t, x) = \Re(b(t, x)e^{-i\omega_c t})$  be two slowly varying envelope signals. We obtain for the averaged value over  $T_c$  for the product of these two functions

$$\langle A \cdot B \rangle_{T_c}(t, x) \simeq \frac{1}{2} \Re(a(t, x) \cdot \overline{b(t, x)}), \quad (2.11)$$

since

$$\begin{aligned} A \cdot B &= \frac{1}{4} \left( a e^{-i\omega_c t} + \overline{a e^{-i\omega_c t}} \right) \cdot \left( b e^{-i\omega_c t} + \overline{b e^{-i\omega_c t}} \right) \\ &= \frac{1}{4} \left( a \cdot b e^{-i2\omega_c t} + \overline{a \cdot b} e^{i2\omega_c t} \right) + \frac{1}{4} (a \cdot \bar{b} + \bar{a} \cdot b). \end{aligned}$$

Here  $\bar{a}$  stands for the complex conjugate of  $a$ . The first two terms correspond to a signal with high frequency components while the last two terms are slowly varying with respect to  $t$ . Thus, their short-time average value is given by

$$\langle A \cdot B \rangle_{T_c}(t, x) \simeq \frac{1}{4} \langle a \cdot \bar{b} + \bar{a} \cdot b \rangle_{T_c}(t, x),$$

resulting in (2.11). One can also show that  $\langle A \cdot \frac{\partial A}{\partial t} \rangle_{T_c}(t, x) \simeq 0$ .

Therefore, the short-time averaged absorbed energy  $\Pi_a$  defined in equation (2.8), using (2.4), (2.11) and the above assumptions, is given by

$$\Pi_a(t, x) \simeq \frac{\epsilon_0 \omega_c}{2} \Im(\hat{\chi}(\omega_c, x)) |e(t, x)|^2 = \frac{\epsilon_0 \omega_c}{2\pi^2} \Im(\hat{\chi}(\omega_c, x)) \left| \int_0^\infty \hat{E}(\omega, x) e^{-i\omega t} d\omega \right|^2. \quad (2.12)$$

where  $\Im(a)$  stands for the imaginary part of the complex number  $a$ .

## 2.2 Pressure and temperature equations

Once we have estimated the absorbed energy  $\Pi_a$ , we may focus on the heating/pressure wave generation processes. Temperature rise and pressure are coupled. Note that most of the TAT models of the literature do not consider the heating process, which is often assumed to be *instantaneous*. This approximation can be justified in the photo-acoustic case, where time scales are quite different: roughly speaking the lightning (and heating) process is much faster than the acoustic wave propagation. When the source is a radio-frequency one, this assumption may not be relevant any longer.

According to [8], the temperature and the pressure are determined by coupled equations which derive from the mass, momentum and energy conservation equations. Assuming that the variations in temperature and pressure are weak, the nonlinear effects are neglected and we obtain the following set of equations, for the temperature rise  $\theta$  and the pressure perturbation  $p$  from the equilibrium steady state:

$$\begin{cases} \frac{\partial^2}{\partial t^2} (K_\theta p - \beta \theta)(t, x) = \operatorname{div}_x \left( \frac{1}{\rho} \nabla p \right)(t, x), & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3, \\ \frac{\partial}{\partial t} (\rho C_p \theta - \theta_0 \beta p)(t, x) = \operatorname{div}_x (\kappa \nabla \theta)(t, x) + \Pi_a(t, x), & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3, \end{cases}$$

where

- $K_\theta$  is the isothermal compressibility,
- $\beta$  is the volume thermal expansivity,
- $\rho$  is the mass density at steady state,
- $\kappa$  is the thermal conductivity,
- $\theta_0$  is the background temperature,
- and  $C_p$  is the isobar specific heat capacity (quantity of heat required to raise the temperature of a unit mass).



All these parameter are assumed to be independent of the time  $t$ , but may depend on the position  $x$ , see [Table 1](#) for some typical values of these parameters.

A combination of the above equations leads to

$$\left( \rho K_\theta - \frac{\theta_0 \beta^2}{C_p} \right) \frac{\partial^2 p}{\partial t^2} - \rho \operatorname{div}_x \left( \frac{1}{\rho} \nabla p \right) = \frac{\beta}{C_p} \frac{\partial \Pi_a}{\partial t} + \frac{\beta}{C_p} \frac{\partial}{\partial t} \operatorname{div}_x (\kappa \nabla \theta).$$

Let us introduce the acoustic wave velocity  $v_s$  which is defined by

$$\frac{1}{v_s^2} = \rho K_\theta - \frac{\theta_0 \beta^2}{C_p} \quad (2.13)$$

to obtain the thermo-acoustic equation in heterogeneous media

$$\frac{1}{v_s^2} \frac{\partial^2 p}{\partial t^2} - \rho \operatorname{div}_x \left( \frac{1}{\rho} \nabla p \right) = \frac{\beta}{C_p} \frac{\partial \Pi_a}{\partial t} + \frac{\beta}{C_p} \frac{\partial}{\partial t} \operatorname{div}_x (\kappa \nabla \theta).$$

We further introduce the Grüneisen parameter  $\Gamma$  defined as

$$\Gamma = \frac{\beta v_s^2}{C_p}. \quad (2.14)$$

It is worth mentioning that  $v_s$  and the Grüneisen parameter  $\Gamma$  may be spatially heterogeneous. The coupled equations now read

$$\begin{cases} \frac{\partial^2 p}{\partial t^2} - \rho v_s^2 \operatorname{div}_x \left( \frac{1}{\rho} \nabla p \right) - \Gamma \frac{\partial}{\partial t} \operatorname{div}_x (\kappa \nabla \theta) = \Gamma \frac{\partial \Pi_a}{\partial t}, & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3, \\ \frac{\partial \theta}{\partial t} - \frac{1}{\rho C_p} \operatorname{div}_x (\kappa \nabla \theta) - \frac{\theta_0 \beta}{\rho C_p} \frac{\partial p}{\partial t} = \frac{\Pi_a}{\rho C_p}, & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3. \end{cases} \quad (2.15)$$

The initial conditions are such that there are no temperature or pressure differences before the absorption of the electromagnetic energy:

$$\theta(0, x) = 0, \quad p(0, x) = 0, \quad \frac{\partial p}{\partial t}(0, x) = 0, \quad x \in \mathbb{R}^3.$$

Let us now introduce

$$P(t, x) = \int_0^t p(\tau, x) d\tau,$$

which corresponds to the integrated pressure. As  $\frac{\partial P}{\partial t} = p$ , integrating the first equation in [\(2.15\)](#) with respect to  $t$  gives

$$\begin{cases} \frac{\partial^2 P}{\partial t^2} - \rho v_s^2 \operatorname{div}_x \left( \frac{1}{\rho} \nabla P \right) - \Gamma \operatorname{div}_x (\kappa \nabla \theta) = \Gamma \Pi_a, & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3, \\ \frac{\partial \theta}{\partial t} - \frac{1}{\rho C_p} \operatorname{div}_x (\kappa \nabla \theta) - \frac{\theta_0 \beta}{\rho C_p} \frac{\partial^2 P}{\partial t^2} = \frac{\Pi_a}{\rho C_p}, & (t, x) \in \mathbb{R}_+ \times \mathbb{R}^3. \end{cases} \quad (2.16)$$

with the initial conditions

$$\theta(0, x) = 0, \quad P(0, x) = 0, \quad \frac{\partial P}{\partial t}(0, x) = 0, \quad x \in \mathbb{R}^3. \quad (2.17)$$

### 2.3 Typical values of soft tissues

To be able to fully understand the time scale and evolution of the various physical quantities, some typical values of the various physical parameters are provided in [Table 1](#). These typical values correspond to the ones of soft tissues that can be found when one considers a biomedical application, as for example breast cancer imaging [[7](#), [9](#), [12](#), [16](#)].

Parameter	Symbol	Value	Units
Permittivity of the vacuum	$\epsilon_0$	$8.85 \cdot 10^{-12}$	F.m <sup>-1</sup>
Permeability of the vacuum	$\mu_0$	$1.25 \cdot 10^{-6}$	H.m <sup>-1</sup>
Electric susceptibility (fat/glandular)	$\xi$	7.3 / 35.5	-
Conductivity (fat/glandular)	$\sigma$	0.23 / 1.34	S.m <sup>-1</sup>
Isobar specific heat capacity	$C_p$	$3.5 - 4 \times 10^3$	J.K <sup>-1</sup> .kg <sup>-1</sup>
Isothermal compressibility	$K_\theta \sim \frac{1}{\rho v_s^2}$	$5 \times 10^{-10}$	Pa <sup>-1</sup>
Volume thermal expansivity	$\beta$	$4 \times 10^{-4}$	K <sup>-1</sup>
Mass density	$\rho$	1000	kg.m <sup>-3</sup>
Thermal conductivity	$\kappa$	0.4	W.m <sup>-1</sup> .K <sup>-1</sup>
Background temperature (20°C)	$\theta_0$	293	K

Table 1: Approximated values of the physical parameters. The electric susceptibility and conductivity are measured at 3 GHz and at room temperature and correspond to fat and glandular tissues, respectively.

## 3 Modelling of the inverse problem within the slowly time-varying envelope approximation

### 3.1 The infinite dimensional model

As we have already seen, if the electromagnetic signal presents a slowly time-varying envelope, meaning that  $J^{ex}$  takes the form [\(2.9\)](#), then  $\hat{E}$  and  $\hat{\chi}$  admit frequency support in  $W_c = [\omega_c - \Delta_c, \omega_c + \Delta_c]$  and

$$\hat{\chi}(\omega, x) \simeq \hat{\chi}(\omega_c, x) \quad \text{for all } x \in \mathbb{R}^3, \omega \in W_c.$$

In the sequel, we denote  $\hat{\chi}_c := \hat{\chi}(\omega_c, \cdot)$  and  $\hat{\chi}_c^{ex} := \hat{\chi}^{ex}(\omega_c, \cdot)$ . We recall that  $\hat{\chi}_c - \hat{\chi}_c^{ex}$  has (spatial) compact support.

So, putting together the equations [\(2.5\)](#), [\(2.12\)](#) and [\(2.16\)](#), the direct problem reads: Solve the system

$$\left\{ \begin{array}{l} \text{curl}_x \text{curl}_x \hat{E} - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c) \hat{E} = i\omega\mu_0 \hat{J}^{ex} \text{ in } W_c \times \mathbb{R}^3 \end{array} \right. \quad (3.1a)$$

$$\left\{ \begin{array}{l} \Pi_a(t, x) = \frac{\epsilon_0 \omega_c}{2\pi^2} \mathfrak{S}(\hat{\chi}_c)(x) \left| \int_{W_c} \hat{E}(\omega, x) e^{-i\omega t} d\omega \right|^2 \text{ in } \mathbb{R}_+ \times \mathbb{R}^3 \end{array} \right. \quad (3.1b)$$

$$\left\{ \begin{array}{l} \frac{\partial^2 P}{\partial t^2} - \rho v_s^2 \text{div}_x \left( \frac{1}{\rho} \nabla P \right) - \Gamma \text{div}_x (\kappa \nabla \theta) = \Gamma \Pi_a \text{ in } \mathbb{R}_+ \times \mathbb{R}^3, \end{array} \right. \quad (3.1c)$$

$$\left\{ \begin{array}{l} \frac{\partial \theta}{\partial t} - \frac{1}{\rho C_p} \text{div}_x (\kappa \nabla \theta) - \frac{\theta_0 \beta}{\rho C_p} \frac{\partial^2 P}{\partial t^2} = \frac{\Pi_a}{\rho C_p} \text{ in } \mathbb{R}_+ \times \mathbb{R}^3, \end{array} \right. \quad (3.1d)$$

with initial conditions

$$\theta(0, x) = 0, \quad P(0, x) = \frac{\partial P}{\partial t}(0, x) = 0 \quad \text{for all } x \in \mathbb{R}^3, \quad (3.2)$$

together with the radiation condition

$$\lim_{|x| \rightarrow \infty} \left( x \times \operatorname{curl}_x \hat{E} - i \frac{\omega}{c_0} \sqrt{1 + \hat{\chi}^{ex}} |x| \hat{E} \right) = 0,$$

where the convergence should be uniformly in  $\frac{x}{|x|}$ , see (2.6); to obtain the Fourier transform of the electric field  $\hat{E}$ , the averaged absorbed energy  $\Pi_\alpha$ , the temperature rise  $\theta$  (supported in  $\Omega$ ) and the integrated pressure  $P$ .

**Remark 3.1.** • *There exist partial results for the Maxwell equations (3.1a). We know, for example that for a fixed frequency  $\omega_c$ , if  $\hat{\chi}_c \in L^\infty(\mathbb{C}^3)$  and  $\hat{J}_c^{ex} \in L^2(\mathbb{C}^3)$  are compact supported (up to a constant function) in  $\mathbb{R}^3$ , then the problem (3.1a) has a unique solution in  $H_{loc}(\operatorname{curl}_x, \mathbb{R}^3)$ , see [18], where*

$$H_{loc}(\operatorname{curl}_x, \mathbb{R}^3) = \{V : \mathbb{R}^3 \rightarrow \mathbb{C}^3 : V|_B \in H(\operatorname{curl}_x, B) \text{ for all balls } B \subseteq \mathbb{R}^3\}$$

and  $H(\operatorname{curl}_x, B) = \{V \in L^2(B) \mid \operatorname{curl}_x V \in L^2(B)\}$ .

• *There are no straightforward existence and/or uniqueness results for the coupled system (3.1c) - (3.1d). If we fix one of the variables  $\theta$  or  $P$ , the equations are classical and we get many existence and regularity results under assumptions on the fixed unknown. However, the coupling imposes to use specific methods (fixed point or diagonalization methods) that we don't want to check in the present paper. This will be addressed in a forthcoming work where rigorous mathematical analysis will be performed.*

**Remark 3.2.** *In the above derivation, we considered the total (electromagnetic) field. We didn't use the perturbed field (or scattered field)  $E_s$  which is directly linked to  $\hat{\chi} - \hat{\chi}^{ex}$  since the dissipation  $\Pi_a$  as a function of  $E_s$  is much more complicated.*

We are now interested in the inverse problem: given a known source  $J^{ex}$  and integrated pressure measurements  $P_{obs}$  on a set  $(0, T) \times \mathcal{W}$ , recover  $\hat{\chi}_c$ . Here, the set  $\mathcal{W}$  denotes the area of the transducers. Following [6] we define the functional  $\mathcal{J}$  by

$$\mathcal{J}(\hat{\chi}_c) = \mathcal{F}(\hat{\chi}_c) + f(\hat{\chi}_c). \quad (3.3)$$

Here  $f(\hat{\chi}_c)$  stands for a regularizing term and  $\mathcal{F}$  is a least square functional with respect to the measured integrated pressure data. We set

$$\mathcal{F}(\hat{\chi}_c) = \frac{1}{2} \int_{(0, T) \times \mathcal{W}} (P[\hat{\chi}_c](t, x) - P_{obs}(t, x))^2 dx dt$$

where  $P_{obs}$  is the measured pressure on  $(0, T) \times \mathcal{W}$  when the source signal is  $J^{ex}$ . Here  $P[\hat{\chi}_c]$  is the solution of equations (3.1c) - (3.1d) with (3.2). We may define  $f$  as

$$f(\hat{\chi}_c) = \frac{\alpha_0}{2} \int_{W_c \times \mathbb{R}^3} |\hat{\chi} - \hat{\chi}^{ex}|^2(\omega, x) d\omega dx = \frac{2\Delta_c \alpha_0}{2} \int_{\mathbb{R}^3} |\hat{\chi}_c - \hat{\chi}_c^{ex}|^2(x) dx \quad (3.4)$$

where  $\alpha_0 > 0$ , for example. Then, the minimization problem reads

$$\min_{\hat{\chi}_c \in \mathcal{U}_{ad}} \mathcal{J}(\hat{\chi}_c), \quad (3.5)$$

where  $\mathcal{U}_{ad}$  is a closed set of admissible functions  $\hat{\chi}_c$  such that  $\hat{\chi}_c = \hat{\chi}_c^{ex}$  outside  $\Omega$ .

In the sequel, we set  $\alpha = 2\Delta_c \alpha_0$  so that

$$f(\hat{\chi}_c) = \frac{\alpha}{2} \int_{\mathbb{R}^3} |\hat{\chi}_c - \hat{\chi}_c^{ex}|^2(x) dx. \quad (3.6)$$

### 3.2 Discrete formulation of the inverse problem

The above formulation is of course quite formal. The study of problem (3.5) in an infinite dimensional setting is challenging and deserves to be precisely studied. Indeed, the operator  $\mathcal{T} : \hat{\chi}_c \mapsto P[\hat{\chi}_c]$  is not easy to handle. In particular, its continuity properties strongly depend on the functional framework and regularity properties of the solutions of the strongly coupled system (3.1).

We now give a finite dimensional (discrete) formulation of the above setting to present the whole reconstruction process. We keep the same notations since we don't want to detail the discretization process. This is equivalent to perform a *formal* analysis of the inverse problem. For numerical purpose, we have replaced  $\mathbb{R}_+$  by  $(0, T)$  with some terminal time  $T$  large enough, and  $\mathbb{R}^3$  by some large ball  $\mathcal{B}$ . We use a Dirichlet boundary condition on  $\partial\mathcal{B}$  (recall that  $T$  is chosen large enough to allow it). The direct problem now reads

$$\left\{ \begin{array}{l} \text{curl}_x \text{curl}_x \hat{E} - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c) \hat{E} = i\omega\mu_0 \hat{j}^{ex} \text{ in } W_c \times \mathcal{B} \quad (3.7a) \\ \Pi_a(t, x) = \frac{\epsilon_0 \omega_c}{2\pi^2} \Im(\hat{\chi}_c(x)) \left| \int_{W_c} \hat{E}(\omega, x) e^{-i\omega t} d\omega \right|^2 \text{ in } (0, T) \times \mathcal{B} \quad (3.7b) \\ \frac{\partial^2 P}{\partial t^2} - \rho v_s^2 \text{div}_x \left( \frac{1}{\rho} \nabla P \right) - \Gamma \text{div}_x(\kappa \nabla \theta) = \Gamma \Pi_a, \text{ in } (0, T) \times \mathcal{B} \quad (3.7c) \\ \frac{\partial \theta}{\partial t} - \frac{1}{\rho C_p} \text{div}_x(\kappa \nabla \theta) - \frac{\theta_0 \beta}{\rho C_p} \frac{\partial^2 P}{\partial t^2} = \frac{\Pi_a}{\rho C_p}, \text{ in } (0, T) \times \mathcal{B} \quad (3.7d) \end{array} \right.$$

with initial conditions

$$\theta(0, x) = 0, \quad P(0, x) = \frac{\partial P}{\partial t}(0, x) = 0 \text{ in } \mathcal{B},$$

and boundary conditions

$$\begin{aligned} \hat{E}(\omega, x) &= 0, \quad (\omega, x) \in W_c \times \partial\mathcal{B} \\ P(t, x) &= 0, \quad \frac{\partial P}{\partial t}(t, x) = 0, \quad \theta(t, x) = 0, \quad (t, x) \in (0, T) \times \partial\mathcal{B}. \end{aligned}$$

**Remark 3.3.** We decided to set a Dirichlet boundary condition for the  $\hat{E}$  field. This is the case for example if either

- $\hat{\chi}^{ex}$  is lossless and the ball  $\mathcal{B}$  is very large,

- $\hat{\chi}^{ex}$  is lossless and there is a metallic casing around  $\mathcal{B}$ , or
- $\hat{\chi}^{ex}$  is lossy and the waves will be automatically damped.

Another possibility could be to use a Robin type boundary, which can be seen as a first-order approximation of the Silver-Müller radiation boundary condition on a bounded surface:

$$n \times \text{curl}_x \hat{E} - i \frac{\omega}{c_0} \sqrt{1 + \hat{\chi}^{ex}} n \times n \times \hat{E} = 0,$$

where  $n$  is the unit outward normal vector on  $\partial\mathcal{B}$ .

Note that, the issue is the same for the acoustic pressure, but as we are looking for  $p$  (or  $P$ ) which only correspond to the variation of the pressure with respect to the initial one, it seems rather natural to assume that  $P = 0$  on the boundary.

**Theorem 3.1.** *Assume  $\mathcal{U}_{ad}$  is bounded or  $\alpha > 0$ . Then, the discrete minimization problem has at least a solution.*

*Proof.* This is clear since either the admissible set  $\mathcal{U}_{ad}$  is bounded or  $\mathcal{J}$  is coercive. Moreover, the continuity properties are fulfilled in the discrete framework.  $\square$

Uniqueness is a challenging problem, since the cost functional is not convex (because of the fitting data term). Nevertheless, any solution  $\hat{\chi}_c^*$  satisfies

$$\nabla \mathcal{J}(\hat{\chi}_c^*) \cdot (\hat{\chi}_c - \hat{\chi}_c^*) \geq 0 \quad \text{for all } \hat{\chi}_c \in \mathcal{U}_{ad}. \quad (3.8)$$

Next subsections are devoted to the computation of  $\nabla \mathcal{J}(\hat{\chi}_c^*)$  and the setting of a necessary optimality system.

We first start to compute  $\nabla \mathcal{F}(\hat{\chi}_c^*) \cdot \hat{\chi}_c$  before tackling the term in  $\nabla f(\hat{\chi}_c^*) \cdot \hat{\chi}_c$ . In the sequel  $\hat{\chi}_c^*$  denotes an optimal solution and  $\hat{E}^*$ ,  $P^*$  and  $\theta^*$  are the corresponding solutions of (the discrete) system (3.7). We previously adopted the notation  $\cdot$  for the  $\mathbb{R}^3$  inner product. However, in the sequel we omit this dot, to make computations more readable. More precisely, if  $A = (A_k)_{1 \leq k \leq 3}$  and  $B = (B_k)_{1 \leq k \leq 3}$  are vector valued functions from  $\mathbb{R}^3$  to  $\mathbb{R}^3$  we write  $A(x)B(x)$  instead of  $A(x) \cdot B(x) (= \sum_{k=1}^3 A_k(x)B_k(x))$ .

### 3.3 The (discrete) pressure-temperature system

The coupling between equations (3.7a) - (3.7b) and (3.7c) - (3.7d) is done via the  $\Pi_a$  term. Let  $\hat{\chi}_c \in \mathcal{U}_{ad}$  and denote by  $\dot{\Pi}_a$  the derivative of  $\Pi_a$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$ :

$$\dot{\Pi}_a \cdot \hat{\chi}_c := \lim_{\rho \rightarrow 0^+} \frac{\Pi_a(\hat{\chi}_c^* + \rho \hat{\chi}_c) - \Pi_a(\hat{\chi}_c^*)}{\rho}.$$

Let us denote similarly  $\dot{P}$ ,  $\dot{\theta}$  the derivatives of  $P$  and  $\theta$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$ . So

$$\nabla \mathcal{F}(\hat{\chi}_c^*) \cdot \hat{\chi}_c = \int_{(0,T) \times \mathcal{W}} (P^* - P_{obs}) \dot{P} dt dx,$$

where  $P^* = P[\hat{\chi}_c^*]$  and  $\theta^* = \theta[\hat{\chi}_c^*]$ . The equations satisfied by  $\dot{P}$  and  $\dot{\theta}$  are

$$\begin{cases} \frac{\partial^2 \dot{P}}{\partial t^2} - \rho v_s^2 \text{div}_x \left( \frac{1}{\rho} \nabla \dot{P} \right) - \Gamma \text{div}_x (\kappa \nabla \dot{\theta}) = \Gamma \dot{\Pi}_a & \text{in } (0, T) \times \mathcal{B}, \\ \rho C_p \frac{\partial \dot{\theta}}{\partial t} - \text{div}_x (\kappa \nabla \dot{\theta}) - \theta_0 \beta \frac{\partial^2 \dot{P}}{\partial t^2} = \dot{\Pi}_a & \text{in } (0, T) \times \mathcal{B}, \end{cases} \quad (3.9a)$$

$$(3.9b)$$

with initial and boundary conditions

$$\begin{cases} \dot{\theta}(0, x) = 0, \dot{P}(0, x) = 0, \frac{\partial \dot{P}}{\partial t}(0, x) = 0, & x \in \mathcal{B} \end{cases} \quad (3.10a)$$

$$\begin{cases} \dot{P}(t, x) = 0, \frac{\partial \dot{P}}{\partial t}(t, x) = 0, \dot{\theta}(t, x) = 0, & (t, x) \in (0, T) \times \partial\mathcal{B}. \end{cases} \quad (3.10b)$$

Let us define the adjoint system for  $(P^*, \theta^*)$ . We consider the following system for  $q^*$  and  $\zeta^*$ :

$$\begin{cases} \frac{\partial^2 q^*}{\partial t^2} - \theta_0 \beta \frac{\partial^2 \zeta^*}{\partial t^2} - \operatorname{div}_x \left( \frac{1}{\rho} \nabla (\rho v_s^2 q^*) \right) = (P^* - P_{obs}) \mathbf{1}_{(0, T) \times \mathcal{W}} & \text{in } (0, T) \times \mathcal{B} \end{cases} \quad (3.11a)$$

$$\begin{cases} -\rho C_p \frac{\partial \zeta^*}{\partial t} - \operatorname{div}_x (\kappa \nabla (\Gamma q^*)) - \operatorname{div}_x (\kappa \nabla \zeta^*) = 0 & \text{in } (0, T) \times \mathcal{B}, \end{cases} \quad (3.11b)$$

with initial and boundary conditions

$$\begin{cases} \zeta^*(T, x) = 0, q^*(T, x) = 0, \frac{\partial q^*}{\partial t}(T, x) = 0, & x \in \mathcal{B} \end{cases} \quad (3.12a)$$

$$\begin{cases} q^*(t, x) = 0, \frac{\partial q^*}{\partial t}(t, x) = 0, \zeta^*(t, x) = 0, & (t, x) \in (0, T) \times \partial\mathcal{B}. \end{cases} \quad (3.12b)$$

Then we get

**Lemma 3.1.** *The gradient of  $\mathcal{F}$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$  is given by*

$$\nabla \mathcal{F}(\hat{\chi}_c^*) \cdot \hat{\chi}_c = \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*) \dot{\Pi}_a \, dt \, dx.$$

where  $(q^*, \zeta^*)$  are defined by the adjoint equations (3.11) - (3.12), and  $\dot{\Pi}_a$  is the derivative of  $\Pi_a$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$ .

*Proof.* Using integration by parts, we obtain

$$\begin{aligned} \nabla \mathcal{F}(\hat{\chi}_c^*) \cdot \hat{\chi}_c &= \int_{(0, T) \times \mathcal{W}} (P^* - P_{obs}) \dot{P} \, dt \, dx = \int_{(0, T) \times \mathcal{B}} (P^* - P^{obs}) \dot{P} \, \mathbf{1}_{(0, T) \times \mathcal{W}} \, dt \, dx \\ &= \int_{(0, T) \times \mathcal{B}} \left[ \frac{\partial^2 q^*}{\partial t^2} - \theta_0 \beta \frac{\partial^2 \zeta^*}{\partial t^2} - \operatorname{div}_x \left( \frac{1}{\rho} \nabla (\rho v_s^2 q^*) \right) \right] \dot{P} \, dt \, dx \\ &\quad + \underbrace{\int_{(0, T) \times \mathcal{B}} \left( -\rho C_p \frac{\partial \zeta^*}{\partial t} - \operatorname{div}_x (\kappa \nabla (\Gamma q^*)) - \operatorname{div}_x (\kappa \nabla \zeta^*) \right) \dot{\theta} \, dt \, dx}_{=0} \\ &= \int_{(0, T) \times \mathcal{B}} \left\{ \left[ \frac{\partial^2 \dot{P}}{\partial t^2} - \rho v_s^2 \operatorname{div}_x \left( \frac{1}{\rho} \nabla \dot{P} \right) \right] q^* - \theta_0 \beta \frac{\partial^2 \dot{P}}{\partial t^2} \zeta^* \right\} \, dt \, dx \\ &\quad + \int_{(0, T) \times \mathcal{B}} \left\{ \left( \rho C_p \frac{\partial \dot{\theta}}{\partial t} - \operatorname{div}_x (\kappa \nabla \dot{\theta}) \right) \zeta^* - \Gamma \operatorname{div}_x (\kappa \nabla \dot{\theta}) q^* \right\} \, dt \, dx \\ &= \int_{(0, T) \times \mathcal{B}} \left[ \frac{\partial^2 \dot{P}}{\partial t^2} - \rho v_s^2 \operatorname{div}_x \left( \frac{1}{\rho} \nabla \dot{P} \right) - \Gamma \operatorname{div}_x (\kappa \nabla \dot{\theta}) \right] q^* \, dt \, dx \end{aligned}$$

$$\begin{aligned}
& + \int_{(0,T) \times \mathcal{B}} \left( \rho C_p \frac{\partial \dot{\theta}}{\partial t} - \operatorname{div}_x(\kappa \nabla \dot{\theta}) - \theta_0 \beta \frac{\partial^2 \dot{P}}{\partial t^2} \right) \zeta^* dt dx \\
& = \int_{(0,T) \times \mathcal{B}} (\Gamma q^* + \zeta^*) \dot{\Pi}_a dt dx.
\end{aligned}$$

□

Now, we have to estimate  $\dot{\Pi}_a$  introducing an adjoint equation for the electromagnetic part.

### 3.4 The (discrete) Maxwell equations

Let us now define the adjoint state  $\Phi^*$  associated to  $E^*$ . To simplify the notation, we introduce the quantities

$$\mathcal{E}^*(t, x) = \int_{W_c} \hat{E}^*(\omega, x) e^{-i\omega t} d\omega \quad \text{and} \quad \dot{\mathcal{E}}^*(t, x) = \int_{W_c} \dot{\hat{E}}^*(\omega, x) e^{-i\omega t} d\omega. \quad (3.13)$$

Then, we set  $\Phi^*$  to be the solution of the equation

$$\operatorname{curl}_x \operatorname{curl}_x \Phi^*(\omega, \cdot) - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c^*) \Phi^*(\omega, \cdot) = \Im(\hat{\chi}_c^*) \left( \int_0^T (\Gamma q^* + \zeta^*)(t, \cdot) \overline{\mathcal{E}^*(t, \cdot)} e^{-i\omega t} dt \right) \quad \text{in } W_c \times \mathcal{B} \quad (3.14)$$

with the homogeneous Dirichlet boundary conditions

$$\Phi^*(\omega, x) = 0, \quad (\omega, x) \in W_c \times \partial \mathcal{B}.$$

**Proposition 3.1.** *The gradient of  $\mathcal{F}$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$  is given by*

$$\begin{aligned}
\nabla \mathcal{F}(\hat{\chi}_c^*) \cdot \hat{\chi}_c &= \frac{\epsilon_0 \omega_c}{2\pi^2} \int_{\mathcal{B}} \left\{ \left( \int_0^T (\Gamma q^* + \zeta^*)(t, x) |\mathcal{E}^*(t, x)|^2 dt \right) \Im(\hat{\chi}_c(x)) \right. \\
& \quad + 2 \left( \Re \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Re(\hat{\chi}_c(x)) \\
& \quad \left. - 2 \left( \Im \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Im(\hat{\chi}_c(x)) \right\} dx
\end{aligned} \quad (3.15)$$

where  $(q^*, \zeta^*)$  are defined by the adjoint equations (3.11) - (3.12), and  $\Phi^*$  by (3.14).

*Proof.* Let us denote by  $\dot{\hat{E}}$  the derivative of  $\hat{E}$  at  $\hat{\chi}_c^*$  in the direction  $\hat{\chi}_c$ . The equations satisfied by  $\dot{\Pi}_a$  and  $\dot{\hat{E}}$  are

$$\left\{ \begin{aligned}
& \operatorname{curl}_x \operatorname{curl}_x \dot{\hat{E}} - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c^*) \dot{\hat{E}} = \frac{\omega^2 \hat{E}^*}{c_0^2} \hat{\chi}_c \quad \text{in } W_c \times \mathcal{B} \quad (3.16a) \\
& \dot{\Pi}_a(t, x) = \frac{\epsilon_0 \omega_c}{\pi^2} \left( \frac{1}{2} \Im(\hat{\chi}_c(x)) \left| \int_{W_c} \hat{E}^*(\omega, x) e^{-i\omega t} d\omega \right|^2 + \right. \\
& \quad \left. \Im(\hat{\chi}_c^*(x)) \Re \left[ \int_{W_c} \dot{\hat{E}}(\omega, x) e^{-i\omega t} d\omega \int_{W_c} \overline{\hat{E}^*(\omega, x) e^{-i\omega t} d\omega} \right] \right) \quad \text{in } (0, T) \times \mathcal{B}. \quad (3.16b)
\end{aligned} \right.$$

Equivalently, with the notation (3.13),

$$\dot{\Pi}_a(t, x) = \frac{\epsilon_0 \omega_c}{2\pi^2} \Im(\hat{\chi}_c(x)) |\mathcal{E}^*(t, x)|^2 + \frac{\epsilon_0 \omega_c}{\pi^2} \Im(\hat{\chi}_c^*(x)) \Re \left[ \dot{\mathcal{E}}(t, x) \overline{\mathcal{E}^*(t, x)} \right] \quad \text{in } (0, T) \times \mathcal{B}.$$

So

$$\begin{aligned} \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*) \dot{\Pi}_a(t, x) dt dx &= \frac{\epsilon_0 \omega_c}{2\pi^2} \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*) \Im(\hat{\chi}_c(x)) |\mathcal{E}^*(t, x)|^2 dt dx \\ &\quad + \frac{\epsilon_0 \omega_c}{\pi^2} \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*) \Im(\hat{\chi}_c^*(x)) \Re \left( \dot{\mathcal{E}}(t, x) \overline{\mathcal{E}^*(t, x)} \right) dt dx. \end{aligned}$$

As the  $\text{curl}_x \text{curl}_x$  operator is self adjoint, performing integration by parts gives

$$\begin{aligned} &\int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*)(t, x) \Im(\hat{\chi}_c^*(x)) \dot{\mathcal{E}}(t, x) \overline{\mathcal{E}^*(t, x)} dx dt \\ &= \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*)(t, x) \Im(\hat{\chi}_c^*(x)) \left( \int_{W_c} \dot{\hat{E}}(\omega, x) e^{-i\omega t} d\omega \right) \overline{\mathcal{E}^*(t, x)} dx dt \\ &= \int_{W_c \times \mathcal{B}} \Im(\hat{\chi}_c^*(x)) \left( \int_0^T (\Gamma q^* + \zeta^*)(t, x) \overline{\mathcal{E}^*(t, x)} e^{-i\omega t} dt \right) \dot{\hat{E}}(\omega, x) d\omega dx \\ &= \int_{W_c \times \mathcal{B}} \left( \text{curl}_x \text{curl}_x \Phi^* - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c^*) \Phi^* \right) (\omega, x) \dot{\hat{E}}(\omega, x) d\omega dx \\ &= \int_{W_c \times \mathcal{B}} \left( \text{curl}_x \text{curl}_x \dot{\hat{E}} - \frac{\omega^2}{c_0^2} (1 + \hat{\chi}_c^*) \dot{\hat{E}} \right) (\omega, x) \Phi^*(\omega, x) d\omega dx \\ &= \int_{W_c \times \mathcal{B}} \frac{\omega^2 \hat{E}^* \Phi^*}{c_0^2} (\omega, x) \hat{\chi}_c(x) d\omega dx \\ &= \int_{\mathcal{B}} \left( \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \hat{\chi}_c(x) dx. \end{aligned}$$

This gives the result since

$$\begin{aligned} &\int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*)(t, x) \Im(\hat{\chi}_c^*(x)) \Re \left( \dot{\mathcal{E}}(t, x) \overline{\mathcal{E}^*(t, x)} \right) dt dx \\ &= \Re \left( \int_{(0, T) \times \mathcal{B}} (\Gamma q^* + \zeta^*)(t, x) \Im(\hat{\chi}_c^*(x)) \dot{\mathcal{E}}(t, x) \overline{\mathcal{E}^*(t, x)} dt dx \right) \\ &= \Re \left( \int_{\mathcal{B}} \left( \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \hat{\chi}_c(x) dx \right) \\ &= \int_{\mathcal{B}} \Re \left( \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Re(\hat{\chi}_c(x)) dx \\ &\quad - \int_{\mathcal{B}} \Im \left( \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Im(\hat{\chi}_c(x)) dx \end{aligned}$$

□



### 3.5 The optimality system

For the regularization term  $f$ , we find that

$$\begin{aligned}\nabla f(\hat{\chi}_c^*) \cdot \hat{\chi}_c &= \alpha \Re \left( \int_{\mathcal{B}} \overline{(\hat{\chi}_c^* - \hat{\chi}_c^{ex})}(x) \hat{\chi}_c(x) dx \right) \\ &= \alpha \int_{\mathcal{B}} (\Re(\hat{\chi}_c^* - \hat{\chi}_c^{ex}) \Re(\hat{\chi}_c) + \Im(\hat{\chi}_c^* - \hat{\chi}_c^{ex}) \Im(\hat{\chi}_c))(x) dx.\end{aligned}\quad (3.17)$$

Thus, putting together the expressions (3.15) and (3.17), we have for every  $\hat{\chi}_c \in \mathcal{U}_{ad}$

$$\begin{aligned}\nabla \mathcal{J}(\hat{\chi}_c^*) \cdot (\hat{\chi}_c - \hat{\chi}_c^*) &= \frac{\epsilon_0 \omega_c}{2\pi^2} \int_{\mathcal{B}} \left\{ \left( \int_0^T (\Gamma q^* + \zeta^*)(t, x) |\mathcal{E}^*(t, x)|^2 dt \right) \Im(\hat{\chi}_c - \hat{\chi}_c^*)(x) \right. \\ &\quad + 2 \left( \Re \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Re(\hat{\chi}_c - \hat{\chi}_c^*)(x) \\ &\quad \left. - 2 \left( \Im \int_{W_c} \frac{\omega^2}{c_0^2} \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega \right) \Im(\hat{\chi}_c - \hat{\chi}_c^*)(x) \right\} dx \\ &\quad + \alpha \int_{\mathcal{B}} [\Re(\hat{\chi}_c^* - \hat{\chi}_c^{ex}) \Re(\hat{\chi}_c - \hat{\chi}_c^*) + \Im(\hat{\chi}_c^* - \hat{\chi}_c^{ex}) \Im(\hat{\chi}_c - \hat{\chi}_c^*)] (x) dx \geq 0.\end{aligned}\quad (3.18)$$

Decoupling with respect to real and imaginary parts, we get for any  $(v_r, v_i)$  real valued functions such that  $v_r + i\Im(\hat{\chi}_c^*) = \hat{\chi}_c \in \mathcal{U}_{ad}$  and  $\Re(\hat{\chi}_c^*) + iv_i = \hat{\chi}_c \in \mathcal{U}_{ad}$

$$\begin{cases} \int_{\mathcal{B}} \Re \left( \frac{\epsilon_0 \omega_c}{c_0^2 \pi^2} \int_{W_c} \omega^2 \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega + \alpha(\hat{\chi}_c^* - \hat{\chi}_c^{ex})(x) \right) (v_r - \Re(\hat{\chi}_c^*)) (x) dx \geq 0 & (3.19a) \\ \int_{\mathcal{B}} \left\{ \frac{\epsilon_0 \omega_c}{2\pi^2} \left( \int_0^T (\Gamma q^* + \zeta^*)(t, x) |\mathcal{E}^*(t, x)|^2 dt \right) \right. \\ \left. - \Im \left( \frac{\epsilon_0 \omega_c}{c_0^2 \pi^2} \int_{W_c} \omega^2 \hat{E}^*(\omega, x) \Phi^*(\omega, x) d\omega - \alpha(\hat{\chi}_c^* - \hat{\chi}_c^{ex})(x) \right) \right\} (v_i - \Im(\hat{\chi}_c^*)) (x) dx \geq 0. & (3.19b) \end{cases}$$

We may now give first order necessary conditions to get a solution to the discretized problem (3.5).

**Theorem 3.2.** *Let  $\chi_c^*$  be an optimal solution of the minimization problem (3.5). Then, the following optimality system is satisfied*

- *State equations: (3.7) with the corresponding initial and boundary conditions.*
- *Adjoint equations: (3.11) - (3.12) for pressure and temperature, and (3.14) for electrical field.*
- *Projection equations: (3.18) (or equivalently (3.19)).*

## 4 Conclusion

We have presented what we consider as a complete modelling of the thermo-acoustic process with microwave sources. Since the complete model is quite complex, we focused on the very case

where the source signal presents a slowly time-varying envelope which is practically relevant. We have presented the inverse and the method to solve it in a formal way. Next steps are the complete theoretical mathematical analysis in an infinite dimensional framework and the numerical experimentation (solving the optimality system). This is challenging since there are many open problems. However the electromagnetic system (in the Fourier space) and the pressure-temperature are slightly coupled. Next issue will be the mathematical study of the pressure-temperature system together with (3.11) - (3.12) and the identification of  $\Pi_a$  in a first step.

## References

- [1] H. Ammari, J. Garnier, W. Jing, and L. H. Nguyen. Quantitative thermo-acoustic imaging: An exact reconstruction formula. *J. Differential Equations*, 254:1375–1395, 2013.
- [2] S. R. Arridge. Optical tomography in medical imaging. *Inverse Problems*, 2, 1999.
- [3] G. Bal and K. Ren. Multi-source quantitative photoacoustic tomography in a diffusive regime. *Inverse Problems*, 27:20p, 2011.
- [4] G. Bal, K. Ren, G. Uhlmann, , and T. Zhou. Quantitative thermo-acoustics and related problems. *Inverse Problems*, 27(5):055007, 2011.
- [5] G. Bal and T. Zhou. Hybrid inverse problems for a system of maxwell’s equations. *Inverse Problems*, 30(5):17p, 2014.
- [6] M. Bergounioux, X. Bonnefond, T. Haberkorn, and Y. Privat. An optimal control problem in photoacoustic tomography. *Mathematical Models and Methods in Applied Sciences*, 24(14):2943–48, 2014.
- [7] M. J. Burfeindt, T. J. Colgan, R. O. Mays, J. D. Shea, N. Behdad, B. D. Van Veen, and S. C. Hagness. Mri-derived 3d-printed breast phantom for microwave breast imaging validation. *IEEE Antennas and Wireless Propagation Letters*, 11:1610–1613, 2012.
- [8] B. Cox and P.C. Beard. Modeling photoacoustic propagation in tissue using k-space techniques. In L.V. Wang, editor, *Photoacoustic Imaging and Spectroscopy*, chapter 3, pages 25–34. CRC Press, 2009.
- [9] F.A. Duck. *Physical Properties of Tissue: A Comprehensive Reference Book*. Institution of Physics & Engineering in Medicine & Biology, 2012.
- [10] P. Elbau, L. Mindrinos, and O. Scherzer. Inverse problems of combined photoacoustic and optical coherence tomography. Technical Report arXiv:1601.03320, 2016.
- [11] D. Fallon, L. Yan, G. W. Hanson, and S. K. Patch. RF testbed for thermoacoustic tomography. *Review of Scientific Instrument*, 80:064301, 2009.
- [12] S. Gabriel, R.W. Lau, and C. Gabriel. The dielectric properties of biological tissues. II. Measurements in the frequency range 10 Hz to 20 GHz. *Physics in Medicine and Biology*, 41(11):2251–2269, 1996.

- [13] H. Gao, H. Zhao, and S. Osher. Bregman methods in quantitative photoacoustic tomography. Technical Report 10-42, Univ. Calif. Los Angeles UCLA, 2010.
- [14] J.D. Jackson. *Classical Electrodynamics*. Wiley, 1998.
- [15] R. A. Kruger, W. L. Kiser, D. R. Reinecke, G. A. Kruger, and R. L. Eisenhart. Thermoacoustic computed tomography of the breast at 434 MHz. *IEEE MTT-S International Microwave Symposium Digest*, 2:591–595, 1999.
- [16] M. Lazebnik, L. McCartney, D. Popovic, C.B. Watkins, M.J. Lindstrom, J. Harter, S. Sewall, A. Magliocco, J.H. Booske, M. Okoniewski, and S.C. Hagness. A large-scale study of the ultrawideband microwave dielectric properties of normal breast tissue obtained from reduction surgeries. *Physics in Medicine and Biology*, 52:2637–2656, 2007.
- [17] C. Li, M. Pramanik, G. Ku, and L.V. Wang. Image distortion in thermoacoustic tomography caused by microwave diffraction. *Physical Review E*, 77:31923, 2008.
- [18] P. Monk. *Finite Element Methods for Maxwell’s Equations*. Oxford University Press, 2003.
- [19] L. Nie, D. Xing, D. Yang, L. Zeng, and Q. Zhou. Detection of foreign body using fast thermoacoustic tomography with a multielement linear transducer array. *Applied Physics Letters*, 90:174109, 2007.
- [20] S. K Patch and O.Scherzer. Photo- and thermo-acoustic imaging introduction. *Inverse Problems*, 6(1-10), 2007.
- [21] T. Saratoon, T. Tarvainen, B. Cox, and S. Arridge. A gradient-based method for quantitative photoacoustic tomography using the radiative transfer equation. *Inverse Problems*, 29, 2013.
- [22] P. Shao, T. Harrison, and R. J. Zemp. Iterative algorithm for multiple illumination photoacoustic tomography (mipat) using ultrasound channel data. *Biomed. Opt. Express.*, 3:3240–49, 2012.
- [23] N. Song, Deumié C., and A. Da Silva. Considering sources and detectors distributions for quantitative photoacoustic tomography (qpat). *Biomed. Opt. Express.*, 5:3960–74, 2014.
- [24] L.V. Wang, editor. *Photoacoustic Imaging and Spectroscopy*, volume 144 of *Optical Science and Engineering*. CRC Press, 2009.
- [25] L.V. Wang, X. Zhao, H. Sun, and G. Ku. Microwave-induced acoustic imaging of biological tissues. *Review of Scientific Instrument*, 70(9):3744, 1999.
- [26] X. Wang, D. R. Bauer, R. Witte, and H. Xin. Microwave-induced thermoacoustic imaging model for potential breast cancer detection. *IEEE Transactions on Biomedical Engineering*, 59(10):2782–2791, 2012.
- [27] Z. Yuan and H. Jiang. Quantitative photoacoustic tomography. *Philos. Trans. R. Soc. -Math. Phys. Eng. Sci.*, 367:3043–54, 2009.