


AUTOMATIC OPTIMAL COMMAND FOR THE LINEARIZATION OF THE CMUT OUTPUT

S. Ménigot ⁽¹⁾, D. Certon⁽²⁾, D. Gross⁽²⁾ and JM Girault⁽¹⁾

¹ Université François Rabelais de Tours, INSERM U930, 10 Bd Tonnellé, 37032 Tours, France


² Université François Rabelais de Tours, GREMAN UMR-CNRS 7347, 10 Bd Tonnellé, 37032 Tours, France





Motivation

Membrane displacement vs input voltage




- ✓ cMUTs are nonlinear devices : distortion and asymmetry,...
- ✓ Output waveform depends on the input waveform: frequency, amplitude, shape, ...
- ✓ Considerable mean displacement amplitude in a large frequency range

Simulated configuration


2D periodic array with a pitch of $25 \mu\text{m}$

Cells	:	$20 \times 20 \mu\text{m}^2$
Gap	:	200 nm
V_c	:	120 V
F_0	:	6 MHz
Excitation	:	CW
Amplitude	:	$0.5 V_c$






Motivation



- **The challenge** : to take advantage of the wide cMUT bandwidth and to control the output waveforms , **input waveforms with complex shape are required**
- **Objectives** : development of an automatic procedure to generate the optimal desired output waveform. This implies :
 - Methods for producing new non-standard input waveforms,
 - Implementation of an iterative optimization procedure in order to match the output waveform with the targeted output waveform







OUTLINE

- Motivation
- Previous literature
- Complex waveform generation with non linear filtering
- Iterative optimization procedure
- Theoretical results : application to the linearization
- Experimental results : application to the linearization
- Summary & conclusions





Previous literature




- **Previous works :** Optimal command of cMUT to linearize the output waveform
- High order harmonic components are added to the input sinus waveform
- **Amplitude and phase are tuned in order to cancel out the 2nd harmonic component of the output waveform**
- **Limitations :**
 - **Mainly done** in low frequency bandwidth : application to harmonic imaging
 - **Minimization** error criterion is defined by the harmonic to fundamental components ratio

[1] S. Zhou, P. Reynolds, and J. Hossack, "Precompensated excitation one parameter : waveforms to suppress harmonic generation in mems electrostatic transducers," IEEE T. Ultrason. Ferr. , vol. 51, no. 11, pp. 1564–1574, Nov. 2004.

[2] A. Novell, M. Legros, N. Felix, and A. Bouakaz, "Exploitation of capacitive micromachined transducers for nonlinear ultrasound imaging," IEEE T. Ultrason. Ferr. , vol. 56, no. 12, pp. 2733–2743, Dec. 2009.







OUTLINE

- Motivation
- Previous literature
- Complex waveform generation with non linear filtering
- Optimization procedure
- Theoretical results
- Experimental results
- Summary & conclusions






Complex waveform generation




- **Our approach** is an extension of previous works but it is applicable to waveform with any shape
- **a non linear filter** is used to modify the input waveform shape
- **Parameters** of the non linear filter are tuned with a simplex algorithm
- **Non linear filtering** models: Hammerstein, Volterra, Wiener...
- **Applications** : linearisation of loudspeakers, μ bubbles driving, all field of physic requiring non linear modelling





Complex waveform generation

Non Linear Filtering : principle with Hammerstein filter




$$x_n(t) = h_n(t) * x^n(t)$$

$$y(t) = \sum_{n=1}^P x_n(t) = \sum_{n=1}^P h_n(t) * x^n(t)$$


- $x(t)$ is transformed into a polynomial series
- Each n order component $x_n(t)$ corresponds to the input signal raised to power n and filtered with its own specific linear filter $h_n(t)$
- The polynome order P defines the highest frequency harmonic component (we fix $P=3$)





Complex waveform generation


Volterra Filtering : numerical implementation



$$x_2(t) = \iint h_2(\tau_1, \tau_2) x(t - \tau_1) x(t - \tau_2) d\tau_1 d\tau_2$$


- Volterra filtering is preferred : a generalisation of Hammerstein filtering
- Each n order component is replaced by a n -D convolution of $x(t)$ with $h_n(t)$ filter (dimension n) : this increases the number of DOF and ensures best convergence





Complex waveform generation


Volterra Filtering : numerical implementation



$$y(t) = \sum_{i=1}^M h_1(i) x(t-i) + \sum_{i=1}^M \sum_{j=1}^M h_2(i, j) x(t-i) x(t-j) + \sum_{i=1}^M \sum_{j=1}^M \sum_{k=1}^M h_3(i, j, k) x(t-i) x(t-j) x(t-k)$$

- n -Dimension convolution with n -Dimension $h_n(t)$ filter
- $h_{1,2,3}(t)$ are three numerical Finite Impulse Response Filters with a memory length of **M=3** : **19 parameters have to be determined**







OUTLINE

- Motivation
- Previous literature
- Complex waveform generation with non linear filtering
- Optimization procedure
- Theoretical results
- Experimental results
- Summary & conclusions






Optimization procedure



- **Optimization procedure** is done with the simplex algorithm defined by Nelder-Mead
- **Cost function** : the relative error between the targetted signal and the output signal
- The 19 parameters of the non linear filter are set to minimize cost function
- **Initialization of iterative procedure**
 - ✓ The input waveform shape is similar to the targetted output waveform shape.
 - ✓ Amplitudes of the input waveform are fixed after a first experiment or with *a-priori* knowledge of the device
 - ✓ Filter Parameters \approx arbitrary very low values , typ. 1%






OUTLINE

- Motivation
- Previous literature
- Complex waveform generation with non linear filtering
- Optimization procedure
- **Theoretical results**
- Experimental results
- Summary & conclusions






Theoretical results

Model

- Assessment of the procedure performed with theoretical model before experiments
- Simple mass spring-model with losses to





- $h_{\text{gap}} = 200 \text{ nm}$ - $V_c = 110 \text{ V}$
- $f_0 = 5.5 \text{ MHz}$
- $V_{\text{bias}} = 65 \text{ V} = 0.7 V_c$

Note: input voltage >0 : the membrane is stretched
input voltage <0 : the membrane is released

Experiments



- Output waveform : mechanical displacement
- Two targetted signals
 - a burst with 5 periods at 1 MHz : $BW_{-6\text{dB}} (\%) \approx 30 \%$
 - a chirp at 1 MHz : $BW_{-6\text{dB}} (\%) \approx 100 \%$







Theoretical results

1 MHz toneburst with 5 periods





- Final relative error $\approx 0.5\%$ with 400 iterations
 $\approx 0.1\%$ with 800 iterations
- The output signal matches very well with the targetted signal (temporal waveform and spectrum)
- The input waveform signal is similar with results published in the previous literature
- Strong diminution of the 2nd and 3rd harmonic







Theoretical results

1 MHz CHIRP signal with 100% BW_{-6dB}



- Basic test signal for coded imaging techniques
- 100 % Bandwidth signal : the output signal matches very well with the targetted signal (temporal waveform and spectrum)
- Final relative error $\approx 0.5\%$ with 200 iterations
 $\approx 0.1\%$ with 500 iterations
- **Higher convergence speed !** The desired signal shows less distortion ?






OUTLINE


- Motivation
- Previous literature
- Complex waveform generation with non linear filtering
- Optimization procedure
- Theoretical results
- **Experimental results**
- Summary & conclusions





Experimental results

Experiment : displacement measurement




- Array was loaded with water
- 30 μm laser spot size
- **Input signal generation** : arbitrary waveform generator driven with a PC computer
- **RF amplifier** : 150A100B, Amplifier Research
- **Output signal** : mechanical displacement in front of the excited emitter

Device

- Surface micromachining process
- 128 elts probe
- Pitch 200 μm
- Cells : 35 \times 35 μm^2
- H_{gap} : 200 nm
- $V_{\text{collapse}} = 70 \text{ V}$
- $f_0 \approx 2.8 \text{ MHz}$
- Array covered with a 500 μm silicone layer
- A mylar film is stuck onto the silicone layer to reflect light beam
- For all experiments : $V_{\text{bias}} \approx 70\% V_c - 50 \text{ V}$

Note: input voltage >0 : the membrane is stretched
input voltage <0 : the membrane is released





Experimental results




1 MHz toneburst with 5 periods


- The output signal matches very well with the targetted signal (temporal waveform and spectrum)

- **2nd harmonic component is « cancelled out »** :
 - ✓ without creating 3rd harmonic component - main risk
 - ✓ without reducing the output displacement amplitude

- Final relative error $\approx 3\%$ with less than 10 iterations : High convergence speed !

- **Optimal input signal** reaches maximum amplitude when membrane is released and not stretched -> there is less distortion





Experimental results

1 MHz toneburst with 5 periods : impact of the phase inversion



- A basic technique to increase contrast in ultrasonic imaging


- the 180° output signal is not the inversion of the 0° phase signal : when the input signal reaches the maximum voltage the membrane is stretched and not released

- 2nd harmonic level : +5 dB - a reduction of 15 dB for a loss of 1 nm on the displacement (not significant)

- Output signal matches with the target signal : relative error of 5 % (10 iterations).


- Note the shape of the optimal solution







Experimental results

1 MHz CHIRP signal with 100% BW_{-6dB}



- Output signal matches with the target signal : relative error of 5 % (10 iterations).
- **Distorsion level** : a reduction of 10 dB (spectrum) for a loss of 1 nm on the peak-to-peak displacement
- Note the shape of the optimal solution






Conclusion & prospects

- Efficiency of optimal command method to control the cMUT output was demonstrated (experiments)
- Optimisation of the temporal waveform :
 - Previous literature focused on minimisation of the second harmonic level
 - The method can be applied to a large range of waveforms and so to coded imaging
 - Other shapes are actually under test
- The procedure is automatic and shows high convergence speed : applicable to industrial devices
- Prospects - application to therapy
 - How these techniques could be used to increase the volume of fluid swept by the membrane without collapsing ?
 - Implementation of non linear filtering models taking into account the collapse event (similar with the modelling of gate function used in electronic)





Acknowledgement



Thanks !

QUESTIONS ?

- COSTUM ANR-09-TECS-005
- THERANOS ANR-10-TECS-007
- FEDER COSTUM II 2657-33868
- Vermon SA for the fabrication of the cMUT array

