



HAL
open science

Technical note for the FS-MMSE-IC receiver

Titouan Petitpied, R Tajan, G. Ferré, Pascal Chevalier, S Traverso

► **To cite this version:**

Titouan Petitpied, R Tajan, G. Ferré, Pascal Chevalier, S Traverso. Technical note for the FS-MMSE-IC receiver. 2019. hal-02063288

HAL Id: hal-02063288

<https://hal.science/hal-02063288>

Preprint submitted on 11 Mar 2019

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution 4.0 International License

Technical note for the FS-MMSE-IC receiver

T. Petitpied^T†, R. Tajan^T, G. Ferré^T, P. Chevalier^{†‡}, S. Traverso[†]

^T IMS, Univ. Bordeaux, Bordeaux INP, CNRS (UMR 5218), F-33405 Talence (FRANCE)

[†] THALES, 4 avenue des Louvresses, 92230 Gennevilliers (FRANCE)

[‡] CEDRIC laboratory – CONSERVATOIRE NATIONAL DES ARTS ET MÉTIERS
292 rue Saint-Martin, 75141 Paris Cedex 3 (FRANCE)

Email: forename.name@{^Tims-bordeaux.fr, [†]thalesgroup.com, [‡]cnam.fr}

February 2019

1 Definitions

For any scalars or vectors \mathbf{x} and \mathbf{y} with convenient sizes, we define:

$$\begin{cases} x_n &= \mathbf{e}_n^\dagger \mathbf{x} \\ \mathbf{R}_{\mathbf{x}\mathbf{y}} &= \mathbb{E}_{\mathbf{x},\mathbf{y}}[\mathbf{x}\mathbf{y}^\dagger] \\ \mathbf{R}_{\mathbf{x}} &= \mathbf{R}_{\mathbf{x}\mathbf{x}} \end{cases}$$

where \mathbf{e}_n is the $(n+1)^{\text{th}}$ element of the canonic base. The operator $\mathbb{E}_{\mathbf{x},\mathbf{y}}[\mathbf{x}\mathbf{y}^\dagger]$ represents the statistical average with respect to \mathbf{x} and \mathbf{y} .

For any matrix \mathbf{A} , we define \mathbf{A}^* the conjugate matrix of \mathbf{A} , \mathbf{A}^T its transpose matrix and $\mathbf{A}^\dagger = (\mathbf{A}^T)^*$.

2 Context & Problem formulation

We suppose having the following expressions:

$$\begin{cases} \mathbf{r} &= \mathbf{H}\mathbf{U}\mathbf{s} + \mathbf{w} \\ \mathcal{I}(\mathbf{f}, p) &= \mathbf{f}^\dagger \mathbf{r} + p \\ \mathcal{J}(\mathbf{f}, p) &= \mathbb{E}_{\mathcal{I}(\mathbf{f}, p)} |\mathcal{I}(\mathbf{f}, p) - s_n|^2 \end{cases}$$

where :

- \mathbf{f} : a $(2N \times 1)$ vector,
- p : a scalar,
- \mathbf{H} : a $(2N \times 2N_s)$ deterministic convolution matrix,
- \mathbf{U} : a $(2N_s \times N_s)$ up-sampling matrix,
- $\mathbf{D} = \mathbf{U}^\dagger$: a down-sampling matrix,
- \mathbf{s} : a $(N_s \times 1)$ probabilistic vector such that $\mathbb{E}[\mathbf{s}] = \mathbf{s}^d$ and $\mathbf{R}_{s_n, s_m} = (v_n^d + |s_n^d|^2)\delta(n-m) \implies \mathbb{E}[(\mathbf{s} - \mathbf{s}^d)(\mathbf{s} - \mathbf{s}^d)^\dagger] = \mathbf{V}^d = \text{diag}(\mathbf{v}^d)$,
- \mathbf{w} : a $(2N \times 1)$ probabilistic vector such that $\mathbb{E}[\mathbf{w}] = \mathbf{0}_N$ and $\mathbf{R}_{\mathbf{w}} = \sigma_w^2 \mathbf{I}_N$,

Typically, the vector \mathbf{r} represents a band-limited received signal after the convolution operation of the shaping filter and the channel \mathbf{H} , corrupted by a centered circular white noise \mathbf{w} with average power σ_w^2 . Moreover, this holds if and only if the shaping filter bandwidth is bounded by $\frac{2}{T_s}$. Hence, \mathbf{r} represents a Fractionally-Spaced (FS) system model where $\mathcal{I}(\mathbf{f}, p)$ is the estimator of \mathbf{s} with Mean Square Error (MSE) $\mathcal{J}(\mathbf{f}, p)$. Furthermore, considering the prior information $(\mathbf{s}^d, \mathbf{V}^d)$ on \mathbf{s} leads to an *Interference-Cancellation (IC)* structure.

Problem formulation: We search for $\tilde{s}_n^e = \mathcal{I}(\mathbf{f}_n, p_n)$, $\tilde{v}_n^e = \mathcal{J}(\mathbf{f}_n, p_n)$ such that:

$$(\mathbf{f}_n, p_n) = \underset{(\mathbf{f}, p)}{\operatorname{argmin}} \mathcal{J}(\mathbf{f}, p)$$

Consequently, \tilde{v}_n^e represents the Minimum MSE of the considered system model (FS-MMSE-IC) and with estimator \tilde{s}_n^e of s_n .

3 Problem resolution

3.1 Expression of the MSE minimizers

$$\begin{aligned} \mathcal{J}(\mathbf{f}, p) &= \mathbb{E}_{\mathcal{I}(\mathbf{f}, p)} |\mathcal{I}(\mathbf{f}, p) - s_n|^2 \\ &= \mathbf{f}^\dagger \mathbf{R}_r \mathbf{f} + \mathbf{f}^\dagger \mathbb{E}[\mathbf{r}] p^* - \mathbf{f}^\dagger \mathbf{R}_{r s_n} + p \mathbb{E}[\mathbf{r}^\dagger] \mathbf{f} + |p|^2 - p \mathbb{E}[s_n^*] - \mathbf{R}_{s_n r} \mathbf{f} - \mathbb{E}[s_n] p^* + \mathbf{R}_{s_n} \end{aligned}$$

Minimizing $\mathcal{J}(\mathbf{f}, p)$ leads us to nullify its the first partial derivatives.

$$\begin{aligned} \frac{\partial \mathcal{J}(\mathbf{f}, p)}{\partial \mathbf{f}} = 0 &\iff 2\mathbf{R}_r \mathbf{f}_n + 2\mathbb{E}[\mathbf{r}] p_n^* - 2\mathbf{R}_{r s_n} = 0 \\ &\iff \mathbf{f}_n = \mathbf{R}_r^{-1} (\mathbf{R}_{r s_n} - \mathbb{E}[\mathbf{r}] p_n^*) \end{aligned}$$

$$\begin{aligned} \frac{\partial \mathcal{J}(\mathbf{f}, p)}{\partial p^*} = 0 &\iff 2\mathbb{E}[\mathbf{r}^\dagger] \mathbf{f}_n + 2p_n^* - 2\mathbb{E}[s_n^*] = 0 \\ &\iff p_n = \mathbb{E}[s_n] - \mathbf{f}_n^\dagger \mathbb{E}[\mathbf{r}] \end{aligned}$$

We check that such an extremum corresponds to a minimum :

$$\begin{cases} \frac{\partial^2 \mathcal{J}(\mathbf{f}, p)}{\partial \mathbf{f}^2} = 2\mathbf{R}_r \geq 0 \\ \frac{\partial^2 \mathcal{J}(\mathbf{f}, p)}{\partial p^{*2}} = 2 \geq 0 \end{cases}$$

3.2 Computation of the MSE minimizers

Let us first compute :

$$\begin{aligned} \mathbb{E}[s_n] &= s_n^d \\ \mathbb{E}[\mathbf{r}] &= \mathbf{H} \mathbf{U} s_n^d \\ \mathbf{R}_r &= \mathbf{H} \mathbf{U} \mathbf{R}_s \mathbf{D} \mathbf{H}^\dagger + \sigma_w^2 \mathbf{I}_N \\ \mathbf{R}_{r s_n} &= \mathbf{H} \mathbf{U} \mathbf{R}_{s s_n} \end{aligned}$$

Then, the MSE minimizers can be computed:

$$\begin{aligned}
\mathbf{f}_n^\dagger &= (\mathbf{R}_{s_n \mathbf{r}} - p_n \mathbb{E}[\mathbf{r}^\dagger]) \mathbf{R}_{\mathbf{r}}^{-1\dagger} \\
&= \left(\mathbf{R}_{s_n \mathbf{r}} - \mathbb{E}[s_n] \mathbb{E}[\mathbf{r}^\dagger] + \mathbf{f}_n^\dagger |\mathbb{E}[\mathbf{r}]|^2 \right) \mathbf{R}_{\mathbf{r}}^{-1\dagger} \\
&= (\mathbf{R}_{s_n \mathbf{r}} - \mathbb{E}[s_n] \mathbb{E}[\mathbf{r}^\dagger]) \mathbf{R}_{\mathbf{r}}^{-1\dagger} (\mathbf{I}_N - |\mathbb{E}[\mathbf{r}]|^2 \mathbf{R}_{\mathbf{r}}^{-1\dagger})^{-1} \\
&= (\mathbf{R}_{s_n \mathbf{r}} - \mathbb{E}[s_n] \mathbb{E}[\mathbf{r}^\dagger]) (\mathbf{R}_{\mathbf{r}}^{-1\dagger} - |\mathbb{E}[\mathbf{r}]|^2)^{-1} \\
&= (\mathbf{R}_{s_n \mathbf{s}} - \mathbb{E}[s_n] \mathbb{E}[\mathbf{s}^\dagger]) \mathbf{D} \mathbf{H}^\dagger \left(\mathbf{H} \mathbf{U} (\mathbf{R}_{\mathbf{s}} - \mathbb{E}[\mathbf{s} \mathbf{s}^\dagger]) \mathbf{D} \mathbf{H}^\dagger + \sigma_w^2 \mathbf{I}_{2N} \right)^{-1} \\
&= v_n^d \mathbf{e}_n^\dagger \mathbf{D} \mathbf{H}^\dagger (\mathbf{H} \mathbf{U} \mathbf{V}^d \mathbf{D} \mathbf{H}^\dagger + \sigma_w^2 \mathbf{I}_{2N})^{-1}
\end{aligned}$$

Using twice the Woodbury identity on any $(K_1 \times K_2)$ matrix A and $(K_2 \times K_1)$ matrix B :

$$\begin{aligned}
\mathbf{A}(\mathbf{B} \mathbf{A} + \mathbf{I}_{K_2})^{-1} &= \mathbf{A}(\mathbf{B} \mathbf{I}_{K_1} \mathbf{A} + \mathbf{I}_{K_2})^{-1} \\
&= \mathbf{A}(\mathbf{I}_{K_2} - \mathbf{B}(\mathbf{I}_{K_1} + \mathbf{A} \mathbf{B}))^{-1} \mathbf{A} \\
&= (\mathbf{I}_{K_1} - \mathbf{A} \mathbf{B}(\mathbf{I}_{K_1} + \mathbf{A} \mathbf{B}))^{-1} \mathbf{A} \\
&= (\mathbf{A} \mathbf{B} \mathbf{I}_{K_1} + \mathbf{I}_{K_1})^{-1} \mathbf{A} \\
&= (\mathbf{A} \mathbf{B} + \mathbf{I}_{K_1})^{-1} \mathbf{A}
\end{aligned}$$

We identify $\begin{cases} \mathbf{A} = \sigma_w^{-2} \mathbf{D} \mathbf{H}^\dagger \\ \mathbf{B} = \mathbf{H} \mathbf{U} \mathbf{V}^d \end{cases}$ leading to:

$$\begin{aligned}
\mathbf{f}_n^\dagger &= v_n^d \mathbf{e}_n^\dagger \mathbf{D} \mathbf{H}^\dagger (\mathbf{H} \mathbf{U} \mathbf{V}^d \mathbf{D} \mathbf{H}^\dagger + \sigma_w^2 \mathbf{I}_{2N})^{-1} \\
&= v_n^d \mathbf{e}_n^\dagger (\mathbf{D} \mathbf{H}^\dagger \mathbf{H} \mathbf{U} \mathbf{V}^d + \sigma_w^2 \mathbf{I}_N)^{-1} \mathbf{D} \mathbf{H}^\dagger \\
&= v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{D} \mathbf{H}^\dagger
\end{aligned}$$

where $\boldsymbol{\Sigma} = \mathbf{G} \mathbf{V}^d + \sigma_w^2 \mathbf{I}_N$ is the MMSE equalization matrix and $\mathbf{G} = \mathbf{D} \mathbf{H}^\dagger \mathbf{H} \mathbf{U}$ is also called *global filter* and gathers the up-sampling, channel and matched filtering and down-sampling operations.

$$\begin{aligned}
p_n &= \mathbb{E}[s_n] - \mathbf{f}_n^\dagger \mathbb{E}[\mathbf{r}] \\
&= s_n^d - v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{s}^d
\end{aligned}$$

3.3 Computation of the FS-MMSE-IC and its estimator

The FS-MMSE-IC estimator is given by:

$$\begin{aligned}
\tilde{s}_n^e &= \mathbf{f}_n^\dagger \mathbf{r} + p_n \\
&= s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{D} \mathbf{H}^\dagger \mathbf{r} - \mathbf{G} \mathbf{s}^d) \\
&= s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G} \mathbf{s}^d)
\end{aligned}$$

where $\mathbf{y} = \mathbf{D} \mathbf{H}^\dagger \mathbf{r}$ represents the received signal after matched filtering and down-sampling.

The FS-MMSE-IC \tilde{v}_n^e of the estimator \tilde{s}_n^e can be computed by first deriving:

$$\begin{aligned}
\mathbf{R}_{\tilde{s}_n^e} &= |s_n^d|^2 + 2(s_n^d)^* v_n^d \mathbf{e}_n^\dagger \operatorname{Re}(\boldsymbol{\Sigma}^{-1} \mathbb{E}_{\mathbf{y}}[(\mathbf{y} - \mathbf{G}\mathbf{s}^d)]) + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbb{E}_{\mathbf{y}}[(\mathbf{y} - \mathbf{G}\mathbf{s}^d)(\mathbf{y} - \mathbf{G}\mathbf{s}^d)^\dagger] \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbb{E}_{\mathbf{s}, \mathbf{w}} |\mathbf{G}(\mathbf{s} - \mathbf{s}^d) + \mathbf{D}\mathbf{H}^\dagger \mathbf{w}|^2 \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{D}\mathbf{H}^\dagger \mathbb{E}_{\mathbf{s}, \mathbf{w}} |\mathbf{H}\mathbf{U}(\mathbf{s} - \mathbf{s}^d) + \mathbf{w}|^2 \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{D}\mathbf{H}^\dagger (\mathbf{H}\mathbf{U}\mathbf{V}^d \mathbf{D}\mathbf{H}^\dagger + \sigma_w^2 \mathbf{I}_{2N}) \mathbf{H}\mathbf{U} \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{D}\mathbf{H}^\dagger \mathbf{H}\mathbf{U}\mathbf{V}^d + \sigma_w^2 \mathbf{I}_N) \mathbf{D}\mathbf{H}^\dagger \mathbf{H}\mathbf{U} \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{e}_n
\end{aligned}$$

$$\begin{aligned}
\mathbf{R}_{\tilde{s}_n^e, s_n} &= \mathbb{E}_{\mathbf{y}}[(s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G}\mathbf{s}^d)) s_n^*] \\
&= |s_n^d|^2 + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbb{E}_{\mathbf{s}}[(\mathbf{s} - \mathbf{s}^d) s_n^*] \\
&= |s_n^d|^2 + (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{e}_n \\
&= \mathbf{R}_{\tilde{s}_n^e}
\end{aligned}$$

$$\mathbf{R}_{s_n} = |s_n^d|^2 + v_n^d$$

This leads to the FS-MMSE-IC \tilde{v}_n^e expression:

$$\begin{aligned}
\tilde{v}_n^e &= \mathbb{E}_{\tilde{s}_n^e} |\tilde{s}_n^e - s_n|^2 \\
&= \mathbf{R}_{\tilde{s}_n^e} - \mathbf{R}_{\tilde{s}_n^e, s_n} - \mathbf{R}_{s_n, \tilde{s}_n^e} + \mathbf{R}_{s_n} \\
&= \mathbf{R}_{s_n} - \mathbf{R}_{s_n, \tilde{s}_n^e} \\
&= |s_n^d|^2 + v_n^d - |s_n^d|^2 - (v_n^d)^2 \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{e}_n \\
&= v_n^d (1 - v_n^d c_n)
\end{aligned}$$

where $c_n = \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{e}_n$.

3.4 Unbiased FS-MMSE-IC and its estimator

We can note that the estimator \tilde{s}_n^e of s_n has a residual bias :

$$\begin{aligned}
\mathbb{E}[s_n^e | \mathbb{E}[s_n] = \mu] &= \mathbb{E}_{\mathbf{s}_{\sim\{n\}}, \mathbf{w}} [s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G}\mathbf{s}^d) | \mathbb{E}[s_n] = \mu] \\
&= s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbb{E}_{\mathbf{s}_{\sim\{n\}}} [\mathbf{s} - \mathbf{s}^d | \mathbb{E}[s_n] = \mu] \\
&= s_n^d + (\mu - s_n^d) v_n^d c_n \\
&= v_n^d c_n \mu + s_n^d (1 - v_n^d c_n)
\end{aligned}$$

where the vector $\mathbf{s}_{\sim\{n\}}$ represents all the components of \mathbf{s} but s_n .

Removing the additive term $s_n^d (1 - v_n^d c_n)$ and dividing the multiplicative term $v_n^d c_n$ leads to:

$$\begin{aligned}
s_n^e &= (v_n^d c_n)^{-1} (\tilde{s}_n^e - s_n^d (1 - v_n^d c_n)) \\
&= s_n^d + c_n^{-1} \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G}\mathbf{s}^d)
\end{aligned}$$

We compute the new statistical matrices:

$$\begin{aligned}\mathbf{R}_{s_n^e} &= |s_n^d|^2 + c_n^{-2} \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbb{E}_{\mathbf{y}}[(\mathbf{y} - \mathbf{G}\mathbf{s}^d)(\mathbf{y} - \mathbf{G}\mathbf{s}^d)^\dagger] \boldsymbol{\Sigma}^{-1} \mathbf{e}_n \\ &= |s_n^d|^2 + c_n^{-1}\end{aligned}$$

$$\begin{aligned}\mathbf{R}_{s_n^e, s_n} &= \mathbb{E}_{\mathbf{y}}[(s_n^d + c_n^{-1} \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1}(\mathbf{y} - \mathbf{G}\mathbf{s}^d)) s_n^*] \\ &= |s_n^d|^2 + c_n^{-1} \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbb{E}_{\mathbf{s}}[(\mathbf{s} - \mathbf{s}^d) s_n^*] \\ &= |s_n^d|^2 + v_n^d\end{aligned}$$

$$\mathbf{R}_{s_n} = |s_n^d|^2 + v_n^d$$

And finally we find we unbiased FS-MMSE-IC:

$$\begin{aligned}v_n^e &= \mathbb{E}_{s_n^e} |s_n^e - s_n|^2 \\ &= \mathbf{R}_{s_n^e} - \mathbf{R}_{s_n^e, s_n} - \mathbf{R}_{s_n, s_n^e} + \mathbf{R}_{s_n} \\ &= |s_n^d|^2 + c_n^{-1} - |s_n^d|^2 - v_n^d - |s_n^d|^2 - v_n^d + |s_n^d|^2 + v_n^d \\ &= c_n^{-1} - v_n^d\end{aligned}$$

4 Conclusion

The biased FS-MMSE-IC receiver is given by:

$$\begin{cases} \tilde{s}_n^e &= s_n^d + v_n^d \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G}\mathbf{s}^d) \\ \tilde{v}_n^e &= v_n^d (1 - v_n^d c_n) \end{cases}$$

where $c_n = \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} \mathbf{G} \mathbf{e}_n$ is a scalar, $\mathbf{y} = \mathbf{D}\mathbf{H}^\dagger \mathbf{r}$ is the receive signal after matched filtering and down-sampling, $\mathbf{G} = \mathbf{D}\mathbf{H}^\dagger \mathbf{H}\mathbf{U}$ is the global effect including up-sampling, channel and matched filtering and down-sampling, $\boldsymbol{\Sigma} = \mathbf{G}\mathbf{V}^d + \sigma_w^2 \mathbf{I}_N$ is the MMSE equalization matrix.

Moreover, the unbiased FS-MMSE-IC receiver is given by:

$$\begin{cases} s_n^e &= s_n^d + c_n^{-1} \mathbf{e}_n^\dagger \boldsymbol{\Sigma}^{-1} (\mathbf{y} - \mathbf{G}\mathbf{s}^d) \\ v_n^e &= c_n^{-1} - v_n^d \end{cases}$$

Consequently, the FS-MMSE-IC receiver leads to a FS matched filter followed by a symbol time equalizer.