

A technique of flux reconstruction at the interfaces of nonconforming grids for aeroacoustic simulations

Sophie Le Bras, Hugues Deniau, Christophe Bogey

▶ To cite this version:

Sophie Le Bras, Hugues Deniau, Christophe Bogey. A technique of flux reconstruction at the interfaces of nonconforming grids for aeroacoustic simulations. International Journal for Numerical Methods in Fluids, 2019, 91 (12), pp.587-614. 10.1002/fld.4767 . hal-02351079

HAL Id: hal-02351079 https://hal.science/hal-02351079

Submitted on 24 Nov 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

A technique of flux reconstruction at the interfaces of 1 non-conforming grids for aeroacoustic simulations 2 S. Le $Bras^{12*}$, H. Deniau³ and C. Bogey⁴ 3 ¹ Centre Européen de Recherche et de Formation Avancée en Calcul Scientifique, 31057 Toulouse, France, 4 ² Siemens Industry Software N.V., 3001 Leuven, Belgium. 5 ³ ONERA, French Aerospace Lab, 31000 Toulouse, France. 6 ⁴ Univ Lvon, Ecole Centrale de Lvon, INSA Lvon, Université Claude Bernard Lvon I, CNRS, Laboratoire de Mécanique 7 des Fluides et d'Acoustique, UMR 5509, F-69134, Ecully, France. 8

SUMMARY

A flux reconstruction technique is presented in order to perform aeroacoustic computations using implicit high-order spatial schemes on multiblock structured grids with non-conforming interfaces. The use of such grids, with mesh spacing discontinuities across the block interfaces, eases local mesh refinements, simplifies the mesh generation process, and thus facilitates the computation of turbulent flows. In this work, the spatial discretization consists of sixth-order finite-volume implicit schemes with low-dispersion and low-dissipation properties. The flux reconstruction is based on the combination of non-centered schemes with local interpolations to define ghost cells and compute flux values at the grid interfaces. The flow variables in

- ⁹ the ghost cells are calculated from the flow field in the grid cells using a meshless interpolation with radial basis functions. In this study, the flux reconstruction is applied to both plane and curved non-conforming interfaces. The performance of the method is first evaluated by performing two-dimensional simulations of the propagation of an acoustic pulse and of the convection of a vortex on Cartesian and wavy grids. No significant spurious noise is produced at the grid interfaces. The applicability of the flux reconstruction to a 3-D computation is then demonstrated by simulating a jet at a Mach number of 0.9 and a diameter-based Reynolds number of 4×10^5 on a Cartesian grid. The non-conforming grid interface located downstream of the jet potential core does not appreciably affect the flow development and the jet sound field, while reducing the number of mesh points by a factor of approximately two. Copyright © 2018 John Wiley & Sons, Ltd.
- 10 Received ...
- 11 KEY WORDS: non-conforming grids, structured grids, high-order schemes, finite volumes, meshless interpolation, aeroacoustics

1. INTRODUCTION

- 12 For flows at high Reynolds numbers, the direct computation of the aerodynamic noise from the
- 13 Navier-Stokes equations requires accurate numerical methods in order to properly compute both the

^{*}Correspondence to: Sophie Le Bras, Siemens Industry Software N.V., Interleuvenlaan 68, 3001 Leuven, Belgium. E-mail: sophie.le_bras@siemens.com

small turbulent motions and the low-frequency sound waves in the radiated pressure field [1–3]. In order to meet these requirements, in addition to high-order discretization schemes, locally refined

¹⁶ meshes are needed in order to capture the turbulent eddies generating noise [4].

- 17 For aeroacoustic simulations performed on multiblock structured grids, the computational domain is usually divided into subdomains composed of conforming grids characterized by a full point-18 matching distribution at the block interface, as shown in Fig. 1(a). Difficulties in performing high-19 fidelity computations with such grids arise when the geometries are complex. Such geometries 20 must be included in the numerical simulations in order to faithfully reproduce the conditions of the 21 experiments [5,6]. In this context, high-quality structured meshes with conforming interfaces are in 22 many cases almost impossible to generate [7]. For instance, for high-speed flows exhausting from 23 turbofan jet engines or developing on aircraft wings [8], extremely fine grids are required to resolve 24 the flow in the boundary layers and the wakes. Using conforming grids, local mesh refinements 25 can be found in all the computational domain, leading to an excessive number of mesh points as 26 well as to the generation of extremely small cells in out of interest areas. Obviously, this increases 27 the computational cost of the simulation. In addition, using an explicit time discretization scheme, 28 the presence of very small mesh cells imposes severe constraints on the time step so that the CFL 29
 - restriction is verified [3].



Figure 1. Representation of 2-D meshes with (a) conforming and (b) non-conforming grid interfaces in blue.

39 In order to perform aeroacoustic simulations of high-Reynolds-number flows at a reasonable computational cost, the use of non-conforming grids [9] without overlapping is attractive. Such 32 meshes exhibit discontinuities of the grid lines across the block interface. This is the case of 33 Fig. 1(b), providing an example of a non-conforming mesh with discontinuous grid spacings in the 34 azimuthal direction at the block interface in blue. Using such a mesh for instance, the refinement at 35 the center of the grid in Fig. 1(a) can be avoided. The size of the smallest cells and thus the time 36 step are therefore chosen such that the acoustic sources are well-discretized. In addition, the use 37 of non-conforming grids simplifies the grid generation process since the mesh blocks composing 38 the computational domain can be created independently and then easily assembled. In return, in 39 order to obtain high-fidelity numerical results using non-conforming grids, an accurate spatial 40 discretization at the grid interfaces is required. Indeed, as the grid spacing is discontinuous at the 41 block interface, the spatial discretization schemes cannot usually be applied close to the interface 42 and their formulations have to be modified. 43

In computational aeroacoustics, the spatial discretization can be carried out using high-order low-dissipation and low-dispersion schemes, amongst which the dispersion-relation-preserving

schemes [10], the optimized explicit schemes in the Fourier space [2], or the implicit schemes [11, 46 12]. In this study, the spatial discretization consists of the sixth-order finite-volume implicit scheme 47 of Fosso et al. [12] in combination with the sixth-order implicit selective filter of Visbal and 48 Gaitonde [13]. Implicit schemes are particularly attractive in order to reach a high-order spectral 49 accuracy using a smaller number of grid points compared to explicit schemes. However, in the 50 context of parallel computations, the flow equations are generally solved locally in each subdomain 51 of the multiblock grid. As a consequence, the implicit centered schemes cannot be applied at the 52 mesh block interfaces. Therefore, in a previous study [12], a technique of flux reconstruction at the 53 interface of conforming grids has been developed. Based on the application of non-centered spatial 54 schemes at the block interface and the use of ghost cells, the technique allowed us to successfully 55 perform massively parallel aerodynamic and aeroacoustic computations of jet flows [14–17]. 56

In the present study, a flux reconstruction technique for the interface of non-conforming grids 57 is proposed. The technique, derived from the method developed for conforming grids [12], is 58 based on the application of non-centered schemes at the grid interface. Due to the mesh line 59 discontinuities at the grid interface, an additional step consisting in reconstructing ghost cells is 60 required. The flow variables in the ghost cells are computed using a local interpolation technique, 61 based on a meshless method involving Radial Basis Functions (RBF) [9,18]. Meshless interpolations 62 are useful in order to alleviate the difficulties caused by the loss of the mesh topology at the 63 interfaces of non-conforming grids. Indeed, since meshless interpolations are performed from 64 arbitrarily scattered spatial data without any geometrical information, computational overheads 65 due to topology reconstructions are avoided. Originally developed by the authors for plane non-66 conforming grid interfaces [19], the technique of flux reconstruction is extended to curved interfaces 67 in this study. In comparison with the preliminary results presented in [19], the properties of the 68 RBF interpolation are examined in 1-D in the wavenumber space, and the performance of the flux 69 reconstruction is further assessed by simulating in 2-D the convection of a vortex on wavy grids 70 and the propagation of an acoustic pulse. In addition, the application of the technique to a three-71 dimensional turbulent jet flow is presented. 72

The present paper is organized as follows. In a first section, the high-order finite-volume approach 73 used in this study and the flux reconstruction method for conforming interfaces are described. 74 In section 2, the reconstruction technique developed at the interface of plane and curved non-75 conforming grids is presented. In section 3, the properties of the RBF interpolations are examined 76 in 1-D in the wavenumber space. In section 4, the accuracy of the flux reconstruction is evaluated 77 by simulating a two-dimensional acoustic pulse propagating through a non-conforming interface. In 78 section 5, the simulations of two-dimensional vortex convection for Cartesian and wavy grids with 79 different spatial resolutions are presented. In particular, the advantages of using RBF interpolations 80 for the reconstruction and the choice of the interpolation parameters are discussed. Finally, the 81 application of the technique to a 3-D turbulent jet flow is presented, using a non-conforming grid 82 downstream of the jet potential core. The reduction in the number of mesh points obtained using a 83 non-conforming grid is evaluated. The effects of the presence of a non-conforming interface on the 84 sound field radiated by the jet are examined. 85

2. FLUX RECONSTRUCTION TECHNIQUE FOR CONFORMING GRIDS

86 2.1. Governing equations

In this study, the 3-D compressible Navier-Stokes equations are solved. Using Cartesian coordinates,
they can be written as:

$$\frac{\partial \mathbf{W}}{\partial t} + \frac{\partial \mathbf{E}_c}{\partial x} + \frac{\partial \mathbf{F}_c}{\partial y} + \frac{\partial \mathbf{G}_c}{\partial z} - \frac{\partial \mathbf{E}_d}{\partial x} - \frac{\partial \mathbf{F}_d}{\partial y} - \frac{\partial \mathbf{G}_d}{\partial z} = 0$$
(1)

where $(\mathbf{E}_c, \mathbf{F}_c, \mathbf{G}_c)$ are the convective fluxes, $(\mathbf{E}_d, \mathbf{F}_d, \mathbf{G}_d)$ are the diffusive fluxes, $\mathbf{W} = (\rho, \rho u, \rho v, \rho w, \rho e)^t$ is the vector of the conservative variables, ρ is the density, (u, v, w) are the velocity components, and ρe is the total energy. For a perfect gas, the total energy ρe is given by:

$$\rho e = \frac{p}{\gamma - 1} + \frac{1}{2}\rho(u^2 + v^2 + w^2) \tag{2}$$

where p is the static pressure and γ is the specific heat ratio. The convective fluxes write as:

$$\begin{cases} \mathbf{E}_{c} = (\rho u, \rho u^{2} + p, \rho uv, \rho uw, (\rho e + p)u)^{t} \\ \mathbf{F}_{c} = (\rho v, \rho uv, \rho v^{2} + p, \rho vw, (\rho e + p)v)^{t} \\ \mathbf{G}_{c} = (\rho w, \rho uw, \rho vw, \rho w^{2} + p, (\rho e + p)w)^{t} \end{cases}$$
(3)

93 and the diffusive fluxes as:

$$\mathbf{E}_{d} = (0, \tau_{11}, \tau_{12}, \tau_{13}, \tau_{11}u + \tau_{12}v + \tau_{13}w + H_{1})^{t}
\mathbf{F}_{d} = (0, \tau_{21}, \tau_{22}, \tau_{23}, \tau_{21}u + \tau_{22}v + \tau_{23}w + H_{2})^{t}
\mathbf{G}_{d} = (0, \tau_{31}, \tau_{32}, \tau_{33}, \tau_{31}u + \tau_{32}v + \tau_{33}w + H_{3})^{t}$$
(4)

where $\mathbf{H} = (H_1, H_2, H_3)^t$ is the heat flux vector, $\tau_{ij} = 2\mu S_{ij}$ is the viscous stress tensor, μ is the dynamic molecular viscosity computed from Sutherland's law, and S_{ij} is the deformation stress tensor:

$$S_{ij} = \frac{1}{2} \left(\frac{\partial u_i}{\partial x_j} + \frac{\partial u_j}{\partial x_i} - \frac{2}{3} \frac{\partial u_k}{\partial x_k} \delta_{i,j} \right)$$
(5)

⁹⁷ The heat flux vector **H** is computed from Fourier's law, yielding:

$$\mathbf{H} = -\lambda \nabla T \tag{6}$$

where ∇T is the temperature gradient, $\lambda = C_p \mu / Pr$ is the thermal conductivity, C_p is the specific heat at constant pressure, and Pr is the Prandtl number.

100 2.2. High-order finite-volume approach

The computations are performed using the finite-volume multi-block structured solver *elsA* [20], allowing us to perform Direct Numerical Simulations (DNS) or Large-Eddy Simulations (LES). In a finite-volume approach, the integral form of the Navier-Stokes equation (1) is solved at a discrete level. For this purpose, the computational domain is divided into non-overlapping control volumes Ω_i , where *i* is the volume index. Integrating Eq. (1) over the elementary volumes Ω_i and using the 106 divergence theorem lead to:

$$|\Omega_i| \frac{d\mathbf{U}_i}{dt} + \int_{\partial\Omega_i} (\mathbf{E}_c + \mathbf{F}_c + \mathbf{G}_c) \cdot \boldsymbol{n} \, \mathrm{d}S + \int_{\partial\Omega_i} (\mathbf{E}_d + \mathbf{F}_d + \mathbf{G}_d) \cdot \boldsymbol{n} \, \mathrm{d}S = 0$$
(7)

where $\mathbf{n} = (n_x, n_y, n_z)$ is the outgoing unitary normal of Ω_i , $\partial \Omega_i$ represents the faces of Ω_i and \mathbf{U}_i is the mean value of \mathbf{W} in the volume Ω_i such as:

$$\mathbf{U}_{i} = \frac{1}{|\Omega_{i}|} \int_{\Omega_{i}} \mathbf{W} \,\mathrm{d}V \tag{8}$$

In the *elsA* solver, the diffusive fluxes in Eq. (7) are calculated from the gradient ∇U estimated at the cell interfaces using a 2nd-order method [21]. For clarity, in the following, only the convective fluxes are presented in the equations. Following Fosso *et al.* [12] and supposing that the volume Ω_i is an hexahedron, the normal *n* is constant along the interface, and the integral of the convective fluxes in Eq. (7) can be approximated as:

$$\int_{\partial\Omega_i} (\mathbf{E}_c + \mathbf{F}_c + \mathbf{G}_c) \cdot \boldsymbol{n} \, \mathrm{d}S \simeq |\partial\Omega_i| \left(\mathbf{E}_c(\widetilde{\mathbf{U}}_{\partial\Omega_i}) n_x + \mathbf{F}_c(\widetilde{\mathbf{U}}_{\partial\Omega_i}) n_y + \mathbf{G}_c(\widetilde{\mathbf{U}}_{\partial\Omega_i}) n_z \right)$$
(9)

where $\widetilde{\mathbf{U}}_{\partial\Omega_i}$ is the averaged value of the variable vector \mathbf{W} at the cell interface $\partial\Omega_i$:

$$\widetilde{\mathbf{U}}_{\partial\Omega_i} = \frac{1}{|\partial\Omega_i|} \int_{\partial\Omega_i} \mathbf{W} \,\mathrm{d}S \tag{10}$$

The convective fluxes are thus computed from the interface-averaged values $\tilde{\mathbf{U}}$ of the flow variables. In order to obtain a high-order calculation of the convective fluxes derivatives, a high-order interpolation of vector $\tilde{\mathbf{U}}$ is performed from the cell-averaged values U. Considering the onedimensional computational domain of Fig. 2, the interpolated vector $\tilde{\mathbf{U}}$ at the interface i + 1/2 is obtained by solving the implicit scheme:

$$\alpha_{i+1/2} \widetilde{\mathbf{U}}_{i-1/2} + \widetilde{\mathbf{U}}_{i+1/2} + \beta_{i+1/2} \widetilde{\mathbf{U}}_{i+3/2} = \sum_{l=-1}^{2} a_l \mathbf{U}_{i+l}$$
(11)

where α_{i+1/2}, β_{i+1/2} and a_l are the scheme coefficients which are obtained from a 5th-order Taylor
series [12]. This scheme correctly resolves the wavelengths discretized by at least 5 points [14].
Note that despite the use of approximation (9) which is formally only second-order accurate, Fosso *et al.* [12] demonstrated that the numerical scheme (11) is equivalent to Lele's 6th-order finite-difference scheme [11] for a uniform Cartesian mesh.



Figure 2. Representation of a one-dimensional computational domain.

124

In order to ensure the stability of the centered scheme (11), the 6th-order compact filter of Visbal and Gaitonde [13] is applied to the flow variables. The filtered values, denoted \hat{U} , are estimated 127 from the values of **U** as:

$$\alpha_f \widehat{\mathbf{U}}_{i-1} + \widehat{\mathbf{U}}_i + \alpha_f \widehat{\mathbf{U}}_{i+1} = \sum_{l=0}^3 \frac{\gamma_l}{2} \left(\mathbf{U}_{i+l} + \mathbf{U}_{i-l} \right)$$
(12)

where $\alpha_f = 0.47$, and γ_l are the filter coefficients [13]. The filter is employed on a uniformly spaced grid thanks to a coordinate transform. For LES computations, the filter also plays the role of a subgrid-scale model, relaxing turbulent energy at high frequencies [22–24]. Time integration is performed by applying a low-storage 6-stage Runge Kutta algorithm [2]. Radiation boundary conditions, Navier-Stokes characteristic boundary conditions, and sponge zones are used in order to avoid significant acoustic reflections at the mesh boundaries. A more detailed description of the numerical algorithm is given in Fosso *et al.* [14].

135 2.3. Reconstruction for conforming grid interfaces

2.3.1. Numerical scheme At the mesh-block interfaces, the implicit centered scheme (11) used in
the computation of the convective fluxes cannot be applied. Thus, in a previous study [12], a flux
reconstruction technique has been proposed at the interfaces of conforming grids. It is presented in
the following by considering a two-dimensional computational domain composed of two blocks L
and R separated by a conforming interface, as shown in Fig. 3.



Figure 3. Flux reconstruction for conforming grids: (a) step 1: computation of the flow variables at the interface I_L using a scheme involving two cells (squares) and an interface (cross) of block L and two ghost cells (stars) of block R, (b) step 2: flux computation from the flow variables at the interfaces I_L and I_R , using a Riemann solver.

140

The reconstruction technique consists of two steps. In the first step, the flow variables \tilde{U} at the grid interface in blocks L and R are determined using upwind schemes. More precisely, in block L, as illustrated in Fig. 3(a), the vector \tilde{U}_L at the interface I_L is computed using a non-centered scheme involving the flow variables in cells of blocks L and R such as:

$$\alpha' \widetilde{\mathbf{U}}_{i=N-1/2,j} + \widetilde{\mathbf{U}}_{L} = \underbrace{a_0' \mathbf{U}_{i=N-1,j} + a_1' \mathbf{U}_{i=N,j}}_{\text{cells of block L}} + \underbrace{a_2' \mathbf{U}_{i'=0,j} + a_3' \mathbf{U}_{i'=1,j}}_{\text{cells of block R}}$$
(13)

where α' and a'_i are the scheme coefficients determined using Taylor series. For block L, the values of U in the cells (i' = 0, j) and (i' = 1, j) of block R are a priori not known. These cells are thus referred to as ghost cells for block L in the following. The values of U in the ghost cells are obtained thanks to data exchanges between the blocks at each time iteration of the simulation. Symmetrically, in block R, the vector $\widetilde{\mathbf{U}}_R$ at the interface I_R in Fig. 3(b) is determined from the upwind scheme:

$$\widetilde{\mathbf{U}}_{R} + \beta'' \widetilde{\mathbf{U}}_{i'=1/2,j} = \underbrace{a_{0}'' \mathbf{U}_{i=N-1,j} + a_{1}'' \mathbf{U}_{i=N,j}}_{\text{cells of block L}} + \underbrace{a_{2}'' \mathbf{U}_{i'=0,j} + a_{3}'' \mathbf{U}_{i'=1,j}}_{\text{cells of block R}}$$
(14)

where β'' and a_i'' are the scheme coefficients. The values of $\widetilde{\mathbf{U}}_L$ and $\widetilde{\mathbf{U}}_R$ are usually not identical, since they are determined from two different upwind schemes (13) and (14). Therefore, in a second step, a Riemann problem [25] is solved in order to ensure the unicity of the flux, hence the scheme conservativity, at the block interface.

2.3.2. Selective filter In the vicinity of conforming grid interfaces, as for the centered scheme (11), 154 the 7-point centered filter (12) cannot be applied, and its formulation has to be modified. However, 155 previous studies [26] demonstrated that the change of the filter formulation at the grid interface is 156 157 likely to significantly decrease the accuracy of the filtering process and generate spurious noise. Therefore, in order to still apply the centered filter (12) at the grid interface, Fosso [26] proposed to 158 artificially extend the size of the mesh blocks using ghost cells, and to modify the filter formulation 159 160 in the ghost cell regions exclusively. In practice, according to the notations of Fig. 4, in order to change the filter formulation as far as possible from the interface, the block L is extended using 161 five ghost cells represented by stars. These cells correspond to the cells of block R indexed by 162 i' = 0, 1, 2, 3, 4. Consequently, in block L, the centered filter (12) on 7 points can be applied in cells 163 i = ..., N - 1, N and in the ghost cell (i' = 0, j). Finally, a non-centered filter is used in order to 164 determine the value of $\widehat{\mathbf{U}}$ in the ghost cell (i' = 1, j) in grey in Fig. 4: 165

$$\alpha_{f}\widehat{\mathbf{U}}_{i'=0,j} + \widehat{\mathbf{U}}_{i'=1,j} = \sum_{k=2}^{3} \frac{\gamma_{k}}{2} \mathbf{U}_{i=N-k+2,j} + \frac{\gamma_{1}}{2} \mathbf{U}_{i'=0,j} + \gamma_{0} \mathbf{U}_{i'=1,j} + \sum_{k=1}^{3} \frac{\gamma_{k}}{2} \mathbf{U}_{i'=k+1,j} - \alpha_{f} \mathbf{U}_{i'=2,j}$$
(15)

¹⁶⁶ The flux reconstruction for conforming grids presented in this section has been successfully applied to massively parallel aeroacoustic simulations of jet flows at high Reynolds numbers [14, 15, 17].



Figure 4. Filter application in block L in the vicinity of a conforming grid interface: the flow variables in the ghost cell i' = 1 in grey are filtered using grid cells of block L (squares) and block R (stars).

167

3. FLUX RECONSTRUCTION TECHNIQUE FOR NON-CONFORMING GRIDS

In this section, the reconstruction presented above for conforming grids is extended to the cases of plane and curved non-conforming meshes.

170 3.1. Plane interfaces

In the case of a non-conforming grid interface, as illustrated in Fig. 5, the flux reconstruction 171 technique described in section 2.3 cannot be used. Indeed, for such grids, as the mesh lines are 172 discontinuous across the block interface, the ghost cells represented by stars in Fig. 4 are not defined 173 anymore. Therefore, the upwind schemes (13) (14) and the filter (15) cannot be applied. In this work, 174 a new flux reconstruction is thus proposed at the non-conforming interfaces. It consists in using non-175 centered schemes and meshless interpolations in order to define the flow variables in ghost cells and 176 at the grid interface. In this section, the flux reconstruction is presented for the plane grid interface 177 displayed in Fig. 5, considering block L as the current block. 178

3.1.1. Numerical scheme In order to compute the flux at the interface I_L in block L, the key idea 179 is to make possible the application of the schemes (13) and (14) thanks to the reconstruction of the 180 flow variables in ghost cells. For this purpose, a methodology, composed of four steps depicted in 181 Fig. 5, is presented. In step 1, two ghost cells, represented in grey in Fig. 5(a), are defined. The 182 centers of these cells, depicted by stars, are located at the intersection between the mesh lines i' = 0183 and i' = 1 and the straight line passing by the centers of the cells (i = N - 1, j) and (i = N, j). 184 The values of the flow variables \mathbf{U} in the ghost cells are determined from the values of \mathbf{U} in 185 the cells of block R using a meshless interpolation. The interpolation technique is presented in 186 section 3.1.3. In step 2, illustrated in Fig. 5(b), the upwind scheme (13) can be applied to compute 187 the flow vector $\widetilde{\mathbf{U}}_L$ at the interface I_L of block L. In step 3, symmetrically with what was done in 188 steps 1 and 2 for block L, ghost cells are defined in block R and the scheme (14) is employed to 189 determine the vector \mathbf{U} at the interfaces (..., $I_{R,j'}$, $I_{R,j'+1}$, ...) in grey in Fig. 5(c). Finally, in step 190 4, a ghost interface I'_L , identical geometrically to I_L , is defined in block R, as shown in Fig. 5(d). 191 The variable vector $\widetilde{\mathbf{U}}'_L$ at the interface I'_L is interpolated from the values $\widetilde{\mathbf{U}}$ obtained in step 3. 192 This second interpolation method is also described in section 3.1.3. Even if the interfaces I'_L and I_L 193 are geometrically identical, the values of U at these two interfaces differ since they are computed 194 from different schemes and interpolations. Therefore, the convective flux at the block interface is 195 determined from the values of $\widetilde{\mathbf{U}}_L$ and $\widetilde{\mathbf{U}}'_L$ by resolving a Riemann flux problem [25]. 196

3.1.2. Selective filter Five ghost cells are necessary in order to apply the non-centered filter (15) 197 near the block interface. For conforming grids, as explained in section 2.3, the flow variables 198 in the ghost cells are directly obtained thanks to data exchanges between blocks. However, 199 for non-conforming grids, these variables first need to be interpolated before being exchanged. 200 Consequently, using five ghost cells results in an extra computational cost compared to conforming 201 grids, which led us to only consider two ghost cells. The application of the filter close to the non-202 conforming interface of block L is illustrated in Fig. 6. The cells and ghost cells of block L involved 203 in the filtering are represented by squares and stars, respectively. As shown in Fig. 6(a), using two 204 ghost cells, the 7-point centered filter (12) can be applied as far as point (i = N - 1, j) in block L. 205 At the cell (i = N, j) adjacent to the block interface, in grey in Fig. 6(b), the filtered field $\widehat{\mathbf{U}}_{i=N,j}$ is 206 computed from the upwind formulation: 207

$$\alpha_f \widehat{\mathbf{U}}_{i=N-1,j} + \widehat{\mathbf{U}}_{i=N,j} + \alpha_f \widehat{\mathbf{U}}_{i'=0,j} = \sum_{k=0}^4 \gamma'_k \mathbf{U}_{N-4+k,j} + \gamma'_5 \mathbf{U}_{i'=0,j} + \gamma'_6 \mathbf{U}_{i'=1,j}$$
(16)

Copyright © 2018 John Wiley & Sons, Ltd. Prepared using fldauth.cls



Figure 5. Flux reconstruction for non-conforming grids at the interface I_L in block L: (a) step 1: definition of two ghost cells (stars), (b) step 2: computation of the flow variables at the interface I_L using a non-centered scheme involving an interface (cross) and two cells (squares) of block L, and two ghost cells (stars), (c) step 3: computation of the flow variables at the interfaces in grey, applying steps 1 and 2 in block R, (d) step 4: interpolation of the flow variables at the ghost interface I'_L using the data computed in step 3, and computation of the resulting flux at the block interface using a Riemann solver.

Finally, the flow variables in the ghost cells (i' = 0, j) and (i' = 1, j) are filtered using non-centered schemes on 7 points, as illustrated in Fig. 6(c) and 6(d), yielding:

$$\begin{cases} \alpha_{f}\widehat{\mathbf{U}}_{i=N,j} + \widehat{\mathbf{U}}_{i'=0,j} + \alpha_{f}\widehat{\mathbf{U}}_{i'=1,j} = \sum_{k=0}^{4} \gamma_{k}^{\prime\prime}\mathbf{U}_{N-4+k,j} + \gamma_{5}^{\prime\prime}\mathbf{U}_{i'=0,j} + \gamma_{6}^{\prime\prime}\mathbf{U}_{i'=1,j} \\ \alpha_{f}\widehat{\mathbf{U}}_{i'=0,j} + \widehat{\mathbf{U}}_{i'=1,j} = \sum_{k=0}^{4} \gamma_{k}^{\prime\prime\prime}\mathbf{U}_{N-4+k,j} + \gamma_{5}^{\prime\prime\prime}\mathbf{U}_{i'=0,j} + \gamma_{6}^{\prime\prime\prime}\mathbf{U}_{i'=1,j} \end{cases}$$
(17)

where $\alpha_f = 0.47$, and γ'_k , γ''_k and γ''_k are the non-centered filter coefficients [27].

3.1.3. Interpolation techniques In the flux reconstruction for non-conforming grids, interpolations are performed in order to compute the flow variables U in two ghost cells and the values of \tilde{U} at the grid interface. As presented in section 3.1.1, in block L, the interpolations are carried out using values of U and \tilde{U} in block R. In practice, block R can be divided into subdomains with a loss of topology information between the domains. Therefore, in this study, meshless interpolations based on Radial Basis Functions (RBF) are employed.

First, the interpolation technique is described for the calculation of a component u of the vector U in the ghost cell located at i' = 0 in Fig. 5(a). The calculation is performed using the value of uknown in n_v cells of block R surrounding the ghost cell. These n_v cells are located along the line i' = 0 for a 2-D mesh, in the plane i' = 0 for a 3-D straight mesh. The RBF approximation u_{RBF} of



Figure 6. Filtering at the non-conforming grid interface in block L. Cells in block L (squares) and ghost cells in block R (stars) used in the filter scheme applied at points: (a) (i = N - 1, j), (b) (i = N, j), (c) (i' = 0, j) and (d) (i' = 1, j).

the variable u at point \boldsymbol{x} writes [9]:

$$u_{\rm RBF}(\boldsymbol{x}) = \sum_{j=1}^{n_v} \xi_j \Phi(\boldsymbol{x}, \boldsymbol{x}_j) + \sum_{q=1}^m \zeta_q P_q(\boldsymbol{x})$$
(18)

where ξ_j and ζ_q are the unknown interpolation coefficients, $(\boldsymbol{x}_j)_{j=1,...,n_v}$ are the centers of the n_v cells, Φ are Wendland's radial basis functions [9, 28], and $\sum \zeta_q P_q(\boldsymbol{x}) = \zeta_0 + \zeta_1 x + \zeta_2 y + ... + \zeta_m z^{\deg(P)}$ is a polynomial term of degree deg(P) that ensures the unicity of the approximation u_{RBF} [18, 29]. The calculation of the coefficients ξ_j and ζ_q is presented in appendix A.1. Similarly, the value of U in the second ghost cell in Fig. 5(a) is interpolated using the RBF approximation (18) and n_v points located at i' = 1. The choice of the interpolation parameters n_v and deg(P) in Eq. (18) is discussed in sections 6 and 7.

A second interpolation technique is proposed in order to interpolate the flow variables $\tilde{\mathbf{U}}$ at the block interface I'_L in Fig. 5(d). As for the interpolation of the flow field in the ghost cells, a RBF interpolation is carried out. However, the quantity to interpolate is not a single-point value u but an averaged value \tilde{u} on a grid interface. Therefore, the interpolation of \tilde{u} on the interface I'_L is performed from n_v values of $\tilde{\mathbf{U}}$ at the interfaces $(I_{R,1}, ..., I_{R,j'}, I_{R,j'+1}, ..., I_{R,n_v})$ represented in grey in Fig. 5(c). The interpolation formulation at the grid interface I'_L is obtained by integrating Eq (18) on I'_L :

$$\tilde{u}_{L'} = \frac{1}{|I'_L|} \int_{I'_L} u_{\text{RBF}}(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x}$$

$$= \sum_{j'=1}^{n_v} \tilde{\xi}_{j'} \left(\frac{1}{|I'_L|} \int_{I'_L} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^m \tilde{\zeta}_q \left(\frac{1}{|I'_L|} \int_{I'_L} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right)$$
(19)

Copyright © 2018 John Wiley & Sons, Ltd. *Prepared using fldauth.cls*

where the point $\boldsymbol{x}_{j'}$ is the center of the surface $I_{R,j'}$. The calculation of the interpolation coefficients $\tilde{\zeta}_{j'}$ and $\tilde{\zeta}_q$ is detailed in appendix A.2.1. A 3rd-order Gaussian quadrature is used in order to compute the integrals of Eq. (19). In practice, the interpolation coefficients in Eq. (18) and (19) are computed only once at the beginning of the simulation and stored in memory, yielding low CPU cost interpolations (see appendix A).

241 3.2. Curved interfaces

For curved grid interfaces, the flux reconstruction presented in section 3.1 cannot be applied. For the interpolation of the flow variables at the grid interface using Eq. (19), as the curvature of the surface is not taken into account to define the ghost interface I'_L , the integral (19) is evaluated on a plane interface that does match the shape of the non-conforming interface. Therefore, a flux reconstruction for curved non-conforming interfaces is also proposed. The objective is to find a function $\sigma(\boldsymbol{x})$ to define a curved interface $I'_{L_{curved}}$ knowing only the position \boldsymbol{x} of the mesh points. The flow variables at the interface $I'_{L_{curved}}$ are then calculated as in Eq. (19):

$$\widetilde{u}_{L'} = \frac{1}{|I'_{L_{curved}}|} \int_{I'_{L_{curved}}} u_{RBF}(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x}$$

$$= \sum_{j'=1}^{n_v} \widetilde{\xi}_{j'} \left(\frac{1}{|I'_{L_{curved}}|} \int_{I'_{L_{curved}}} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^m \widetilde{\zeta}_q \left(\frac{1}{|I'_{L_{curved}}|} \int_{I'_{L_{curved}}} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right)$$
(20)

The calculation of the RBF coefficients $\tilde{\xi}_{j'}$ and $\tilde{\zeta}_q$ is described in appendix A.2.2.

The method to determine the function σ is presented for the 2-D grid of Fig. 7(a), composed of two blocks L and R separated by a curved interface. The curved interfaces to be defined by the function σ are denoted by $I'_{L_{curved}}$ and $(I_{R,1_{curved}}, ..., I_{R,j'+1_{curved}}, ..., I_{R,n_{v_{curved}}})$. In order to determine the function σ , a technique proposed by Carr et *al.* [30] for 3-D imaging reconstruction is employed. First, relations to be verified by the function σ at given mesh points are imposed. In particular, at the N_p grid points of blocks L and R lying on the interfaces $(I_{R,1_{curved}}, ..., I_{R,j'_{curved}}, I_{R,j'+1_{curved}}, ..., I_{R,n_{v_{curved}}})$ in Fig. 7(a), the function σ cancels out:

$$\sigma(\boldsymbol{x}_i) = 0 \quad 1 \le i \le N_p \tag{21}$$

where $x_i = (x_i, y_i, z_i)$ are the spatial coordinates of the *i*th-mesh point. In order to ensure that function σ differs from the zero-function, off-surface points are considered and non-zero values are given to the function σ at these points. In the present study, n_v points of block L and n_v points of block R are selected, corresponding to the centers of the cells adjacent to the grid interface. They are represented by black and grey circles in Fig. 7(b) for $n_v = 3$. A value of $\sigma = -1$ is given to the n_v points of block L, and $\sigma = 1$ is attributed to the n_v points of block R. Thus, the objective is to find the function σ so that the following relations are satisfied:

$$\begin{cases} \sigma(\boldsymbol{x}_i) = 0 & 1 \le i \le N_p \\ \sigma(\boldsymbol{x}_r) = 1 & 1 \le r \le n_v \\ \sigma(\boldsymbol{x}_l) = -1 & 1 \le l \le n_v \end{cases}$$
(22)

Copyright © 2018 John Wiley & Sons, Ltd. *Prepared using fldauth.cls*

where $(\boldsymbol{x}_r)_{1,...,n_v}$ and $(\boldsymbol{x}_l)_{1,...,n_v}$ are the positions of the centers of the n_v cells of blocks L and R, respectively. Then, given the set of points $S_N = [(\boldsymbol{x}_i)_{1,...,N_p}, (\boldsymbol{x}_r)_{1,...,n_v}, (\boldsymbol{x}_l)_{1,...,n_v}] = [(\boldsymbol{x}_j)_{1,...,N_s}]$ and the relations (22), the function σ is calculated by RBF interpolation [30]:

$$\sigma(\boldsymbol{x}) \simeq \sigma_{\text{RBF}}(\boldsymbol{x}) = \sum_{j=1}^{N_S} \Theta_j \Phi(\boldsymbol{x}, \boldsymbol{x}_j) + \sum_{q=1}^m \kappa_q P_q(\boldsymbol{x})$$
(23)

where $N_S = N_p + 2n_v$, and Θ_j and κ_q are the unknown interpolation coefficients computed similarly as for the ghost cells (see appendix A.1).



Figure 7. Computation of the function σ that defines the curved interfaces $I'_{L_{curved}}$ and $(I_{R,j'_{curved}})_{1 \le j' \le n_v = 3}$: (a) interfaces $I'_{L_{curved}}$ and $(I_{R,j'_{curved}})_{1 \le j' \le 3}$ and N_p points (squares) lying on the interfaces, (b) surface points (squares) where $\sigma = 0$ and off-surface points (circles) where $\sigma \neq 0$.

4. PROPERTIES OF THE RBF INTERPOLATION IN THE WAVENUMBER SPACE

The performance of the RBF interpolation is evaluated in the wavenumber space. For this purpose, a uniform 1-D mesh extending over the range [0, 1], composed of 81 points $(x_j)_{1 \le j \le 81}$ is considered:

$$x_j = (j-1)\Delta \quad \text{for} \quad 1 \le j \le 81 \tag{24}$$

with $\Delta = 1/80$. At the points x_j , a harmonic function $f_k(x) = \exp(ikx)$ is imposed, where k is the wavenumber with $k\Delta$ varying from 0 to π , and i is the complex number verifying $i^2 = -1$. For RBF interpolations, a second 1-D mesh, referred to as the RBF grid, is defined using $N_{\text{RBF}} = 41$ points located at the following positions:

$$x'_{j} = \left(0.2\Delta + \frac{j-1}{N_{\text{RBF}} - 1}\right) \quad \text{for} \quad 1 \le j \le N_{\text{RBF}}$$
(25)

In this way, the distance between two consecutive RBF grid points is equal to 2Δ and there is a full point-mismatch between the two 1-D meshes. The interpolation of f_k on the RBF grid is denoted g_k in the following. For consistency with the finite-volume flux reconstruction proposed in this study, the function g_k is defined over each segment $[x'_j, x'_{j+1}]$, with $j \in [1, N_{\text{RBF}} - 1]$. For $x \in [x'_j, x'_{j+1}]$, from Eq. (18), the function g_k writes as follows:

$$g_k(x) = \sum_{l=1}^{n_v} \xi_l \Phi(x, x_l) + P(x)$$
(26)

The n_v nearest mesh points (x_l) that surround point $x'_{j_M} = (x'_j + x'_{j+1})/2$ and where the values of f_k are known are used to determine the interpolation coefficients in Eq. (26). In this section, the influence of the number of points n_v is evaluated by performing interpolations using $n_v = 4$, 6, 8 and 20 points. The interpolations are carried out using the 2nd-degree polynomial function $P(x) = \zeta_0 + \zeta_1 x + \zeta_2 x^2$, where $(\zeta_j)_{0 \le j \le 2}$ are the unknown interpolation coefficients. The influence of the degree of P on the accuracy of the spatial discretization is discussed in section 5.

First, the accuracy of the RBF interpolation is examined. For this purpose, an interpolation error ϵ is computed as a function of the wavenumber k from the difference between the values of f_k and g_k over each segment $[x'_j, x'_{j+1}]$ as:

$$\epsilon(k) = \sum_{j=1}^{N_{\text{RBF}}-1} \int_{x'_j}^{x'_{j+1}} |f_k(x) - g_k(x)| \,\mathrm{d}x$$
(27)

where $|\cdot|$ is the complex modulus. Secondly, the energy of the interpolated signal g_k is compared with the energy of the original signal f_k through the evaluation of the integrals E_f and E_g defined as:

$$E_f(k) = \int_{x'_1}^{x'_{N_{\text{RBF}}}} |f_k(x)|^2 \, \mathrm{d}x = 1 \quad \text{and} \quad E_g(k) = \int_{x'_1}^{x'_{N_{\text{RBF}}}} |g_k(x)|^2 \, \mathrm{d}x \tag{28}$$

For comparison, interpolations are also performed using the polynomial functions of degrees 2 and 3 given by:

$$P_2(x) = c_1 + c_2 x + c_3 x^2 \tag{29}$$

$$P_3(x) = c_4 + c_5 x + c_6 x^2 + c_7 x^3$$
(30)

where $(c_j)_{1 \le j \le 7}$ are the interpolation coefficients. Note that, as for the RBF interpolations, the polynomial approximations (29) and (30) are defined by pieces over each segment $[x'_j, x'_{j+1}]$. The interpolations coefficients (c_i) are determined using a least-square approximation involving n_v nearest points surrounding point x'_{j_M} . More precisely, over each segment $[x'_j, x'_{j+1}]$, the values of (c_i) are calculated to minimize the functions χ_{P_2} and χ_{P_3} :

$$\chi_{P_2}(c_1, c_2, c_3) = \sum_{l=1}^{n_v=4} \frac{|P_2(x_l) - f_k(x_l)|^2}{(x_l - x'_{j_{\rm M}})^2}$$
(31)

$$\chi_{P_3}(c_4, c_5, c_6, c_7) = \sum_{l=1}^{n_v=6} \frac{|P_3(x_l) - f_k(x_l)|^2}{(x_l - x'_{j_M})^2}$$
(32)

299

The variations of the energy E_g obtained from the RBF interpolations using $n_v = 4$, 6, 8 and 20 points and from the polynomial interpolations with P_2 and P_3 are represented in Fig. 8(a) as a function of the normalized wavenumber $k\Delta$. When RBF is used, the value of E_q decreases with $k\Delta$,

indicating higher levels of dissipation at high wavenumbers. The highest levels of dissipation are 303 obtained using $n_v = 4$. In particular, for $k\Delta = \pi/3$, the energy is equal to 0.995 for $n_v = 4$ whereas 304 values $0.99 < E_q < 1$ are obtained for $n_v = 6$, 8 and 20. The dissipation obtained using RBF is 305 306 lower than that calculated from a polynomial interpolation of degree 2 over all the wavenumber range. In addition, using RBF, no energy amplification is observed whereas energy values $E_q > 1$ 307 are found using polynomial interpolation P_3 for $\pi/8 \le k\Delta \le \pi/2$ in Fig. 8(a). Therefore, it is 308 interesting to use RBF to preserve the energy stability and to maintain low dissipation levels for 309 wavenumbers $k\Delta < \pi/4$, which are well resolved by the present spatial discretization schemes. 310

The interpolation errors ϵ obtained using RBF and polynomial interpolations are represented in 311 Fig. 8(b) as a function of the wavenumber $k\Delta$. When RBF is used, the highest values of ϵ are 312 obtained for $n_v = 4$. In this case, the interpolation error is stronger than that calculated with the 313 polynomial interpolation P_3 for $k\Delta < \pi/2$. However, it is lower than the error computed with P_2 314 which involves the same number of interpolation points. When the number of interpolation points 315 n_v increases, as expected, the value of ϵ decreases all over the wavenumber range. For $n_v = 20$, as 316 a result, the error ϵ is lower than the error computed using P_3 for $\pi/12 < k\Delta < \pi$. For $k\Delta < \pi/12$, 317 it is higher than that obtained using P_3 , but is very small and lower than 5×10^{-6} . 318



Figure 8. Representation of (a) the energy E_g and (b) the interpolation error ϵ as a function of the normalized wavenumber $k\Delta$: RBF interpolations using $\circ n_v = 4, \dots, n_v = 6, - - n_v = 8, \dots, n_v = 20$, polynomial interpolations of \blacksquare degree 2 and \times degree 3. $- E_g = E_f = 1$.

5. ACOUSTIC PULSE

In order to examine the overall accuracy of the flux reconstruction presented for non-conforming grids above, an acoustic pulse is imposed in the vicinity of a non-conforming interface in a medium at rest. For this purpose, the two-dimensional domain of size $\ell \times \ell$ shown in Fig. 9(a) is considered, with $\ell = 100$ m. It is composed of two blocks separated by a non-conforming interface located at

323 $x = 0.6\ell$. At t = 0, the pulse is introduced at $x_p = 0.4\ell$ and $y_p = 0.5\ell$ as:

$$\begin{pmatrix}
\rho'(x,y) = A_p \exp\left(-\ln 2 \frac{(x-x_p)^2 + (y-y_p)^2}{\hbar^2}\right) \\
u'(x,y) = v'(x,y) = 0 \\
p'(x,y) = c_0^2 \rho'(x,y)
\end{cases}$$
(33)

where $\hbar = 0.03\ell$ is the pulse half-width, A_p is the pulse amplitude, and c_0 is the ambient sound speed. The ambient pressure and temperature are equal to $p_0 = 10^5$ Pa and $T_0 = 300$ K, respectively. Radiation boundary conditions and sponge layers are used. An exact solution of the problem can be derived from the linearized Euler equations [31]. In order to compare the numerical results obtained from the Navier-Stokes equations with the exact solution, an amplitude A_p of 0.1 Pa is chosen. In addition, the viscous terms in Eq. (1) are neglected in the simulations.

The performance of the flux reconstruction is evaluated using six Cartesian grids referred 330 to as pulsegrid1, pulsegrid2, pulsegrid3, pulsegrid4, pulsegrid5 and pulsegrid6, and two flux 331 reconstruction techniques with and without RBF interpolation. The RBF interpolations are carried 332 out using a number of $n_v = 8$ points. The influence of the degree deg(P) of the RBF polynomial 333 function in Eq. (18) is examined using polynomial functions of degree 0, 1 and 2. For the flux 334 reconstruction without RBF, 2nd-order interpolations are used in order to reconstruct the flow 335 variables in the ghost cells and at the grid interface [32]. This reconstruction, available in the elsA 336 solver [20], is described in appendix A.3. 337

The mesh parameters, namely the grid spacings Δx , and the grid spacings Δy^L and Δy^R at the 338 left and right hand sides of the block interface are given in Tab. I. The meshes pulsegrid2, pulsegrid3, 339 pulsegrid4, pulsegrid5 and pulsegrid6 are respectively 2, 3, 4, 5 and 6 times finer than pulsegrid1. 340 In all cases, at the left-hand side of the interface, a uniform grid spacing $\Delta x = \Delta y^L$ is used in the 341 directions x and y. For pulsegrid1, it is equal to 0.02ℓ . At the right hand-side of the interface, the 342 grid spacing is also equal to Δx in x direction whereas the mesh spacing Δy^R is twice larger than 343 Δy^L in y direction. In order to have a full point-mismatch at the grid interface, for $x > 0.6\ell$, in all 344 cases, the grid cells are shifted upwards of $0.5\Delta y^L$. 345

mesh	Δx	Δy^L	Δy^R
pulsegrid1	$\ell/50$	$\ell/50$	$\ell/25$
pulsegrid2	$\ell/100$	$\ell/100$	$\ell/50$
pulsegrid3	$\ell/150$	$\ell/150$	$\ell/75$
pulsegrid4	$\ell/200$	$\ell/200$	$\ell/100$
pulsegrid5	$\ell/250$	$\ell/250$	$\ell/125$
pulsegrid6	$\ell/300$	$\ell/300$	$\ell/150$

Table I. Mesh spacings used in the simulations of the pulse.

The time step Δt of the simulations is chosen sufficiently small so that the errors related to the time discretization are negligible. More precisely, its value is calculated in order to provide a CFL number $c_0\Delta t/\Delta x$ of 0.05 for $\Delta x = \ell/300$. The fluctuating pressure field p' obtained at $t = 1200\Delta t$ using pulsegrid2 is represented in Fig. 9(a). At this instant, the acoustic wave reaches the non-conforming interface. In order to evaluate the effective order of the spatial discretization in the presence of the non-conforming interface, the pressure fluctuation obtained at $t = 1200\Delta t$ is compared to the exact solution p'_{exact} through the L_2 relative error:

$$\epsilon_p = \left(\frac{\int_{\Omega_\epsilon} (p' - p'_{\text{exact}})^2 \mathrm{d}\Omega}{\int_{\Omega_\epsilon} p'^2_{\text{exact}} \mathrm{d}\Omega}\right)^{1/2}$$
(34)

where $\Omega_{\epsilon} = \{(x, y) \in \mathbb{R}^2 \mid 0.2\ell \le x, y \le 0.8\ell\}$. In finite-volume, p' is the averaged value of the fluctuating pressure over each cell of domain Ω_{ϵ} (see Eq. (8)). Therefore, for consistency, the exact solution is calculated similarly. The discrete form of Eq. (34) thus writes as:

$$\epsilon_p = \left(\frac{\sum_{\text{cell}\in\Omega_{\epsilon}} (p' - p'_{\text{exact cell}})^2}{\sum_{\text{cell}\in\Omega_{\epsilon}} p'^2_{\text{exact cell}}}\right)^{1/2}$$
(35)

where $p'_{\text{exact cell}} = (1/|\Omega_{\text{cell}}|) \int_{\Omega_{\text{cell}}} p'_{\text{exact}} d\Omega$ and $|\Omega_{\text{cell}}|$ is the volume of the cell. Simulations with four uniform Cartesian meshes without grid interfaces with grid spacings of $\Delta x = \Delta y = \ell/50$, $\ell/100, \ell/200$ and $\ell/300$ respectively have also been done for comparisons.

The errors ϵ_p obtained using the non-conforming grids with and without the flux reconstruction 359 based on RBF for polynomial functions of degrees 0, 1 and 2 are presented in Fig 9(b), as a function 360 of the grid spacing $\Delta x/\ell$. Those obtained using the meshes without grid interface are also indicated. 361 In all cases, the amplitude of ϵ_p decreases as the value of Δx tends to 0. Using the grid without 362 interface, the error profile follows a 6th-order convergence slope. This result is expected since the 363 present spatial discretization is based on 6th-order numerical schemes (see Fosso et al. [12]). With 364 non-conforming interfaces, the 6th-order convergence slope is not retrieved, and higher error levels 365 are obtained for $\Delta x \leq 0.005\ell$ compared to the simulations without interfaces. The stronger errors 366 are obtained using the flux reconstruction without RBF, with an error profile varying following a 367 2nd-order slope. When RBF is used, lower errors are obtained, and they decrease with the degree 368 of P. In particular, the error profile calculated with deg(P)=2 is in good agreement with that 369 obtained for conforming grids. In the following, the RBF interpolations are therefore performed 370 using deg(P)=2. 371



Figure 9. (a) Fluctuating pressure p' at $t = 1200\Delta t$ using pulsegrid2, with 10 isocontours from 10^{-4} to 10^{-2} Pa following a geometric progression of ratio 1.67. The non-conforming interface is shown in blue. (b) Error profiles ϵ_p as a function of the grid spacing $\Delta x/\ell$: RBF interpolations with polynomial functions $\triangle \deg(P)=0, \circ \deg(P)=1, \times \deg(P)=2, \bullet$ interpolation without RBF and \Box grids without interface.

Copyright © 2018 John Wiley & Sons, Ltd. Prepared using fldauth.cls

6. CONVECTION OF A VORTEX

The performance of the flux reconstruction on non-conforming grids is then evaluated by performing

2-D simulations of vortex convection on Cartesian and wavy meshes.

374 6.1. Cartesian grids

A round vortex is convected in a mean flow defined by a uniform Mach number M of 0.5, a pressure of 10^5 Pa and a temperature of 300 K. The two-dimensional computational domain used in the simulations extends from x = 0 down to x = 3L in the streamwise direction, and from y = 0 up to y = L in the transverse direction, where L = 0.1 m. It is divided into two blocks separated by a vertical non-conforming interface located at x = L. The vortex is defined by the velocity and pressure fluctuations:

$$\begin{cases} u' = -\frac{\Gamma}{R^2} (y - y_c) \exp\left(-\ln 2 \frac{(x - x_c)^2 + (y - y_c)^2}{2b^2}\right) \\ v' = \frac{\Gamma}{R^2} (x - x_c) \exp\left(-\ln 2 \frac{(x - x_c)^2 + (y - y_c)^2}{2b^2}\right) \\ p' = -\frac{\rho \Gamma^2}{2R^2} \exp\left(-\ln 2 \frac{(x - x_c)^2 + (y - y_c)^2}{b^2}\right) \end{cases}$$
(36)

where $(x_c = 0.5L, y_c = 0.5L)$ is the position of the vortex center at the initial time t = 0, $b = (\sqrt{\ln 2}/20)L \simeq 0.04L$ is the vortex Gaussian half-width, and Γ represents the vortex intensity given by:

$$\frac{\rho\Gamma^2}{2R^2} = 10^3 \operatorname{Pa} \tag{37}$$

where $R = b/\sqrt{\ln 2}$. The velocity and pressure fluctuations are superimposed onto the mean flow at t = 0.

The performance of the flux reconstruction is examined by performing simulations using 386 four meshes referred to as Finegrid, Mediumgrid, Coarsegrid, and Verycoarsegrid, and two flux 387 reconstruction techniques with and without RBF interpolations. When RBF is applied, the influence 388 of the number of interpolation points n_v is studied by carrying out interpolations with $n_v = 4$, 389 6, 8 and 12 points. The RBF interpolations are performed using a second-degree polynomial 390 function in Eq. (18). The influence of the degree of the polynomial function has been examined 391 by performing simulations using polynomial functions of degrees 0, 1 and 2. The use of the second-392 degree polynomial function provided the lowest spurious noise levels at the grid interface. For the 393 sake of concision, these results are not presented in this study. Views of the four meshes close to 394 the block interface are given in Fig. 10. The mesh parameters, including the grid spacings Δx in 395 the streamwise direction, and the grid spacings Δy^L and Δy^R at the left and the right sides of 396 the block interface are provided in Tab. II. In all cases, in the streamwise direction, a grid spacing 397 of $\Delta x = \Delta = L/255$ is used. The vortex half-width b is thus discretized by 10 points, given that 398 $b = 10.6\Delta$. In the transverse direction, on the left hand side of the interface, the grid spacing Δy^L 399 is equal to Δ . On the right hand side, the mesh resolution in the y direction is different from Δ . 400 More precisely, the grid spacing Δy^R is respectively equal to 0.5 Δ , 2 Δ , 4 Δ and 6 Δ for Finegrid, 401 Mediumgrid, Coarsegrid and Verycoarsegrid, corresponding to a discretization of the vortex half-402 width by 21.2, 5.3, 2.6 and 1.8 points. In addition, in order to ensure a full point-mismatch at the 403

18

grid interface, for x > L, the cells are shifted upwards of $\Delta y^R/2$ for Finegrid and of $\Delta y^L/2$ for the meshes Mediumgrid, Coarsegrid and Verycoarsegrid.



Figure 10. Representation of the meshes close to the block interface: (a) Finegrid, (b) Mediumgrid, (c) Coarsegrid, and (d) Verycoarsegrid.

mesh	Δx	Δy^L	Δy^R
Finegrid	Δ	Δ	0.5 Δ
Mediumgrid	Δ	Δ	2Δ
Coarsegrid	Δ	Δ	4Δ
Verycoarsegrid	Δ	Δ	6Δ

Table II. Mesh spacings for the Fine, Medium, Coarse, and Verycoarse grids.

The time step Δt in the computations is chosen in order to impose a CFL number 406 $(1+M)c_0\Delta t/\Delta$ of 0.4, where c_0 is the ambient sound speed. When the vortex crosses the block 407 interface, spurious waves are generated due to the difference in grid resolution as well as to the 408 specific spatial discretization at the interface. The objective here is to ensure that the amplitude 409 of these spurious waves is very low with respect to the pressure deficit in the vortex. For that, 410 the pressure field $p_{\text{interface}}$ obtained in the multiblock simulations is compared with the pressure 411 field $p_{\text{no-interface}}$ computed from a simulation without block interface. That monoblock simulation is 412 carried out using the same computational domain with mesh spacings $\Delta x = \Delta y = \Delta$. By comparing 413 the pressure $p_{\text{interface}}$ with $p_{\text{no-interface}}$ instead of with the analytical vortex solution (36), the error 414 thus obtained only results from the effects of the non-conforming grid and not from discretization 415 errors. In addition, the pressure field differences $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ are only computed at 416 the left side of the block interface where the mesh is similar in the two computations. In this way, 417 the pressure fields p_{interface} and p_{no-interface} are computed at the same point. In particular, the time 418 evolution of Δp is recorded at the two mesh points A and B, indicated by squares in Fig. 11. They 419 are located, respectively, at the interface at x = L and y = 0.5L, and upstream of the block interface 420 at x = 0.8L and y = 0.75L. The signal recorded at point A provides information on the vortex 421 deformation at the block interface, while the signal at point B gives the amplitude of the spurious 422 waves propagating from the interface. 423

6.1.1. Grid sensitivity The influence of the mesh resolution is evaluated by performing four simulations using Finegrid, Mediumgrid, Coarsegrid and Verycoarsegrid. The simulation settings are given in Tab. III. In the four simulations, the flux reconstruction at the block interface is



Figure 11. Representation of the mesh points A and B (squares) where the pressure field is recorded.

⁴²⁷ performed using RBF, with interpolations on $n_v = 8$ points and the second-degree polynomial function $(P_q)_{(1,...,m)} = (1, x, y, x^2, y^2, xy)$.

mesh	flux reconstruction technique	n_v	RBF polynomial degree
Finegrid	RBF	8	2
Mediumgrid	RBF	8	2
Coarsegrid	RBF	8	2
Verycoarsegrid	RBF	8	2

Table III. Parameters of the simulations in the grid sensitivity study.

428

The time evolution of the pressure $|\Delta p| = |p_{\text{interface}} - p_{\text{no-interface}}|$ recorded at points A and B in 429 the simulations is presented in Fig. 12, where $|\cdot|$ is the absolute value. The vertical blue line in the 430 figures indicates the moment when the vortex hits the block interface. The signal amplitudes are 431 displayed in log scale in order to enhance the differences between the simulations. At point A, in 432 Fig. 12(a), the maximum value of $|\Delta p|$ is obtained at the instant when the vortex crosses the interface 433 in all cases. Using Verycoarsegrid, the pressure fluctuation peak is equal to 28.1 Pa, corresponding 434 to 2.7% of the pressure at the center of the vortex. Using Coarsegrid, the pressure difference reaches 435 a value of 5 Pa. Using the medium and the refined meshes, the amplitudes of the spurious waves at 436 point A are significantly lower than those found for the coarse grids, and do not exceed 0.9 Pa and 437 0.2 Pa, respectively. At point B in Fig 12(b), the noise level also decreases as the mesh is refined at 438 the right hand side of the block interface. Indeed, maximum pressure differences of 3.6 Pa, 0.4 Pa, 439 0.1 Pa and 0.03 Pa are obtained in Verycoarsegrid, Coarsegrid, Mediumgrid and Finegrid. These 440 levels are much lower than those at point A. Note that using Verycoarsegrid, the vortex half-width b 441 is only discretized by 1.8 points at the right side of the block interface. As a consequence, the mesh 442 is not fine enough and the vortex structure is strongly modified when it crosses the block interface, 443 yielding $|\Delta p| > 0.5$ Pa at points A and B for $t > 10000\Delta t$. These results demonstrate that non-444 conforming grids must be designed such that the flow field is correctly discretized at both sides 445 of the interface. In the present simulations, given the vortex Gaussian half-width b, a grid spacing 446 $\Delta y^R \leq 4\Delta$ is recommended, corresponding to a discretization of the half-width b by 2.6 points 447 (i.e 5.2 points in the vortex width). This result was expected since the numerical methods used 448 in this study well-calculate the scales discretized by at least 5 points per wavelength [14]. Let us 449 mention that values $\Delta y^R > 4\Delta$ could be used in sponge zones, that is to say in flow regions close 450 to the domain boundaries where the mesh is deliberately coarse in order to damp hydrodynamic 451 fluctuations before they reach the boundary conditions. 452



Figure 12. Representation of the time evolution of the pressure difference $|\Delta p| = |p_{\text{interface}} - p_{\text{no-interface}}|$ (a) at point A and (b) at point B: - - - Finegrid, — Mediumgrid, - - Coarsegrid, and · · · · Verycoarsegrid. The vertical blue line indicates the moment when the vortex hits the interface.

6.1.2. Influence of the number of points used for RBF interpolations In order to study the
influence of the number of points n_v used for RBF interpolations, four simulations are carried
out using n_v = 4, 6, 8 and 12 points respectively. The simulation parameters are given in Tab. IV.
The medium grid with mesh spacings Δx = Δy^L = Δ and Δy^R = 2Δ, and the second-degree polynomial function for RBF interpolation are used in all cases.

mesh	flux reconstruction technique	n_v	RBF polynomial degree
Mediumgrid	RBF	4	2
Mediumgrid	RBF	6	2
Mediumgrid	RBF	8	2
Mediumgrid	RBF	12	2

Table IV. Parameters of the simulations in the study of the influence of the number of points for RBF interpolations.

457

The time variations of the pressure difference $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ recorded at points A and 458 B are displayed in Fig. 13. The maximum spurious noise levels are observed using $n_v = 4$, when 459 interpolations are performed using 4 points. In this case, peaks of 1.6 Pa and 0.3 Pa are obtained 460 at the interface and upstream. When interpolations are carried out on 6 points, the noise levels are 461 reduced by at least 60% at both points A and B compared to the case using $n_v = 4$. Increasing the 462 number of interpolation points from 6 to 8 also leads to a decrease of noise levels upstream of the 463 block interface in Fig. 13(b), whereas no improvement is found at the interface in Fig. 13(a). Finally, 464 the pressure signals obtained using $n_v = 8$ and 12 have similar shapes suggesting that using 8 points 465 for RBF interpolations is sufficient to reach accurate results in the present test case. 466

6.1.3. Influence of the flux reconstruction technique In this section, the performance of the flux reconstruction based on RBF interpolations is compared with that of a flux reconstruction without RBF. The flux reconstruction without RBF, available in the *elsA* solver [20], is described in appendix A.3. In the following, four simulations are performed with and without RBF, using Mediumgrid and Coarsegrid. The simulation parameters are provided in Tab. V. The RBF interpolations are carried out using $n_v = 8$ points and the second-degree polynomial function.



Figure 13. Representation of the time evolution of the pressure difference $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ (a) at point A and (b) at point B: $\dots n_v = 4$, $\circ n_v = 6$, $\blacktriangle n_v = 8$ and $\dots n_v = 12$ points. The vertical blue line indicates the moment when the vortex hits the interface.

The time variations of the pressure error Δp obtained at points A and B in the simulations using 473 Mediumgrid are presented in Fig. 14. The flux reconstruction technique without RBF provides 474 higher noise levels compared to the technique using RBF, especially at point B where the signal 475 amplitude is 7.5 times higher. The pressure signals obtained using Coarsegrid are displayed in 476 Fig. 15. Using the RBF technique, maximum values of 5 Pa and 0.45 Pa are reached at points 477 A and B, whereas values of 17.8 Pa and 2 Pa are obtained without RBF. Thus, the use of the flux 478 reconstruction technique based on RBF allows us to reduce both the modifications of the vortex 479 structure and the generation of spurious pressure waves at the block interface. 480

mesh	flux reconstruction technique	n_v	RBF polynomial degree
Mediumgrid	RBF	8	2
Mediumgrid	no RBF	8	2
Coarsegrid	RBF	8	2
Coarsegrid	no RBF	8	2

Table V. Parameters of the simulations in the study of the influence of the flux reconstruction technique.



Figure 14. Representation of the time evolution of the pressure difference $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ (a) at point A and (b) at point B using Mediumgrid: — RBF, – – – no RBF. The vertical blue line indicates the moment when the vortex hits the interface.

Copyright © 2018 John Wiley & Sons, Ltd. *Prepared using fldauth.cls*



Figure 15. Representation of the time evolution of the pressure difference $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ (a) at point A and (b) at point B using Coarsegrid: — RBF, – – no RBF. The vertical blue line indicates the moment when the vortex hits the interface.

481 6.2. Wavy grids

In order to examine the performance of the flux reconstruction for curved non-conforming 482 interfaces, the vortex defined in section 6.1 is convected on 2-D wavy grids. Three computational 483 domains, presented in Fig. 16, are considered. They are composed of 2 blocks separated by a wavy 484 non-conforming interface located close to x = L, where L = 0.1 m. The wavy grid interfaces are 485 defined by a sinusoïdal shape of wavelength λ_x and of amplitude λ_y . The values of λ_x and λ_y are 486 provided in Tab. VI for the different meshes. In the grid referred to as wavy1, the block interface 487 has a height of $\lambda_y = 24b$ and a sinusoïdal shape of amplitude of $\lambda_x = 8b$, where b is the vortex half-488 width. In wavy2, the amplitude of the sinusoïdal interface is two times higher than in wavy1, i.e. 489 $\lambda_x = 16b$, but $\lambda_y = 24b$ as previously. In wavy3, the block interface is composed of three sinusoïdal 490 arches with $\lambda_x = \lambda_y = 8b$. In all cases, a grid spacing $\Delta x = \Delta = L/127$ is used in the x direction, 491 leading to a vortex half-width discretized by 5.3 points. In the y direction, the grid spacing is equal 492 to $\Delta y^L = \Delta$ at the left hand side of the interface. In order to create non-conforming grids, a mesh 493 spacing $\Delta y^R = L/87$ is applied at the right hand side of the interface, yielding $b = 2.6\Delta$. The 494 vortex, convected from the left to the right, is initially located at $y_0 = 0.5L$, and at equal distance 495 from the domain inlet and the block interface in the x direction. 496

mesh	λ_x	λ_y
wavy1	8b	24b
wavy2	16b	24b
wavy3	8b	8b

Table VI. Parameters of the wavy grid interfaces.

Six simulations are performed using wavy1, wavy2 and wavy3, and the flux reconstructions designed for plane and curved interfaces. Their parameters are given in Tab. VII. In all cases, RBF interpolations are carried out using a number of $n_v = 8$ points and the second-degree polynomial function. The time step Δt in the computations is chosen such that CFL number $(1+M)c_0\Delta t/\Delta=0.2$.



Figure 16. Representation of the wavy computational domains: (a) wavy1, (b) wavy2, and (c) wavy3. The non-conforming interface is indicated by a bold line.

The spurious noise generated at the block interface is not recorded at specific points as for the 502 Cartesian grids in section 6.1. Indeed, since the shapes of the block interfaces in wavy1, wavy2, and 503 wavy3 differ, the distance between a given point and the interface is not identical in the three grids. 504 Therefore, the computation of the pressure difference $\Delta p = p_{\text{interface}} - p_{\text{no-interface}}$ at specific points 505 is not relevant. Instead, the pressure difference is determined over all the computational domain. 506 In order to compute the pressure field p_{no-interface}, for each wavy grid, two simulations are carried 507 out using conforming meshes. The first conforming mesh coincides with the non-conforming grid 508 at the left-hand side of the interface, whereas the second mesh matches the resolution of the non-509 conforming grid at the right-hand side. 510

mesh	flux reconstruction technique	n_v	RBF polynomial degree
wavy1	RBF curve	8	2
wavy2	RBF curve	8	2
wavy3	RBF curve	8	2
wavy1	RBF plane	8	2
wavy2	RBF plane	8	2
wavy3	RBF plane	8	2

Table VII. Parameters of the simulations in the study of the influence of the flux reconstruction technique for curved interfaces.

Snapshots of the pressure difference Δp obtained at $t = 2800\Delta t$ using wavy1 and the flux reconstruction for plane and curved interfaces are presented in Fig. 17. At this time, the vortex core is located at x = 1.5L. In both cases, the presence of the non-conforming grid interface results in a significant discretization error around the vortex core as well as in the emission of spurious pressure waves of amplitude about 10 Pa. The simulation using the flux reconstruction technique designed for curved interfaces provides a maximum noise level of 5.2 Pa, which is two times lower than that obtained in the simulation using the reconstruction for plane interfaces.



Figure 17. Representation of the pressure difference Δp at $t = 2800\Delta t$ using wavy1: flux reconstruction for (a) plane interfaces and (b) curved interfaces, levels given in Pa.

The pressure difference Δp obtained at $t = 2800\Delta t$ using wavy2 is plotted in Fig. 18. Noise levels of 10-20 Pa are found. They are higher compared to the results obtained using wavy1 in Fig. 17. This is due to the block interface which displays stronger variations than that using wavy1. The pressure difference obtained in Fig. 18 (a) with the flux reconstruction technique for curved interfaces shows weaker pressure wave amplitudes compared to the pressure difference obtained in Fig. 18 (b) for the plane interface reconstruction.



Figure 18. Representation of the pressure difference Δp at $t = 2800\Delta t$ using wavy2: flux reconstruction for (a) plane interfaces and (b) curved interfaces, levels given in Pa.

Snapshots of the pressure difference Δp obtained using wavy3 at $t = 2800\Delta t$ are displayed in Fig. 19. As for wavy1 and wavy2, lower spurious noise is found using the curved reconstruction technique than the plane one. However, the use of a block interface with 3 arches generates higher spurious noise levels than previously, with maximum values of Δp of 200 Pa reached at this instant. In particular, the vortex core, located at x = 1.5L is strongly affected by the presence of the block interface. The use of non-conforming interfaces with low curvature therefore seems to be recommended.



Figure 19. Representation of the pressure difference Δp at $t = 2800\Delta t$ using wavy3: flux reconstruction for (a) plane interfaces and (b) curved interfaces, levels given in Pa.

Copyright © 2018 John Wiley & Sons, Ltd. *Prepared using fldauth.cls*

7. THREE-DIMENSIONAL JET

In order to demonstrate the applicability of the flux reconstruction technique to a 3-D simulation, a circular isothermal jet is computed using a Cartesian mesh with a non-conforming interface. The aim is to prove that the use of non-conforming interfaces does not significantly affect the jet flow development and the sound field radiated by the jet in the near-field region.

535 7.1. Jet definition

The jet flow has a Mach number of $M = u_j/c_0 = 0.9$ and a Reynolds number of Re_D = $u_j D/\nu = 4 \times 10^5$, corresponding to the conditions of the jet in the numerical simulation of Bogey and Bailly [33], where D and u_j are the jet diameter and velocity, c_0 is the sound speed and ν is the molecular viscosity. The ambient pressure p_0 and temperature T_0 are respectively equal to 10^5 Pa and 300 K. The jet inflow, located at x = 0, is characterized by the mean longitudinal velocity profile given by the hyperbolic tangent-profile:

$$u(r) = \frac{1}{2}u_j \left(1 + \tanh\left(\frac{r_0 - r}{2\delta_\theta}\right)\right)$$
(38)

where $\delta_{\theta} = r_0/20$ is the initial momentum thickness of the shear layer, $r_0 = D/2$ is the jet radius, and $r = \sqrt{y^2 + z^2}$. The mean density profile is computed from a Crocco-Busemann relation:

$$\rho(r) = \rho_j \left(1 + \frac{\gamma - 1}{2} M^2 \frac{u(r)}{u_j} \left(1 - \frac{u(r)}{u_j} \right) \right)^{-1}$$
(39)

The azimuthal and radial velocities are initially null, and the pressure is equal to p_0 . In order to seed the laminar-turbulent transition of the jet flow, vortex rings are added to the flow field in the shear layer at $x = r = r_0$, at each time step of the computation [34]. The amplitude of the perturbations is equal to $\alpha = 0.007$ and the half-width of the Gaussian profile that defines the vortices is equal to $\Delta_0 = 0.045r_0$. The small disturbances are divergence-free to minimize the production of spurious acoustic waves.

550 7.2. Numerical set-up

Two simulations are carried out using Cartesian grids with and without a non-conforming interface. The computational domain extends from x = 0 up to $x = 48r_0$ in the flow direction and from 0 up to $20r_0$ in the y and z directions.

The spatial discretization in the grid without a non-conforming interface is presented in Fig. 20. In the x direction, for $0 \le x \le 25r_0$, the axial mesh spacing is constant with $\Delta x = 0.1r_0$, and then increases with a rate of 0.4% up to $x = 35r_0$, and with a rate of 8% for $x > 35r_0$. In the y and z directions, the mesh is finer than in the x direction in order to resolve the shear layers. The grid spacing does not vary for $y, z \le r_0$, with $\Delta y = \Delta z = r_0/30$. For $y, z > r_0$, a stretching ratio of 2% is applied up to $r = 20r_0$.

The non-conforming mesh is built from the conforming mesh. Figure 21 provides a simplified representation of the two meshes in the x-y plane, with the non-conforming interface indicated by a bold line in Fig. 21(b). In the jet flow region, for $x \le 14r_0$, the two meshes are identical.



Figure 20. Representation of the spatial discretizations in the conforming grid: (a) axial discretization and (b) discretization in the y and z directions.

Downstream of the end of the jet potential core expected to be around $x_p \simeq 10r_0$ according to 563 reference [35], a non-conforming interface is defined at $x = 14r_0$, as shown in Fig. 21(b). The 564 location of the interface is chosen downstream of the jet sound source region, which is found for 565 $x \leq x_p$. For $x > 14r_0$, the very fine mesh spacings used in the y and z directions at the jet inlet to 566 discretize the jet shear layers are not necessary due to the jet spreading. Therefore, downstream of 567 the interface, the grid spacings Δy and Δz in the non-conforming mesh are twice as coarse as in the 568 conforming grid. Thus, the number of mesh points in the non-conforming grid, equal to 42 million 569 points, is reduced by 44% compared to the conforming grid. 570

571 The conforming grid used in the present work is finer than the one used in the reference [33] by

- 572 factors of 1.3 and 2 in the axial and radial directions respectively. In addition, since the resolutions
- of the two grids used in this study differ for $x > 14r_0$, small differences between the results from the
- two simulations are expected, as demonstrated by the grid sensitivity of turbulent jet flows presented in reference [36].



Figure 21. Sketch of (a) the conforming grid and (b) the non-conforming grid in the x-y plane.

575

In each computation, the jet flow is simulated over a time period $T = 2 \times 10^5 \Delta t = 2000 r_0/c_0$. The flow initialization lasts over $600r_0/c_0$. The velocity and pressure fields are then recorded during a sampling period $T_s = 1400r_0/c_0$, leading to a minimum Strouhal number St_{min} = $D/(T_s u_j)$ of 1.6×10^{-3} . In order to study the development of the jet flow, the velocity field is recorded along the jet axis and at $r = r_0$. In order to examine the acoustic sound radiated in the near-field region, pressure spectra at $r = 8r_0$ are computed by averaging over 8 points equally distributed on circles centered on the jet axis. The data are sampled every 10 time steps in order to compute spectra up to a maximum Strouhal number $St_{max} = fD/u_j = 5.55$, and the spectra are evaluated from overlapping samples of duration $93.3r_0/c_0$.

At the non-conforming interface, the flux reconstruction for plane interfaces presented in section 3.1 is applied. The RBF interpolations are performed using $n_v = 8$ points and seconddegree polynomial functions. The choice of the values of n_v and deg(P) is motivated by the fact that it provided accurate results for an acoustic pulse propagation and for a vortex convection on non-conforming Cartesian grids in two-dimensional problems (see sections 5 and 6.1).

590 7.3. Results

Snapshots of the vorticity magnitude and the fluctuating pressure obtained in the two simulations 591 are presented in Fig. 22. The non-conforming interface at $x = 14r_0$ is indicated by a vertical line 592 in Fig. 22(b). In the two simulations, the jet mixing layers are found to develop from $x = r_0$ and 593 to interact around $x = 12r_0$. Farther downstream, in Fig. 22(b), vortical structures cross the non-594 conforming interface and display lower levels than those located upstream for $x < 14r_0$. These 595 levels are also lower than those obtained for $x > 14r_0$ in Fig. 22(a). This is most likely due to 596 the mesh resolution that is twice as coarse in the y direction for $x > 14r_0$ in the non-conforming 597 grid [36]. In the pressure field, acoustic waves propagate from the jet with an angle of about 30° 598 relative to the x-axis. In Fig. 22(b), no discontinuity of the pressure waves radiated from the jet and 599 no spurious reflection are visible in the vicinity of the non-conforming interface. 600



Figure 22. Snapshots in the x-y plane of the vorticity modulus in the flow and of the fluctuating pressure outside obtained from the simulations using (a) a conforming grid and (b) a non-conforming grid. The color scale is from 0 to $2.5u_j/r_0$ for the vorticity and the grey scale is from -70 to 70 Pa for the pressure.

More quantitative results are shown in Fig. 23, where the mean axial velocity profiles obtained in the two simulations are given along the jet axis and at $r = r_0$. In Fig. 23(a), the two profiles along the jet axis are superimposed for $x \le 20r_0$. They indicate that in both jets, the jet potential core ends at $x_p = 12r_0$. For $x > 20r_0$, slightly lower velocity values are found using the non-conforming grid, with differences that do not exceed $0.025u_j$. In Fig. 23(b), the velocity profiles at $r = r_0$ are also superimposed upstream of the grid interface, whereas velocity is lower by $0.02u_j$ for $x > 14r_0$ in the simulation using a non-conforming grid.



Figure 23. Representation of the mean axial velocity (a) along the jet centerline and (b) at $r = r_0$: simulations with — a conforming grid and — a non-conforming grid.

The rms axial and radial velocities $\langle u'_x u'_x \rangle^{1/2} / u_j$ and $\langle u'_r u'_r \rangle^{1/2} / u_j$ calculated at $r = r_0$ 608 are represented in Fig. 24, where the prime stands for the fluctuating quantity and $\langle \cdot \rangle$ for time 609 average. In Fig. 24(a) and 24(b), in the same way as for the mean profiles of Fig. 23(b), the 610 profiles from the two simulations are identical for $x < 14r_0$, with the same peaks of turbulence. 611 For $x \ge 14r_0$, small differences of less than 1% appear between the two computations. In particular, 612 using a non-conforming grid, the rms profiles slightly decrease at the non-conforming interface 613 $x = 14r_0$ and present a small hump downstream for $17r_0 \le x \le 27r_0$. Despite this, for $x \ge 27r_0$, 614 very similar turbulent levels are found in the two simulations. The small differences reported 615 between the two simulations in Fig. 23 and 24 are likely due to the resolution of the non-conforming 616 grid that is coarser for $x \ge 14r_0$ [36]. 617



Figure 24. Representation of the (a) axial and (b) radial rms velocity profiles at $r = r_0$: simulations with — a conforming grid and — a non-conforming grid.

In order to investigate the effects of the presence of the non-conforming interface on the jet flow features, axial velocity spectra are computed at three locations along the jet axis, upstream of the non-conforming interface at $x = 13.4r_0$, and downstream of the interface at $x = 14.7r_0$ and at $x = 20r_0$. The spectra are represented in Fig. 25 as a function of the Strouhal number. At $x = 13.4r_0$, the spectra exhibit similar shapes and levels, which suggests that the jet flow components are not affected by the close proximity of the non-conforming interface. Downstream of the interface, at $x = 14.7r_0$, the spectra from the two simulations show similar levels for St < 2whereas a more pronounced decrease is observed for St ≥ 2 for the spectrum obtained using the non-conforming grid. At $x = 20r_0$, the spectrum from the non-conforming grid displays slightly higher levels at low Strouhal numbers and collapses more rapidly for St ≥ 2 . The origin of the small differences observed here does not seem to be related to the presence of the non-conforming interface but to a poorer discretization of the jet coherent structures using the non-conforming mesh [36].



Figure 25. Representation of the axial velocity spectra on the jet axis (a) upstream of the grid interface at $x = 13.4r_0$, and downstream at (b) $x = 14.7r_0$ and (c) $x = 20r_0$: — conforming grid and — non-conforming grid.



Figure 26. Representation of the pressure spectra at $r = 8r_0$ (a) upstream of the grid interface at $x = 13.4r_0$, and downstream at (b) $x = 14.7r_0$ and (c) $x = 20r_0$: — conforming grid and — non-conforming grid.

Finally, to examine the acoustic results in the near-field region, pressure spectra at $r = 8r_0$ are 631 plotted in Fig. 26 for the axial positions $x = 13.4r_0$, $x = 14.7r_0$ and $x = 20r_0$. The spectra at the 632 three locations display broadband shapes, which is typical of subsonic turbulent jet noise [37]. 633 Upstream of the grid interface, at $x = 13.4r_0$, the spectra from the two simulations are very similar, 634 which is expected since the two meshes are identical for $x \leq 14r_0$. Downstream of the interface, 635 at $x = 14.7r_0$ and $x = 20r_0$, the acoustic spectra predicted by the two simulations are in good 636 agreement for Strouhal numbers St < 2. For $St \ge 2$, the spectrum obtained from the non-conforming 637 grid collapses more rapidly. This drop is due to the lower mesh cut-off Strouhal number in that 638 case. Indeed, at $r = 8 r_0$, considering that the spatial schemes resolve wavelengths discretized by at 639 least 5 points [14], the cut-off Strouhal number is of $St_{cut-off} = 2$ for the non-conforming grid and of 640 $St_{cut-off} = 4$ for the conforming grid. 641

These results demonstrate that the present non-conforming grid methodology can be used in order to reduce the size of the mesh and thus the computational cost, without appreciably biasing the jet development and the noise field radiated by the jet.

8. CONCLUSION

In this study, a flux reconstruction technique is presented in order to perform aeroacoustic 645 computations using high-order finite-volume spatial schemes on structured meshes including non-646 conforming grid interfaces. The spatial discretization is carried out using a sixth-order implicit 647 scheme in combination with a sixth-order implicit selective filter. The flux reconstruction can 648 be applied to plane or curved non-conforming interfaces. It is performed using non-centered 649 formulations for the spatial scheme and the selective filter at the non-conforming interface. These 650 formulations require the definition of ghost cells and ghost interfaces. The flow variables in the 651 ghost cells and at the interfaces are computed using meshless interpolations with radial basis 652 functions. For computational efficiency, all the interpolation coefficients are computed once in the 653 beginning of the simulation and then stored in memory. The properties of the RBF interpolations 654 in the wavenumber space are studied. The accuracy of the flux reconstruction is evaluated for an 655 acoustic pulse introduced in the vicinity of a non-conforming interface using 2-D Cartesian grids. 656 RBF interpolations using $n_v = 8$ points in conjunction with a 2nd-degree polynomial function are 657 found to be sufficient to obtain accurate results. The performance of the flux reconstruction is 658 then examined for the convection of a vortex using 2-D Cartesian and wavy grids. The results 659 on Cartesian grids highlight the benefits of using RBF interpolations, instead of a low-order flux 660 reconstruction, in order to reduce the spurious pressure waves produced at the block interface. The 661 results obtained with different spatial resolutions also show that the non-conforming grids must 662 be designed such that the flow field is well discretized by the mesh before and after the grid 663 interface. The results of the computations performed on wavy grids demonstrate the advantages 664 of using the flux reconstruction for curved interfaces. More precisely, the flux reconstruction 665 technique designed for curved interfaces produces lower spurious noise level than those obtained 666 using the reconstruction for plane interfaces. It seems also recommended to use low curvature 667 non-conforming interfaces. Finally, the application of the flux reconstruction technique to 3-D 668 flows is illustrated for a turbulent round jet flow at a diameter-based Reynolds number of 4×10^5 . 669 Simulations are performed with and without a non-conforming grid interface downstream of the jet 670 potential core. The jet development is only slightly affected by the presence of the non-conforming 671 grids, and the acoustic spectra in the near-field region are very similar. 672

ACKNOWLEDGMENTS

This study, financially supported by Airbus, was performed at CERFACS in the context of the PhD thesis of the first author. The authors gratefully acknowledge Dr. Marc Montagnac for his crucial help in the development of the numerical code used in this work. The post-processing of the numerical results is carried out using Antares (release 1.11.0, https://www.cerfacs.fr/antares) [38].

APPENDIX

A. CALCULATION OF RBF INTERPOLATION COEFFICIENTS

677 A.1. Interpolation of the flow variables in the ghost cells

As presented in section 3.1.3, in order to reconstruct the flow variables in the ghost cells, RBF interpolations are performed. A RBF interpolation u_{RBF} of the variable u at point \boldsymbol{x} is defined as a linear combination of Wendland's radial basis functions Φ and a polynomial term:

$$u_{\rm RBF}(\boldsymbol{x}) = \sum_{j=1}^{n_v} \xi_j \Phi(\boldsymbol{x}, \boldsymbol{x}_j) + \sum_{q=1}^m \zeta_q P_q(\boldsymbol{x})$$
(40)

where ξ_j and ζ_q are the unknown interpolation coefficients. In this study, C^2 Wendland's basis functions [9,28] with compact support are used:

$$\Phi(\boldsymbol{x}, \boldsymbol{x}_j) = \Phi(r_j) = \left(1 - \frac{r_j}{R_v}\right)_+^4 \left(4\frac{r_j}{R_v} + 1\right) \quad 1 \le j \le n_v \tag{41}$$

where r_j is the Euclidian distance between the points \boldsymbol{x} and \boldsymbol{x}_j , $(1 - \frac{r_j}{R})_+$ is defined by:

$$\left(1 - \frac{r_j}{R_v}\right)_+ = \begin{cases} \left(1 - \frac{r_j}{R_v}\right) & \text{if } 0 \le r_j \le R_v \\ 0 & \text{if } r_j > R_v \end{cases}$$
(42)

and R_v is the radius of the circle of center \boldsymbol{x} defined such that $R_v = Ar_{\min}$, with $r_{\min} = \min(r_j)_{(j=1,..,n_v)}$ and A is a value chosen such that n_v cells are contained inside the circle. A representation of the ghost cell and the n_v cells is provided in Fig. 27.



Figure 27. Representation of the cloud of n_v cells used for the interpolation of the flow variables in the ghost cell. The center of the ghost cell is indicated by a star.

The values of ξ_j and ζ_q are determined so that the approximation $u_{\text{RBF}}(\boldsymbol{x})$ is exact for all the n_v points. Therefore, the interpolation formulation (40) satisfies the following relations:

$$u_{\text{RBF}}(\boldsymbol{x}_k) = u_k = \sum_{j=1}^{n_v} \xi_j \Phi(\boldsymbol{x}_k, \boldsymbol{x}_j) + \sum_{q=1}^m \zeta_q P_q(\boldsymbol{x}_k) \quad \text{for } 1 \le k \le n_v$$
(43)

where $(u_k)_{k=1,..,n_v}$ are the values of u known in the n_v cells considered for the interpolation. In order to ensure that approximation (40) has a unique solution [18, 29], the following orthogonality

Copyright © 2018 John Wiley & Sons, Ltd. Prepared using fldauth.cls

691 constraints are imposed:

$$\sum_{j=1}^{n_v} P_q(\boldsymbol{x}_j)\xi_j = 0 \quad \text{for } 1 \le q \le m$$
(44)

⁶⁹² Therefore, the values of ξ_j and ζ_q are computed by resolving the linear system:

$$\mathbf{M}\begin{pmatrix}\boldsymbol{\xi}\\\boldsymbol{\zeta}\end{pmatrix} = \begin{pmatrix}\boldsymbol{\Phi} & \mathbf{P}\\\mathbf{P}^T & \mathbf{0}\end{pmatrix}\begin{pmatrix}\boldsymbol{\xi}\\\boldsymbol{\zeta}\end{pmatrix} = \begin{pmatrix}\mathbf{u}^{\text{set}}\\\mathbf{0}\end{pmatrix}$$
(45)

where $\boldsymbol{\xi} = (\xi_1, ..., \xi_{n_v})^T$ and $\boldsymbol{\zeta} = (\zeta_1, ..., \zeta_m)^T$ are the vectors of the interpolation coefficients to be determined, $\mathbf{u}^{\text{set}} = (u_1, ..., u_{n_v})^T$, and $\boldsymbol{\Phi} \in \mathbb{R}^{n_v \times n_v}$ and $\mathbf{P} \in \mathbb{R}^{n_v \times m}$ are the matrices defined by:

$$\begin{aligned} \Phi_{kj} &= \Phi(\boldsymbol{x}_k, \boldsymbol{x}_j) \quad \text{for } 1 \le k, j \le n_v \\ \mathbf{P}_{kq} &= P_q(\boldsymbol{x}_k) \quad \text{for } 1 \le k \le n_v \text{ and } 1 \le q \le m \end{aligned}$$
 (46)

695 The solution of the system (45) writes:

$$\begin{pmatrix} \boldsymbol{\xi} \\ \boldsymbol{\zeta} \end{pmatrix} = \mathbf{M}^{-1} \begin{pmatrix} \mathbf{u}^{\text{set}} \\ \mathbf{0} \end{pmatrix} = \begin{pmatrix} \sum_{k=1}^{n_v} m_{1,k} u_k \\ \dots \\ \dots \\ \sum_{k=1}^{n_v} m_{n_v+m,k} u_k \end{pmatrix}$$
(47)

where $m_{i,j}$ are the coefficients of the matrix \mathbf{M}^{-1} . Introducing Eq. (47) in Eq. (40), the RBF interpolation applied to a ghost cell of center $\boldsymbol{x}_{\text{ghost}}$ is given by the relation:

$$u_{\rm RBF}(\boldsymbol{x}_{\rm ghost}) = \sum_{k=1}^{n_v} \Psi_k(\boldsymbol{x}_{\rm ghost}) u_k$$
(48)

where the coefficients $\Psi_k(\boldsymbol{x}_{\text{ghost}})$ are defined as:

$$\Psi_k(\boldsymbol{x}_{\text{ghost}}) = \sum_{j=1}^{n_v} m_{j,k} \Phi(\boldsymbol{x}_{\text{ghost}}, \boldsymbol{x}_j) + \sum_{q=1}^m m_{n_v+q,k} P_q(\boldsymbol{x}_{\text{ghost}})$$
(49)

Note that the n_v coefficients $\Psi_k(\boldsymbol{x}_{\text{ghost}})$ are independent of the flow variables. Therefore, they are computed and stored in memory at the beginning of the simulation. The interpolation is therefore performed at a low CPU cost since the value of u_{RBF} is simply obtained from the sum (48).

702 A.2. Interpolation of the flow variables at the non-conforming grid interface

A.2.1. Plane interfaces As described in section 3.1.3, the interpolation formulation at the block interface writes:

$$\tilde{u}_{L'} = \frac{1}{|I'_L|} \int_{I'_L} u_{\text{RBF}}(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x}$$

$$= \sum_{j'=1}^{n_v} \tilde{\xi}_{j'} \left(\frac{1}{|I'_L|} \int_{I'_L} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^m \tilde{\zeta}_q \left(\frac{1}{|I'_L|} \int_{I'_L} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right)$$
(50)

The interpolation coefficients $\tilde{\xi}_{j'}$ and $\tilde{\zeta}_q$ are determined by integrating Eq. (40) on the n_v interfaces ($I_{R,1}, ..., I_{R,j'}, I_{R,j'+1}, ..., I_{R,n_v}$) of Fig. 5(c), and by imposing that the integrals obtained are equal to the component \tilde{u} of vectors ($\widetilde{\mathbf{U}}_{R,1}, ..., \widetilde{\mathbf{U}}_{R,j'}, ..., \widetilde{\mathbf{U}}_{R,n_v}$) of block R. It yields for the interface $I_{R,k}$:

$$\tilde{u}_{R,k} = \sum_{j'=1}^{n_v} \tilde{\xi}_{j'} \left(\frac{1}{|I_{R,k}|} \int_{I_{R,k}} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^{m} \tilde{\beta}_q \left(\frac{1}{|I_{R,k}|} \int_{I_{R,k}} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right) \quad \text{for } 1 \le k \le n_v$$
(51)

708

where $\tilde{u}_{R,k}$ is a component of the averaged field $\widetilde{\mathbf{U}}_{R,k}$ at the interface $I_{R,k}$. In practice, the coefficients $\tilde{\xi}_{j'}$ and $\tilde{\zeta}_q$ are estimated by solving the linear system:

$$\begin{pmatrix} \widetilde{\Phi} & \widetilde{P} \\ \widetilde{P}^{T} & \mathbf{0} \end{pmatrix} \begin{pmatrix} \widetilde{\xi} \\ \widetilde{\zeta} \end{pmatrix} = \begin{pmatrix} \widetilde{\mathbf{u}}^{\text{set}} \\ \mathbf{0} \end{pmatrix}$$
(52)

711

⁷¹² where $\tilde{\boldsymbol{\xi}} = (\tilde{\xi}_1, ..., \tilde{\xi}_{n_v})^T$ and $\tilde{\boldsymbol{\zeta}} = (\tilde{\zeta}_1, ..., \tilde{\zeta}_m)^T$ are the vectors of the interpolation coefficients, ⁷¹³ $\tilde{\mathbf{u}}^{\text{set}} = (\tilde{u}_{R,1}, ..., \tilde{u}_{R,n_v})^T$, and $\tilde{\boldsymbol{\Phi}} \in \mathbb{R}^{n_v \times n_v}$ and $\tilde{\mathbf{P}} \in \mathbb{R}^{n_v \times m}$ are the matrices defined by:

$$\widetilde{\boldsymbol{\Phi}}_{kj'} = \frac{1}{|I_{R,k}|} \int_{I_{R,k}} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \quad \text{for } 1 \le k, l \le n_v$$

$$\widetilde{\boldsymbol{P}}_{kq} = \frac{1}{|I_{R,k}|} \int_{I_{R,k}} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \quad \text{for } 1 \le k \le n_v \text{ and } 1 \le q \le m$$
(53)

As in section A.1, the RBF interpolation (50) can be reformulated as:

$$\tilde{u}_{L'} = \sum_{k=1}^{n_v} \tilde{\Psi}_k u_k \tag{54}$$

715 where the coefficients $\widetilde{\Psi}_k$ are defined as:

$$\widetilde{\Psi}_{k} = \sum_{j'=1}^{n_{v}} \frac{1}{|I'_{L}|} \int_{I'_{L}} m'_{j',k} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \,\mathrm{d}\boldsymbol{x} + \sum_{q=1}^{m} m'_{n_{v}+q,k} \frac{1}{|I'_{L}|} \int_{I'_{L}} P_{q}(\boldsymbol{x}) \,\mathrm{d}\boldsymbol{x}$$
(55)

where $m'_{i,j}$ are the coefficients of the inverse of the matrix of the system (52). In practice, the values of $\tilde{\Psi}_k$ are computed only once and then stored in memory at the beginning of the simulation. 718 A.2.2. Curved interfaces In order to take into account the curvature effect of grid interfaces, the 719 interface $I'_{L_{curved}}$ is defined by the function σ . The interpolation formulation to compute the flow 720 component u at the interface $I'_{L_{curved}}$ writes, as in Eq. (50):

$$\widetilde{u}_{L'} = \frac{1}{|I'_{L_{\text{curved}}}|} \int_{I'_{L_{\text{curved}}}} u_{\text{RBF}}(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x}$$

$$= \sum_{j'=1}^{n_v} \widetilde{\xi}_{j'} \left(\frac{1}{|I'_{L_{\text{curved}}}|} \int_{I'_{L_{\text{curved}}}} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^{m} \widetilde{\zeta}_{q} \left(\frac{1}{|I'_{L_{\text{curved}}}|} \int_{I'_{L_{\text{curved}}}} P_{q}(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right)$$
(56)

The interpolation coefficients $\tilde{\xi}_{j'}$ and $\tilde{\zeta}_q$ are calculated by integrating Eq. (40) on the n_v interfaces ($I_{R,1_{curved}}, ..., I_{R,j'_{curved}}, I_{R,j'+1_{curved}}, ..., I_{R,n_{vcurved}}$) also defined by the function σ , and by imposing that the integrals thus obtained are equal to the component \tilde{u} of vectors ($\widetilde{\mathbf{U}}_{R,1}, ..., \widetilde{\mathbf{U}}_{R,j'}, ..., \widetilde{\mathbf{U}}_{R,n_v}$) of block R. It yields for the interface $I_{R,k_{curved}}$:

$$\tilde{u}_{R,k} = \sum_{j'=1}^{n_v} \tilde{\xi}_{j'} \left(\frac{1}{|I_{R,k_{\text{curved}}}|} \int_{I_{R,k_{\text{curved}}}} \Phi(\boldsymbol{x}, \boldsymbol{x}_{j'}) \, \mathrm{d}\boldsymbol{x} \right) + \sum_{q=1}^{m} \tilde{\zeta}_q \left(\frac{1}{|I_{R,k_{\text{curved}}}|} \int_{I_{R,k_{\text{curved}}}} P_q(\boldsymbol{x}) \, \mathrm{d}\boldsymbol{x} \right) \quad \text{for } 1 \le k \le n_v$$
(57)

725

where $\tilde{u}_{R,k}$ is a component of the averaged field $\widetilde{\mathbf{U}}_{R,k}$ at the interface $I_{R,k_{\text{curved}}}$. The coefficients $\tilde{\xi}_{j'}$ and $\tilde{\zeta}_q$ are then computed from the resolution of a linear system similar to (52).

729 A.3. Flux reconstruction without RBF interpolation

The technique of flux reconstruction without RBF interpolation is identical to the technique presented in section 3, except for the calculation of the flow variables in the ghost cells and at the grid interfaces which is performed using 2nd-order interpolations.

A.3.1. Interpolation for ghost cells The interpolation technique is described for the calculation of the flow variables **U** in the ghost cell located at (i' = 0, j) in Fig. 5(a). For this purpose, as shown in Fig. 28, the interface I_L in blue is divided in two parts I_{AM} and I_{MB} . The interface I_{AM} is the intersection between the interfaces I_L and $I_{R,j'}$, and the interface I_{MB} is the intersection between the interfaces I_L and $I_{R,j'+1}$. The value of **U** in the ghost cell is determined as the weighted sum of **U** in the cells (i' = 0, j') and (i' = 0, j' + 1) in block R:

$$\mathbf{U}_{i'=0,j} = \frac{S_{\rm AM}}{S_{\rm AB}} \mathbf{U}_{i'=0,j'} + \frac{S_{\rm BM}}{S_{\rm AB}} \mathbf{U}_{i'=0,j'+1}$$
(58)

where S_k is the surface of interface I_k . Similarly, the value of **U** in the second ghost cell in Fig. 5(a) is calculated as the weighted sum of **U** in the cells (i' = 1, j') and (i' = 1, j' + 1).

741 A.3.2. Interpolation at the grid interface In order to compute the convective flux at the non-742 conforming interface, the value of the vector $\tilde{\mathbf{U}}$ at the ghost interface I'_L in block R is computed



Figure 28. Representation of a non-conforming grid where the interface I_L is divided in two interfaces I_{AM} and I_{MB} . The flow variables in the ghost cell indicated in grey are computed as a weighted sum of the flow variables in cells (i' = 0, j') and (i' = 0, j' + 1).

743 as the weighted sum:

748 749

$$\widetilde{\mathbf{U}}_{L}^{\prime} = \frac{S_{\mathrm{AM}}}{S_{\mathrm{AB}}} \widetilde{\mathbf{U}}_{R,j^{\prime}} + \frac{S_{\mathrm{BM}}}{S_{\mathrm{AB}}} \widetilde{\mathbf{U}}_{R,j^{\prime}+1}$$
(59)

where the values of $\tilde{\mathbf{U}}$ at the interfaces $I_{R,j'}$ and $I_{R,j'+1}$ are computed from the upwind scheme (14). The value of $\tilde{\mathbf{U}}$ at the interface I_L is calculated from the upwind scheme (13). Finally, the convective flux at the block interface is determined from the values of $\tilde{\mathbf{U}}_L$ and $\tilde{\mathbf{U}}'_L$ by resolving a Riemann flux problem [25].

REFERENCES

- C Bailly, C Bogey, and O Marsden. Progress in direct noise computation. *International Journal of Aeroacoustics*, 9(1-2):123–143, 2010.
- C Bogey and C Bailly. A family of low dispersive and low dissipative explicit schemes for flow and noise computations. *Journal of Computational Physics*, 194(1):194–214, 2004.
- T Colonius and SK Lele. Computational aeroacoustics: progress on nonlinear problems of sound generation.
 Progress in Aerospace Sciences, 40(6):345–416, 2004.
- 4. C Bogey, O Marsden, and C Bailly. Large-eddy simulation of the flow and acoustic fields of a Reynolds number
 ⁷⁵⁷ 10⁵ subsonic jet with tripped exit boundary layers. *Physics of Fluids*, 23:035104, 2011.
- 5. C Bogey and C Bailly. Influence of nozzle-exit boundary-layer conditions on the flow and acoustic fields of initially
 laminar jets. *Journal of Fluid Mechanics*, 663:507–538, 2010.
- 6. GA Brès, P Jordan, T Colonius, M Le Rallic, V Jaunet, and SK Lele. Large eddy simulation of a Mach 0.9 turbulent
 jets. *Proceedings of the Summer Program*, pages 221–230, 2014.
- 762 7. D Desvigne, O Mardsen, C Bogey, and C Bailly. Development of noncentered wavenumber-based optimized 763 interpolation schemes with amplification control for overlapping grids. *SIAM Journal on Scientific Computing*, 764 32(4):2074–2098, 2010.
- J Huber, G Drochon, A Pintado-Peno, F Cléro, and G Bodard. Large-Scale Jet Noise Testing, Reduction and Methods validation "EXEJET": 1. Project Overview and Focus on Installation. 20th AIAA/CEAS Aeroacoustics Conference, paper AIAA-2014-3032, 2014.
- 9. WJ Costin and CB Allen. Numerical study of radial basis function interpolation for data transfer across discontinuous mesh interfaces. *International Journal for Numerical Methods in Fluids*, 72(10):1076–1095, 2013.
- 10. CKW Tam and JC Webb. Dispersion-relation-preserving finite difference schemes for computational acoustics.
 Journal of Computational Physics, 107:262–281, 1993.
- 11. SK Lele. Compact finite difference schemes with spectral-like resolution. *Journal of Computational Physics*, 103:16–42, 1992.
- 12. F Fosso Pouangué, H Deniau, F Sicot, and P Sagaut. Curvilinear finite volume scheme using high order compact interpolation. *Journal of Computational Physics*, 229(13):5090–5122, 2010.
- 13. MR Visbal and DV Gaitonde. On the use of higher-order finite-difference schemes on curvilinear and deforming
 meshes. *Journal of Computational Physics*, 181:155–185, 2002.

- 14. A Fosso Pouangué, M Sanjosé, S Moreau, G Daviller, and H Deniau. Subsonic jet noise simulations using both structured and unstructured grids. *AIAA Journal*, 53(1):55–69, 2014.
- R Biolchini, C Bailly, J-F Boussuge, and R Fernando. Numerical study on the relation between hydrodynamic
 fluctuations and noise in hot jets at high Reynolds numbers. In 22nd AIAA/CEAS Aeroacoustics Conference, paper
 AIAA-2016-3048, 2016.
- P Grenson and H Deniau. Large-eddy simulation of an impinging heated jet for a small nozzle-to-plate distance
 and high Reynolds number. *International Journal of Heat and Fluid Flow*, 68:348–363, 2017.
- 17. CP Arroyo, G Daviller, G Puigt, C Airiau, and S Moreau. Identification of temporal and spatial signatures of broadband shock-associated noise. *Shock Waves*, pages 1–18, 2018.
- 18. JG Wang and GR Liu. A point interpolation meshless method based on radial basis functions. *International Journal for Numerical Methods in Engineering*, 54(11):1623–1648, 2002.
- 19. S Le Bras, H Deniau, and C Bogey. A flux reconstruction technique for non-conforming grid interfaces in aeroacoustic simulations. In 22nd AIAA/CEAS Aeroacoustics Conference, paper AIAA-2016-2972, 2016.
- 20. L Cambier, S Heib, and S Plot. The Onera elsA CFD Software: Input from Research and Feedback from Industry.
 Mechanics & Industry, 14(03):159–174, 2013.
- 793 21. M Lazareff, AM Vuillot, and L Cambier. Manuel théorique du logiciel elsA, 2010.
- 22. D Fauconnier, C Bogey, and E Dick. On the performance of relaxation filtering for large-eddy simulation. *Journal of Turbulence*, 14(1):22–49, 2013.
- 796 23. F Kremer and C Bogey. Large-eddy simulation of turbulent channel flow using relaxation filtering: Resolution
 797 requirement and Reynolds number effects. *Computers & Fluids*, 116:17–28, 2015.
- S Le Bras, H Deniau, C Bogey, and G Daviller. Development of compressible large-eddy simulations combining
 high-order schemes and wall modeling. *AIAA Journal*, pages 1–12, 2017.
- 25. EF Toro, M Spruce, and W Speares. Restoration of the contact surface in the HLL-Riemann solvers. *Shock waves*, 4(1):25–34, 1994.
- 26. A Fosso Pouangué. Schémas Volumes Finis Précis: application à l'aéroacoustique numérique de jets subsoniques.
 PhD thesis, Université Pierre et Marie Curie, 2011.
- 27. DV Gaitonde and MR Visbal. High-order schemes for Navier-Stokes equations: algorithm and implementation into
 fdl3di. Technical report, DTIC Document, 1998.
- 28. H Wendland. Scattered data approximation, volume 17. Cambridge University Press, 2004.
- 29. MA Golberg, CS Chen, and H Bowman. Some recent results and proposals for the use of radial basis functions in
 the BEM. *Engineering Analysis with Boundary Elements*, 23(4):285–296, 1999.
- 30. JC Carr, RK Beatson, JB Cherrie, TJ Mitchell, WR Fright, BC McCallum, and TR Evans. Reconstruction and
 representation of 3D objects with radial basis functions. In *Proceedings of the 28th annual conference on Computer graphics and interactive techniques*, pages 67–76. ACM, 2001.
- 31. CKW Tam and JC Webb. Dispersion-relation-preserving finite difference schemes for computational acoustics.
 Journal of Computational Physics, 107(2):262–281, 1993.
- 32. G Fillola, MC Le Pape, and M Montagnac. Numerical simulations around wing control surfaces. 24th International
 Council of Aeronautical Sciences, paper ICAS-2004-2.3.2, 2004.
- 33. C Bogey and C Bailly. Computation of a high Reynolds number jet and its radiated noise using large eddy
 simulation based on explicit filtering. *Computers & Fluids*, 35(10):1344–1358, 2006.
- 34. C Bogey, C Bailly, and D Juvé. Noise investigation of a high subsonic, moderate Reynolds number jet using a
 compressible large eddy simulations. *Theoretical and Computational Fluid Dynamics*, 16(4):273–297, 2003.
- 35. JC Lau, PJ Morris, and MJ Fisher. Measurements in subsonic and supersonic free jets using a laser velocimeter.
 Journal of Fluid Mechanics, 93(01):1–27, 1979.
- 36. C Bogey. Grid sensitivity of flow field and noise of high-Reynolds-number jets computed by large-eddy
 simulations. *International Journal of Aeroacoustics*, 17(4-5):399–424, 2018.
- 37. CKW Tam, K Viswanathan, KK Ahuja, and J Panda. The sources of jet noise: experimental evidence. *Journal of Fluid Mechanics*, 615:253–292, 2008.
- 38. Antares Development Team. Antares Documentation Release 1.11.0, 2012–2018.