



HAL
open science

Flat inputs: theory and applications

Florentina Nicolau, Witold Respondek, Jean-Pierre Barbot

► **To cite this version:**

Florentina Nicolau, Witold Respondek, Jean-Pierre Barbot. Flat inputs: theory and applications. SIAM Journal on Control and Optimization, 2020, 58 (6), pp.3293-3321. 10.1137/19M127776X . hal-02440452v2

HAL Id: hal-02440452

<https://hal.science/hal-02440452v2>

Submitted on 17 Jun 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Flat inputs: theory and applications

Florentina Nicolau*, Witold Respondek † and Jean-Pierre Barbot ‡

Abstract

In this paper, we study the problem of constructing flat inputs for multi-output dynamical systems. The notion of flat inputs has been introduced by Waldherr and Zeitz in [31, 32] and can be seen as dual to that of flat outputs. In the single-output case, a flat input can be constructed if and only if the original dynamical system together with its output is observable. In the multi-output case, the observability is not necessary for the existence of flat inputs. The observable case has been treated in [32], where a system of linear algebraic equations has been proposed in order to determine the control vector fields associated to the flat inputs. The goal of this paper is to treat the unobservable case for multi-output dynamical systems. We start by discussing the case when the dynamical system together with the given output is observable and we present a generalization of the results of [32] by relating them with the notion of minimal differential weight. Then we give our main results. We consider the unobservable case for which locally, around any point of an open and dense subset of \mathbb{R}^n , we construct control vector fields g_1, \dots, g_m such that the associated control system is flat (where n and m denote, resp., the state and the output dimensions). Finally, we explain how our results can be applied to private communication.

Keywords: Flat inputs, flatness, observed dynamical systems, constructing control vector fields, private communication.

1 Introduction

Consider the following nonlinear observed dynamics:

$$\Sigma : \dot{x} = f(x), \quad y = h(x), \tag{1}$$

where x is the state defined on \mathbb{R}^n and $y \in \mathbb{R}^m$ are the measurements, assumed independent everywhere. The vector field f and the functions h_i , $1 \leq i \leq m$, are supposed smooth (the word smooth will always mean \mathcal{C}^∞ -smooth). The problem that we are studying in this paper is to find control vector fields g_1, \dots, g_m (or equivalently, to place the actuators or

*QUARTZ EA7393 Laboratory, ENSEA, 6 Avenue du Ponceau, 95014 Cergy-Pontoise, France. Research partially supported by the Natural Science Foundation of China (61573192). florentina.nicolau@ensea.fr

†Normandie Université, INSA de Rouen, Laboratoire de Mathématiques EA 3226 - FR CNRS 3335, 76801 Saint-Etienne-du-Rouvray, France. witold.respondek@insa-rouen.fr

‡QUARTZ EA7393 Laboratory, ENSEA, 6 Avenue du Ponceau, 95014 Cergy-Pontoise, France, barbot@ensea.fr

the inputs) such that the control-affine system $\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$, associated to Σ , is flat with the original measurements (h_1, \dots, h_m) being a flat output. The notion of flatness was introduced in control theory in the 1990's, by Fliess, Lévine, Martin and Rouchon [4, 5], see also [12, 13, 19, 26], and has attracted a lot of attention because of its multiple applications in the problems of constructive controllability and motion planning (see [17, 20] and references therein). Flat systems form a class of control systems whose all controls and state trajectories can be parametrized by m functions and their time-derivatives, m being the number of controls. More precisely, the control system $\dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$, where $x \in \mathbb{R}^n$, $u \in \mathbb{R}^m$, is *flat* if we can find m functions $\varphi_i(x, u, \dots, u^{(q)})$ such that

$$x = \gamma(\varphi, \dots, \varphi^{(s-1)}) \text{ and } u = \delta(\varphi, \dots, \varphi^{(s)}),$$

for certain integers q and s , where $\varphi = (\varphi_1, \dots, \varphi_m)$ is called a *flat output*. The construction of a flat output $h = \varphi$ can be seen as a problem of sensor placement in order to achieve flatness of the resulting input-state-output system. Dual to this, one can consider the problem of actuator placement, i.e., given (f, h) , find control vector fields g_1, \dots, g_m , in order to achieve the same property. This dual problem has been introduced by Waldherr and Zeitz [31, 32] who call inputs u_1, \dots, u_m multiplying, resp., g_1, \dots, g_m , as *flat inputs* (which are objects dual to flat outputs).

In the single-output case, a flat input can be constructed if and only if the system Σ together with its output h is observable; moreover, the control vector field associated to the flat input can be computed from a system of linear algebraic equations, see [31]. In the multi-output case, the observability is not necessary for the existence of flat inputs. The observable case has been discussed in [32] and the control vector fields (the number of them is that of outputs) associated to the flat inputs can be determined in a similar way as for the SISO case. Another approach in the observable case, based on the notion of unimodularity, has been recently proposed in [6], together with an algorithm for constructing flat inputs and it is then shown that in the observable case, the integrability condition is always satisfied. The goal of this paper is to treat the unobservable multi-output case (the two-output case has been solved by the authors in [22]). It is crucial to distinguish the observability (or unobservability) of controlled systems from observability of uncontrolled ones (recall that for nonlinear systems, the observability property depends on the control [7, 9]). Here we deal with unobservable uncontrolled system that become at least locally observable due to a suitable design of flat inputs.

In this paper, we give a complete solution for a local construction of flat inputs: we show that locally (around any point of an open and dense subset of the state space, where suitable ranks are constant), for any observed dynamical system (Σ, h) , observable or not, there always exist control vector fields g_1, \dots, g_m such that the control-affine system Σ_c is flat with h being a flat output. Our results can be summarized by the following:

Theorem 1.1. *Any observed dynamical system (Σ, h) admits flat inputs almost everywhere (that is, on an open and dense subset $\mathcal{X} \subset \mathbb{R}^n$). Moreover the control vector fields g_1, \dots, g_m can be calculated on \mathcal{X} algebraically.*

When comparing the problem of existence of flat inputs with that of verifying flatness for control systems, an interesting phenomenon can be noted: contrary to flat control systems that are very rare (the class of flat control systems is of codimension infinity among all control systems), any dynamical system (Σ, h) can be rendered flat by adding suitable control vector fields (or equivalently, suitable flat inputs). Our construction is the simplest possible; namely,

g_1, \dots, g_m are the simplest possible control vector fields: they can be chosen constant if (Σ, h) is observable and almost all of them (except g_1) are constant if (Σ, h) is not observable (in that case, they are actually in the multi-chained form when restricted to a suitable submanifold). All results use the following three notions introduced in the paper: observability quasi-indices (called OQI's) for the observable case, partial observability quasi-indices (called POQI's) and cascade observability quasi-indices (called COQI's) for the unobservable case. Our main results are based on several normal forms (for which h is a flat output). It is however important to highlight that for the construction of flat inputs, we do not need to transform the system into the normal forms and moreover, algebraic conditions for calculating vector fields g_1, \dots, g_m (that render the system flat) are provided.

One of the motivations to construct a flat input for a given output is that with such an input, the tracking problem for that output can be solved with no need to calculate the zero dynamics (see, e.g., [8]), but constructing flat inputs may be useful for other problems as well: in this paper, we explain how it can be applied to private communication.

The paper is organized as follows. In Section 2, we recall the definition of flatness and the notion of differential weight of a flat system. In Section 3, we discuss (from the point of view of minimal differential weight) the case when the dynamical system Σ together with a given output h is observable and we present a generalization of the results of [32]. In Section 4, we give our main results: we construct flat inputs in the unobservable case. We completely describe the local case (and, as a consequence, we obtain solutions almost everywhere, that is, on an open and dense subset). We illustrate our results by several examples throughout the paper and we explain how it can be applied to private communication in Section 5. We provide proofs in Section 6.

2 Definitions and problem statement

Consider a nonlinear control system of the form $\Xi : \dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$, where $x \in \mathbb{R}^n$ and $u \in \mathbb{R}^m$.

Definition 2.1. The system $\Xi : \dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$ is *x-flat* around x_0 , generically with respect to u , if there exist m smooth functions $\varphi_i = \varphi_i(x)$, $1 \leq i \leq m$, defined in a neighborhood \mathcal{O} of x_0 , having the following property: there exist an integer $s \geq 0$ and smooth maps $(\gamma, \delta) : \tilde{\mathcal{O}} \times \mathbb{R}^{m(s-1)} \rightarrow \mathbb{R}^n \times \mathbb{R}^m$ such that

$$x = \gamma(\varphi, \dot{\varphi}, \dots, \varphi^{(s-1)}) \text{ and } u = \delta(\varphi, \dot{\varphi}, \dots, \varphi^{(s)}) \quad (2)$$

for any C^{s-1} -control $u(t)$ and corresponding trajectory $x(t)$ that satisfy $(x(t), u(t)) \in \tilde{\mathcal{O}}$, where either $\tilde{\mathcal{O}} = \mathcal{O} \times \mathbb{R}^m$ or $\tilde{\mathcal{O}}$ is a subset of $\mathcal{O} \times \mathbb{R}^m$ such that for any $x \in \mathcal{O}$, the set $\{u : (x, u) \in \tilde{\mathcal{O}}\}$ is open and dense in \mathbb{R}^m . The m -tuple $\varphi = (\varphi_1, \dots, \varphi_m)$ is called a *flat output*.

Remark 2.1. It is commonly accepted [5, 17] that flatness is a local and generic property, that is, even if all functions φ_i depend on x only and are defined globally, desired description (2) is local (valid for trajectories which stay close to the nominal point) and holds out of singular states and singular values of controls. If $\tilde{\mathcal{O}} = \mathcal{O} \times \mathbb{R}^m$, then representation (2) is global with respect to the controls. In the second case, the condition on $\tilde{\mathcal{O}}$ simply means that for each $x \in \mathcal{O}$, the set of controls u for which representation (2) holds, is open and

dense in \mathbb{R}^m and the pairs $(x, u) \notin \tilde{\mathcal{O}}$ form singularities of flatness because (2) fails to hold. From now on, when we say that a control system is x -flat (or simply flat) at x_0 , we mean that it is x -flat at x_0 , generically with respect to u (i.e., satisfies Definition 2.1).

Remark 2.2. There exists a more general notion of flatness for which the functions φ_i may depend on the control and its successive time-derivatives up to a certain order q (i.e., $\varphi_i = \varphi_i(x, u, \dot{u}, \dots, u^{(q)})$, as in the introduction). We do not need this general notion since, in our study, all functions φ_i will depend on the state x only and singularities will depend on x and/or u (but never on derivatives of u).

The minimal number of derivatives of components φ_i of a flat output φ , needed to express x and u , is called the differential weight of that flat output and is formalized as follows [21, 28]. By definition, for any flat output φ of Ξ there exist integers s_1, \dots, s_m such that

$$x = \gamma(\varphi_1, \dots, \varphi_1^{(s_1)}, \dots, \varphi_m, \dots, \varphi_m^{(s_m)}) \text{ and } u = \delta(\varphi_1, \dots, \varphi_1^{(s_1)}, \dots, \varphi_m, \dots, \varphi_m^{(s_m)}). \quad (3)$$

Moreover, we can choose (s_1, \dots, s_m) , γ and δ such that (see [28]) if for any other m -tuple $(\tilde{s}_1, \dots, \tilde{s}_m)$ and functions $\tilde{\gamma}$ and $\tilde{\delta}$, we have

$$x = \tilde{\gamma}(\varphi_1, \dots, \varphi_1^{(\tilde{s}_1)}, \dots, \varphi_m, \dots, \varphi_m^{(\tilde{s}_m)}) \text{ and } u = \tilde{\delta}(\varphi_1, \dots, \varphi_1^{(\tilde{s}_1)}, \dots, \varphi_m, \dots, \varphi_m^{(\tilde{s}_m)}),$$

then $s_i \leq \tilde{s}_i$, for $1 \leq i \leq m$. We call $\sum_{i=1}^m (s_i + 1) = m + \sum_{i=1}^m s_i$ the differential weight of φ . A flat output of Ξ is called *minimal* if its differential weight is the lowest among all flat outputs of Ξ . The *differential weight* of a flat systems Ξ is equal to the differential weight of a minimal flat output, and is at least $n + m$, since we have to express n states and m independent controls and in order to do that, we need at least $n + m$ derivatives (taking into account also those of order zero).

Flatness is a property of the state-space dynamics $\dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$ of a control system. It can also be described as a property of the input-state-output map for a dummy output y . In fact, x -flatness is equivalent to the existence of an \mathbb{R}^m -valued dummy output $y = \varphi(x)$ that renders $\dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$ observable [10, 15, 33] and left-invertible [27]. Indeed, expressing the state as $x = \gamma(\varphi, \dot{\varphi}, \dots, \varphi^{(s-1)})$ and the control as $u = \delta(\varphi, \dot{\varphi}, \dots, \varphi^{(s)})$ corresponds, resp., to observability and left invertibility.

Consider the dynamical system Σ whose state $x \in \mathbb{R}^n$ (all results of the paper also hold if x is defined on an open subset of \mathbb{R}^n or, more generally, on an n -dimensional manifold) together with the output $y = h(x) \in \mathbb{R}^m$, given by (1). In order to emphasize the fact that the system is observed, we will use the notation (Σ, h) . When we say that a dynamical system Σ is observed, this does not mean that Σ is necessarily observable with respect to the output h .

The problem that we are studying in this paper is the construction of control vector fields g_1, \dots, g_m (whose inputs u_1, \dots, u_m are called *flat inputs*) such that the control-affine system Σ_c associated to Σ and given by

$$\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i,$$

is x -flat with respect to the the original output (h_1, \dots, h_m) . In that case, we will say that the pair (Σ_c, h) is x -flat. As we have already noticed, flatness is closely related to observability. Thus for the problem of constructing flat inputs, it is natural to start by checking

observability of Σ with respect to h . We denote by $\mathcal{H}(x)$ the observability codistribution (see, e.g., [10])

$$\mathcal{H}(x) = \text{span} \{dL_f^{j-1}h_i(x), j \geq 1, 1 \leq i \leq m\} \quad (4)$$

associated with the output h . We say that (Σ, h) satisfies the observability rank condition [10] if $\dim \mathcal{H}(x) = n$. In our study, we will distinguish the observable case $\dim \mathcal{H}(x) = n$ and the unobservable case $\dim \mathcal{H}(x) = k < n$.

3 Observable case

For the construction of flat inputs in the observable case, we need the following definition.

Definition 3.1. The observed system (Σ, h) is said to have observability quasi-indices (ρ_1, \dots, ρ_m) at $x_0 \in \mathbb{R}^n$, called OQI's, if

$$\sum_{i=1}^m \rho_i = n \quad \text{and} \quad \text{span} \{dL_f^{j-1}h_i(x_0), 1 \leq j \leq \rho_i, 1 \leq i \leq m\} = \mathbb{R}^n.$$

If, moreover, the quasi-indices satisfy $\rho_1 \geq \rho_2 \geq \dots \geq \rho_m$, then the smallest, in the lexicographic ordering, quasi-indices are called observability indices.

For nonlinear systems, the notion of observability indices goes back to [15], see also [33, 34], while the notion of OQI's is used in [32] under the name of (non-unique) observability indices. For linear systems, an analogous notion was proposed under the name of pseudo-observability indices in [2]. The existence of OQI's, and thus of observability indices, at x_0 implies observability of (Σ, h) . More precisely, we can distinguish points in a neighborhood of x_0 with the help of exactly $\rho_1 + \dots + \rho_m = n$ derivatives of the output components (actually, using ρ_i time-derivatives of $y_i(t) = h_i(x(t))$). Conversely, if (Σ, h) satisfies $\dim \mathcal{H}(x) = n$ for any x in \mathbb{R}^n , i.e., is locally observable everywhere on \mathbb{R}^n (see [10], for various concepts of nonlinear observability), then it possesses OQI's on an open and dense subset $\mathcal{X}^O \in \mathbb{R}^n$ (see Lemma 4.1 in Section 4 and its proof in Section 6) and thus, although it is locally observable everywhere, fails to have OQI's around singular points of $\mathbb{R}^n \setminus \mathcal{X}^O$. Contrary to the observability indices (which are unique), the OQI's (ρ_1, \dots, ρ_m) are not unique and we do not suppose any order relation between them. Since OQI's may depend on a point, we say that quasi-indices (ρ_1, \dots, ρ_m) are uniform in a subset X of \mathbb{R}^n if (ρ_1, \dots, ρ_m) form quasi-indices at any $x_0 \in X$. We will keep denoting by \mathcal{X} (sometimes with suitable indices) open and dense subsets of \mathbb{R}^n and by X just open subsets of \mathbb{R}^n .

Example 3.1. Consider the following dynamics

$$\begin{aligned} \dot{x}_1 &= x_2 + x_3 & \dot{x}_3 &= x_4 \\ \dot{x}_2 &= 0 & \dot{x}_4 &= 0 \end{aligned} \quad (5)$$

with the outputs $y_1 = x_1$ and $y_2 = x_3$. A straightforward calculation shows that both couples $(\rho_1, \rho_2) = (2, 2)$ and $(\rho_1, \rho_2) = (3, 1)$ are (uniform) OQI's on \mathbb{R}^4 (but only the first one corresponds to the observability indices). \triangleleft

In Example 4.1, we illustrate how for a given system different choices of OQI's may exist on different domains.

The following theorem states that the observed system (Σ, h) can be made flat of differential weight $n + m$ (which is the minimal possible) if and only if it admits OQI's. Moreover, Proposition 3.1 gives a system of algebraic equations, whose terms are calculated as Lie derivatives of the outputs, to be solved in order to construct control vector fields (and thus flat inputs). Proofs of Theorem 3.1 and of all results of this section are given in Section 6.

Theorem 3.1. *Consider the observed system (Σ, h) around $x_0 \in \mathbb{R}^n$. The following conditions are equivalent:*

(O1) *There exist OQI's (ρ_1, \dots, ρ_m) around x_0 ;*

(O2) *There exist vector fields g_1, \dots, g_m such that the system (Σ_c, h) is x -flat at x_0 of differential weight $n + m$, with h being a minimal flat output, that is, equivalently, the system Σ_c is static feedback linearizable with h_1, \dots, h_m being linearizing outputs.*

Moreover, if $\dim \mathcal{H}(x) = n$, for any $x \in \mathbb{R}^n$, then OQI's exist for any $x_0 \in \mathcal{X}^O$, with \mathcal{X}^O an open and dense subset of \mathbb{R}^n , and thus g_1, \dots, g_m of (O2) exist on \mathcal{X}^O .

A constructive procedure to find flat inputs is given as follows (where the value of a differential form $\omega = \sum_{i=1}^n \omega_i(x) dx_i$ on a vector field $v = \sum_{i=1}^n v_i(x) \frac{\partial}{\partial x_i}$ is $\langle \omega, v \rangle = \sum_{i=1}^n \omega_i(x) v_i(x)$).

Proposition 3.1. *Consider the observed system (Σ, h) around $x_0 \in \mathbb{R}^n$ and assume that condition (O1) of Theorem 3.1 holds. Then all choices of the vector fields g_1, \dots, g_m that meet condition (O2) of Theorem 3.1 are given by*

$$(i) \quad \langle dL_f^{q-1} h_i, g_j \rangle = 0 \text{ and } \langle dL_f^{\rho_i-1} h_i, g_j \rangle(x) = D_{ij}(x), \text{ for } 1 \leq i, j \leq m, 1 \leq q \leq \rho_i - 1, \\ \text{where } (D_{ij}(x)) \text{ is any smooth invertible } m \times m\text{-matrix}$$

or, equivalently, by

(ii) *The distribution $\mathcal{G} = \text{span} \{g_1, \dots, g_m\}$ satisfies*

$$\mathcal{G}^\perp = \text{span} \{dL_f^{j-1} h_i, 1 \leq j \leq \rho_i - 1, 1 \leq i \leq m\}.$$

Moreover, if $\rho = (\rho_1, \dots, \rho_m)$ are uniform OQI's on X_ρ^O (in particular, on $X_\rho^O = \mathbb{R}^n$), then the vector fields g_1, \dots, g_m exist globally on X_ρ^O , on which are given by (i), and they yield a global system Σ_c on X_ρ^O that is locally flat around any $x \in X_\rho^O$ with the help of the flat output $(\varphi_1, \dots, \varphi_m) = (h_1, \dots, h_m)$ globally defined on X_ρ^O .

Notice that in the analytic case each set X_ρ^O is open and dense (so could also be denoted \mathcal{X}_ρ^O) but in the \mathcal{C}^∞ -case the sets X_ρ^O are, in general, open only. Clearly, in both cases, the open and dense set \mathcal{X}^O of Theorem 3.1 is $\mathcal{X}^O = \cup X_\rho^O$, where the union is taken over all OQI's $\rho = (\rho_1, \dots, \rho_m)$, see also Lemma 4.1 and the comments following it. Proposition 3.1 gives the following system of algebraic equations.

Corollary 3.1. *In a local coordinate system $x = (x_1, \dots, x_n)$, form the $n \times n$ -matrix $H(x)$ whose first $n - m$ rows are the differentials $dL_f^q h_i(x)$, $0 \leq q \leq \rho_i - 2$, and the last m rows are the differentials $dL_f^{\rho_i-1} h_i(x)$, $1 \leq i \leq m$. Then the equations of condition (i) of Proposition 3.1 are equivalent to*

$$H(x) \cdot g(x) = \begin{pmatrix} 0 \\ D(x) \end{pmatrix},$$

where $g(x) = (g_1(x) \dots g_m(x))$, $0 = 0_{(n-m) \times m}$ and $D(x)$ is any smooth invertible $m \times m$ -matrix. Under condition (O1) of Theorem 3.1, $H(x)$ is invertible and

$$g(x) = H^{-1}(x) \cdot \begin{pmatrix} 0 \\ D(x) \end{pmatrix}.$$

Proof. Follows directly from Proposition 3.1. □

The vector fields g_1, \dots, g_m lead to a control system Σ_c that is actually locally static feedback linearizable [11, 14] with h being a linearizing output (or, equivalently, of differential weight $n + m$, see [21] where that equivalence is discussed). The following two results are direct consequences of Theorem 3.1, see Section 6 for their proofs.

Corollary 3.2. *If (Σ, h) is not locally observable at x_0 or is locally observable but does not have any OQI's and nevertheless admits g_1, \dots, g_m such that the system (Σ_c, h) is x -flat at x_0 with $\varphi = h$ being a minimal flat output at x_0 , then the control system Σ_c , independently of the choice of g_1, \dots, g_m , is never static feedback linearizable around x_0 .*

Corollary 3.3. *Assume that (Σ, h) is a linear system of the form $\Sigma : \dot{x} = Ax, y = h(x) = Cx$. There exist constant vector fields $g_1 = b_1, \dots, g_m = b_m$ such that the system $\Sigma_c : \dot{x} = Ax + \sum_{i=1}^m b_i u_i$ is x -flat at x_0 with flat output $\varphi = y = Cx$ if and only if the pair (A, C) is observable.*

According to Corollary 3.3, if the original dynamical system is linear and if we want to obtain a flat control system Σ_c that is also linear, i.e., Σ_c is $\dot{x} = Ax + \sum_{i=1}^m b_i u_i$, then flat inputs can be constructed if and only if $(\Sigma, h) = (Ax, Cx)$ is observable. Notice also that no condition on the differential weight of Cx as a flat output of the flat linear control system Σ_c is required, so observability of (A, C) is always necessary. If we do not necessarily require to remain within the linear category, flat inputs can (generically) always be constructed following the procedure explained in Section 4 but for the price of losing linearity.

Remark 3.1 (Comparison with [32]). Theorem 3.1 and Proposition 3.1 generalize the result of [32] according to which if a system has OQI's (ρ_1, \dots, ρ_m) and the vector fields g_1, \dots, g_m satisfy (i) with $D_{ij}(x) = \delta_{ij}$, where δ_{ij} denotes the Kronecker delta, then the control system (Σ_c, h) is flat. All other vector fields g_i corresponding to all other invertible matrices $(D_{ij}(x))$ render the system feedback linearizable and are given up to a transformation $g_i \mapsto \sum_{j=1}^m D_{ij}(x) g_j$. In our result, we prove additionally that such g_i 's (and only such) lead to a flat system Σ_c of differential weight $n + m$, which is minimal and implies that Σ_c is static feedback linearizable.

The following example illustrates the last statement of Proposition 3.1. Namely, even if we construct a global system Σ_c , the globally defined flat output $\varphi = h$ guarantees local flatness only, since the map $(x, u) \rightarrow (h_1, \dot{h}_1, \dots, h_1^{(s_1)}, \dots, h_m, \dot{h}_m, \dots, h_m^{(s_m)})$ need not be globally invertible.

Example 3.2. Consider the following dynamics on \mathbb{R}^2

$$\begin{aligned} \dot{x}_1 &= f_1(x_1, x_2) \\ \dot{x}_2 &= f_2(x_1, x_2), \end{aligned}$$

with the outputs $y_1 = e^{x_1} \cos x_2$ and $y_2 = e^{x_1} \sin x_2$. Independently of $f = (f_1, f_2)^T$, the above system is locally everywhere observable, with $(\rho_1, \rho_2) = (1, 1)$ being uniform observability indices on \mathbb{R}^2 . Hence, by Theorem 3.1, the control vector fields g_1 and g_2 exist globally on \mathbb{R}^2 and can be defined by $L_{g_j} h_i(x) = D_{ij}(x)$, $1 \leq i, j \leq 2$, where $(D_{ij}(x))$ is any smooth invertible 2×2 -matrix. They yield, on \mathbb{R}^2 , the global control system $\Sigma_c : \dot{x} = f(x) + u_1 g_1(x) + u_2 g_2(x)$. The flat output $\varphi(x) = h(x) = (e^{x_1} \cos x_2, e^{x_1} \sin x_2)$ is globally defined on \mathbb{R}^2 but the map $(x, u) \rightarrow (h, \dot{h})$ is not globally invertible (because the map $x \rightarrow h(x) = (e^{x_1} \cos x_2, e^{x_1} \sin x_2)$ is not). Notice, however, that Σ_c is globally flat with another flat output $\tilde{\varphi} = (x_1, x_2)$. \triangleleft

Notice that a given system may possess many different OQI's, and different OQI's (ρ_1, \dots, ρ_m) lead to different control vector fields g_1, \dots, g_m , not equivalent via $g_i \mapsto \sum_{j=1}^m \beta_{ij} g_j$, and thus to flat control systems (Σ_c, h) that are not static feedback equivalent, see Example 3.3 below. In particular, to any choice of OQI's (ρ_1, \dots, ρ_m) , there correspond flat inputs u_1, \dots, u_m giving (3) with $s_i = \rho_i$.

Example 3.3. Consider again system (5) of Example 3.1. For the first couple of quasi-indices $(\rho_1, \rho_2) = (2, 2)$, we get $\mathcal{G}^\perp = \text{span} \{dx_1, dx_3\}$. Thus $\mathcal{G} = \text{span} \left\{ \frac{\partial}{\partial x_2}, \frac{\partial}{\partial x_4} \right\}$ and the associated flat control system for $D_{ij}(x) = \delta_{ij}$, $1 \leq i, j \leq 2$, is

$$\begin{aligned} \dot{x}_1 &= x_2 + x_3 & \dot{x}_3 &= x_4 \\ \dot{x}_2 &= u_1 & \dot{x}_4 &= u_2 \end{aligned} \quad (6)$$

with $h = (x_1, x_3)$ a minimal flat output of differential weight $n + 2 = 6$.

The second couple of quasi-indices $(\rho_1, \rho_2) = (3, 1)$ leads to $\mathcal{G}^\perp = \text{span} \{dx_1, dx_2 + dx_3\}$. Thus $\mathcal{G} = \text{span} \left\{ \frac{\partial}{\partial x_4}, \frac{\partial}{\partial x_2} - \frac{\partial}{\partial x_3} \right\}$ and the associated flat control system for $D_{ij}(x) = \delta_{ij}$, $1 \leq i, j \leq 2$, is

$$\begin{aligned} \dot{x}_1 &= x_2 + x_3 & \dot{x}_3 &= x_4 - u_1 \\ \dot{x}_2 &= u_1 & \dot{x}_4 &= u_2 \end{aligned} \quad (7)$$

with $h = (x_1, x_3)$ a minimal flat output of differential weight $n + 2 = 6$. \triangleleft

In some practical applications, it may be interesting to use more derivatives of a particular output component to decrease the number of derivatives of another (more sensitive) component. For instance, in the above example, if the output $y_1 = x_1$ contains less measurement noise than $y_2 = x_3$ or if the system were nonlinear, with fewer nonlinear terms in successive time-derivatives of $y_1 = x_1$ than of $y_2 = x_3$, then it is natural to consider the quasi-indices $(\rho_1, \rho_2) = (3, 1)$. Notice also that both resulting control systems (6) and (7) are static feedback linearizable with (x_1, x_3) playing the role of the linearizing output, but they are not static feedback equivalent to each other. This is so because their quasi-indices coincide with their controllability indices. The former being different implies that the latter are different as well and thus the systems cannot be static feedback equivalent.

Finally, notice that in the observable case, even if the proposed construction of g_1, \dots, g_m is local around a given x_0 , description (2) for (Σ_c, h) is always global with respect to the control, so we never face singularities in the control space. This is to be expected since our solution leads to a static feedback linearizable system (with h being a linearizing output) and the observability (and thus flatness) properties of a linear system do not depend on controls.

To sum up the above results, if a pair (Σ, h) is observable and admits OQI's, then there always exist g_1, \dots, g_m such that the associated control system Σ_c is flat with h being a flat output and, moreover, g_1, \dots, g_m can be chosen such that Σ_c is static feedback linearizable and can be calculated via a system of algebraic equations. Our goal is thus to solve the problem of finding flat inputs for the unobservable multi-output case and to generalize the results of [22] treating the two-output case.

4 Main results: unobservable case

Similarly to the definition of OQI's, we introduce the notion of partial observability quasi-indices. Recall that to the output h , we associated the observability codistribution \mathcal{H} given by (4).

Definition 4.1. The observed system (Σ, h) is said to have partial observability quasi-indices (ρ_1, \dots, ρ_m) at x_0 , called POQI's, if in a neighborhood of x_0 ,

$$\dim \mathcal{H}(x) = \text{const.} = k < n \quad \text{and} \\ \dim \text{span} \{dL_f^{j-1}h_i(x), 1 \leq j \leq \rho_i, 1 \leq i \leq m\} = \sum_{i=1}^m \rho_i = k.$$

Remark 4.1. According to the above definition, if the system (Σ, h) has POQI's at x_0 , then $\dim \mathcal{H}(x_0) = k < n$, i.e., it is unobservable at x_0 and, in addition, the associated codistribution $\mathcal{H}(x)$ is of constant rank, equal to k , in a neighborhood of x_0 . This means that only k directions can be observed (and this is valid around any point of that neighborhood). The above definition is more restrictive than just the lack of observability at a point: we require the system to be nowhere observable on a whole neighborhood of x_0 and, moreover, its observability defect to be constant on that neighborhood. It turns out that on an open and dense subset of \mathbb{R}^n , the lack of observability and the existence of POQI's coincide.

Lemma 4.1 (Genericity of constant rank). *For any observed dynamics (Σ, h) there exists an open and dense subset $\mathcal{X}^P \subset \mathbb{R}^n$ on which $\dim \mathcal{H}(x)$ is locally constant and on each connected component X_c^P of \mathcal{X}^P where $\dim \mathcal{H}(x) = \text{const.} = k$ (the value of k may depend on the component), POQI's exist at any $x_0 \in X_c^P$, if $k < n$, or OQI's exist at any $x_0 \in X_c^P$, if $k = n$ (in which case it is natural to denote X_c^P by X_c^O).*

In the analytic case, the dimension k is the same on all components X_c^P but it may vary from one X_c^P to another in the C^∞ -case (this does not affect our constructions below, that are local, so given on an arbitrary but fixed connected component). On the other hand, different choices (ρ_1, \dots, ρ_m) of POQI's or OQI's may in general be possible in both analytic and C^∞ -case and the domain of validity of each choice (ρ_1, \dots, ρ_m) may be different. If $\dim \mathcal{H}(x) = n$, for all $x \in \mathbb{R}^n$, it follows that (Σ, h) admits OQI's at any $x_0 \in \mathcal{X}^P$ in which case, we denote the open and dense subset \mathcal{X}^P by \mathcal{X}^O . Proofs of Lemma 4.1 and all results of this section are given in Section 6.

Example 4.1. Consider the following dynamics

$$\begin{aligned} \dot{x}_1 &= f_1(x_2) & \dot{x}_3 &= x_4 \\ \dot{x}_2 &= 0 & \dot{x}_4 &= f_4(x_2) \end{aligned} \tag{8}$$

with the outputs $y_1 = x_1$ and $y_2 = x_3$. We consider the following cases:

- (a) $f_1 = x_2$ and $f_4 = x_2$. Then both pairs (2,2) and (1,3) form uniform OQI's on \mathbb{R}^4 .
- (b) $f_1 = x_2^3$ and $f_4 = x_2$. Then the pair (1,3) forms uniform OQI's on $\mathcal{X}_{(1,3)}^O = \mathbb{R}^4$ and the pair (2,2) forms uniform OQI's on $\mathcal{X}_{(2,2)}^O = \{x \in \mathbb{R}^4 : x_2 \neq 0\}$. The pair (2,2) is that constructed in the proof of Lemma 4.1.

(c) $f_1 = x_2^3$ and $f_4 = (x_2 - 1)^3$. Then the pair (1,3) forms uniform OQI's on $\mathcal{X}_{(1,3)}^O = \{x \in \mathbb{R}^4 : x_2 \neq 1\}$ and the pair (2,2) forms uniform OQI's on $\mathcal{X}_{(2,2)}^O = \{x \in \mathbb{R}^4 : x_2 \neq 0\}$. Both pairs have singularities which differ from one case to the other.

(d) $f_1 = x_2^3$ and $f_4 = \begin{cases} 0, & x_2 \leq 0, \\ \exp(-\frac{1}{x_2^2}), & x_2 > 0. \end{cases}$ Then the pair (1,3) forms uniform OQI's on $X_{(1,3)}^O = \{x \in \mathbb{R}^4 : x_2 > 0\}$ and the pair (2,2) forms uniform OQI's on $\mathcal{X}_{(2,2)}^O = \mathbb{R}^4$. The pair (2,2) is that constructed in the proof of Lemma 4.1, so the pair (1,3) exists on a proper subset $X_{(1,3)}^O$ of $\mathcal{X}_{(2,2)}^O$.

(e) $f_1 = \begin{cases} 0, & x_2 \leq 0, \\ \exp(-\frac{1}{x_2^2}), & x_2 > 0 \end{cases}$ and $f_4 = x_2$. Then the pair (1,3) forms uniform OQI's on $\mathcal{X}_{(1,3)}^O = \mathbb{R}^4$. The pair (2,2) forms uniform OQI's on $X_{(2,2)}^O = \{x \in \mathbb{R}^4 : x_2 > 0\}$ and the set $\mathcal{X}^O = \mathcal{X}^P$ constructed in the proof of Lemma 4.1 is $\mathcal{X}^O = \{x \in \mathbb{R}^4 : x_2 < 0\} \cup \{x \in \mathbb{R}^4 : x_2 < 0\}$ with OQI's given by (1,3) and (2,2) on two connected components, respectively (although OQI's (1,3) exists everywhere).

The five cases above may serve to illustrate different behaviors of POQI's if we add an unobservable part to the system, like $\dot{x}_5 = 0$. ◁

As for the OQI's, there can be many POQI's and different POQI's (ρ_1, \dots, ρ_m) will lead to different control vector fields g_1, \dots, g_m and thus to different flat control systems (Σ_c, h) , as explained in Section 4.

Our main results are based on the observation that a flat system is observable with respect to its flat output. To start with, we render (Σ, h) observable by completing the original output h to a new output $h^\ell = (h, \psi^1, \dots, \psi^\ell)$, such that (Σ, h^ℓ) is locally observable. For $1 \leq s \leq \ell - 1$, each ψ^s of h^ℓ is an $(m - 1)$ -tuple of independent functions and plays the role of an \mathbb{R}^{m-1} -valued dummy output and ψ^ℓ is an $\mathbb{R}^{m'-1}$ -valued dummy output, with $2 \leq m' \leq m$. This justifies the notation

$$\bar{m} = \begin{cases} m, & \text{for } 1 \leq s \leq \ell - 1, \\ m', & \text{for } s = \ell. \end{cases} \quad (9)$$

For any $1 \leq s \leq \ell$, we denote $h^s = (h, \psi^1, \dots, \psi^s)$. The integer ℓ denotes the number of additional dummy outputs ψ^s that have to be added to obtain a locally observable (Σ, h^ℓ) . For each $\psi^s = (\psi_2^s, \dots, \psi_{\bar{m}}^s)$, $1 \leq s \leq \ell$, the components ψ_i^s are numbered between 2 and \bar{m} (that is, $\psi^s = (\psi_2^s, \dots, \psi_m^s)$, for $1 \leq s \leq \ell - 1$, and $\psi^\ell = (\psi_2^\ell, \dots, \psi_{m'}^\ell)$).

Definition 4.2. The observed system (Σ, h) with POQI's $\rho = (\rho_1, \dots, \rho_m)$ at x_0 is said to have cascade observability quasi-indices at x_0 , called COQI's, if there exist smooth $\mathbb{R}^{\bar{m}-1}$ -valued functions ψ^1, \dots, ψ^ℓ defined in a neighborhood of x_0 , for an integer $\ell \geq 1$, and integers $\nu^s = (\nu_2^s, \dots, \nu_{\bar{m}}^s)$, for $1 \leq s \leq \ell$, such that $(\rho, \nu^1, \dots, \nu^s)$ are POQI's of (Σ_c, h^s) , for any $1 \leq s \leq \ell - 1$, and are OQI's of (Σ_c, h^ℓ) , for $s = \ell$.

The above definition implies that $\sum_{s=1}^{\ell} \sum_{i=2}^{\bar{m}} \nu_i^s = n - k$. The name COQI's is suggested by the procedure of completing h to h^ℓ by adding successively dummy outputs ψ^1, \dots, ψ^ℓ . We will explain, see the algorithm in Section 4.1.1, that ψ_i^s can be suitably chosen among the coordinates x_1, \dots, x_n thus proving that COQI's exist on an open and dense $\mathcal{X}^C \subset \mathbb{R}^n$. Note that, in general, the inclusion $\mathcal{X}^C \subset \mathcal{X}^P$ is proper (with both sets being open dense).

The main result of the paper is summarized by the following theorem (then completed by Theorems 4.2, 4.3 and 4.4) that fully solves the problem of constructing flat inputs. It states that for any observed dynamical system (Σ, h) , observable or not, we can almost everywhere construct flat inputs.

Theorem 4.1. *The following conditions hold:*

(Flat 1) *Any observed dynamical system (Σ, h) admits flat inputs on an open and dense subset $\mathcal{X} \subset \mathbb{R}^n$. Moreover the control vector fields g_1, \dots, g_m can be calculated on \mathcal{X} via differentiation and algebraic operations.*

(Flat 2) *If (Σ, h) is observable and possesses OQI's at x_0 , then it admits flat inputs locally around x_0 .*

(Flat 3) *If (Σ, h) is not observable but admits COQI's around x_0 , as introduced in Definition 4.2, then (Σ, h) admits flat inputs locally around x_0 .*

Remark 4.2. The open and dense subset \mathcal{X} of (Flat 1) is always $\mathcal{X} = X^O \cup X^C$, where X^O is the set of points where OQI's exist and X^C is the set of points where COQI's exist. If $\dim \mathcal{H}(x) = n$, for all $x \in \mathbb{R}^n$ (the observable case), then $X^C = \emptyset$ and $\mathcal{X} = X^O$ is open and dense (see Theorem 3.1) and thus denoted $X^O = \mathcal{X}^O$. If $\dim \mathcal{H}(x) < n$, for all $x \in \mathbb{R}^n$ (the unobservable case), then $X^O = \emptyset$ and $\mathcal{X} = X^C$ is open and dense (see Theorem 4.2(A1)) and thus denoted $X^C = \mathcal{X}^C$. In the \mathcal{C}^∞ -case with no assumption on the dimension of $\mathcal{H}(x)$, it may happen that, although $\mathcal{X} = X^O \cup X^C$ is open and dense, neither X^O nor X^C is dense (both are open only).

Statement (Flat 2) is contained in Theorem 3.1, so we do not discuss it here. In the unobservable case, (Flat 3) can be further detailed when working in well chosen coordinates and will be expressed as Theorems 4.2 and 4.3 if the observability defect verifies $n - k \geq m - 1$ (resp., as Theorem 4.4, if $n - k < m - 1$). All theorems are stated with the help of normal forms. It is however important to highlight that for the construction of flat inputs, we do not need to transform the system into the normal forms and, similarly to the observable case, algebraic conditions for computing g_1, \dots, g_m for the original system are provided in the following subsections.

From now on, we consider the unobservable case only, so by Lemma 4.1, there exists an open and dense subset \mathcal{X}^P of \mathbb{R}^n where POQI's (ρ_1, \dots, ρ_m) are well defined. Locally, around $x_0 \in \mathcal{X}^P$, introduce coordinates

$$w_i^j = L_f^{j-1} h_i, \quad 1 \leq j \leq \rho_i, \quad 1 \leq i \leq m, \quad (10)$$

in which Σ can be locally transformed into the following observed-unobserved form

$$\begin{aligned} \dot{w}_i^j &= w_i^{j+1}, & 1 \leq j \leq \rho_i - 1, \\ \dot{w}_i^{\rho_i} &= a_i(w), & 1 \leq i \leq m, \end{aligned} \quad (11)$$

$$\dot{z} = b(w, z), \quad (12)$$

with $\sum_{i=1}^m \rho_i = \dim w = k < n$ and $\dim w + \dim z = n$, where z consists of any coordinates completing w to a coordinate system (for instance, z can be taken as well chosen original coordinates $x_{i_1}, \dots, x_{i_{n-k}}$), and $(h_1, \dots, h_m) = (w_1^1, \dots, w_m^1)$. The w -coordinates of the above form are the states observed with the help of the output h and its successive time-derivatives,




Figure 1: Observed-unobserved subsystems.

and there are k of them. The z -coordinates correspond to the unobserved directions, there are $n - k$ (which is the observability defect) of them and they may be affected by w . Figure 1 summarizes the above remarks.

Since a flat system is observable (with respect to its flat output and independently of the applied input signal), we have to render the original system (Σ, h) observable. For observability we need a link going from the z -subsystem into the w -subsystem (Figure 2a) but for Σ there is no such a link, see the observed-unobserved form (11)-(12) illustrated by Figure 2b. It follows that we have to create a link assuring observability with the help of the control vector fields (see Figure 2c, where Π stands for products $z_i^{q+1}u_1$).




Figure 2: Obtaining observability for (Σ, h) .

We first give Theorems 4.2 and 4.3 in Section 4.1, which apply to the case $n - k \geq m - 1$, and then Theorem 4.4 in Section 4.2, which deals with $n - k < m - 1$.

4.1 Construction of the control vector fields: the case $n - k \geq m - 1$

Theorem 4.2 presents a normal form NF1 whose construction is performed on a an open and dense subset $\mathcal{X}^C \subset \mathbb{R}^n$ on which (Σ, h) admits COQI's. Recall that COQI's are obtained by completing the original output h to a new output $h^\ell = (h, \psi^1, \dots, \psi^\ell)$ such that (Σ, h^ℓ) is locally observable, see Definition 4.2.

Notations of NF1. The integers $(\rho, \nu^1, \dots, \nu^\ell)$ defining NF1, where $\rho = (\rho_1, \dots, \rho_m)$ and $\nu^s = (\nu_2^s, \dots, \nu_{\bar{m}}^s)$, for $1 \leq s \leq \ell$, and with \bar{m} defined by (9), are OQI's of (Σ, h^ℓ) , see the algorithm of Section 4.1.1. The variables $z_i^{s,q}$ are defined by (18) and form ℓ blocks, for $s = 1, \dots, \ell$. In each block, the index q corresponds to successive derivatives and the index s to subsystems. There are ℓ subsystems, each of them containing $m - 1$ chains z_i^s (indexed by i , for $2 \leq i \leq m$), with the exception of the ℓ -th subsystem, where there can be $m' - 1 < m - 1$ chains z_i^s (indexed by i , for $2 \leq i \leq m'$), i.e., to summarize (using \bar{m} -notation), each z^s -subsystem, for $1 \leq s \leq \ell$, has $\bar{m} - 1$ chains. We will also use the following notation

$$\bar{\ell} = \begin{cases} \ell, & \text{for } 2 \leq i \leq m', \\ \ell - 1, & \text{for } m' + 1 \leq i \leq m. \end{cases} \quad (13)$$

The only nonlinearities of the observed w -subsystem are in last $w_i^{\rho_i}$ -components and in the last $z_i^{s,q}$ -components, with $q = \nu_i^1, \dots, \nu_i^\ell$, of each unobserved z^s -subsystem, for $s = 1, \dots, \ell$. Only those nonlinear components are modified by the control vector fields g_1, \dots, g_m . In particular, only to the equations for $\dot{z}_i^{\bar{\ell},q}$, with $q = \nu_i^{\bar{\ell}}$, for $2 \leq i \leq \bar{m}$, (that is, for $\dot{z}_i^{\ell,q}$,

with $q = \nu_i^\ell$, for $2 \leq i \leq m'$, and for $\dot{z}_i^{\ell-1,q}$, with $q = \nu_i^{\ell-1}$, for $m' + 1 \leq i \leq m$), we add, respectively, the term u_i , while u_1 affects all other nonlinear components. For $1 \leq s \leq \ell$, denote $\bar{z}^s = (z_i^{j,q}, 1 \leq q \leq \nu_i^j, 1 \leq j \leq s, 2 \leq i \leq \bar{m})$, i.e., \bar{z}^s consists of all components of first s blocks.

Theorem 4.2. *Consider (Σ, h) and assume that $n - k \geq m - 1$. Then:*

- (A1) *There exists $\mathcal{X}^C \subset \mathbb{R}^n$, open and dense, such that around any $x_0 \in \mathcal{X}^C$, the observed system (Σ, h) admits COQI's.*
- (A2) *For any ψ^1, \dots, ψ^ℓ defining COQI's $(\rho, \nu^1, \dots, \nu^\ell)$ at x_0 for (Σ, h) , there exist local coordinates (w, z) , with w given by (10) and z consisting of $z_i^{s,q}$ given by (18) in Section 4.1.1 below, bringing (Σ, h) into (11)-(12) with the unobserved subsystem (12) of the form:*

$$\dot{z}_i^{s,q} = \begin{cases} z_i^{s,q+1}, & 1 \leq q \leq \nu_i^s - 1, \\ b_i^s(w, \bar{z}^s), & q = \nu_i^s, \end{cases} \quad (14)$$

$$1 \leq s \leq \ell, 2 \leq i \leq \bar{m},$$

and for this form, we can always locally construct g_1, \dots, g_m such that (Σ_c, h) is x -flat at x_0 and is given by the following form:

$$NF1 : \begin{cases} \dot{w}_1^j = w_1^{j+1} & \dot{w}_i^j = w_i^{j+1} \\ \dot{w}_1^{\rho_1} = a_1(w) + u_1 & \dot{w}_i^{\rho_i} = a_i(w) + z_i^{1,1} u_1, \\ \dot{z}_i^{s,q} = \begin{cases} z_i^{s,q+1}, & 1 \leq q \leq \nu_i^s - 1, \\ b_i^s(w, \bar{z}^s) + z_i^{s+1,1} u_1, & q = \nu_i^1, \dots, \nu_i^{\bar{\ell}-1}, \\ b_i^{\bar{\ell}}(w, \bar{z}^{\bar{\ell}}) + u_i, & q = \nu_i^{\bar{\ell}} \end{cases} \end{cases}$$

$$1 \leq s \leq \ell, 2 \leq i \leq \bar{m},$$

where $1 \leq j \leq \rho_i - 1$, the integers \bar{m} and $\bar{\ell}$ are given by (9) and (13), respectively, and $h = (w_1^1, \dots, w_m^1)$ is a flat output of differential weight at least $n + m + \max_{2 \leq i \leq \bar{m}} \{\nu_i^1 + \dots + \nu_i^{\bar{\ell}}\}$.

In Section 4.1.1, we present an algorithm constructing, first, the dummy-outputs ψ^1, \dots, ψ^ℓ on an open and dense subset \mathcal{X}^C (and showing the existence of COQI's on \mathcal{X}^C) and, second, the control vector fields g_1, \dots, g_m of NF1. A proof of Theorem 4.2, based on that algorithm, is given in Section 6.7.

Theorem 4.2 constructs flat inputs around any x_0 (equilibrium or not) belonging to an open and dense subset $\mathcal{X}^C \subset \mathbb{R}^n$. If x_0 is not an equilibrium point of the original system, i.e., $f(x_0) \neq 0$, then we can locally around x_0 rectify f and simplify the solution of the problem as described in Theorem 4.3 below. Indeed, first, we render (Σ, h) flat around x_0 provided that it has POQI's at x_0 . Second, the proposed normal form NF2 is obtained by adding to (Σ, h) a multi-input chained form for the whole z -space (with respect to z -variables that rectify the z -components of the drift f). Third, the control system (Σ_c, h) that we obtain (by adding a multi-input chained form) turns out to be not only flat, which is our primary goal, but the differential weight of h as a flat output of NF2 is the lowest (minimal possible) among all differential weights of h as a flat output of any Σ_c .

Notations of NF2. Recall that $\dim \mathcal{H}(x) = k$ and set

$$n - k = p(m - 1) + r \quad \text{and} \quad p^* = \begin{cases} p, & \text{if } r = 0, \\ p + 1, & \text{if } r > 0, \end{cases} \quad (15)$$

be the Euclidean division of $n - k$ (the observability defect) and $m - 1$ (the number of output components being m). Define

$$\mu_i = \begin{cases} p, & 2 \leq i \leq m - r, \\ p + 1, & m - r + 1 \leq i \leq m, \end{cases} \quad \text{and} \quad b_i = \begin{cases} 1, & i = 2, \\ 0, & 3 \leq i \leq m, \end{cases} \quad (16)$$

that will correspond, respectively, to the lengths and to the last components of the z_i -chains of the form NF2, (in fact, all last components of z_i -chains are zero, except that of the z_2 -chain that equals 1).

Theorem 4.3. *Consider (Σ, h) and assume that $n - k \geq m - 1$. Then:*

(B1) *For any $x_0 \in \mathbb{R}^n$ satisfying $f(x_0) \neq 0$ and such that (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) at x_0 , there exist local coordinates (w, z) in a neighborhood X_0 of x_0 , with w given by (10) and z defined explicitly in Section 4.1.2 below, bringing (Σ, h) into (11)-(12) with the unobserved subsystem (12) of the form:*

$$\begin{aligned} \dot{z}_i^q &= 0, & 1 \leq q \leq \mu_i - 1, \\ \dot{z}_i^{\mu_i} &= b_i, & 2 \leq i \leq m, \end{aligned} \quad (17)$$

where μ_i and b_i are given by (16), and for this form, we can always construct vector fields g_1, \dots, g_m on X_0 such that (Σ_c, h) is x -flat at x_0 of differential weight $n + m + p^*$, and is given by the following form with $h = (w_1^1, \dots, w_m^1)$:

$$\text{NF2} \left\{ \begin{array}{ll} \dot{w}_1^j = w_1^{j+1} & \dot{w}_i^j = w_i^{j+1} \\ \dot{w}_1^{\rho_1} = a_1(w) + u_1 & \dot{w}_i^{\rho_i} = a_i(w) + z_i^1 u_1 \\ & \dot{z}_i^q = z_i^{q+1} u_1 \\ & \dot{z}_i^{\mu_i} = b_i + u_i, \\ & 2 \leq i \leq m, \end{array} \right.$$

where $1 \leq j \leq \rho_i - 1$, $1 \leq q \leq \mu_i - 1$.

(B2) *Let $x_0 \in \mathbb{R}^n$ and assume that $\dim \mathcal{H}(x) = k$ and is constant around x_0 . If there exist g_1, \dots, g_m such that (Σ_c, h) is x -flat at x_0 , then the differential weight of h as a flat output of Σ_c is at least $n + m + p^*$. In particular, the differential weight of h as a flat output of NF2 is the lowest (minimal possible) among all differential weights of h as a flat output of any Σ_c .*

An algorithm constructing the z -variables and the control vector fields g_1, \dots, g_m of normal form NF2 is given in Section 4.1.2, and a proof of Theorem 4.3, based on that algorithm, in Section 6.8.

Remark 4.3 (Singularities in the control space). We would like to emphasize that singularities in the control space are unavoidable (recall that we defined flatness at x_0 as a generic property with respect to the control u , see Definition 2.1). Indeed, if the system (Σ, h) is not observable, we add to f the sum $\sum_{i=1}^m u_i g_i$ to render it observable. Now it is clear that if the values of u , that form a link between the originally observable and unobservable subsystems, are zero, then the link is broken, the system (Σ_c, h) loses its observability and,

as a consequence, is not flat for those control values. In our forms only the vector field g_1 (and thus only the input u_1) is used for the link between the observed w -subsystem and the unobserved z -subsystem, see Figure 2c, while the remaining u_2, \dots, u_m affect the unobserved z -subsystem only. Hence it is clear that any control $u(t) = (u_1(t), u_2(t), \dots, u_m(t))^T$ for which $u_1 = 0$ creates singularities of observability (and thus of flatness).

4.1.1 Algorithm for constructing the dummy outputs ψ^1, \dots, ψ^ℓ and the vector field g_1, \dots, g_m of normal form NF1

Consider (Σ, h) around any $x_0 \in \mathbb{R}^n$ such that (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) at x_0 (thus, according to Lemma 4.1, on an open and dense subset \mathcal{X}^P of \mathbb{R}^n). Transform it locally into the observed-unobserved form (11)-(12) and denote $x = (w, z)$. We first show the existence of ψ^1, \dots, ψ^ℓ leading to new coordinates z in which the subsystem $\dot{z} = b(w, z)$ of (11)-(12) takes the form (14) and then for (14) we construct vector fields g_1, \dots, g_m yielding normal form NF1. Denote: $\mathcal{X}^0 = \mathcal{X}^P$, $\mathcal{H}^0 = \mathcal{H}$, where \mathcal{H} is the observability codistribution given by (4), and $k_0 = k = \dim \mathcal{H}(x)$.

Choose $m - 1$ functions $\psi_i^1(w, z)$, for $2 \leq i \leq m$, satisfying $(d\psi_2^1 \wedge \dots \wedge d\psi_m^1)(x_0) \neq 0 \pmod{\mathcal{H}^0(x_0)}$, where, in the (w, z) -coordinates, $\mathcal{H}^0(x) = \text{span} \{dw_i^j, 1 \leq i \leq m, 1 \leq j \leq \rho_i\}$. The functions ψ_i^1 always exist, since $\dim z = p(m - 1) + r$, with $p \geq 1$ and $r < m - 1$, and can be, for instance, taken as $m - 1$ well chosen original coordinates z_{i_2}, \dots, z_{i_m} . Consider $\psi^1 = (\psi_2^1, \dots, \psi_m^1)$ as dummy outputs that complete the original output h to a new output $h^1 = (h, \psi^1)$ and denote by \mathcal{H}^1 its associated observability codistribution $\mathcal{H}^1(x) = \mathcal{H}^0(x) + \text{span} \{dL_f^{q-1}\psi_i^1(x), 2 \leq i \leq m, q \geq 1\}$.

There exists an open and dense subset $\mathcal{X}^1 \subset \mathcal{X}^0$ (thus open and dense in \mathbb{R}^n as well) such that for any $x_0 \in \mathcal{X}^1$, we can find integers ν_2^1, \dots, ν_m^1 and a neighborhood $X_{x_0}^1$ of x_0 satisfying $\mathcal{H}^1(x) = \mathcal{H}^0(x) + \text{span} \{dL_f^{q-1}\psi_i^1(x), 2 \leq i \leq m, 1 \leq q \leq \nu_i^1\}$ for $x \in X_{x_0}^1$, where $\dim \mathcal{H}^1(x) = k_0 + \sum_{i=2}^m \nu_i^1 = k_1$, for all $x \in X_{x_0}^1$. Two cases are to be distinguished. Either $k_1 = n$, for $x \in X_{x_0}^1$, and then (f, h^1) is observable at x_0 and $(\rho_1, \dots, \rho_m, \nu_2^1, \dots, \nu_m^1)$ form OQI's at x_0 . Or $k_1 < n$, for $x \in X_{x_0}^1$, and then (f, h^1) is not observable at x_0 and $(\rho_1, \dots, \rho_m, \nu_2^1, \dots, \nu_m^1)$ are POQI's at x_0 (of the output h^1). Notice that in both cases, observable and unobservable, the choice of ν_2^1, \dots, ν_m^1 is, in general, not unique. For $2 \leq i \leq m$, in both cases, introduce coordinates

$$z_i^{1,q} = L_f^{q-1}\psi_i^1, \text{ for } 1 \leq q \leq \nu_i^1.$$

In the observable case, we set $\ell = 1$, and the construction of the z -variables ends up, while in the unobservable case, we complete the output h^1 to a new output $h^2 = (h^1, \psi^2)$ by choosing $m - 1$ functions $\psi_i^2(w, z)$, $2 \leq i \leq m$, such that $(d\psi_2^2 \wedge \dots \wedge d\psi_m^2)(x_0) \neq 0 \pmod{\mathcal{H}^1(x_0)}$. Denote by \mathcal{H}^2 its associated observability codistribution $\mathcal{H}^2(x) = \mathcal{H}^1(x) + \text{span} \{dL_f^{q-1}\psi_i^2(x), 2 \leq i \leq m, q \geq 1\}$. There exists an open and dense subset $\mathcal{X}^2 \subset \mathcal{X}^1$ (thus open and dense in \mathbb{R}^n as well) such that for any $x_0 \in \mathcal{X}^2$, we can find integers ν_2^2, \dots, ν_m^2 and a neighborhood $X_{x_0}^2$ of x_0 satisfying $\mathcal{H}^2(x) = \mathcal{H}^1(x) + \text{span} \{dL_f^{q-1}\psi_i^2(x), 2 \leq i \leq m, 1 \leq q \leq \nu_i^2\}$ for $x \in X_{x_0}^2$, where $\dim \mathcal{H}^2(x) = k_1 + \sum_{i=2}^m \nu_i^2 = k_2$. For $2 \leq i \leq m$, introduce coordinates

$$z_i^{2,q} = L_f^{q-1}\psi_i^2, \text{ for } 1 \leq q \leq \nu_i^2.$$

If $k_2 = n$, we set $\ell = 2$, and the construction of the z -variables stops, if $k_2 < n$, we continue. Repeat this process until the system (f, h^ℓ) , where $h^\ell = (h, \psi^1, \dots, \psi^\ell)$, obtained at the ℓ -th

step, has OQI's on an open and dense subset $\mathcal{X}^\ell \subset \mathcal{X}^{\ell-1}$ (thus open and dense in \mathbb{R}^n). Notice that for any $1 \leq s \leq \ell - 1$, we have $\psi^s = (\psi_2^s, \dots, \psi_m^s)$ and $\nu_i^s \geq 1$, for $2 \leq i \leq m$. Define now the integer d by

$$d = n - k - \sum_{i=2}^m \sum_{s=1}^{\ell-1} \nu_i^s,$$

and observe that d corresponds to the number of still unobserved directions after performing the penultimate $(\ell - 1)$ -step, that is, $k + \dim \bar{z}^{\ell-1} = n - d$. For $s = \ell$, we have either $d \geq m - 1$ (first case) and then $\psi^\ell = (\psi_2^\ell, \dots, \psi_m^\ell)$ and $\nu_i^\ell \geq 1$, for $2 \leq i \leq m$ (like in all preceding steps) and we put $m' = m$, or $d < m - 1$ (second case) and then $\psi^\ell = (\psi_2^\ell, \dots, \psi_{m'}^\ell)$, where $m' - 1 = d$, and $\nu_i^\ell = \nu_i^{\bar{\ell}} = 1$ for $2 \leq i \leq m'$, see (13) defining $\bar{\ell}$. Recall also the definition of \bar{m} given by (9) and define $\mathcal{X}^C = \mathcal{X}^\ell$.

Around any point $x_0 \in \mathcal{X}^C = \mathcal{X}^\ell$, we introduce $n - k$ coordinates

$$z_i^{s,q} = L_f^{q-1} \psi_i^s, \quad 1 \leq s \leq \ell, \quad 2 \leq i \leq \bar{m}, \quad 1 \leq q \leq \nu_i^s, \quad (18)$$

that are independent modulo $\mathcal{H} = \text{span} \{dw_i^j, 1 \leq i \leq m, 1 \leq j \leq \rho_i\}$, and bring the unobserved subsystem (12) into form (14). Define the control vector fields

$$g_1 = \frac{\partial}{\partial w_1^{\rho_1}} + \sum_{i=2}^m \left(z_i^{1,1} \frac{\partial}{\partial w_i^{\rho_i}} + \sum_{s=1}^{\bar{\ell}-1} z_i^{s+1,1} \frac{\partial}{\partial z_i^{s,\nu_i^s}} \right) \quad \text{and} \quad g_i = \frac{\partial}{\partial z_i^{\bar{\ell},\nu_i^{\bar{\ell}}}}, \quad 2 \leq i \leq m.$$

In $z_i^{s,q}$ -coordinates, the vector fields g_1, \dots, g_m give normal form NF1 with $(h_1, \dots, h_m) = (w_1^1, \dots, w_m^1)$, which is clearly x -flat at x_0 with (h_1, \dots, h_m) being a flat output of differential weight at least $n + m + \max_{2 \leq i \leq \bar{m}} \{\nu_i^1 + \dots + \nu_i^{\bar{\ell}}\}$, see the proof of Theorem 4.2. \triangleleft

The above algorithm provides an explicit construction, that uses differentiation and algebraic operations only, of g_i 's.

Proposition 4.1. *Consider the observed dynamical system (Σ, h) around any $x_0 \in \mathcal{X}^C = \mathcal{X}^\ell$ and denote $\Psi_i^{s,q} = L_f^{q-1} \psi_i^s$, for $1 \leq s \leq \ell$, $2 \leq i \leq \bar{m}$, $1 \leq q \leq \nu_i^s$, where the functions ψ_i^s and the set \mathcal{X}^ℓ are given by the above algorithm. Denote $\varphi_i^q = L_f^{q-1} h_i$, for $1 \leq q \leq \rho_i$. Vector fields g_1, \dots, g_m such that (Σ_c, h) is x -flat with h being a flat output can be constructed for g_1 by*

$$\left\{ \begin{array}{ll} \langle d\varphi_i^q, g_1 \rangle = 0, \quad 1 \leq q \leq \rho_i - 1, & \langle d\varphi_i^{\rho_i}, g_1 \rangle = \Psi_i^1, \\ 1 \leq i \leq m, & \langle d\Psi_i^q, g_1 \rangle = \begin{cases} \Psi_i^{s+1,1}, & q = \nu_i^1, \dots, \nu_i^{\bar{\ell}-1}, \\ 0, & q \neq \nu_i^1, \dots, \nu_i^{\bar{\ell}-1}, \end{cases} \\ & 2 \leq i \leq m, \quad 1 \leq s \leq \bar{\ell}, \end{array} \right. \quad (19)$$

and for g_2, \dots, g_m by

$$\left\{ \begin{array}{ll} \langle d\varphi_i^q, g_j \rangle = 0, \quad 1 \leq q \leq \rho_i, & \langle d\Psi_i^{s,q}, g_j \rangle = \begin{cases} 0, & (s, q) \neq (\bar{\ell}, \nu_i^{\bar{\ell}}), \\ \delta_{ij}, & (s, q) = (\bar{\ell}, \nu_i^{\bar{\ell}}), \end{cases} \\ 1 \leq i \leq m, & 2 \leq i \leq m, \quad 1 \leq s \leq \bar{\ell}, \end{array} \right. \quad (20)$$

where $2 \leq j \leq m$, and $\delta_{ij} = 1$, if $i = j$, and 0, otherwise. If all functions φ_i^q and $\Psi_i^{s,q}$ are global, i.e., $\mathcal{X}^\ell = \mathbb{R}^n$, then the vector fields g_i are defined globally and assure local flatness around any $x_0 \in \mathbb{R}^n$.

Corollary 4.1. *In a local coordinate system $x = (x_1, \dots, x_n)$, form the $n \times n$ -matrix $H^\ell(x) = \begin{pmatrix} H(x) \\ \Psi(x) \end{pmatrix}$ whose first k rows $H(x)$ are the differentials $d\varphi_i^q(x) = dL_f^{q-1}h_i(x)$ and the last $n - k$ rows $\Psi(x)$ are the differentials $d\Psi_i^{s,q} = dL_f^{q-1}\psi_i^s$, where we use the notations of Proposition 4.1. Then equations (19) and (20) are equivalent to*

$$H^\ell(x) \cdot g(x) = D(x), \quad (21)$$

where $g(x) = (g_1(x) \dots g_m(x))$, and $D(x) = (d_1(x) \dots d_m(x))$ with d_i denoting suitable terms of the right hand-side of (19) and (20) and both matrices $H^\ell(x)$ and $D(x)$ are thus determined by elements of $H(x)$ and $\Psi(x)$. If $x_0 \in \mathcal{X}^C = \mathcal{X}^\ell$ (in particular, COQI's exist at x_0), the matrix $H^\ell(x)$ is invertible around x_0 and

$$g(x) = (H^\ell)^{-1}(x) \cdot D(x). \quad (22)$$

Proof. The proofs of Proposition 4.1 and Corollary 4.1 follow directly from the algorithm in Section 4.1.1 for constructing g_1, \dots, g_m of NF1. \square

4.1.2 Algorithm for constructing the z -variables and g_1, \dots, g_m of normal form NF2

Consider (Σ, h) around any $x_0 \in \mathbb{R}^n$ satisfying $f(x_0) \neq 0$ and such that (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) at x_0 . By $f(x_0) \neq 0$, the first order partial differential equation $L_f\psi(x) = \sum_{i=1}^n \frac{\partial \psi}{\partial x_i} f_i = 0$ admits $n - 1$ solutions independent at x_0 . We choose among them any $n - k - 1$ solutions independent modulo $\mathcal{H} = \text{span} \{dL_f^{j-1}h_i, 1 \leq j \leq \rho_i, 1 \leq i \leq m\}$ at x_0 and we label them as ψ_i^q , $1 \leq q \leq \mu_i$, where $\mu_i = p$ for $2 \leq i \leq m - r$ and $\mu_i = p + 1$ for $m - r + 1 \leq i \leq m$, and $(i, q) \neq (2, p)$ (recall that $n - k = p(m - 1) + r$). Choose a solution of $L_f\psi(x) = 1$, and denote it ψ_2^p , such that the differentials of ψ_2^p and of the just constructed ψ_i^q are independent modulo \mathcal{H} . Around x_0 , introduce (w, z) -coordinates with w given by (10) and $z_i^q = \psi_i^q$, where $2 \leq i \leq m$, $1 \leq q \leq \mu_i$. For the system (Σ, h) , whose w -subsystem is given by (11) and the z -subsystem is represented by (17) in just constructed z_i^q -coordinates, define

$$g_1 = \frac{\partial}{\partial w_1^{\rho_1}} + \sum_{i=2}^m \left(z_i^1 \frac{\partial}{\partial w_i^{\rho_i}} + \sum_{q=1}^{\mu_i-1} z_i^{q+1} \frac{\partial}{\partial z_i^q} \right) \quad \text{and} \quad g_i = \frac{\partial}{\partial z_i^{\mu_i}}, \quad 2 \leq i \leq m. \quad (23)$$

In (w, z_i^q) -coordinates, the corresponding control system is in the form NF2, with $(h_1, \dots, h_m) = (w_1^1, \dots, w_m^1)$, which is clearly x -flat at x_0 of differential weight $n + m + p^*$ (where $p^* = p$, if $r = 0$, and $p^* = p + 1$, if $r > 0$, see (15)). \triangleleft

Once independent solutions ψ_i^q of $L_f\psi(x) = 0$ and $L_f\psi(x) = 1$ have been computed, the above algorithm provides an explicit construction of g_i 's (that uses differentiation and algebraic operations only in original coordinates).

Proposition 4.2. *Consider the dynamical system (Σ, h) around any $x_0 \in \mathbb{R}^n$ satisfying $f(x_0) \neq 0$ and such that (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) at x_0 . Denote $\varphi_i^q = L_f^{q-1}h_i$, for $1 \leq q \leq \rho_i$, and compute the functions ψ_i^q , for $1 \leq q \leq \mu_i$, $2 \leq i \leq m$, of the above algorithm. Vector fields g_1, \dots, g_m such that (Σ_c, h) is x -flat with h being a flat output can be constructed for g_1 by*

$$\left\{ \begin{array}{ll} \langle d\varphi_i^q, g_1 \rangle = 0, & 1 \leq q \leq \rho_i - 1, & \langle d\varphi_i^{\rho_i}, g_1 \rangle = \psi_i^1, \\ \langle d\varphi_1^{\rho_1}, g_1 \rangle = 1, & & \langle d\psi_i^q, g_1 \rangle = \psi_i^{q+1}, & 1 \leq q \leq \mu_i - 1, \\ & & \langle d\psi_i^{\mu_i}, g_1 \rangle = 0, & \\ & & & 2 \leq i \leq m, \end{array} \right. \quad (24)$$

and for g_2, \dots, g_m by

$$\left\{ \begin{array}{ll} \langle d\varphi_i^q, g_j \rangle = 0, & 1 \leq q \leq \rho_i, & \langle d\psi_i^q, g_j \rangle = 0, & 1 \leq q \leq \mu_i - 1, \\ & 1 \leq i \leq m, & \langle d\psi_i^{\mu_i}, g_j \rangle = \delta_{ij}, & \\ & & & 2 \leq i \leq m, \end{array} \right. \quad (25)$$

where $2 \leq j \leq m$, and $\delta_{ij} = 1$, if $i = j$, and 0, otherwise. If all functions φ_i^q and ψ_i^q are global, then the vector fields g_i are defined globally and assure local flatness around any $x_0 \in \mathbb{R}^n$.

Proof. Follows directly from the algorithm for constructing g_1, \dots, g_m of NF2. \square

Corollary 4.1 holds also for the computations of $g_1(x), \dots, g_2(x)$ of the form NF2, with the $(n-k) \times n$ -submatrix $\Psi(x)$ of $H^\ell(x)$ and the matrix $D(x)$ being this time defined, respectively, by the differentials $d\psi_i^q$, and the right hand-side terms of (24) and (25). In particular, relations (21)-(22) remain the same. Notice that now, in order to get the expressions of $\Psi(x)$ and $D(x)$, we first have to compute the solutions ψ_i^q of $L_f\psi(x) = 0$ and $L_f\psi(x) = 1$.

4.1.3 Discussion of the normal form NF1

The two extreme cases of the z -part of NF1 are $\ell = 1$ and $\ell = p$, if $n - k = p(m - 1)$, or $\ell = p + 1$, if $n - k = p(m - 1) + r$, where $1 \leq r \leq m - 2$. In the first case, we have (we drop the index s from $z_i^{s,q}$, ν_i^s and b_i^s , since it takes only one value, namely $s = 1$)

$$\begin{aligned} \dot{z}_i^q &= z_i^{q+1}, & 1 \leq q \leq \nu_i - 1, \\ \dot{z}_i^{\nu_i} &= b_i(w, z) + u_i, & 2 \leq i \leq m, \end{aligned}$$

the z -subsystem is formed by $m - 1$ almost linear chains (the nonlinearities as well as the inputs appear at the bottom level of each z_i -chain only). In the second case, we have $\nu_i^s = 1$, for $1 \leq s \leq \ell$, $2 \leq i \leq \bar{m}$, where \bar{m} is given by (9) with $m' = m$ if $r = 0$ and $m' = r + 1$ if $r > 0$, and the z -subsystem is given by (we drop the index q from $z_i^{s,q}$ since it takes only one value, namely $q = 1$)

$$\begin{aligned} \dot{z}_i^s &= b_i^s(w, \bar{z}^s) + z_i^{s+1}u_1, & 1 \leq s \leq p, & \dot{z}_i^s &= b_i^s(w, \bar{z}^s) + z_i^{s+1}u_1, & 1 \leq s \leq p - 1, \\ \dot{z}_i^{p+1} &= b_i^{p+1}(w, z) + u_i, & 2 \leq i \leq r + 1, & \dot{z}_i^p &= b_i^p(w, z) + u_i, & r + 2 \leq i \leq m, \end{aligned}$$

where the z_i -chains of length $p + 1$ are missing if $r = 0$. This case reminds very much form NF2; indeed the vector fields g_i are in the multi-chained form and it is due to g_1 only (the drift does not play any role) that for each s , the successive derivatives $L_{g_1}z_i^s = z_i^{s+1}$, for $2 \leq i \leq m$, provide $m - 1$ new states z_i^{s+1} (as many as possible).

While for NF2, the drift is rectified and plays no role in the triangular structure of the z -subsystem, for NF1 the drift is not rectified (actually, we cannot rectify it if x_0 is an equilibrium point). Therefore, we need to identify its triangular structure and to respect it. Any system can always be transformed into NF1 which actually works around any x_0 , equilibrium or not, and in order to compute the z -coordinates we do not have to compute any partial differential equation, see the algorithm for the construction of NF1, Proposition 4.1, and

Corollary 4.1 in Section 4.1.1. For NF1, the linking terms, that is, the nonzero components of g_1 , are the dummy outputs $\psi_i^1, \dots, \psi_i^\ell$ defining, respectively, the variables $z_i^{1,1}, \dots, z_i^{\ell,1}$. Notice that the choice of linking terms ψ_i^s is far from being unique which may be important in applications.

For fixed ψ_i^s , constructing the z -variables (and thus the form NF1) is performed on an open and dense subset $\mathcal{X}^C = \mathcal{X}^\ell \subset \mathbb{R}^n$ (see the algorithm in Section 4.1.1) which we will denote \mathcal{X}_ψ to indicate that, indeed, it depends on ψ . If it is important to work at a fixed point x_0 (around which we need COQI's to exist) and if $x_0 \notin \mathcal{X}_\psi$, we can choose another family of dummy outputs $\tilde{\psi}_i^s$ because, in general, $\mathcal{X}_\psi \neq \mathcal{X}_{\tilde{\psi}}$. Choosing different $\tilde{\psi}_i^s$'s will lead, in general, to different control vector fields and thus to different flat control systems with different differential weights. Finally, observe that if the system Σ is analytic and defined on \mathbb{R}^n , then there exist functions ψ^1, \dots, ψ^ℓ globally defined on \mathbb{R}^n such that (Σ, h^ℓ) , with $h^\ell = (h, \psi^1, \dots, \psi^\ell)$, admits COQI's on an open and dense subset of \mathbb{R}^n (that is, the same choice of ψ^1, \dots, ψ^ℓ works around any x_0 of that open and dense subset).

For NF1 (resp., NF2), in order to connect the w - and the z -subsystems, one linking term for each w_i -chain is needed and the variables $(z_2^{1,1}, \dots, z_m^{1,1})$ for NF1 (resp., (z_2^1, \dots, z_m^1) for NF2) play indeed the role of those linking terms, as $z_i^{1,1}$ (resp., z_i^1) affects $\dot{w}_i^{\rho_i}$. The link between the observed w -subsystem and the unobserved z -subsystem for both NF1 and NF2 as well as the link between the z^s -blocks is made with the help of the control vector field g_1 only and the remaining $m - 1$ inputs u_2, \dots, u_m appear at the bottom level of each z_i -chain. It follows that the input u_1 always needs to be differentiated in order to express all states and controls with the help of flat outputs $h_1 = w_1^1, \dots, h_m = w_m^1$ and their derivatives. While for NF2, the control u_1 is the only one that has to be differentiated, for NF1 other controls among the remaining ones may also need to be differentiated (implying that the differential weight of h is, in general, not minimal, see the proof of Theorem 4.2).

4.1.4 Discussion of the normal form NF2

If the observability defect verifies $n - k = p(m - 1)$, i.e., $n - k$ is a multiple of $m - 1$, then each z_i -chain is of length p , and the control u_1 needs to be differentiated p times, so the differential weight is $n + m + p$. If $n - k = p(m - 1) + r$, with $1 \leq r \leq m - 2$, then the r last z_i -chains are of length $p + 1$, the input u_1 needs to be differentiated $p + 1$ times and, hence the differential weight is $n + m + p + 1$.

If $f(x_0) \neq 0$, then the drift corresponding to the z -variables, that we denote by $b(w, z)$ in (12), can be rectified (even if $b(w_0, z_0) = 0$ and a non vanishing component of f is in the w -part) and, in well chosen z -coordinates, we have $b(w, z) = \frac{\partial}{\partial z_2^{\mu_2}}$ (which is of the form (17)). It follows that there is a significant freedom in constructing g_i 's, see the algorithm describing NF2 and Proposition 4.2 in Section 4.1.2. First, the condition $f(x_0) \neq 0$ allows to choose z_i^q as any independent (modulo \mathcal{H}) solutions of $L_f \psi(x) = 0$ and $L_f \psi(x) = 1$ (for $z_2^p = \psi_2^p$). Second, there is a full arbitrariness of labelling them as ψ_i^q . In particular μ_i can be taken not as p or $p + 1$ but (almost) arbitrarily respecting $\sum_{i=2}^m \mu_i = n - k$. Our choice is simple (the form of g_i 's is the simplest possible) and natural (chosen μ_i give the minimal differential weight) but other choices may also be interesting (in applications, for instance).

Notice that the components of the vector fields g_1, \dots, g_m depend on the unobserved (with respect to the original output h) states z_i^q only and they are designed to be in the multi-chained form. This particular form guarantees that the differential weight of h as a flat output of NF2 is the minimal possible (equal to $n + m + p^*$) among all differential weights of h as a

flat output of any Σ_c . It is clear that NF2 is not linearizable via invertible static feedback, however, NF2 becomes static feedback linearizable after pre-integrating p^* times the first control u_1 , thus after the application of a dynamical precompensator of dimension p^* .

4.2 Construction of the control vector fields: the case $n - k < m - 1$

If the observability defect satisfies $n - k = r < m - 1$ (i.e., $p = 0$, see (15)), then a result similar to Theorem 4.2 holds (but including it into Theorem 4.2 would significantly complicate the notations) and is given by Theorem 4.4 below.

Theorem 4.4. *Consider (Σ, h) and assume that $n - k = r < m - 1$. Then:*

- (A1)' *There exists $\mathcal{X}^P \subset \mathbb{R}^n$, open and dense, such that (Σ, h) admits POQI's around any point of \mathcal{X}^P , and at any point at which POQI's exist, COQI's exist as well.*
- (A2)' *Around any point x_0 of \mathcal{X}^P , independently of whether $f(x_0) = 0$ or $f(x_0) \neq 0$, choose any z -coordinates $(z_{m'+1}^1, \dots, z_m^1)$, where $m' = m - r$, completing the w -coordinates, given by (10), to a local coordinate system and transform Σ into (11)-(12). For that form, the vector fields*

$$g_1 = \frac{\partial}{\partial w_1^{\rho_1}} + \sum_{i=m'+1}^m z_i^1 \frac{\partial}{\partial w_i^{\rho_i}}, \quad g_i = \frac{\partial}{\partial w_i^{\rho_i}}, \text{ for } 2 \leq i \leq m', \quad (26)$$

$$g_i = \frac{\partial}{\partial z_i^1}, \text{ for } m' + 1 \leq i \leq m,$$

yield the system (Σ_c, h) that is x -flat at x_0 and given by

$$NF3 \begin{cases} \dot{w}_i^j = w_i^{j+1} & \dot{w}_i^j = w_i^{j+1} \\ \dot{w}_i^{\rho_i} = a_i(w) + u_i, & \dot{w}_i^{\rho_i} = a_i(w) + z_i^1 u_1, \\ 1 \leq i \leq m', & \dot{z}_i^1 = b_i^1(w, z) + u_i, \\ & m' + 1 \leq i \leq m, \end{cases}$$

where $b_i^1(w, z)$ are arbitrary functions of w and z , and $h = (w_1^1, \dots, w_m^1)$ is a flat output of differential weight $n + m + 1$. In particular, if $\mathcal{X}^P = \mathbb{R}^n$, then g_1, \dots, g_m exist locally around any $x_0 \in \mathbb{R}^n$.

- (B2)' *Let $x_0 \in \mathbb{R}^n$ and assume that $\dim \mathcal{H}(x) = k$ and is constant around x_0 . If there exist g_1, \dots, g_m such that (Σ_c, h) is x -flat at x_0 then the differential weight of h as a flat output of Σ_c is at least $n + m + 1$. In particular, the g_i 's defining NF3 give the lowest (minimal possible) differential weight of h among all choices of g_1, \dots, g_m .*

4.2.1 Algorithm for constructing g_1, \dots, g_m of the normal form NF3

Consider the dynamical system (Σ, h) around any x_0 such that (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) at x_0 and transform it locally into the observed-unobserved form (11)-(12). Since $\dim z = r < m - 1$, it follows that at least $m' = m - r$ controls, say $u_1, \dots, u_{m'}$, must affect the w -subsystem. So we can choose $g_i = \frac{\partial}{\partial w_i^{\rho_i}}$, for $2 \leq i \leq m'$ (the control u_1 will play a special role), and thus modify the corresponding w -equations as $\dot{w}_i^{\rho_i} = a_i(w) + u_i$, for $2 \leq i \leq m'$. The remaining equations for $\dot{w}_i^{\rho_i}$ have to be linked to the z -subsystem to render the whole system observable and we use all z -variables, where $z = (z_{m'+1}^1, \dots, z_m^1)$, as linking terms

multiplying the control u_1 , that is, we define g_1 and g_i , for $m' + 1 \leq i \leq m$, by (26), to get $\dot{w}_1^{\rho_1} = a_1(w) + u_1$, $\dot{w}_i^{\rho_i} = a_i(w) + z_i^1 u_1$ and $\dot{z}_i^1 = b_i^1(w, z) + u_i$, $m' + 1 \leq i \leq m$. We thus have obtained the normal form NF3 which is clearly x -flat at x_0 , with $(h_1, \dots, h_m) = (w_1^1, \dots, w_m^1)$ being a flat output of differential weight $n + m + 1$. \triangleleft

Like for the form NF1, the above algorithm provides an explicit construction, that uses differentiation and algebraic operations only, of g_i 's. The algebraic system giving g_1, \dots, g_m for NF3 is very similar to that for NF1 and left to the reader.

4.2.2 Discussion of the normal form NF3

If $f(x_0) \neq 0$, the drift b of the unobserved subsystem (12) can be rectified and, in well chosen z -coordinates, we obtain the normal form NF3 with $b_{m'+1}^1 = 1$ and $b_i^1 = 0$, for $m' + 2 \leq i \leq m$. This is the analogue of NF2 in the case $n - k < m - 1$. The main difference between NF3 and the forms NF1 and NF2 is, as explained in the above algorithm, that the unobserved z -part of NF3 can be affected by at most $r = n - k$ inputs, so the remaining controls necessarily appear in the w -equations. As for the case $n - k \geq m - 1$, the control vector fields are designed to be in the simplest possible form and only the vector field g_1 is used to link the observed and the unobserved subsystems although g_2, \dots, g_{m-r} affect the w -subsystem of NF3 as well (which is, in the case $n - k \geq m - 1$, affected by g_1 only). This, together with the fact that each z_i -chain is of length one, guarantee that the differential weight of h as a flat output of NF3 is the minimal possible, which is $n + m + 1$ (recall that flatness of differential weight $n + m$ characterizes the observable case (Σ, h) , see Section 2). Notice also that in the case $n - k = r < m - 1$, we are able to construct g_1, \dots, g_m around any x_0 of \mathcal{X}^P , the open and dense subset of \mathbb{R}^n consisting of points at which (Σ, h) admits POQI's, while Theorem 4.2, treating the case $n - k \geq m - 1$, enables us to construct g_1, \dots, g_m around any x_0 in an open and dense subset \mathcal{X}^C of \mathcal{X}^P (but, in general, not equal to \mathcal{X}^P , see Section 4.1.1). In particular, if POQI's exist around any $x_0 \in \mathbb{R}^n$, then NF3 is established around any $x_0 \in \mathbb{R}^n$ and not only on an open and dense subset like NF1.

Summing up, in all cases, we can always construct (locally, on an open and dense subset of \mathbb{R}^n), control vector fields g_1, \dots, g_m such that the associated control system (Σ_c, h) is flat and thus, generically, the problem of constructing flat inputs is completely solved.

4.3 Avoiding singularities in the control space

If the system (Σ, h) is observable at a given x_0 , then for the corresponding flat control system (Σ_c, h) , constructed by Theorem 3.1, Proposition 3.1, and Corollary 3.1, even if $\varphi_i = h_i$ yield local flatness only, representing the states and the controls with the help of $\varphi_i = h_i$ and their derivatives is global with respect to u , so we never face singularities in the control space. This is no longer the case if (Σ, h) is unobservable and all normal forms NF1, NF2, and NF3 exhibit singularities in the control space. Namely, for all of them, the system ceases to be flat (with h as a flat output) at $u_1 = 0$ (which is a singular control for flatness, see Remark 4.3). If we want to avoid singularities in the control space, we can construct another control system as follows: in all equations of NF1, NF2, and NF3, we replace u_1 by $\exp(u_1)$, except for the equation $\dot{w}_1^{\rho_1} = a_1(w) + u_1$ that we keep unchanged. For instance, for NF1, the equations involving u_1 become:

$$\begin{aligned} \dot{w}_1^{\rho_1} &= a_1(w) + u_1 & \dot{w}_i^{\rho_i} &= a_i(w) + z_i^{1,1} \exp(u_1) \\ \dot{z}_i^{s,q} &= b_i^s(w, \bar{z}^s) + z_i^{s+1,1} \exp(u_1), & q &= \nu_i^1, \dots, \nu_i^{\bar{\ell}-1}, \end{aligned}$$

where $1 \leq s \leq \ell$, $2 \leq i \leq \bar{m}$. We have thus constructed a new control system Σ_c that does no longer display singularities in the control space (representing the state z and the control u , with the help of components of $\varphi_i = h_i$ and their derivatives, is global with respect to u), but the system is nonlinear with respect to u_1 (which is the price for avoiding singularities).

5 Application to private communication

Since the trendsetting work of [25], it is known that the problem of private communication can be investigated with the help of a unidirectional synchronization of chaotic systems (see also [24] for an observer point of view). The goal of this section (which is based on the preliminary paper [23]) is to explain how constructing flat inputs for a given observed dynamics can be applied to private communication via both, using chaotic models and including the messages into the dynamics (see also [1], for a related approach using the design of nonlinear observers with unknown inputs, and [3] and [30], where invertibility and flatness of switched linear discrete-time systems is applied to private communication).

The general problem can be summarized as follow. Suppose that m confidential messages $u_1(t), \dots, u_m(t)$ have to be sent to the receiver. To this aim, we use a transmitter (Σ, h) that consists of a dynamical system together with an output

$$\Sigma : \dot{x} = f(x), \quad y = h(x), \quad x \in \mathbb{R}^n, \quad y \in \mathbb{R}^m.$$

In order to transmit messages $(u_1(t), \dots, u_m(t))$, we will add to Σ control vector fields g_1, \dots, g_m whose controls are, resp., u_1, \dots, u_m (that is, messages to be sent) in such a way that

$$\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m u_i g_i(x), \quad y = h(x),$$

is a flat system with $\varphi = (h_1, \dots, h_m)$ being a flat output. Both the sender and receiver know completely the equations of the flat control system $\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m u_i g_i(x)$ and in order to transmit $u(t) = (u_1(t), \dots, u_m(t))$, the sender calculates the corresponding output signal $y(t) = h(x(u(t), t))$, where $x(u(t), t)$ is the solution corresponding to $u(t)$, and transmits the masked information via the communication multiplexed channel. The receiver receives the signal $y(t)$ and knowing Σ_c calculates $u(t)$ (recall that (Σ_c, h) is flat). The original output h being a flat output of (Σ_c, h) is essential to express the confidential message $u(t)$ as function of the masked information $y(t)$ sent to the receiver (we thus study not only a synchronization problem, but also an input reconstruction problem). In order to compute $u(t)$ based on the knowledge of $y(t)$, left invertibility of Σ_c (which is a weaker property than flatness) would be sufficient but, in that case, the receiver should know not only $y(t)$ but also the initial condition and the internal dynamics of the inverse, see [27]. So the advantage of using the flat system Σ_c is that the receiver uses the masked information $y(t)$ only. To assure that $y(t)$ is well masked (cannot be decrypted by a third person), we use as Σ a chaotic system. To illustrate that general scheme, assume that two messages $u_1(t)$ and $u_2(t)$ have to be sent to the receiver. We use a transmitter, composed of two independent chaotic systems, a Lorenz circuit (x_ℓ, y_ℓ, z_ℓ) , see, e.g., [18], and a Rössler circuit (x_r, y_r, z_r) , see, e.g., [29], of the form (the notation (Ch) referring to the chaotic behavior):

$$(Ch) : \begin{cases} \dot{x}_\ell = \sigma(y_\ell - x_\ell) & \dot{x}_r = -y_r - z_r \\ \dot{y}_\ell = -k_d x_\ell z_\ell + r x_\ell - y_\ell & \dot{y}_r = x_r + a y_r \\ \dot{z}_\ell = k_d x_\ell y_\ell - \beta z_\ell & \dot{z}_r = b + z_r(x_r - c), \end{cases}$$

where the parameters $a, b, c, \beta, \sigma, r$ and k_d are constant. As explained above, in order to transmit messages $u_1(t)$ and $u_2(t)$, we add to (Ch) two control vector fields g_1 and g_2 whose controls are, resp., u_1 and u_2 :

$$(Ch_c) : \dot{x} = f(x) + u_1 g_1(x) + u_2 g_2(x), \quad y_i = h_i(x), \quad 1 \leq i \leq 2,$$

and the masked information transmitted via the communication multiplexed channel is $(y_1(t), y_2(t)) = (x_\ell(t), z_\ell(t))$, where g_1 and g_2 are chosen in such a way that (Ch_c) is flat with $\varphi = (h_1, h_2) = (x_\ell, z_\ell)$ being a flat output, and f is the right-hand side of (Ch) . The chaotic behavior of (Ch) (depending on the values of the constant parameters) is crucial and has to be preserved by adding the modification $u_1 g_1(x) + u_2 g_2(x)$ to (Ch) . It is clear that with $(h_1, h_2) = (x_\ell, z_\ell)$ only the Lorenz variables can be observed and in the observed-unobserved form (11)-(12), using the new global w -coordinates $w_1^1 = x_\ell$, $w_1^2 = L_f x_\ell = \sigma(y_\ell - x_\ell)$, $w_2^1 = z_\ell$, the Lorenz circuit is equivalently given by: $\dot{w}_1^1 = w_1^2$, $\dot{w}_1^2 = -\sigma k_d w_1^1 w_2^1 + \sigma(r-1)w_1^1 - (\sigma+1)w_1^2 = a_1(w)$ and $\dot{w}_2^1 = k_d w_1^1 (\frac{1}{\sigma} w_1^2 + w_1^1) - \beta w_2^1 = a_2(w)$. Notice that here, the unobserved subsystem described by the Rössler circuit is completely independent of the observed Lorenz circuit. Define the linking term $z_2^1 = \psi(w, x_r, y_r, z_r)$ by $\psi = y_r$ and compute its successive time-derivatives (we drop the index s since, as we will see, only one dummy output $\psi = y_r$ is necessary to render the system observable, i.e., s takes only one value, namely $s = 1$). We get $L_f \psi = x_r + a y_r$ and $L_f^2 \psi = -(y_r + z_r) + a(x_r + a y_r)$. It is clear that $d\psi$, $dL_f \psi$ and $dL_f^2 \psi$ are independent everywhere, and $z_2^q = L_f^{q-1} \psi$, $1 \leq q \leq 3$, (together with the w -coordinates) define a global system of coordinates on $\mathbb{R}^3 \times \mathbb{R}^3$. According to our results, we globally define $g_1 = \frac{\partial}{\partial w_1^2} + z_2^1 \frac{\partial}{\partial w_2^1}$ and $g_2 = \frac{\partial}{\partial z_2^3}$ and obtain in (w, z) -coordinates a system in NF1-form

$$NF1 : \begin{cases} \dot{w}_1^1 = w_1^2 & \dot{w}_2^1 = a_2(w) + z_2^1 u_1 \\ \dot{w}_1^2 = a_1(w) + u_1 & \dot{z}_2^1 = z_2^2 \\ & \dot{z}_2^2 = z_2^3 \\ & \dot{z}_2^3 = b_2(w, z) + u_2, \end{cases} \quad (27)$$

where $b_2(w, z) = -b - z_2^2 - a z_2^3 - (z_2^3 - z_2^1 + a z_2^2)(z_2^2 - a z_2^1)$, which is flat with $(w_1^1, w_2^1) = (x_\ell, z_\ell)$ being a flat output. This system in the original coordinates is:

$$(Ch_c) : \begin{cases} \dot{x}_\ell = \sigma(y_\ell - x_\ell) & \dot{x}_r = -y_r - z_r \\ \dot{y}_\ell = -k_d x_\ell z_\ell + r x_\ell - y_\ell + \frac{1}{\sigma} u_1 & \dot{y}_r = x_r + a y_r \\ \dot{z}_\ell = k_d x_\ell y_\ell - \beta z_\ell + y_r u_1 & \dot{z}_r = b + z_r(x_r - c) - u_2. \end{cases}$$

The receiver knows completely the dynamics of the flat control system (Ch_c) as well as the transmitted output $(y_1(t), y_2(t)) = (x_\ell(t), z_\ell(t))$ and therefore using the flatness property the original messages $u = (u_1(t), u_2(t))$ can be recovered by the receiver as functions of the received output and its successive time-derivatives: $u_1(t) = \delta_1(y_1, \dot{y}_1, y_2)$ and $u_2(t) = \delta_1(y_1, \dots, y_1^{(5)}, y_2, \dots, y_2^{(4)})$.

Remark 5.1. An interesting question is why the unobserved part z is needed. The unobserved z -subsystem plays an important role for increasing the safety. Indeed, represent the system (Ch_c) in (w, z) -coordinates, as NF1 given by (27), and notice that the message u_1 has a degree of security significantly lower than that of u_2 . The z -subsystem can be seen as a second level of security. This motivates even more the use of quasi-indices: for a general two-output system, in order to decode u_1 , we may need only the output $h_1 = w_1^1$ (if the function a_1 of equation $\dot{w}_1^{\rho_1} = a_1(w) + u_1$, allowing to decode u_1 , depends on w_1^j -variables only)

but we never need the linking term z_2^1 , however, we always need it for decoding u_2 . Notice that for the proposed transmitter (Ch_c), the function a_1 involves both outputs $h_1 = w_1^1$ and $h_2 = w_2^1$. Another issue (closely related to the above question) is the motivation for using a two-output system for transmitting the two messages u_1 and u_2 (whose encodings are thus coupled), instead of using two independent systems, each one being used to encode a single message. Again it is clear that the proposed transmitter guarantees a higher security level for u_2 : in order to decode it, we have to decode beforehand u_1 .

5.1 Simulations

In this section we present a preliminary analysis that first shows, using numerical simulations, that the chaotic behavior of the transmitter (Ch) is preserved by adding control vector fields multiplied by suitable periodic messages into the dynamics, and second, that for suitable amplitudes of the encoded messages, the messages are recovered with a good accuracy by the receiver. The amplitudes should not be too small, otherwise the messages will be hidden into the chaos or will have the same order of magnitudes as numerical errors or perturbations and it will be difficult to distinguish between them; they should not be too large either, otherwise the chaotic behavior will be strongly modified and the messages will be easily detected by a hacker. We will first give the phase plots for the uncontrolled dynamical transmitter composed of the Lorenz and Rössler circuits which are well known to be chaotic. Then we apply two sinusoidal input signals u_1 and u_2 . We present three cases for different amplitudes of the inputs (the frequencies of u_1 and u_2 are the same for all cases). As expected, we observe that the larger the amplitudes of u_1 and u_2 are, the more the chaotic behavior is modified (but in all cases it seems to be preserved). A theoretical confirmation of this preliminary study will be the subject of a future work. Neither noise nor parameter uncertainties between the sender and the receiver nor the robustness with respect to different classical attacks have been considered here. It is, however, obvious that in practice those problems cannot be neglected and they have to be discussed in practical applications of the proposed method.

Figures 3a and 4a give the phase plots for the original Lorenz and Rössler subsystems (with no control), see the last paragraph of this section for the parameters values used in simulations. Figures 3b and 4b correspond to the solutions of the control system (Ch_c) and show that the chaotic behavior is preserved after modifying the original dynamical chaotic system (Ch) by applying the following inputs: $u_1 = 0.5 + 0.1 \sin(2\pi t)$ and $u_2 = 0.5 \sin(1.8\pi t)$ to the control system (Ch_c). For such (small) amplitudes, the first message is recovered with a good accuracy (Figure 5a), but the second one does not converge to the transmitted u_2 (Figure 5b). This is due to the fact that in order to decode u_2 , we need the third derivative of y_r (the linking term between the two chaotic subsystems) and even if the decoded y_r is close to the transmitted one (Figure 5c), it still contains some approximation errors (namely, the pick around 3.5 s in Figure 5c) that are amplified at each new differentiation and lead to a decoded u_2 which is very far from the transmitted one.

Figures 3c and 4c correspond to the solutions of the control system (Ch_c) obtained for $u_1 = 5 + \sin(2\pi t)$ and $u_2 = 5 \sin(1.8\pi t)$. Notice that, the amplitude of the control values equals ten times that used in the previous example. For such inputs values, only the Lorenz strange attractor is slightly modified (a peak appears). Figures 6a and 6b show that, for $u_1 = 5 + \sin(2\pi t)$ and $u_2 = 5 \sin(1.8\pi t)$, the input u_1 (which corresponds to one of the confidential messages) can be exactly recovered after a very short time ($t \cong 0.1$ s) and u_2 can be recovered with a very good accuracy after 2 s. In order to obtain u_2 , first we have to




Figure 3: Phase plots for the Lorenz state variables for different inputs.




Figure 4: Phase plots for the Rössler state variables for different inputs.




Figure 5: To-be-sent messages and y_r of the transmitter in red, decoded messages and decoded y_r in blue for $u_1 = 0.5 + 0.1 \sin(2\pi t)$, $u_2 = 0.5 \sin(1.8\pi t)$.




Figure 6: To-be-sent messages and y_r of the transmitter in red, decoded messages and decoded y_r in blue for $u_1 = 5 + \sin(2\pi t)$, $u_2 = 5 \sin(1.8\pi t)$.

decode u_1 , then y_r and, finally, to differentiate three times the filtered y_r . Figure 6c shows that, after 0.5 s, the real y_r of the transmitter and the decoded one coincide. The purpose of this paper is not to present the receiver (observer or/and differentiator), nevertheless it is important to note that the presented simulations have been obtained using two homogeneous differentiators [16] in order to compute u_1 and y_r . Then, after filtering the obtained y_r , via a low pass filter, we use again a homogeneous differentiator to decode u_2 . The above time constants (0.1 s, 2 s, etc.) are related to the differentiators gains.

From Figures 3d-4d, we see that for $u_1 = 10 + 2 \sin(2\pi t)$, $u_2 = 10 \sin(1.8\pi t)$, the chaotic behavior of the Lorenz and Rössler subsystems are modified. For such amplitudes, the messages are perfectly recovered by the receiver (as above, after 0.1 s and 2 s, resp.) but the structure of the strange attractors are too strongly modified and a hacker would be able to detect the messages. We do not give the curves for the decoded messages since they are very similar to those of the previous case.

The parameters for the simulations are given by $\beta = 8/3$, $\sigma = 10$, $r = 28$, $k_d = 10$, $a = 0.15$, $b = 0.20$, $c = 10$, with initial conditions $x_\ell(0) = y_\ell(0) = z_\ell(0) = 1$ and $x_r(0) = y_r(0) = z_r(0) = 1$.

6 Proofs

6.1 Proof of Theorem 3.1

Proof of (O1) \Rightarrow (O2). Consider the system Σ , around x_0 , together with its output $h = (h_1(x), \dots, h_m(x))$ and assume that there exist OQI's (ρ_1, \dots, ρ_m) at x_0 . Around x_0 , the system Σ can be locally brought into $\dot{w}_i^j = w_i^{j+1}$, $1 \leq j \leq \rho_i - 1$, $\dot{w}_i^{\rho_i} = a_i(w)$, $1 \leq i \leq m$, with $w_i^j = L_f^{j-1} h_i$, for $1 \leq i \leq m$ and $1 \leq j \leq \rho_i$. For this form, define $g_i(w) = \frac{\partial}{\partial w_i^{\rho_i}}$, $1 \leq i \leq m$. It is clear that

$$\Sigma_c : \begin{cases} \dot{w}_i^j &= w_i^{j+1}, & 1 \leq j \leq \rho_i - 1, \\ \dot{w}_i^{\rho_i} &= a_i(w) + u_i, & 1 \leq i \leq m, \end{cases}$$

is static feedback linearizable around x_0 (with linearizing outputs $h_i = w_i^1$, $1 \leq i \leq m$) and thus x -flat at x_0 of differential weight $n + m$, with h a minimal flat output.

Proof of (O2) \Rightarrow (O1). Suppose that there exist g_1, \dots, g_m , around x_0 , such that the associated control system $\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m g_i(x) u_i$ is x -flat at x_0 of differential weight $n + m$, with $h = (h_1(x), \dots, h_m(x))$ being a minimal flat output. Let ν_1, \dots, ν_m denote the relative degrees of $h_1(x), \dots, h_m(x)$, that is, $h_i^{(\nu_i)}$ is the lowest time-derivative of $h_i(x(t))$ depending explicitly on u . Since the flat outputs and all their successive derivatives are

independent at x_0 , we can introduce the new coordinates $\tilde{x}_i^j = L_f^{j-1}h_i$, for $1 \leq i \leq m$ and $1 \leq j \leq \nu_i$. We get

$$\begin{aligned}\tilde{x}_i^j &= \tilde{x}_i^{j+1}, & 1 \leq j \leq \nu_i - 1, \\ \tilde{x}_i^{\nu_i} &= L_f^{\nu_i}h_i + \sum_{j=1}^m (L_{g_j}L_f^{\nu_i-1}h_i)u_j, & 1 \leq i \leq m.\end{aligned}\tag{28}$$

Flatness of differential weight $n + m$ implies that we necessarily have $\sum_{i=1}^m \nu_i = n$ and that the decoupling matrix $D_{ij}(x) = L_{g_j}L_f^{\nu_i-1}h_i(x)$, for $1 \leq i, j \leq m$, is of full rank around x_0 (otherwise the system would not be flat of differential weight $n + m$). It is clear that for the initial Σ , the integers $\rho_i = \nu_i$, $1 \leq i \leq m$, are OQI's at x_0 .

In order to complete the proof, observe that, by Lemma 4.1, $\dim \mathcal{H}(x) = n$, for any $x \in \mathbb{R}^n$, implies that OQI's exist on an open and dense subset $\mathcal{X}^O \subset \mathbb{R}^n$.

6.2 Proof of Proposition 3.1

Suppose that (Σ, h) admits OQI's (ρ_1, \dots, ρ_m) at x_0 . It follows from the proof of the implication $(\mathcal{O}2) \Rightarrow (\mathcal{O}1)$ of Theorem 3.1 that desired vector fields g_1, \dots, g_m satisfy (i) for a suitable invertible matrix $(D_{ij}(x))$. Conversely, consider g_1, \dots, g_m satisfying (i). If $D(x) = I_m$, where I_m denotes the identity $m \times m$ -matrix, then by the proof of the implication $(\mathcal{O}1) \Rightarrow (\mathcal{O}2)$, we get $g_i = \frac{\partial}{\partial w_i^{\rho_i}}$. If we take $D(x)$ instead of I_m , then we have to replace $g(x) \mapsto g(x)\beta(x)$, where $\beta(x) = (D(x))^{-1}$ proving that for both choices of g_i 's we get a feedback linearizable system for which h is a flat output of differential weight $n + m$. Independently of $D(x)$, all corresponding vector fields g_1, \dots, g_m define the same distribution \mathcal{G} given by (ii).

6.3 Proof of Corollary 3.2

Assume that (Σ_c, h) is static feedback linearizable around x_0 . Then by Theorem 3.1, there exists OQI's at x_0 and, in particular, (Σ, h) is locally observable at x_0 .

6.4 Proof of Corollary 3.3

Consider a linear dynamical system $\Sigma : \dot{x} = Ax, y = Cx$, and assume that (A, C) is observable. Clearly, there exist OQI's for (A, C) and vector fields g_1, \dots, g_m that render the system flat can be constructed with the help of condition Proposition 3.1(i), in which we take $D_{ij}(x) = \delta_{ij}$. It is clear that $g_i = b_i$, $1 \leq i \leq m$. Let us now suppose that there exist constant vector fields $g_1 = b_1, \dots, g_m = b_m$ such that the associated linear control system is flat at x_0 . Since a flat control system is observable with respect to its flat output and since the observability of linear control systems does not depend on the control vector fields, it follows that (A, C) is necessarily observable.

6.5 Proof of Lemma 4.1

For $1 \leq j \leq n$, denote $\mathcal{H}^j(x) = \text{span} \{dL_f^{q-1}h_i(x), 1 \leq i \leq m, 1 \leq q \leq j\}$ not to be confused with \mathcal{H}^j of Section 4.1.1. The rank of each distribution $\mathcal{H}^j(x)$, for $1 \leq j \leq n$, is locally constant on an open and dense subset \mathcal{X}^j of \mathbb{R}^n . So all those ranks are locally constant on $\mathcal{X}^P = \bigcap_{1 \leq j \leq n} \mathcal{X}^j$, open and dense subset of \mathbb{R}^n . On each connected component X_c^P of \mathcal{X}^P , we have $\dim \mathcal{H}^n(x) = k \leq n$ (with k that may depend on the component). It follows that on each X_c^P there exist integers (ρ_1, \dots, ρ_m) such that $\sum_{i=1}^m \rho_i = k$ and

$\mathcal{H}^j(x) = \text{span} \{dL_f^{q-1}h_i(x), 1 \leq i \leq m, 1 \leq q \leq \min\{j, \rho_i\}\}$ and thus on each component X_c^P such that $k < n$ there exist POQI's (that may depend on the component) at any $x_0 \in X_c^P$, and on each component X_c^P such that $k = n$ (in which case we denote X_c^P by X_c^O) there exist OQI's (that may depend on the component) at any $x_0 \in X_c^O$. In the analytic case k and (ρ_1, \dots, ρ_m) are the same for all components. The proof of Lemma 4.1 provides a construction of one choice of POQI's only: namely, the smallest (ρ_1, \dots, ρ_m) satisfying $\rho_1 \geq \rho_2 \geq \dots \geq \rho_m$.

6.6 Proof of Theorem 4.1

Statement (Flat 2) follows directly from Theorem 3.1 while that of (Flat 3) from Theorems 4.2 and 4.4. In the observable case, by Lemma 4.1, OQI's exist on an open and dense subset of \mathbb{R}^n , while in the unobservable case, by the algorithm of Section 4.1.1, COQI's exist on an open and dense subset of \mathbb{R}^n , implying the first part of (Flat 1). Construction of g_1, \dots, g_m , via differentiations and algebraic operations, is guaranteed by Proposition 3.1 and Corollary 3.1 (observable case) and Proposition 4.1 and Corollary 4.1 (unobservable case).

6.7 Proof of Theorem 4.2

Proof of (A1). The proof is contained in the algorithm of Section 4.1.1 which constructs, around any point of an open and dense subset $\mathcal{X}^C = \mathcal{X}^\ell$ of \mathbb{R}^n , dummy outputs ψ^1, \dots, ψ^ℓ leading to COQI's at that point.

Proof of (A2). The algorithm of Section 4.1.1 constructs the vector field g_1, \dots, g_m leading to the flat control system (NF1, h). To show that, h is indeed a flat output, notice that $w_i^j = h_i^{(j-1)}$, for $1 \leq i \leq m$, $1 \leq j \leq \rho_i$, $h_1^{(\rho_1)} = \dot{w}_1^{\rho_1} = a_1(w) + u_1$ yielding $u_1 = \delta_1(\bar{h}_1^{\rho_1}, \bar{h}_2^{\rho_2-1}, \dots, \bar{h}_m^{\rho_m-1})$, where \bar{h}_i^j denotes $\bar{h}_i^j = (h_i, \dot{h}_i, \dots, h_i^{(j)})$. Then, provided that $u_1 \neq 0$, equations $h_i^{(\rho_i)} = \dot{w}_i^{\rho_i} = a_i(w) + z_i^{1,1}u_1$, for $2 \leq i \leq m$, allow to express $z_i^{1,1} = \gamma_i^{1,1}(\bar{h}_1^{\rho_1}, \bar{h}_2^{\rho_2}, \dots, \bar{h}_m^{\rho_m})$. By differentiating $z_i^{1,1}$, we get $z_i^{1,2} = \dot{z}_i^{1,1} = \gamma_i^{1,2}(\bar{h}_1^{\rho_1+1}, \bar{h}_2^{\rho_2+1}, \dots, \bar{h}_m^{\rho_m+1})$, for $2 \leq i \leq m$, and so on. For $2 \leq i \leq \bar{m}$, denote $\mu_i = \nu_i^1 + \dots + \nu_i^{\bar{\ell}}$ and $\mu = \max_{2 \leq i \leq \bar{m}} \{\mu_i\}$. In order to see that the differential weight of h is at least $n + m + \mu$, recall that we have just expressed u_1 as $u_1 = \delta_1(\bar{h}_1^{\rho_1}, \bar{h}_2^{\rho_2-1}, \dots, \bar{h}_m^{\rho_m-1})$ and the remaining $m - 1$ inputs u_2, \dots, u_m appear at the bottom level of each z_i -chain. It follows that, in the best case, u_1 is the only input that needs to be differentiated in order to express all states and controls with the help the h_i 's and their derivatives. For each z_i -chain, the input u_1 needs to be differentiated μ_i times. Hence, in the best case, the differential weight of h is $n + m + \mu$. In some cases, we may need additionally to differentiate other inputs among u_2, \dots, u_m . To understand this, consider the following simple example with $m = 3$, $\ell = 2$, $\nu_2^1 = \nu_3^1 = \nu_2^2 = 1$ and $\nu_3^2 = 3$, and for which the equations of the z_2 - and z_3 -chains are:

$$\begin{aligned} \dot{z}_2^{1,1} &= w_1^1 + z_2^{2,1}u_1 & \dot{z}_3^{1,1} &= z_2^{1,1} + z_3^{2,1}u_1 \\ \dot{z}_2^{2,1} &= u_2 & \dot{z}_3^{2,q} &= \dot{z}_3^{2,q+1}, \quad q = 1, 2, \\ & & \dot{z}_3^{2,3} &= u_3. \end{aligned}$$

For this example, in addition to u_1 , also the control u_2 necessarily has to be differentiated in order to express all $z_3^{s,q}$ -states and control u_3 in terms of h and its derivatives. It follows that, in general, the differential weight of h is greater than $n + m + \mu$.

6.8 Proof of Theorem 4.3

Proof of (B1). The proof is given by the algorithm constructing the flat control system NF2 in Section 4.1.2.

Proof of (B2). Consider the system Σ , around x_0 , together with its output $h = (h_1(x), \dots, h_m(x))$ and suppose that there exist g_1, \dots, g_m such that the associated control system $\Sigma_c : \dot{x} = f(x) + \sum_{i=1}^m g_i(x)u_i$ is x -flat at x_0 with $\varphi = (h_1(x), \dots, h_m(x))$ an x -flat output, defined in a neighborhood of x_0 . Recall that $n - k = p(m - 1) + r$ is the Euclidean division of the observability defect $n - k$ and $m - 1$. We will show that the differential weight of $\varphi = (h_1(x), \dots, h_m(x))$ is at least $n + m + p^*$ (where $p^* = p$, if $r = 0$ and $p^* = p + 1$ otherwise). We denote by s_i the order of the highest derivative of $\varphi_i = h_i$, for $1 \leq i \leq m$, involved in the expression of x and u , i.e.,

$$x = \gamma(\bar{\varphi}_1^{s_1}, \dots, \bar{\varphi}_m^{s_m}) \text{ and } u = \delta(\bar{\varphi}_1^{s_1}, \dots, \bar{\varphi}_m^{s_m}),$$

where $\bar{\varphi}_i^j = (\varphi_i, \dot{\varphi}_i, \dots, \varphi_i^{(j)})$ and the differential weight of $\varphi = h$ equals $\sum_{i=1}^m (s_i + 1)$.

Let ν_i , for $1 \leq i \leq m$, be the relative degree of $\varphi_i = h_i$, that is, the smallest integer such that the derivative $h_i^{(\nu_i)}$ depends explicitly on the control u . We clearly have $\nu_i \geq 1$ (since all h_i depend on x only), the functions $L_f^{j-1}\varphi_i = L_f^{j-1}h_i$, for $1 \leq i \leq m$ and $1 \leq j \leq \nu_i$, are independent (as successive derivatives of flat outputs) and $dL_f^{j-1}h_i \in \mathcal{H}$, so $\dim \mathcal{H}(x) = k$ implies $\sum_{i=1}^m \nu_i \leq k$ (and, in particular, $\sum_{i=1}^m \nu_i < n$, since $k < n$). For $1 \leq i, j \leq m$, denote $\text{rk}(L_{g_j}L_f^{j-1}h_i)(x_0) = \text{rk}(D_{ij})(x_0) = d > 0$. We clearly have $d \leq m - 1$, otherwise the control system Σ_c would not be flat since $\sum_{i=1}^m \nu_i < n$. We first suppose that the rank d of the decoupling matrix $(D_{ij}(x))$ is constant around x_0 . By the definition of the relative degree, we introduce new coordinates $\tilde{w}_i^j = L_f^{j-1}\varphi_i = L_f^{j-1}h_i$, for $1 \leq i \leq m$ and $1 \leq j \leq \nu_i$, and let ξ be any coordinates completing the \tilde{w} -variables to a coordinate system and thus $\dim \xi \geq n - k$ (we use \tilde{w} , and not w because, in general $\nu_i \neq \rho_i$, where ρ_i 's are POQI's of (Σ, h)). By applying a suitable feedback transformation (permute the outputs h_i , if necessary), the system in the (\tilde{w}, ξ) -coordinates reads

$$\begin{aligned} \dot{\tilde{w}}_i^j &= \tilde{w}_i^{j+1}, \quad 1 \leq j \leq \nu_i - 1, & \dot{\tilde{w}}_i^{\nu_i} &= a_i(\tilde{w}, \xi, v_1, \dots, v_d), \quad d+1 \leq i \leq m, \\ \dot{\tilde{w}}_i^{\nu_i} &= v_i, \quad 1 \leq i \leq d, & \dot{\xi} &= G(\tilde{w}, \xi, v), \end{aligned}$$

for a smooth map G and smooth functions a_i , all of them affine with respect to the controls. By assumption, the above system is flat with $\varphi = (\tilde{w}_1^1, \dots, \tilde{w}_m^1)$ a flat output. We have $\tilde{w}_i^j = h_i^{(j-1)}$, for $1 \leq i \leq m$, $1 \leq j \leq \nu_i$, and $v_i = h_i^{(\nu_i)}$, for $1 \leq i \leq d$. Thus the remaining $n - \sum_{i=1}^m \nu_i$ states ξ_i and remaining $m - d$ controls v_{d+1}, \dots, v_m are expressed via $h_i^{(\nu_i+j)}$, for $d+1 \leq i \leq m$ and $0 \leq j \leq s_i - \nu_i$. This is possible only if $\sum_{i=d+1}^m (s_i - \nu_i + 1) \geq \dim \xi + m - d$ implying

$$\sum_{i=d+1}^m (s_i - \nu_i) \geq \dim \xi \geq n - k = p(m - 1) + r. \quad (29)$$

We claim that there exists $s_{i^*} - \nu_{i^*} \geq p^*$; if not, then $s_i - \nu_i < p^*$, for all $d+1 \leq i \leq m$, and in the case $r = 0$ (implying $p^* = p$), we have $\sum_{i=d+1}^m (s_i - \nu_i) < p(m - d) \leq p(m - 1)$, while in the case $r \neq 0$ (implying $p^* = p + 1$), we have $\sum_{i=d+1}^m (s_i - \nu_i) \leq p(m - d) \leq p(m - 1) < p(m - 1) + r$, which, in both cases, contradicts (29). Each $h_i^{(s_i)}$ depends on $s_i - \nu_i$ derivatives of at least one control among v_{d+1}, \dots, v_m , so $h_{i^*}^{(s_{i^*})}$ depends on at least p^* of them and the differential weight of $\varphi = (h_1(x), \dots, h_m(x))$ is at least $n + m + p^*$ around x_0 . The set of points around which the decoupling matrix $(D_{ij}(x))$ is of constant rank is open and dense in \mathbb{R}^n , so the differential weight of $\varphi = (h_1(x), \dots, h_m(x))$ is at least $n + m + p^*$ everywhere.

6.9 Proof of Theorem 4.4

Proof of (A1)'. By Lemma 4.1, (Σ, h) admits POQI's (ρ_1, \dots, ρ_m) on an open and dense subset \mathcal{X}^P of \mathbb{R}^n . Consider (Σ, h) around any point $x_0 \in \mathcal{X}^P$ and choose any z -coordinates $(z_{m'+1}^1, \dots, z_m^1)$, where $m' = m - r$, completing, around x_0 , the w -coordinates, given by (10) to a local coordinate system (recall that $n - k = r < m - 1$). Put $\psi_i^1 = z_i^1$, for $m' + 1 \leq i \leq m$. It is clear that the r -tuple of dummy outputs $\psi^1 = (\psi_{m'+1}^1, \dots, \psi_m^1)$ completes the original h to a new output $h^1 = (h, \psi^1)$ such that $(\rho_1, \dots, \rho_m, 1, \dots, 1)$ are OQI's of (Σ, h^1) at x_0 , so they also form COQI's of (Σ, h) at x_0 , see Definition 4.2 and the remark following it.

Proof of (A2)'. The proof is given by the (constructive) algorithm providing the construction of the flat control system NF3 associated to (Σ, h) in Section 4.2.1.

Proof of (B2)'. Repeat the proof of item (B2) of Theorem 4.3 for $p = 0$ and $r \neq 0$.

Acknowledgment

We would like to thank anonymous reviewers whose suggestions and remarks have substantially improved the final presentation of the paper.

References

- [1] J. BARBOT, M. FLIESS, AND T. FLOQUET, *An algebraic framework for the design of nonlinear observers with unknown inputs*, in Proc. IEEE CDC, 2007, pp. 384–389.
- [2] S. BINGULAC AND R. KRTOLICA, *On admissibility of pseudoobservability and pseudo-controllability indexes*, IEEE Trans. Automat. Control, 32 (1987), pp. 920–922.
- [3] B. DRAVIE, P. GUILLOT, AND G. MILLÉRIOUX, *Flatness and structural analysis as a constructive framework for private communication*, Nonlinear Analysis: Hybrid Systems, 30 (2018), pp. 92–105.
- [4] M. FLIESS, J. LÉVINE, P. MARTIN, AND P. ROUCHON, *Flatness and defect of nonlinear systems: introductory theory and examples*, Internat. J. Control, 61 (1995), pp. 1327–1361.
- [5] M. FLIESS, J. LÉVINE, P. MARTIN, AND P. ROUCHON, *A Lie-Bäcklund approach equivalence and flatness of nonlinear systems*, IEEE Trans. Automat. Control, 44 (1999), pp. 922–937.
- [6] K. FRITZSCHE AND K. RÖBENACK, *On the computation of differentially flat inputs*, in Proc. of the 22nd ICSTCC, IEEE, 2018, pp. 12–19.
- [7] J.-P. GAUTHIER, H. HAMMOURI, AND S. OTHMAN, *A simple observer for nonlinear systems with applications to bioreactors*, IEEE Trans. Automat. Control, 37 (1992), pp. 875–880.
- [8] K. GRAICHEN, V. HAGENMEYER, AND M. ZEITZ, *A new approach to inversion-based feedforward control design for nonlinear systems*, Automatica, 41 (2005), pp. 2033 – 2041.

- [9] H. HAMMOURI AND J. DE LEON MORALES, *Observer synthesis for state-affine systems*, in Proc. IEEE CDC, vol. 2, IEEE, 1990, pp. 784–785.
- [10] R. HERMANN AND A. J. KRENER, *Nonlinear controllability and observability*, IEEE Trans. Automat. Control, 22 (1977), pp. 728–740.
- [11] L. HUNT AND R. SU, *Linear equivalents of nonlinear time varying systems*, in Proc. MTNS, Santa Monica, CA, 1981, pp. 119–123.
- [12] A. ISIDORI, C. MOOG, AND A. DE LUCA, *A sufficient condition for full linearization via dynamic state feedback*, in Proc. IEEE CDC, vol. 25, IEEE, 1986, pp. 203–208.
- [13] B. JAKUBCZYK, *Invariants of dynamic feedback and free systems*, in Proc. ECC, 1993, pp. 1510–1513.
- [14] B. JAKUBCZYK AND W. RESPONDEK, *On linearization of control systems*, Bull. Acad. Polonaise Sci. Ser. Sci. Math., (1980), pp. 517–522.
- [15] A. KRENER AND W. RESPONDEK, *Nonlinear observers with linearizable error dynamics*, SIAM J. Control Optim., 23 (1985), pp. 197–216.
- [16] A. LEVANT, *Homogeneity approach to high-order sliding mode design*, Automatica, 41 (2005), pp. 823–830.
- [17] J. LÉVINE, *Analysis and Control of Nonlinear Systems: A Flatness-Based Approach*, Springer, 2009.
- [18] E. N. LORENZ, *Deterministic nonperiodic flow*, Journal of the Atmospheric Sciences, 20 (1963), pp. 130–141.
- [19] P. MARTIN, *Contribution à l'étude des systèmes différentiellement plats*, PhD thesis, l'Ecole Nationale Supérieure de Mines de Paris, 1992.
- [20] P. MARTIN, P. ROUCHON, AND R. MURRAY, *Flat systems, equivalence and trajectory generation*, CDS Technical Report, Caltech, (2003).
- [21] F. NICOLAU AND W. RESPONDEK, *Flatness of multi-input control-affine systems linearizable via one-fold prolongation*, SIAM J. Control Optim., 55 (2017), pp. 3171–3203.
- [22] F. NICOLAU, W. RESPONDEK, AND J. BARBOT, *Constructing flat inputs for two-output systems*, in Proc. MTNS, 2018, pp. 414–421.
- [23] F. NICOLAU, W. RESPONDEK, J. BARBOT, AND A. OUSLIMANI, *Secure communication with the help of flat inputs for chaotic systems*, IFAC-PapersOnLine, 51 (2018), pp. 109 – 114. 5th IFAC Conference on Analysis and Control of Chaotic Systems CHAOS 2018.
- [24] H. NIJMEIJER AND I. MAREELS, *An observer looks at synchronization*, IEEE Trans. Circuits Syst. I: Fundamental theory and Applications, 44 (1997), pp. 882–890.
- [25] L. M. PECORA AND T. L. CARROLL, *Synchronization in chaotic systems*, Physical review letters, 64 (1990), pp. 1196–1199.

- [26] J. POMET, *A differential geometric setting for dynamic equivalence and dynamic linearization*, Banach Center Publ., Vol. 32, (1995), pp. 319–339.
- [27] W. RESPONDEK, *Right and left invertibility of nonlinear control systems*, in Sussmann. Nonlinear controllability and optimal control, Routledge New York, 1990, pp. 133–176.
- [28] W. RESPONDEK, *Symmetries and minimal flat outputs of nonlinear control systems*, in New Trends in Nonlinear Dynamics and Control and their Applications, vol. LNCIS 295, Springer, 2003, pp. 65–86.
- [29] O. RÖSSLER, *An equation for continuous chaos*, Phys. Let. A, 57 (1976), pp. 397–398.
- [30] P. TAN, G. MILLÉRIOUX, AND J. DAAFOUZ, *Invertibility, flatness and identifiability of switched linear dynamical systems: an application to secure communications*, in 47th IEEE CDC'08, 2008, pp. 959–964.
- [31] S. WALDHERR AND M. ZEITZ, *Conditions for the existence of a flat input*, Internat. J. Control, 81 (2008), pp. 439–443.
- [32] S. WALDHERR AND M. ZEITZ, *Flat inputs in the mimo case*, IFAC Proceedings Volumes, 43 (2010), pp. 695–700.
- [33] X. XIA AND W. GAO, *Non-linear observer design by observer canonical forms*, Internat. J. Control, 47 (1988), pp. 1081–1100.
- [34] X. XIA AND W. GAO, *Nonlinear observer design by observer error linearization*, SIAM J. Control Optim., 27 (1989), pp. 199–216.