



HAL
open science

Feedback stabilization of parabolic systems with input delay

Imene A Djebour, Takéo Takahashi, Julie Valein

► **To cite this version:**

Imene A Djebour, Takéo Takahashi, Julie Valein. Feedback stabilization of parabolic systems with input delay. 2020. hal-02545562v1

HAL Id: hal-02545562

<https://hal.science/hal-02545562v1>

Preprint submitted on 17 Apr 2020 (v1), last revised 18 Jan 2022 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Feedback stabilization of parabolic systems with input delay

Imene Aicha Djebour¹, Takéo Takahashi¹, and Julie Valein¹

¹Université de Lorraine, CNRS, Inria, IECL, F-54000 Nancy

April 17, 2020

Abstract

This work is devoted to the stabilization of parabolic systems with a finite-dimensional control subjected to a constant delay. Our main result shows that the Fattorini-Hautus criterion yields the existence of such a feedback control, as in the case of stabilization without delay. The proof consists in splitting the system into a finite dimensional unstable part and a stable infinite-dimensional part and to apply the Artstein transformation on the finite-dimensional system to remove the delay in the control. Using our abstract result, we can prove new results for the stabilization of parabolic systems with constant delay: the N -dimensional linear convection-diffusion equation with $N \geq 1$ and the Oseen system. We end the article by showing that this theory can be used to stabilize nonlinear parabolic systems with input delay by proving the local feedback distributed stabilization of the Navier-Stokes system around a stationary state.

Keywords: stabilizability, delay control, parabolic systems, finite-dimensional control

2010 Mathematics Subject Classification 93B52, 93D15, 35Q30, 76D05, 93C20.

Contents

1	Introduction	1
2	Proof of Theorem 1.1	3
3	Feedback boundary stabilization of the convection-diffusion equation	8
4	Feedback distributed stabilization of the Oseen system	9
5	Local feedback distributed stabilization of the Navier-Stokes system	11

1 Introduction

Time delay phenomena appear in many applications, for instance in biology, mechanics, automatic control or engineering and are inevitable due to the time-lag between the measurements and their exploitation. For instance in control problems, one need to take into account the analysis time or the computation time. In the context of stability problems for partial differential equations with delay, it is classical that a small delay in the feedback mechanism can destabilize a system (see for instance [7, 6]). On the other hand, a delay term can also improve the performance of a system (see for instance [1]). These features appear for hyperbolic systems and here our aim is to consider the stabilization problems for a large class of parabolic systems with a particular delay input.

More precisely this article is devoted to the feedback stabilization of the system

$$z' = Az + Bv + f, \quad z(0) = z^0, \quad (1.1)$$

where A is the generator of an analytic semigroup $(e^{tA})_{t \geq 0}$ on a Hilbert space \mathbb{H} , where $B : \mathbb{U} \rightarrow \mathcal{D}(A^*)'$ is a linear operator on a Hilbert space \mathbb{U} and where f is a given source satisfying an exponential decay at infinity. Our aim is to obtain a feedback control $v(t)$ that depends on the values of $z(s)$ for $s \leq t - \tau$, where $\tau > 0$ is a positive constant corresponding to a delay. With such a feedback control, our aim is to obtain exponential stabilization of (1.1) if we assume that it is the case without delay. A characterization of the exponential stabilization of (1.1) in the case without delay is the well-known Fattorini-Hautus criterion (see [10], [11] and [3]):

$$\forall \varepsilon \in \mathcal{D}(A^*), \forall \lambda \in \mathbb{C}, \operatorname{Re} \lambda \geq -\sigma \quad A^* \varepsilon = \lambda \varepsilon \quad \text{and} \quad B^* \varepsilon = 0 \quad \implies \quad \varepsilon = 0. \quad (\text{UC}_\sigma)$$

Here and in what follows, we denote by $A^* : \mathcal{D}(A^*) \rightarrow \mathbb{H}$ and by $B^* : \mathcal{D}(A^*) \rightarrow \mathbb{U}$ the adjoint operators of A and B . This criterion is equivalent to the exponential stabilization of (1.1) with a rate larger than σ provided we assume the following hypotheses:

$$\begin{aligned} \text{The spectrum of } A \text{ consists of isolated eigenvalues } (\lambda_j) \text{ with finite algebraic multiplicity } N_j \\ \text{and there is no finite cluster point in } \{\lambda \in \mathbb{C} ; \operatorname{Re} \lambda \geq -\sigma\}, \end{aligned} \quad (\text{Hyp1})$$

$$B \in \mathcal{L}(\mathbb{U}, \mathbb{H}_{-\gamma}) \quad \text{for some } \gamma \in [0, 1). \quad (\text{Hyp2})$$

The spaces \mathbb{H}_α are defined as follows: we fix $\mu_0 \in \rho(A)$, then

$$\mathbb{H}_\alpha := \begin{cases} \mathcal{D}((\mu_0 - A)^\alpha) & \text{if } \alpha \geq 0 \\ \mathcal{D}((\mu_0 - A^*)^{-\alpha})' & \text{if } \alpha < 0 \end{cases} \quad \text{and} \quad \mathbb{H}_\alpha^* := \begin{cases} \mathcal{D}((\mu_0 - A^*)^\alpha) & \text{if } \alpha \geq 0 \\ \mathcal{D}((\mu_0 - A)^{-\alpha})' & \text{if } \alpha < 0. \end{cases} \quad (1.2)$$

To deal with the source f , we also assume the following hypothesis

$$\mathbb{H}_\alpha = [\mathbb{H}, \mathcal{D}(A)]_\alpha \quad (\alpha \in [0, 1]), \quad (\text{Hyp3})$$

where $[\cdot, \cdot]_\alpha$ denotes the complex interpolation method. We assume that

$$f_\sigma : t \mapsto e^{\sigma t} f(t) \in L^2(0, \infty; \mathbb{H}_{-\gamma'}) \quad \gamma' < 1/2. \quad (1.3)$$

We say that $f \in L^2_\sigma(0, \infty; \mathbb{H}_{-\gamma'})$ if $f_\sigma \in L^2(0, \infty; \mathbb{H}_{-\gamma'})$ and we write

$$\|f\|_{L^2_\sigma(0, \infty; \mathbb{H}_{-\gamma'})} = \|f_\sigma\|_{L^2(0, \infty; \mathbb{H}_{-\gamma'})}.$$

The same definition can be extended to spaces of the kind $L^p_\sigma(0, \infty; \mathbb{X})$, $C^0_\sigma([0, \infty); \mathbb{X})$, $H^m_\sigma(0, \infty; \mathbb{X})$, with \mathbb{X} a Banach space.

Note that a sufficient condition for (Hyp1) is that A has compact resolvent. For all λ_j eigenvalue of A , we define its geometric multiplicity

$$\ell_j := \dim \ker(A - \lambda_j \operatorname{Id}) \in \mathbb{N}^*.$$

We also define the maximum of the geometric multiplicities of the unstable modes:

$$N_+ := \max\{\ell_i, \operatorname{Re} \lambda_i \geq -\sigma\}. \quad (1.4)$$

Our main result is the following theorem:

Theorem 1.1. *Let us consider $\sigma > 0$ and let us assume (Hyp1), (Hyp2), (Hyp3) and (UC $_\sigma$). Then there exist $K \in L^\infty_{\text{loc}}(\mathbb{R}^2; \mathcal{L}(\mathbb{H}))$, $\zeta_k \in \mathcal{D}(A^*)$, $v_k \in B^*(\mathcal{D}(A^*))$, $k = 1, \dots, N_+$, such that if*

$$v(t) = \mathbb{1}_{[\tau, +\infty)}(t) \sum_{k=1}^{N_+} \left(z(t - \tau) + \int_0^{t-\tau} K(t - \tau, s) z(s) ds, \zeta_k \right)_{\mathbb{H}} v_k, \quad (1.5)$$

then for any $z^0 \in \mathbb{H}$, f satisfying (1.3), the solution z of (1.1) satisfies

$$\|z(t)\|_{\mathbb{H}} \leq C e^{-\sigma t} \left(\|z^0\|_{\mathbb{H}} + \|f\|_{L^2_\sigma(0, \infty; \mathbb{H}_{-\gamma, \tau})} \right) \quad (t > 0). \quad (1.6)$$

Assume moreover that $\gamma = 0$, $\gamma' = 0$ and that $z^0 \in \mathbb{H}_{1/2}$. Then,

$$z \in L^2_\sigma(0, \infty; \mathbb{H}_1) \cap C^0_\sigma([0, \infty); \mathbb{H}_{1/2}) \cap H^1_\sigma(0, \infty; \mathbb{H}),$$

and

$$\|z\|_{L^2_\sigma(0, \infty; \mathbb{H}_1) \cap C^0_\sigma([0, \infty); \mathbb{H}_{1/2}) \cap H^1_\sigma(0, \infty; \mathbb{H})} \leq C \left(\|z^0\|_{\mathbb{H}_{1/2}} + \|f\|_{L^2_\sigma(0, \infty; \mathbb{H})} \right). \quad (1.7)$$

Here and in all what follows, $\mathbb{1}_{\mathcal{O}}$ is the characteristic function of the set \mathcal{O} .

The above result shows that we can stabilize the above general class of linear parabolic systems with a finite number of controls and with a constant delay: the feedback control $v(t)$ at time t , given by (1.5), only depends on value of the state $z(s)$ for $s \leq t - \tau$. This result can be seen as a generalization of several recent results on the stabilization of parabolic systems with delay control, in particular [5] where the authors constructed a feedback control for finite dimensional linear systems, and [17] where the authors obtained a stabilizing feedback control of a one-dimensional reaction-diffusion equation with a boundary control subjected to a constant delay. Let us mention some ideas of their method that we adapt to prove our result: using that their operator is self-adjoint of compact resolvent they split the system into an unstable finite-dimensional part and a stable infinite-dimensional part. They are thus led to stabilize the finite-dimensional unstable system and to do this with a delay, they use the Artstein transformation and obtain an autonomous control system without delay satisfying the Kalman condition. Finally, by using an appropriate Lyapunov function, they prove that the feedback control designed in the finite-dimensional part actually stabilizes the whole system.

We can mention several articles in this direction: in [15], the authors consider the stabilization of a structurally damped Euler-Bernoulli beam. The corresponding system is parabolic but the main operator is no more self-adjoint. Then [14] generalizes the result of [17] in the case where the main operator is a Riesz spectral operator with simple eigenvalues. In [16] they manage to extend the result of [17] to the case where the control contains some disturbances and where the delay can depend on time.

Here our aim is to extend the result of [17] for a large class of parabolic systems, and in particular with the possibility to consider partial differential equations in dimension larger than one. We also precise the number of controls N_+ needed to stabilize the system by using the approach developed in [2] in the case of the Navier-Stokes system or in [3], for general linear and nonlinear parabolic systems. We present two important examples, that is the reaction-diffusion equation and the Oseen system and we end this paper to show that within this framework, we can also handle some nonlinear parabolic systems such as the Navier-Stokes system.

The present paper is organized as follows. In Section 2, the proof of Theorem 1.1 is given. As in [17], it relies on the decomposition of the system (1.1) into two parts: an unstable finite-dimensional part and an infinite-dimensional part. This decomposition is possible thanks to (Hyp1) and [13, Theorem 6.17, p.178]. Due to the presence of a constant delay, an equivalent autonomous control system is considered for the finite-dimensional part by means of the Artstein transformation. This system is exponentially stabilizable by using (UC_σ) . Using the inverse of the Artstein transform, a stabilizing feedback control is designed in the finite-dimensional space that stabilizes exponentially the finite-dimensional unstable system (with delay control). Finally, we prove that the designed feedback stabilizes exponentially the complete system. Thereafter, we illustrate our results by some precise examples: the case of the feedback stabilization of the N -dimensional linear convection-diffusion equation with $N \geq 1$ with delay boundary control in Section 3, the case of the feedback stabilization of the Oseen system with delay distributed control in Section 4 and finally, a local feedback distributed stabilization of the Navier-Stokes system around a stationary state in Section 5.

2 Proof of Theorem 1.1

Let us consider $\sigma > 0$. We first decompose the spectrum of A into the ‘‘unstable’’ modes and the ‘‘stable’’ modes:

$$\Sigma_+ := \{\lambda_j ; \operatorname{Re} \lambda_j \geq -\sigma\}, \quad \Sigma_- := \{\lambda_j ; \operatorname{Re} \lambda_j < -\sigma\}. \quad (2.1)$$

Using that $(e^{tA})_{t \geq 0}$ is an analytic semigroup (see [4, Theorem 2.11, p.112]) and (Hyp1), we see that Σ_+ is of finite cardinal.

Thus, we can introduce the projection operator (see [13, Thm. 6.17, p.178]) defined by

$$P_+ := \frac{1}{2\pi i} \int_{\Gamma_+} (\lambda - A)^{-1} d\lambda, \quad (2.2)$$

where Γ_+ is a contour enclosing Σ_+ but no other point of the spectrum of A . We can define

$$\mathbb{H}_+ := P_+ \mathbb{H}, \quad \mathbb{H}_- := (\text{Id} - P_+) \mathbb{H}.$$

From [13, Thm. 6.17, p.178], we have $\mathbb{H}_+ \oplus \mathbb{H}_- = \mathbb{H}$ and if we set

$$A_+ := A|_{\mathbb{H}_+} : \mathbb{H}_+ \rightarrow \mathbb{H}_+, \quad A_- := A|_{\mathbb{H}_-} : \mathcal{D}(A) \cap \mathbb{H}_- \rightarrow \mathbb{H}_-,$$

then the spectrum of A_+ (resp. A_-) is exactly Σ_+ (resp. Σ_-). By using the analyticity of $(e^{At})_{t \geq 0}$, (Hyp1) and (2.1), we deduce the existence of $\sigma_- > \sigma$ such that

$$\|e^{A-t}\|_{\mathcal{L}(\mathbb{H}_-)} \leq C e^{-\sigma-t}, \quad \|(\lambda_0 - A)^\gamma e^{A-t}\|_{\mathcal{L}(\mathbb{H}_-)} \leq C \frac{1}{t^\gamma} e^{-\sigma-t}. \quad (2.3)$$

We can proceed similarly for A^* : we write

$$P_+^* := \frac{1}{2\pi i} \int_{\Gamma_+} (\lambda - A^*)^{-1} d\lambda, \quad (2.4)$$

$$\mathbb{H}_+^* := P_+^* \mathbb{H}, \quad \mathbb{H}_-^* := (\text{Id} - P_+^*) \mathbb{H},$$

$$A_+^* := A|_{\mathbb{H}_+^*} : \mathbb{H}_+^* \rightarrow \mathbb{H}_+^*, \quad A_-^* := A|_{\mathbb{H}_-^*} : \mathcal{D}(A^*) \cap \mathbb{H}_-^* \rightarrow \mathbb{H}_-^*.$$

Note that P_+^* is the adjoint of P_+ . In particular, we see that if $z \in \mathbb{H}_-$ and $\zeta \in \mathbb{H}_+^*$, then

$$(z, \zeta)_{\mathbb{H}} = ((\text{Id} - P_+)z, \zeta)_{\mathbb{H}} = (z, (\text{Id} - P_+^*)\zeta)_{\mathbb{H}} = 0. \quad (2.5)$$

We also define

$$\mathbb{U}_+ := B^* \mathbb{H}_+^*, \quad \mathbb{U}_- := B^* \mathbb{H}_-^*,$$

and

$$p_+ : \mathbb{U} \rightarrow \mathbb{U}_+, \quad p_- : \mathbb{U} \rightarrow \mathbb{U}_-, \quad i_+ : \mathbb{U}_+ \rightarrow \mathbb{U}, \quad i_- : \mathbb{U}_- \rightarrow \mathbb{U},$$

the orthogonal projections and the inclusion maps. Then we write

$$B_+ := P_+ B i_+ \in \mathcal{L}(\mathbb{U}_+, \mathbb{H}_+), \quad B_- := (\text{Id} - P_+) B i_- \in \mathcal{L}(\mathbb{U}_-, \mathbb{H}_- \cap \mathbb{H}_{-\gamma}).$$

We have that

$$P_+ B = B_+ p_+ \quad (\text{Id} - P_+) B = B_- p_-.$$

Indeed, for any $w \in \mathcal{D}(A)$ and $v \in \mathbb{U}$ we can write

$$\langle P_+ B v, w \rangle_{\mathbb{H}_{-1}, \mathbb{H}_1} = \langle v, B^* P_+^* w \rangle_{\mathbb{U}} = \langle p_+ v, p_+ B^* P_+^* w \rangle_{\mathbb{U}} = \langle P_+ B i_+ p_+ v, w \rangle_{\mathbb{H}_{-1}, \mathbb{H}_1} = \langle B_+ p_+ v, w \rangle_{\mathbb{H}_{-1}, \mathbb{H}_1},$$

and we can prove similarly the other relation.

From the above notation, we can split (1.1) into the two equations (see [3, 19]).

$$z'_+ = A_+ z_+ + B_+ p_+ v + P_+ f, \quad z_+(0) = P_+ z^0, \quad (2.6)$$

$$z'_- = A_- z_- + B_- p_- v + (\text{Id} - P_+) f, \quad z_-(0) = (\text{Id} - P_+) z^0. \quad (2.7)$$

In order to study the stabilization of the finite-dimensional system (2.6), we use the Artstein transformation that allows us to pass from (2.6) in the case of a delay input to an autonomous system. More precisely, we consider

$$w(t) := z_+(t) + \int_t^{t+\tau} e^{(t-s)A_+} B_+ p_+ v(s) ds.$$

Then in what follows, we study the stabilization of the autonomous system satisfied by w (Lemma 2.1). Since the corresponding feedback is expressed with w , we also consider the inverse of the Artstein transformation and more precisely show the existence of a kernel K to write w in terms of z_+ (Lemma 2.2).

Lemma 2.1. *Assume (UC_σ) for $\sigma > 0$. Then, there exist $C > 0$ and $G \in \mathcal{L}(\mathbb{H}_+, \mathbb{U}_+)$, with $\text{rank } G \leq N_+$ where N_+ is defined by (1.4), such that for any $f \in L^2_\sigma(0, \infty; \mathbb{H}_{-\gamma'})$ and $w^0 \in \mathbb{H}_+$, the solution of*

$$\begin{cases} w' = A_+ w + e^{-\tau A_+} B_+ p_+ G w + P_+ f, \\ w(0) = w^0, \end{cases} \quad (2.8)$$

satisfies

$$\|w\|_{H^1_\sigma(0, \infty; \mathbb{H}_+)} \leq C (\|w^0\|_{\mathbb{H}_+} + \|P_+ f\|_{L^2_\sigma(0, \infty; \mathbb{H}_+)}). \quad (2.9)$$

Proof. Let us consider $\sigma_* > \sigma$. First we notice that $(A_+, e^{-\tau A_+} B_+ p_+)$ satisfies the Fattorini-Hautus test: assume

$$A_+^* \varepsilon = \bar{\lambda}_j \varepsilon, \quad B_+^* e^{-\tau A_+^*} \varepsilon = 0.$$

Then we deduce

$$A_+^* \varepsilon = \bar{\lambda}_j \varepsilon, \quad B_+^* e^{-\tau A_+^*} \varepsilon = e^{-\tau \bar{\lambda}_j} B_+^* P_+^* \varepsilon = e^{-\tau \bar{\lambda}_j} B^* \varepsilon = 0.$$

Thus from (UC_σ) , we deduce $\varepsilon = 0$. We can thus use the standard result of Fattorini or Hautus (see also [3, Theorem 1.6]) to deduce that there exists $G \in \mathcal{L}(\mathbb{H}_+, \mathbb{U}_+)$, with $\text{rank } G \leq N_+$ such that the solution of

$$\begin{cases} w' = A_+ w + e^{-\tau A_+} B_+ p_+ G w, \\ w(0) = w^0 \in \mathbb{H}_+, \end{cases} \quad (2.10)$$

satisfies

$$\|w(t)\|_{\mathbb{H}_+} \leq C e^{-\sigma_* t} \|w^0\|_{\mathbb{H}_+}, \quad t \geq 0. \quad (2.11)$$

Then we write the Duhamel formula for the solutions of (2.8)

$$w(t) = e^{A_* t} w^0 + \int_0^t e^{A_*(t-s)} P_+ f(s) ds,$$

with

$$A_* = A_+ + e^{-\tau A_+} B_+ p_+ G,$$

to deduce (2.9). □

Lemma 2.2. *There exists $K \in L^\infty_{\text{loc}}(\mathbb{R}^2; \mathcal{L}(\mathbb{H}_+))$ such that*

$$\begin{aligned} K(t, s) &= e^{(t-s-\tau)A_+} B_+ p_+ G \mathbb{1}_{(\max\{t-\tau, 0\}, t)}(s) \\ &\quad + \int_{\max\{t-\tau, s\}}^t e^{(t-\xi-\tau)A_+} B_+ p_+ G K(\xi, s) d\xi \quad (t > 0, s \in (0, t)). \end{aligned} \quad (2.12)$$

Proof. The proof relies on a fixed point argument. We set

$$K_0(t) := e^{(t-\tau)A_+} B_+ p_+ G, \quad K_0 \in L^\infty(0, \tau; \mathcal{L}(\mathbb{H}_+)),$$

so that (2.12) writes

$$K(t, s) = K_0(t - s)\mathbf{1}_{(\max\{t-\tau, 0\}, t)}(s) + \int_{\max\{t-\tau, s\}}^t K_0(t - \xi)K(\xi, s) d\xi.$$

Let $T > 0$, and let us define

$$D_T = \{(t, s) \in \mathbb{R}^2, \quad t \in (0, T), \quad s \in (0, t)\},$$

and

$$\begin{aligned} \Phi &: L^\infty(D_T; \mathcal{L}(\mathbb{H}_+)) \rightarrow L^\infty(D_T; \mathcal{L}(\mathbb{H}_+)), \\ (\Phi K)(t, s) &= \int_{\max\{t-\tau, s\}}^t K_0(t - \xi)K(\xi, s) d\xi \quad ((t, s) \in D_T). \end{aligned}$$

The mapping Φ is well-defined, and is a linear and bounded operator of $L^\infty(D_T; \mathcal{L}(\mathbb{H}_+))$. Moreover,

$$\|(\Phi K)(t, s)\|_{\mathcal{L}(\mathbb{H}_+)} \leq t \|K_0\|_{L^\infty(0, \tau; \mathcal{L}(\mathbb{H}_+))} \|K\|_{L^\infty(D_T; \mathcal{L}(\mathbb{H}_+))}.$$

This yields

$$\|(\Phi^2 K)(t, s)\|_{\mathcal{L}(\mathbb{H}_+)} \leq \frac{t^2}{2} \|K_0\|_{L^\infty(0, \tau; \mathcal{L}(\mathbb{H}_+))}^2 \|K\|_{L^\infty(D_T; \mathcal{L}(\mathbb{H}_+))},$$

and by induction

$$\|(\Phi^n K)(t, s)\|_{\mathcal{L}(\mathbb{H}_+)} \leq \frac{t^n}{n!} \|K_0\|_{L^\infty(0, \tau; \mathcal{L}(\mathbb{H}_+))}^n \|K\|_{L^\infty(D_T; \mathcal{L}(\mathbb{H}_+))} \quad (n \in \mathbb{N}^*).$$

In particular, for n large enough, Φ^n is a strict contraction and so is

$$(\tilde{\Phi} K)(t, s) := (\Phi K)(t, s) + K_0(t - s)\mathbf{1}_{(\max\{t-\tau, 0\}, t)}(s).$$

Thus, $\tilde{\Phi}$ admits a unique fixed point which is a solution of (2.12). □

We are now in a position to prove the main result

Proof of Theorem 1.1. We consider G and $K(t, s)$ obtained in Lemma 2.1 and Lemma 2.2, and we set

$$v(t) = \mathbf{1}_{[\tau, +\infty)}(t)G \left[z_+(t - \tau) + \int_0^{t-\tau} K(t - \tau, s)z_+(s) ds \right]. \quad (2.13)$$

Note that, we can write G as

$$G(\phi) = \sum_{k=1}^{N_+} (\phi, \zeta_k)_{\mathbb{H}} v_k, \quad (\phi \in \mathbb{H}_+)$$

with $\zeta_k \in \mathbb{H}_+^*$ and $v_k \in \mathbb{U}_+$, $k = 1, \dots, N_+$. We can take $\zeta_k \in \mathbb{H}_+^*$ due to a standard result in linear algebra: combining $\dim \mathbb{H}_+^* = \dim \mathcal{L}(\mathbb{H}_+, \mathbb{C})$ and (2.5), we can identify these two spaces. The interest to take $\zeta_k \in \mathbb{H}_+^*$ is that the above formula for G can be applied to $\phi \in \mathbb{H}$ and extend G as a linear bounded operator in \mathbb{H} satisfying $G = 0$ in \mathbb{H}_- (see (2.5)). Extending also the family K by $K(t, s) = 0$ in \mathbb{H}_- , we see that (2.13) can be written as (1.5).

Let us define

$$w(t) := z_+(t) + \int_0^t K(t, s)z_+(s) ds, \quad (2.14)$$

so that (2.6) can be written

$$\begin{cases} z'_+(t) = A_+ z_+(t) + B_+ p_+ \mathbf{1}_{[\tau, +\infty)}(t) G w(t - \tau) + P_+ f(t) & t > 0, \\ z_+(0) = P_+ z^0. \end{cases} \quad (2.15)$$

Then we use (2.12), (2.14) and the Fubini theorem to perform the following computation for $t > 0$:

$$\begin{aligned}
\int_t^{t+\tau} e^{(t-s)A_+} B_+ p_+ G w(s-\tau) \mathbb{1}_{[\tau, +\infty)}(s) ds &= \int_{\max\{t-\tau, 0\}}^t e^{(t-s-\tau)A_+} B_+ p_+ G w(s) ds \\
&= \int_{\max\{t-\tau, 0\}}^t e^{(t-s-\tau)A_+} B_+ p_+ G \left[z_+(s) + \int_0^s K(s, \xi) z_+(\xi) d\xi \right] ds \\
&= \int_0^t \left[\mathbb{1}_{(\max\{t-\tau, 0\}, t)}(s) e^{(t-s-\tau)A_+} B_+ p_+ G + \int_{\max\{t-\tau, s\}}^t e^{(t-\xi-\tau)A_+} B_+ p_+ G K(\xi, s) d\xi \right] z_+(s) ds \\
&= \int_0^t K(t, s) z_+(s) ds = w(t) - z_+(t). \quad (2.16)
\end{aligned}$$

Consequently,

$$w(t) = z_+(t) + \int_t^{t+\tau} e^{(t-s)A_+} B_+ p_+ G w(s-\tau) \mathbb{1}_{[\tau, +\infty)}(s) ds. \quad (2.17)$$

From (2.15), we deduce that w is solution of (2.8) with $w^0 = z_+(0)$. Thus w satisfies (2.9) and from (2.17),

$$\|z_+\|_{H_\sigma^1(0, \infty; \mathbb{H}_+)} \leq C (\|P_+ z^0\|_{\mathbb{H}_+} + \|P_+ f\|_{L_\sigma^2(0, \infty; \mathbb{H}_+)}). \quad (2.18)$$

This yields in particular that if $z^0 \in \mathbb{H}_{1/2}$ and if $f \in L_\sigma^2(0, \infty; \mathbb{H})$, then

$$\|z_+\|_{L_\sigma^2(0, \infty; \mathbb{H}_1) \cap C_\sigma^0([0, \infty); \mathbb{H}_{1/2}) \cap H_\sigma^1(0, \infty; \mathbb{H})} \leq C (\|z^0\|_{\mathbb{H}_{1/2}} + \|f\|_{L_\sigma^2(0, \infty; \mathbb{H})}). \quad (2.19)$$

Then, we can consider the solution of (2.7): for $t \geq \tau$,

$$\begin{aligned}
z_-(t) = e^{A-t} (\text{Id} - P_+) z^0 + \int_\tau^t (\lambda_0 - A)^\gamma e^{A-(t-s)} (\lambda_0 - A)^{-\gamma} B_- p_- G w(s-\tau) ds \\
+ \int_0^t e^{A-(t-s)} (\text{Id} - P_+) f(s) ds. \quad (2.20)
\end{aligned}$$

Using (2.3) and (2.9), we deduce that

$$\begin{aligned}
\|z_-(t)\|_{\mathbb{H}} \leq C e^{-\sigma t} \|z^0\|_{\mathbb{H}} + C e^{-\sigma t} \int_\tau^t \frac{1}{(t-s)^\gamma} e^{-(\sigma_- - \sigma)(t-s)} ds (\|P_+ z^0\|_{\mathbb{H}_+} + \|P_+ f\|_{L_\sigma^2(0, \infty; \mathbb{H}_+)}) \\
+ C e^{-\sigma t} \int_0^t \frac{1}{(t-s)^{\gamma'}} e^{-(\sigma_- - \sigma)(t-s)} \|e^{\sigma s} f(s)\|_{\mathbb{H}_{-\gamma'}} ds.
\end{aligned}$$

Using that $\sigma_- > \sigma$, $\gamma < 1$ and $\gamma' < 1/2$, we deduce from the above estimate that

$$\|z_-(t)\|_{\mathbb{H}_-} \leq C e^{-\sigma t} (\|z^0\|_{\mathbb{H}} + \|f\|_{L_\sigma^2(0, \infty; \mathbb{H}_{-\gamma'})}) \quad (t > 0).$$

Combing this with (2.18), we deduce (1.6).

Let us prove now (1.7). If $f \in L_\sigma^2(0, \infty; \mathbb{H})$, $B \in \mathcal{L}(\mathbb{U}, \mathbb{H})$ and if $z^0 \in \mathbb{H}_{1/2}$, then the first part remains unchanged, and we have (2.19) and

$$\|v\|_{L_\sigma^2(0, \infty; \mathbb{U})} \leq C (\|z^0\|_{\mathbb{H}_+} + \|f\|_{L_\sigma^2(0, \infty; \mathbb{H}_+)}). \quad (2.21)$$

Consequently,

$$B_- p_- v + (\text{Id} - P_+) f \in L_\sigma^2(0, \infty; \mathbb{H}_-), \quad (2.22)$$

and

$$z_-(0) = z^0 - P_+ z^0 \in \mathbb{H}_{1/2} \cap \mathbb{H}_-.$$

Using that A_- is the infinitesimal generator of an analytic semigroup of type smaller than $-\sigma$ (see, for instance [4, Proposition 2.9, p.120]), then

$$z_- \in L^2_\sigma(0, \infty; \mathbb{H}_1) \cap C^0_\sigma([0, \infty); \mathbb{H}_{1/2}) \cap H^1_\sigma(0, \infty; \mathbb{H}),$$

and from (2.21)

$$\begin{aligned} \|z_-\|_{L^2_\sigma(0, \infty; \mathbb{H}_1) \cap C^0_\sigma([0, \infty); \mathbb{H}_{1/2}) \cap H^1_\sigma(0, \infty; \mathbb{H})} &\leq C (\|z^0 - P_+ z^0\|_{\mathbb{H}_{1/2}} + \|B_- p - v\|_{L^2_\sigma(0, \infty; \mathbb{H})} + \|(\text{Id} - P_+)f\|_{L^2_\sigma(0, \infty; \mathbb{H})}) \\ &\leq C (\|z^0\|_{\mathbb{H}_{1/2}} + \|f\|_{L^2_\sigma(0, \infty; \mathbb{H})}). \end{aligned}$$

Combining this with (2.19), we deduce (1.7). \square

3 Feedback boundary stabilization of the convection-diffusion equation

Let $\Omega \subset \mathbb{R}^N$ ($N \geq 1$) be a bounded domain of class $C^{1,1}$. In this section, we apply Theorem 1.1 for the stabilization of the convection-diffusion equation. Let us consider Γ a non-empty open subset of $\partial\Omega$ and the control problem:

$$\begin{cases} \partial_t z - \Delta z - b \cdot \nabla z - cz = 0 & \text{in } (0, \infty) \times \Omega, \\ z = v & \text{on } (0, \infty) \times \Gamma, \\ z = 0 & \text{on } (0, \infty) \times (\partial\Omega \setminus \Gamma), \\ z(0, \cdot) = z^0 & \text{in } \Omega, \end{cases} \quad (3.1)$$

where $c, b, \text{div } b \in L^\infty(\Omega)$. In order to write (3.1) under the form (1.1), we introduce the following functional setting:

$$\begin{aligned} \mathbb{H} &= L^2(\Omega), \quad \mathbb{U} = L^2(\Gamma), \\ Az &= \Delta z + b \cdot \nabla z + cz, \quad \mathcal{D}(A) = H^2(\Omega) \cap H^1_0(\Omega). \end{aligned}$$

From standard results on this operator A (see for example [8, Theorem 5, p.305]), we see that (Hyp1) holds true. To define the control operator B , we use a standard method (see, for instance [20, pp.341-343] or [18]): we first consider the lifting operator $D_0 \in \mathcal{L}(L^2(\partial\Omega); L^2(\Omega))$ such that for any $v \in L^2(\partial\Omega)$, $w = D_0 v$ is the unique solution of the following system

$$\begin{cases} \lambda_0 w - \Delta w - b \cdot \nabla w - cw = 0 & \text{in } \Omega, \\ w = v & \text{on } \partial\Omega, \end{cases}$$

where $\lambda_0 \in \rho(A)$. Then, we set

$$B = (\lambda_0 - A)D_0 : \mathbb{U} \longrightarrow (\mathcal{D}(A^*))',$$

where we have extended the operator A as an operator from $L^2(\Omega)$ into $(\mathcal{D}(A^*))'$ and where we see \mathbb{U} as a closed subspace of $L^2(\partial\Omega)$ (by extending by zero in $\partial\Omega \setminus \Gamma$ any $v \in \mathbb{U}$). Using standard results on elliptic equations, we have that B satisfies (Hyp2) for any $\gamma > 3/4$.

Let us recall how we can see that with A and B defined as above (3.1) writes as (1.1). We set $\tilde{z} = z - w$, with $w = D_0 v$. Then \tilde{z} satisfies the system

$$\begin{cases} \partial_t \tilde{z} - \Delta \tilde{z} - b \cdot \nabla \tilde{z} - c\tilde{z} = -\partial_t w + \lambda_0 w & \text{in } (0, \infty) \times \Omega, \\ \tilde{z} = 0 & \text{on } (0, \infty) \times \partial\Omega, \\ \tilde{z}(0, \cdot) = \tilde{z}^0 := z^0 - w(0, \cdot) & \text{in } \Omega. \end{cases}$$

Using the Duhamel formula, we have

$$\tilde{z}(t) = e^{tA} \tilde{z}^0 + \int_0^t e^{(t-s)A} (-\partial_t w(s) + \lambda_0 w(s)) ds.$$

By integrating by parts, we obtain

$$z(t) = e^{tA} z^0 + \int_0^t e^{(t-s)A} (\lambda_0 - A) w(s) ds,$$

that is

$$\begin{cases} z' = Az + (\lambda_0 - A) D_0 v, \\ z(0) = z^0. \end{cases}$$

To apply Theorem 1.1, we only need to check (UC_σ) . We recall that

$$\mathcal{D}(A^*) = H^2(\Omega) \cap H_0^1(\Omega), \quad A^* \varepsilon = \Delta \varepsilon - \bar{b} \cdot \nabla \varepsilon + (\overline{c - \operatorname{div} b}) \varepsilon,$$

(see, for instance, [20, p.345]). Moreover, by classical results (see [20, Proposition 10.6.7]), we see that

$$D_0^* := -\frac{\partial}{\partial \nu} (\lambda_0 - A^*)^{-1},$$

and thus

$$B^* \varepsilon := -\frac{\partial \varepsilon}{\partial \nu} \Big|_\Gamma.$$

Thus if ε satisfies $A^* \varepsilon = \lambda \varepsilon$ and $B^* \varepsilon = 0$, then

$$\begin{cases} \lambda \varepsilon - \Delta \varepsilon + \bar{b} \cdot \nabla \varepsilon - (\overline{c - \operatorname{div} b}) \varepsilon = 0 & \text{in } \Omega, \\ \varepsilon = 0 & \text{on } \partial \Omega, \\ \frac{\partial \varepsilon}{\partial \nu} = 0 & \text{on } \Gamma. \end{cases}$$

From standard results on the unique continuation of the Laplace operator (see for instance [12, Theorem 5.3.1, p.125]), we deduce that $\varepsilon = 0$. Thus (UC_σ) holds for any σ and we deduce the following result by applying Theorem 1.1:

Theorem 3.1. *Assume $\sigma > 0$ and let us define N_+ by (1.4). Then there exist $K \in L_{\text{loc}}^\infty(\mathbb{R}^2; \mathcal{L}(L^2(\Omega)))$, $\zeta_k \in H^2(\Omega) \cap H_0^1(\Omega)$, $v_k \in H^{1/2}(\Gamma)$, $k = 1, \dots, N_+$, such that the solution z of (3.1) with*

$$v(t) = \mathbf{1}_{[\tau, +\infty)}(t) \sum_{k=1}^{N_+} \left(\int_\Omega \left[z(t-\tau) + \int_0^{t-\tau} K(t-\tau, s) z(s) ds \right] \zeta_k dx \right) v_k, \quad (3.2)$$

and for $z^0 \in L^2(\Omega)$ satisfies

$$\|z(t)\|_{L^2(\Omega)} \leq C e^{-\sigma t} \|z^0\|_{L^2(\Omega)}. \quad (3.3)$$

4 Feedback distributed stabilization of the Oseen system

Let $\Omega \subset \mathbb{R}^3$ be a bounded domain of class $C^{1,1}$. In this section, we apply Theorem 1.1 to the Oseen system:

$$\begin{cases} \partial_t z + (w^S \cdot \nabla) z + (z \cdot \nabla) w^S - \nu \Delta z + \nabla q = \mathbf{1}_\mathcal{O} v & \text{in } (0, \infty) \times \Omega, \\ \nabla \cdot z = 0 & \text{in } (0, \infty) \times \Omega, \\ z = 0 & \text{on } (0, \infty) \times \partial \Omega, \\ z(0, \cdot) = z^0 & \text{in } \Omega, \end{cases} \quad (4.1)$$

where $w^S \in [H^2(\Omega)]^3$ is a fixed (real) velocity and v is the control that acts on the nonempty open subset $\mathcal{O} \subset \Omega$. We could also consider the boundary stabilization of the Oseen system by using the same method as in the above section but with some adaptations due the incompressibility condition and due to the pressure (see [2] for more details).

Let us give the functional setting:

$$\mathbb{H} = \{z \in [L^2(\Omega)]^3, \quad \nabla \cdot z = 0 \text{ in } \Omega, \quad z \cdot n = 0 \text{ on } \partial\Omega\}, \quad \mathbb{U} = [L^2(\mathcal{O})]^3.$$

We denote by \mathbb{P} the orthogonal projection $\mathbb{P} : [L^2(\Omega)]^3 \rightarrow \mathbb{H}$ and we define the Oseen operator:

$$\mathcal{D}(A) = [H^2(\Omega) \cap H_0^1(\Omega)]^3 \cap \mathbb{H}, \quad Az = \mathbb{P}(\nu \Delta z - (w^S \cdot \nabla)z - (z \cdot \nabla)w^S).$$

We recall (see, for instance [2, Theorem 20]) that the operator A is the infinitesimal generator of an analytic semigroup on \mathbb{H} and has a compact resolvent. Moreover,

$$\mathcal{D}(A^*) = [H^2(\Omega) \cap H_0^1(\Omega)]^3 \cap \mathbb{H}, \quad A^* \varepsilon = \mathbb{P}(\nu \Delta \varepsilon + (w^S \cdot \nabla)\varepsilon - (\nabla w^S)^* \varepsilon).$$

We also define the control operator $B \in \mathcal{L}(\mathbb{U}, \mathbb{H})$ by

$$Bv = \mathbb{P}(\mathbf{1}_{\mathcal{O}}v),$$

and we can check that

$$B^* \varepsilon = \varepsilon|_{\mathcal{O}}.$$

In particular, we see that (Hyp1) and (Hyp2) hold true and if ε satisfies $A^* \varepsilon = \lambda \varepsilon$ and $B^* \varepsilon = 0$, then

$$\begin{cases} \lambda \varepsilon - \nu \Delta \varepsilon - (w^S \cdot \nabla)\varepsilon + (\nabla w^S)^* \varepsilon + \nabla \pi = 0 & \text{in } \Omega, \\ \nabla \cdot \varepsilon = 0 & \text{in } \Omega, \\ \varepsilon = 0 & \text{on } \partial\Omega, \\ \varepsilon \equiv 0 & \text{in } \mathcal{O}. \end{cases}$$

Then using [9], we deduce that $\varepsilon = 0$. Thus (UC $_{\sigma}$) holds for any σ and we deduce the following result by applying Theorem 1.1:

Theorem 4.1. *Assume $\sigma > 0$ and let us define N_+ by (1.4). Then there exist $K \in L_{\text{loc}}^{\infty}(\mathbb{R}^2; \mathcal{L}(\mathbb{H}))$, $\zeta_k \in \mathcal{D}(A^*)$, $v_k \in [L^2(\mathcal{O})]^3$, $k = 1, \dots, N_+$, such that the solution z of (4.1) with*

$$v(t) = \mathbf{1}_{[\tau, +\infty)}(t) \sum_{k=1}^{N_+} \left(\int_{\Omega} \left[z(t-\tau) + \int_0^{t-\tau} K(t-\tau, s)z(s) ds \right] \zeta_k dx \right) v_k, \quad (4.2)$$

and for $z^0 \in \mathbb{H}$ satisfies

$$\|z(t)\|_{[L^2(\Omega)]^3} \leq C e^{-\sigma t} \|z^0\|_{[L^2(\Omega)]^3}. \quad (4.3)$$

Let us define

$$\mathbb{V} = [H_0^1(\Omega)]^3 \cap \mathbb{H}, \quad (4.4)$$

then we have that $\mathbb{V} = \mathbb{H}_{1/2}$ (see again [2, Theorem 20]). Thus applying Theorem 1.1, we have also the following result on

$$\begin{cases} \partial_t z + (w^S \cdot \nabla)z + (z \cdot \nabla)w^S - \nu \Delta z + \nabla q = \mathbf{1}_{\mathcal{O}}v + f & \text{in } (0, \infty) \times \Omega, \\ \nabla \cdot z = 0 & \text{in } (0, \infty) \times \Omega, \\ z = 0 & \text{on } (0, \infty) \times \partial\Omega, \\ z(0, \cdot) = z^0 & \text{in } \Omega. \end{cases} \quad (4.5)$$

Theorem 4.2. *Assume $\sigma > 0$ and let us consider v given by (4.2). Then for any $z^0 \in \mathbb{V}$ and for any $f \in L_{\sigma}^2(0, \infty; \mathbb{H})$ the solution of (4.5) satisfies*

$$z \in L_{\sigma}^2(0, \infty; [H^2(\Omega)]^3) \cap C_{\sigma}^0([0, \infty); [H^1(\Omega)]^3) \cap H_{\sigma}^1(0, \infty; [L^2(\Omega)]^3),$$

and

$$\|z\|_{L_{\sigma}^2(0, \infty; [H^2(\Omega)]^3) \cap C_{\sigma}^0([0, \infty); [H^1(\Omega)]^3) \cap H_{\sigma}^1(0, \infty; [L^2(\Omega)]^3)} \leq C (\|z^0\|_{[H^1(\Omega)]^3} + \|f\|_{L_{\sigma}^2(0, \infty; [L^2(\Omega)]^3)}). \quad (4.6)$$

5 Local feedback distributed stabilization of the Navier-Stokes system

We use the same notation as in the previous section. We consider the stabilization of the Navier-Stokes system with internal control:

$$\begin{cases} \partial_t \tilde{z} + (\tilde{z} \cdot \nabla) \tilde{z} - \nu \Delta \tilde{z} + \nabla \tilde{q} = \mathbb{1}_{\mathcal{O}} v + f^S & \text{in } (0, \infty) \times \Omega, \\ \nabla \cdot \tilde{z} = 0 & \text{in } (0, \infty) \times \Omega, \\ \tilde{z} = b^S & \text{on } (0, \infty) \times \partial\Omega, \\ \tilde{z}(0, \cdot) = \tilde{z}^0 & \text{in } \Omega, \end{cases} \quad (5.1)$$

around the stationary state

$$\begin{cases} (w^S \cdot \nabla) w^S - \nu \Delta w^S + \nabla r^S = f^S & \text{in } \Omega, \\ \nabla \cdot w^S = 0 & \text{in } \Omega, \\ w^S = b^S & \text{on } \partial\Omega. \end{cases} \quad (5.2)$$

We assume that (w^S, r^S) is a solution of (5.2) such that $w^S \in [H^2(\Omega)]^3$ as in the previous section. The functions $f^S \in [L^2(\Omega)]^3$ and $b^S \in [W^{3/2}(\partial\Omega)]^3$ are independent of time.

We define

$$z = \tilde{z} - w^S, \quad q = \tilde{q} - r^S, \quad z^0 = \tilde{z}^0 - w^S,$$

so that

$$\begin{cases} \partial_t z + (w^S \cdot \nabla) z + (z \cdot \nabla) w^S - \nu \Delta z + \nabla q = \mathbb{1}_{\mathcal{O}} v - (z \cdot \nabla) z & \text{in } (0, \infty) \times \Omega, \\ \nabla \cdot z = 0 & \text{in } (0, \infty) \times \Omega, \\ z = 0 & \text{on } (0, \infty) \times \partial\Omega, \\ z(0, \cdot) = z^0 & \text{in } \Omega. \end{cases} \quad (5.3)$$

Then we consider the following mapping

$$\mathcal{Z} : L^2_\sigma(0, \infty; [L^2(\Omega)]^3) \rightarrow L^2_\sigma(0, \infty; [L^2(\Omega)]^3), \quad f \mapsto -(z \cdot \nabla) z,$$

where z is the solution given in Theorem 4.2, associated with $z^0 \in \mathbb{V}$ and $f \in L^2_\sigma(0, \infty; \mathbb{H})$. Then by standard Sobolev embeddings, we find

$$\|z^1 \cdot \nabla z^2\|_{L^2_\sigma(0, \infty; [L^2(\Omega)]^3)} \leq C \|z^1\|_{C^0_\sigma([0, \infty); [H^1(\Omega)]^3)} \|z^2\|_{L^2_\sigma(0, \infty; [H^2(\Omega)]^3)}. \quad (5.4)$$

Thus \mathcal{Z} is well-defined. Let us set

$$R = \|z^0\|_{[H^1(\Omega)]^3},$$

and

$$B_R = \{f \in L^2_\sigma(0, \infty; [L^2(\Omega)]^3) ; \|f\|_{L^2_\sigma(0, \infty; [L^2(\Omega)]^3)} \leq R\}.$$

Then from (5.4) and (4.6),

$$\|\mathcal{Z}(f)\|_{L^2_\sigma(0, \infty; [L^2(\Omega)]^3)} \leq 4CR^2,$$

and B_R is invariant by \mathcal{Z} for R small enough. Similarly, using (5.4) and (4.6), for any $f^1, f^2 \in B_R$, then

$$\|\mathcal{Z}(f^1) - \mathcal{Z}(f^2)\|_{L^2_\sigma(0, \infty; [L^2(\Omega)]^3)} \leq 2CR \|f^1 - f^2\|_{L^2_\sigma(0, \infty; [L^2(\Omega)]^3)},$$

and thus \mathcal{Z} is a strict contraction on B_R for R small enough. We thus deduce that \mathcal{Z} admits a fixed point f for $\|z^0\|_{[H^1(\Omega)]^3}$ small enough and we notice that the solution z given in Theorem 4.2, associated with $z^0 \in \mathbb{V}$ and $f \in L^2_\sigma(0, \infty; [L^2(\Omega)]^3)$ is a solution of (5.3).

We have obtained the following local stabilization result for the Navier-Stokes system with internal control with delay:

Theorem 5.1. Assume $\sigma > 0$ and let us define N_+ by (1.4). Then there exist $K \in L_{\text{loc}}^\infty(\mathbb{R}^2; \mathcal{L}(\mathbb{H}))$, $\zeta_k \in \mathcal{D}(A^*)$, $v_k \in [L^2(\mathcal{O})]^3$, $k = 1, \dots, N_+$ and $R > 0$, such that for any

$$\tilde{z}^0 \in [H^1(\Omega)]^3, \quad \nabla \cdot \tilde{z}^0 = 0 \quad \text{in } \Omega, \quad \tilde{z}^0 = b^S \quad \text{on } \partial\Omega,$$

and

$$\|\tilde{z}^0 - w^S\|_{[H^1(\Omega)]^3} \leq R,$$

there exists a unique solution z of (5.1) with

$$v(t) = \mathbb{1}_{[\tau, +\infty)}(t) \sum_{k=1}^{N_+} \left(\int_{\Omega} \left[(\tilde{z} - w^S)(t - \tau) + \int_0^{t-\tau} K(t - \tau, s)(\tilde{z} - w^S)(s) ds \right] \zeta_k dx \right) v_k, \quad (5.5)$$

satisfying

$$\tilde{z} - w^S \in L_\sigma^2(0, \infty; [H^2(\Omega)]^3) \cap C_\sigma^0([0, \infty); [H^1(\Omega)]^3) \cap H_\sigma^1(0, \infty; [L^2(\Omega)]^3).$$

Moreover we have the estimate

$$\|\tilde{z} - w^S\|_{L_\sigma^2(0, \infty; [H^2(\Omega)]^3) \cap C_\sigma^0([0, \infty); [H^1(\Omega)]^3) \cap H_\sigma^1(0, \infty; [L^2(\Omega)]^3)} \leq C \|\tilde{z}^0 - w^S\|_{[H^1(\Omega)]^3}. \quad (5.6)$$

Acknowledgments.

The two first authors were partially supported by the ANR research project IFSMACS (ANR-15-CE40-0010). The third author was partially supported by the ANR research projects ISDEEC (ANR-16-CE40-0013) and ANR ODISSE (ANR-19-CE48-0004-01).

References

- [1] Chaouki Abdallah, Peter Dorato, J. Benites-Read, and R. Byrne. Delayed positive feedback can stabilize oscillatory systems. In *1993 American Control Conference*, pages 3106–3107. IEEE, 1993.
- [2] Mehdi Badra and Takéo Takahashi. Stabilization of parabolic nonlinear systems with finite dimensional feedback or dynamical controllers: application to the Navier-Stokes system. *SIAM J. Control Optim.*, 49(2):420–463, 2011.
- [3] Mehdi Badra and Takéo Takahashi. On the Fattorini criterion for approximate controllability and stabilizability of parabolic systems. *ESAIM Control Optim. Calc. Var.*, 20(3):924–956, 2014.
- [4] Alain Bensoussan, Giuseppe Da Prato, Michel C. Delfour, and Sanjoy K. Mitter. *Representation and control of infinite dimensional systems*. Systems & Control: Foundations & Applications. Birkhäuser Boston, Inc., Boston, MA, second edition, 2007.
- [5] Delphine Bresch-Pietri, Christophe Prieur, and Emmanuel Trélat. New formulation of predictors for finite-dimensional linear control systems with input delay. *Systems Control Lett.*, 113:9–16, 2018.
- [6] Richard Datko. Not all feedback stabilized hyperbolic systems are robust with respect to small time delays in their feedbacks. *SIAM J. Control Optim.*, 26(3):697–713, 1988.
- [7] Richard Datko, John Lagnese, and Michael P. Polis. An example on the effect of time delays in boundary feedback stabilization of wave equations. *SIAM J. Control Optim.*, 24(1):152–156, 1986.
- [8] Lawrence C. Evans. *Partial differential equations*, volume 19 of *Graduate Studies in Mathematics*. American Mathematical Society, Providence, RI, 1998.

- [9] Caroline Fabre and Gilles Lebeau. Prolongement unique des solutions de l'équation de Stokes. *Comm. Partial Differential Equations*, 21(3-4):573–596, 1996.
- [10] Hector O. Fattorini. Some remarks on complete controllability. *SIAM J. Control*, 4:686–694, 1966.
- [11] Matheus L. J. Hautus. Controllability and observability conditions of linear autonomous systems. *Nederl. Akad. Wetensch. Proc. Ser. Indag. Math.*, 72(5):443–448, 1969.
- [12] Lars Hörmander. *Linear partial differential operators*. Springer Verlag, Berlin-New York, 1976.
- [13] Tosio Kato. *Perturbation theory for linear operators*. Die Grundlehren der mathematischen Wissenschaften, Band 132. Springer-Verlag New York, Inc., New York, 1966.
- [14] Hugo Lhachemi and Christophe Prieur. Feedback stabilization of a class of diagonal infinite-dimensional systems with delay boundary control. *IEEE Transactions on Automatic Control*, PP:1–1, 02 2020.
- [15] Hugo Lhachemi and Robert Shorten. Boundary input-to-state stabilization of a damped Euler-Bernoulli beam in the presence of a state-delay. <https://arxiv.org/pdf/1912.01117.pdf>, 2019.
- [16] Hugo Lhachemi, Robert Shorten, and Christophe Prieur. Exponential input-to-state stabilization of a class of diagonal boundary control systems with delay boundary control. *Systems & Control Letters*, 138:104651, Apr 2020.
- [17] Christophe Prieur and Emmanuel Trélat. Feedback stabilization of a 1-D linear reaction-diffusion equation with delay boundary control. *IEEE Trans. Automat. Control*, 64(4):1415–1425, 2019.
- [18] Jean-Pierre Raymond. Stokes and Navier-Stokes equations with a nonhomogeneous divergence condition. *Discrete Contin. Dyn. Syst. Ser. B*, 14(4):1537–1564, 2010.
- [19] Jean-Pierre Raymond and Laetitia Thevenet. Boundary feedback stabilization of the two dimensional Navier-Stokes equations with finite dimensional controllers. *Discrete Contin. Dyn. Syst.*, 27(3):1159–1187, 2010.
- [20] Marius Tucsnak and George Weiss. *Observation and control for operator semigroups*. Birkhäuser Advanced Texts: Basler Lehrbücher. [Birkhäuser Advanced Texts: Basel Textbooks]. Birkhäuser Verlag, Basel, 2009.