



**HAL**  
open science

## Replicability and portability of an advanced grid-forming VSG control for electrical grid with high rate of renewable energies

Audrey Moulichon, Mazen Alamir, Lauric Garbuio, Vincent Debusschere, Mustapha Amine Rahmani, Cedric Boudinet, William Norris, Nouredine Hadjsaid

### ► To cite this version:

Audrey Moulichon, Mazen Alamir, Lauric Garbuio, Vincent Debusschere, Mustapha Amine Rahmani, et al.. Replicability and portability of an advanced grid-forming VSG control for electrical grid with high rate of renewable energies. CIRED 2021-26th International Conference & Exhibition on Electricity Distribution, Sep 2021, Genève, Switzerland. hal-03368921

**HAL Id: hal-03368921**

**<https://hal.science/hal-03368921>**

Submitted on 7 Oct 2021

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Replicability and portability of an advanced grid-forming VSG control for electrical grid with high rate of renewable energies

*Audrey Moulichon<sup>1,2,3\*</sup>, Mazen Alamir<sup>2</sup>, Lauric Garbuio<sup>1</sup>, Vincent Debusschere<sup>1</sup>, Mustapha Amine Rahmani<sup>3</sup>, Cedric Boudinet<sup>1</sup>, William Norris<sup>1</sup> and Nouredine Hadjsaid<sup>1</sup>*

<sup>1</sup>Univ. Grenoble Alpes, CNRS, Grenoble INP, G2ELab, F-38000 Grenoble, France

<sup>2</sup>Univ. Grenoble Alpes, CNRS, Grenoble INP, Gipsa-lab, F-38000 Grenoble, France

<sup>3</sup>Schneider Electric Industries, Power Conversion department, 38000 Grenoble, France

\* [audrey.moulichon@grenoble-inp.fr](mailto:audrey.moulichon@grenoble-inp.fr)

**Keywords:** GRID FORMING INVERTERS, VIRTUAL SYNCHRONOUS GENERATOR, POWER GENERATION, RENEWABLE ENERGIES

## Abstract

The objective of his paper is to present a replicability and portability methodology of a virtual synchronous generator (VSG) to facilitate its development in an industrial context. This solution is designed to improve the electrical grid stability when facing a high penetration rate of renewable energies. In order to validate both the methodology and the portability of the proposed model, the VSG-based inverter is tested at different scales of inverters. The solutions are integrated in experimental grid for validation: at the Schneider Electric microgrid Lab facility as well in a simple microgrid, a laboratory-scale prototype system available at the G2ELab, France.

## 1 Introduction

Microgrids have received substantial attention as possible relevant solutions for the integration of renewable energy sources (RES), for allowing the energy access to remote locations and ensuring a potential increase of the system resiliency and reliability. Indeed, in recent years, the traditional distributed energy resources (DER) supplying energy to microgrids (usually diesel generator-sets) are supplanted by supplier based on RES. However, their intermittency leads to major stability issues, notably because these sources usually decrease the available inertia of already weak grids [5]. Hence, the traditional control strategies for inverters, interfacing the various DERs connected to the microgrid, needs adapting.

Hence, in order to increase the participation of renewable energy to the microgrid stability, the development of advanced inverter controller have been the centre of attention of recent research. The virtual synchronous generator (VSG) is a popular solution to increase the microgrid inertia, which is easily integrated thanks to its similarity with the well-known synchronous machines (SM) [13, 14]. Various projects have demonstrated and validated the advantages of VSG to better accept renewable DERs in microgrids [6, 15].

Different studies have been conducted to improve the performances of VSGs in microgrids. Those studies concerned the mode of reference of SM [16–18] or the controller, but few have tried improving the development of VSG considering an industrial context. Hence, to shift VSG from proof of concept to actual industrial inverter-based solution for microgrids,

it is necessary to simplify the integration of the controller in industrial inverters.

To that regard, a methodology is described in this paper to ease the development of VSG controller, under the technical constraints of the inverter characteristics. Indeed, two problems can be identified in this context: the reference SM model is not adapted and/or the entire VSG controller has to be redesign depending of the voltage or current nominal values. Based on the proposed controller in [7], built in p.u., a methodology is first developed to ensure the adaptation of the SM model to the inverter characteristics adapting its performances to the inverter's capability. Then, in a second part, the methodology is performed and integrated in an inverter and tested to ensure the reliability and the portability of the proposed method.

## 2 Methodology

The objective of the proposed methodology is to select the most adapted SM model to implement as a reference for the VSG solution in a controller [7], based on the inverter's characteristics, to ensure the replicability and portability of the VSG solution for different inverter characteristics. The generality of the implementation is one of its clear added values.

The second objective of this methodology is to ensure that the SM reference is still similar to a real SM, maintaining the principal characteristics of a VSG to operate as a SM solution. Hence, when possible, the designed SM model is based on real SM characteristics and only adapted to the inverter characteristics.

Different SM models were studied to be considered as reference, a complete [19], a reduced [22] or a static/simple one [8]. To ensure that the methodology can be applied to any VSG solution, we have chosen the most complete SM model with the highest number of parameters (worse case scenario).

### 2.1 Inverter characteristics

The inverter's characteristics used in the proposed methodology to determine the SM reference are:

- The maximal inverter currents,  $I_{ond}^{max}$  (A);
- The PWM switching frequency,  $f_{IGBT}$  (Hz);
- The inverter output nominal phase-phase voltage,  $E_n$  (V);
- The inverter output nominal current,  $I_n$  (A).

The following SM parameters must be determined to design the SM complete model:

- *Reactances:*  $X_d, X'_d, X''_d, X_q, X'_q, X''_q$ ;
- *Stator resistor:*  $R_s$ ;
- *Time constants:*  $T'_d, T''_d, T'_{d0}, T''_{d0}, T'_q, T''_q, T_a$ .

The SM model should be based on the equations extracted from [23, 24]:

$$\text{d-axis: } \frac{T'_{d0}}{T'_d} = \frac{X_d}{X'_d} \text{ and } \frac{T''_{d0}}{T''_d} = \frac{X'_d}{X''_d} \quad (1)$$

$$\text{q-axis: } \frac{T'_{q0}}{T'_q} = \frac{X'_q}{X''_q} = \frac{X_q}{X''_q} \quad (2)$$

### 2.2 Methodology

The frequency,  $f_{IGBT}$ , permits to determine the time responses of the SM complete model. The maximal inverter currents and the nominal voltage and current help determining the reactances and the resistors of the SM reference.

In case none of the inverter characteristics or the SM intrinsic equations permit to select parameter values, datasheets of real SM are used as support for hypothesis.

**2.2.1 Determination of the reactances:** To design the reactances of the d-axis ( $X_d, X'_d, X''_d$ ), the maximal current admissible by the inverter  $I_{ond}^{max}$  and the nominal parameters of the inverter are used. The inverter's characteristics are linked to the d-axis reactance of the SM model ( $X_d, X'_d, X''_d$ ). The SM short-circuit currents are considered, and defined in (3), where  $\psi$  is the phase angle (rad), and  $\omega$  the angular velocity (rad/s).

$$\begin{aligned} I_{sc}(t) = E_n & \left[ \frac{1}{X_d} + \left( \frac{1}{X'_d} - \frac{1}{X_d} \right) \times \exp^{-t/T'_d} \right. \\ & + \left. \left( \frac{1}{X''_d} - \frac{1}{X'_d} \right) \times \exp^{-t/T''_d} \right] \cos(\omega t + \psi) \\ & + \frac{E_n}{2} \left( \frac{1}{X''_d} - \frac{1}{X'_d} \right) \times \exp^{-t/T_a} \left] \cos(\psi) \right. \\ & + \left. \frac{E_n}{2} \left( \frac{1}{X''_d} - \frac{1}{X'_d} \right) \times \exp^{-t/T_a} \right] \cos(2\omega t + \psi) \quad (3) \end{aligned}$$

Contrary to a traditional SM, the maximal/short-circuit inverter's current is usually limited to 1.5 or 2 times the nominal one. Therefore, the proposed methodology for the sizing of the  $X_d$  parameter is based on the permanent short-circuit current, to simplify the short-circuit detection by the inverter's protection. We have:

$$I_{sc}(t = \infty) = I_{ond}^{max} = \frac{E_n}{X_d} \quad (4)$$

Hence, the reactance  $X_d$  is defined by:

$$X_d = \frac{E_n}{I_{ond}^{max}} \quad (5)$$

The maximal and sub-transient SM current during a short-circuit could reach up to 10 to 20 times the nominal current. For the proposed methodology, the short-circuit current is fixed to 15 times the maximal inverter's current:

$$I_{sc}(t = 0) = \frac{2E_n}{X''_d} \quad (6)$$

The inverter cannot reach the same current. It is dealt with the saturation of the current's reference. Hence, the reactance  $X''_d$  is based on the equation:

$$X''_d = \frac{2E_n}{15 \times I_{ond}^{max}} \quad (7)$$

In order to determine the value of  $X'_d$  based on the inverter's characteristics, the relationship between the reactances  $X'_d$  and  $X''_d$  is used [23]. Traditionally, the value of the reactance  $X''_d$  is slightly superior to the reactance  $X'_d$ . So, based on different datasheet, the relation  $X'_d = 2X''_d$  is used.

With the same idea as using the most complete SM model to validate the replicability of the proposed methodology, a salient-pole SM is used, where the reactance  $X_d$  is from 2 to 10 times superior to the reactance  $X_q$ . In order to avoid an over-salient machines, which have no impact on the VSG performances, the parameters  $X_q$  with the relation  $2X_q = X_d$ .

The value of the sub-transitory reactance  $X''_q$  is similar to the sub-transitory reactance  $X''_d$ . In addition, the value of the reactance  $X''_q$  is selected in order to minimise the value of the output harmonics following the relation  $X''_q = 1.5 \times X''_d$  [23].

Based on the model of a SM, the stator winding resistor  $R_s$  is defined by (8).

$$R_s = \frac{X''_d + X''_q}{2T_a} \quad (8)$$

Now that all the SM reactances are linked to the inverter characteristics, the time response of the SM model is designed.

**2.2.2 Determination of the times constant:** The PWM switching frequency is considered to design the sub-transient time responses  $T'_d$  and  $T''_d$ . To ensure that the model is stable, enough calculation points are necessary. Hence, the coefficient multiplying the PWM switching frequency to obtain the SM sub-transient time response needs to be sufficient to ensure the model stability [11, 12]. However, the ratio between the PWM

switching frequency and the time response should not be too important to ensure that the performances are not impacted, thus minimising the microgrid fast stability recovery after an impact. Hence, the times responses  $T_d''$  and  $T_q''$  are chosen as  $T_d'' = T_q'' = 50/f_{IGBT}$ .

Knowing  $X_q''$ ,  $X_d''$  and  $T_q''$ , the response time  $T_{q0}''$  can be determined thanks to the SM characteristics in (2) [13].

Similarly, it is possible to determine the relationship between  $T_{d0}'$  and  $T_d'$  as using (1).

However, to determine  $T_d'$  or  $T_{d0}'$ , another relationship is necessary to identify one of the two parameters. Based on different datasheet, the  $T_d'$  parameters is often included between  $2T_d''$  and  $10T_d''$ . Similarly to the time responses  $T_d''$  and  $T_q''$ , the  $T_d'$  or  $T_{d0}'$  parameter affect both the stability of the model and the performance of the inverter. Hence, the time response  $T_d'$  is chosen as  $T_d' = 4T_d''$ . The entire methodology is summarized in Table 1.

Table 1 Recapitulation of parameters expressions.

Parameters (p.u.)	Time response (s)
$X_d = \frac{E_n}{I_{ond}^{max} \times Z_{base}}$	$T_d'' = T_q'' = \frac{50}{f_{IGBT}}$
$X_d'' = \frac{2E_n}{15I_{ond}^{max} \times Z_{base}}$	$T_{q0}'' = T_q'' \frac{X_q}{X_d''}$
$X_d' = 2X_d''$	$T_d' = 4T_d''$
$2X_q = X_d$	$T_{d0}' = 30T_d''$
$X_q'' = 1.5 \times X_d''$	
$R_s = \frac{(X_d'' + X_q'')}{2T_d''}$	$X_l = 0$
$X_0 = 0$	

The integration of the proposed methodology is experimented and validated in the following section.

### 3 Experimental validation

#### 3.1 Experimental laboratory presentation

A power-in-the-loop (PHIL), with a real inverter, has been used to validate the proposed methodology, to transfer the VSG-based control to another inverter with different characteristics that have been used in [7].

To that purpose, in the facilities of the G2ELab, a laboratory-scale prototype has been built to develop and validate control strategies that enhance the capabilities of inverter-based generation systems, notably used for renewable energies such as photovoltaic [9, 20, 21], wind turbines [10], or microgrid controllers [25].

The test-bench is constituted of two main systems: the VSG inverter and the microgrid used to validate the replicability of the VSG controller. Each system can be divided in two layers: software and hardware. Both are controlled and represented by their associated real-time digital simulators, dSPACE and RT-LAB respectively.

#### 3.2 Testbench characteristics

The local grid is connected to the test bench via a transformer imposing the nominal inverter voltage and frequency. Hence, in

order to benefit from that connexion, the inverter voltage reference is imposed at 240 V and the frequency at 50 Hz. Knowing the nominal voltage, it is possible to determine the DC voltage, input of the inverter.

To limit the risk of deterioration, the VSG inverter's maximal current is also limited, and so the admissible power of the inverter. Concerning the PWM switching frequency, the test-bench is limited to 10 kHz. Table 2 details the characteristics of the prototype that is considered to validate proposed methodology.

Experiments were validated for different PWM switching frequency, however, due to the page limitation, only a PWM switching frequency of 5 kHz is presented in this paper.

Table 2 Test-bench setup.

Inverter parameters	Value	
Maximal apparent Power	$S_{max}$	5 kVA
Maximal output 3-phase voltage	$E_{max}$	400 V
Maximal output current	$I_{ond}^{max}$	20 A
Maximal PWM frequency	$f_{PWM}$	5 kHz
Maximal DC voltage	$V_{DC}$	800 V

#### 3.3 VSG model characteristics with the methodology

Following the proposed methodology and based on the test-bench characteristics, the adapted SM parameters established considering the SM characteristics are defined in Table 3 and Table 4.

Table 3 Synchronous machine reactance values.

Parameters	Value (p.u.)
$X_d$	3.7712
$X_d''$	0.1257
$X_d'$	0.2514
$X_q$	1.8856
$X_q'' = 1.5 \times X_d''$	
$R_s$	0.10

Table 4 Synchronous machine time constant values.

Parameters	Value (p.u.)
$T_d''$	10
$X_{q0}''$	100
$T_d'$	40
$T_{d0}'$	12,000

#### 3.4 Experimental results

Now that the prototype system has been presented, the experimental results are studied to validate the replicability of the proposed controller and the methodology to determine the SM model reference of the VSG controller.

The experimental tests are separated in two parts: a stand-alone and a grid-connected mode. Due to the page limitation, one test for each mode is represented but more experiments have been conducted to ensure the replicability of the VSG control in industrial conditions.

**3.4.1 Standalone operations:** In this section, the implemented prototype VSG represents the unique power source connected to the microgrid. Fig. 1 shows the general schematic of the tests conducted in the stand-alone application with the test-bench.




Fig. 1 Schematic representation for the stand-alone test-bench.

Fig. 2 shows the transient dynamic behaviour of the VSG under a 4 kW load impact (i.e., 100 % of its power) realised with the real loads. The voltages and currents waveforms are similar to the one of a real SM.




Fig. 2. VSG behaviour during a 4 kW load impact (100 %).

During the load impact, the three-phase voltage decreases immediately and then stabilizing at its nominal value. Similarly, during the load impact, the current rapidly increases before stabilizing. To conclude, the VSG based on the proposed methodology is able to cope with a significant load impact, equal to its maximal power.

**3.4.2 Parallel operations:** In this section, the VSG is integrated in a microgrid to validate its parallel operation. Fig. 3 represents the VSG integration in the microgrid. Each element of the microgrid, real or emulated, can be connected or disconnected depending on the desired configuration, thanks to controllable interrupters. The two emulated power sources connected to the microgrid can be both a generator set and another VSG, each of 4 kVA, as the prototype VSG.

For the test presented in Fig. 4, a 12 kW load (i.e., 100 % of the power sources in the microgrid) is connected (a) and disconnected (b) to/from the microgrid constituted of the three power sources: a real and an emulated VSG and a generator.

The three-phase voltage of the microgrid are shown in Fig. 4 during the load impact and the load shedding (100 % of the




Fig. 3 Schematic representation for the VSG in a microgrid test-bench.




Fig. 4 Three-phase voltages behaviour of the microgrid after a 12 kW (a) load impact and (b) load shedding.

load). The voltage rapidly returns to its nominal value after the load impact and shedding without creation of oscillation between the three power sources, as shown by the RMS voltage value in violet on Fig. 4 (a) and (b).

## 4 Conclusion

In the first part of the paper, a methodology is detailed in order to ensure the design of a SM model for a virtual synchronous generator specified for the integration of the controller considering the inverter characteristics.

In order to validate the proposed methodology, the VSG inverter is tested in both stand-alone and parallel operations. In the stand-alone operation, the VSG control is stable for step-like load impact, unbalanced and non-linear loads connection (the first experiment only being presented in the paper due to page limitations). For the parallel operation, the VSG-based inverter is integrated in a basic microgrid connecting multiple power sources to a load where different use-cases have been tested, such as load impacts.

As presented in this paper, the proposed model of VSG is stable through 100 % loads impacts in various configuration of



grids as well as multiple integration in industrial inverters. This proves its replicability and portability in such contexts.

## 5 References

### Journal articles

- [5] Hoke, A., Butler, R., Hambrick, J., Kroposki, B.: ‘Maximum Photovoltaic Penetration Levels on Typical Distribution Feeders’, *IEEE Transactions on Sustainable Energy*, 2012., 4 (2), pp. 350-357, doi: 10.1109/TSTE.2012.2225115.
- [6] Bevrani, H., Ise, T., Miura, Y.: ‘Virtual synchronous generators: A survey and new perspectives’, *International Journal of Electrical Power & Energy Systems*, 54, pp. 244-254, 2014, doi: 10.1016/j.ijepes.2013.07.009.
- [7] Moullichon, A., Alamir, M., Debusschere, V., Garbuio, L., Rahmani, M. A., Wang, M.-X., Hadjsaid, N.: ‘Observer-Based Current Controller for Virtual Synchronous Generator in Presence of Unknown and Unpredictable Loads’, *IEEE Transactions on Power Electronics*, 2021, 36 (2), pp. 1708-1716, 2021, doi: 10.1109/TPEL.2020.3010085.
- [8] Hirase, Y., Abe, K., Sugimoto, K., Shindo, Y.: ‘A grid-connected inverter with virtual synchronous generator model of algebraic type’, *Electrical Engineering in Japan*, 184 (4), 2013, pp. 10-21, doi: 10.1002/eej.22428.
- [9] Ovalle, A., Ramos, G., Bacha, S., Hably, A., Rumeau, A.: ‘Decentralized Control of Voltage Source Converters in Microgrids Based on the Application of Instantaneous Power Theory’, *IEEE Transactions on Industrial Electronics*, 62 (2), 2015, pp. 1152-1162, doi: 10.1109/TIE.2014.2336638.
- [10] Djoudi, A., Bacha, S., Chekireb, H., Iman-Eini, H., Boudinet, C.: ‘Adaptive Sensorless SM-DPC of DFIG-Based WECS under Disturbed Grid: Study and Experimental Results’, *IEEE Transactions on Sustainable Energy*, 9 (2), 2018, pp. 570-581, doi: 10.1109/TSTE.2017.2748966.
- [11] Lüke, H. D.: ‘The Origins of the Sampling Theorem’, *IEEE Communications Magazine*, 37 (4), 1999, pp. 106-108, doi: 10.1109/35.755459.
- [12] Unser, M., ‘Sampling-50 years after Shannon’, *Proceedings of the IEEE*, 88 (4), 2000, pp. 596-587, doi: 10.1109/5.843002.
- [13] Driesen, J., Visscher, K.: ‘Virtual synchronous generators’, *IEEE Power and Energy Society General Meeting*, Pittsburgh, U.S.A., Jul. 2008, pp. 1-3, doi: 10.1109/PES.2008.4596800.
- [14] Hesse, R., Turschner, D., Beck, H.-P.: ‘Micro grid stabilization using the Virtual Synchronous Machine (VISMA)’, *International Conference on Renewable Energies and Power Quality*, Valencia, Spain, 2009, pp 15-17.
- [15] Van Thong, V., Woyte, A., Albu, M., Van Hest, M., Bozelie, J., Diaz, J., Loix, T., Stanculescu, D., Visscher, K.: ‘Virtual synchronous generator: Laboratory scale results and field demonstration’, *IEEE PowerTech*, Bucharest, Romania, 2009, pp. 1-6, doi: 10.1109/PTC.2009.5281790.
- [16] Visscher, K., De Haan, S. W. H.: ‘Virtual synchronous machines (VSG’S) for frequency stabilisation in future grids with a significant share of decentralized generation’, *CIRED Seminar: SmartGrids for Distribution*, Frankfurt, Germany, 2008, 0118, pp. 82-87, doi: 10.1049/ic:20080487.
- [17] Hojo, M., Ikeshita, R., Terauchi, T., Ueda, Y., Funabashi, T.: ‘A Converter Controller Of Virtual Synchronous Machine For Stable Operation Of Microgrid’, *CIRED*, Frankfurt, Germany, 2011, 0535, pp. 6-9.
- [18] Frack, P. F., Mercado, P. E., Molina, M. G.: ‘Extending the VISMA concept to improve the frequency stability in Microgrids’, *International Conference on Intelligent System Application to Power Systems (ISAP)*, 2015, 1, pp. 1-6, doi: 10.1109/ISAP.2015.7325530.
- [19] Chen, Y., Hesse, R., Turschner, D., Beck, H.-P.: ‘Dynamic Properties of the Virtual Synchronous Machine (VISMA)’, *International Conference Renewable Energies Power Quality*, 1 (9), 2011, pp. 755-759.
- [20] Bun, L., Raison, B., Rostaing, G., Bacha, S., Rumeau, A., Labonne, A.: ‘Development of a real time photovoltaic simulator in normal and abnormal operations’, *Annual Conference of the IEEE Industrial Electronics Society (IECON)*, 2011, pp. 867-872, doi: 10.1109/IECON.2011.6119424.
- [21] Mercier, A., Benoit, C., Besanger, Y., Rumeau, A., Boudinet, C.: ‘Comparative study of solar panel decentralized controls in low voltage network with real time simulation’, *IEEE Power and Energy Society General Meeting*, 2015, pp. 1-6, doi: 10.1109/PESGM.2015.7286205.

### Book, book chapter and manual

- [22] Zhong, Q., Weiss, G.: ‘Synchronverters: Grid-Friendly Inverters That Mimic Synchronous Generators’, in *IEEE (Ed.): ‘Control of Power Inverters in Renewable Energy and Smart Grid Integration’* (John Wiley & Sons, 2012), pp. 277-296, doi: 10.1002/9781118481806.ch18.
- [23] Kundur, P.: ‘Power System Stability and Control’ (McGraw-Hill Professional, 1994).
- [24] Kimbark, E. W., ‘Power system stability’ (IEEE Press, 1995, New York).

### Thesis

- [25] Q. L. Lam: ‘Advanced control of microgrids for frequency and voltage stability: robust control co-design and real-time validation’, *PhD thesis*, Université Grenoble Alpes, 2018.