



HAL
open science

Experimental Investigation on the Bias and Temperature Dependence of the Forward Transmission Coefficient for HEMT Technologies

Mohammad Abdul Alim, Christophe Gaquière, Giovanni Crupi

► **To cite this version:**

Mohammad Abdul Alim, Christophe Gaquière, Giovanni Crupi. Experimental Investigation on the Bias and Temperature Dependence of the Forward Transmission Coefficient for HEMT Technologies. 2021 15th International Conference on Advanced Technologies, Systems and Services in Telecommunications (TELSIKS), Oct 2021, Nis, Serbia. pp.70-73, 10.1109/TELSIKS52058.2021.9606356 . hal-03547028

HAL Id: hal-03547028

<https://hal.science/hal-03547028v1>

Submitted on 1 Mar 2022

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Experimental Investigation on the Bias and Temperature Dependence of the Forward Transmission Coefficient for HEMT Technologies

Mohammad Abdul Alim, Christophe Gaquière, and Giovanni Crupi

Abstract—The goal of this research is to look at the effects of temperature on the forward transmission coefficient (S_{21}) of high electron-mobility transistors (HEMTs), employing various technologies. The analysis is carried out on six different devices under different bias conditions with the ambient temperature varied from -40°C to 150°C . The low-frequency magnitude of S_{21} is significantly reduced in GaN-based HEMTs when the temperature is increased. On the other hand, an operating bias point where this magnitude is temperature insensitive has been identified in GaAs-based HEMTs.

Keywords—Ambient temperature, Bias condition, Forward transmission coefficient, HEMT, Scattering-parameter measurements.

I. INTRODUCTION

In the last decades, large efforts have been made to explore how the temperature impacts on the bias-dependent small-signal behavior of high electron-mobility transistors (HEMTs), going from low- to high-temperatures [1]–[11], in order to support the circuit design for microwave applications. Aiming at gaining insights on this research subject, this work is focused on a measurement-based analysis of the forward transmission coefficient (S_{21}), since this is a key parameter for assessment of the device performance. The analysis was carried out using scattering (S-) parameters measurements performed in the frequency range of 45 MHz to 50 GHz with an ambient temperature (T_a) changed from -40°C to 150°C . The drain-source voltage (V_{ds}) was fixed in the saturation region, whereas gate-source voltage (V_{gs}) was changed to check its impact on the temperature-dependent behavior of S_{21} . To analyze various technologies, six different HEMT devices were considered.

Mohammad Abdul Alim is with Department of Electrical and Electronic Engineering, University of Chittagong, Chittagong 4331, Bangladesh (e-mail: mohammadabdulalim@cu.ac.bd).

Christophe Gaquiere is with Institute of Electronic, Microelectronic and Nanotechnology (IEMN), The University of Lille, Lille F-59000, France (e-mail: christophe.gaquiere@iemn.univ-lille1.fr).

Giovanni Crupi is with BIOMORF Department, University of Messina, Messina 98125, Italy (e-mail: giovanni.crupi78@unime.it).

This work is structured as follows: Section II briefly describes the six analyzed HEMTs, Section III reports the experimental findings and discussion, and the last section concludes this work.

II. STUDIED DEVICES

The studied transistors consist of six on-wafer multi-finger HEMTs fabricated using different types of technologies: gallium arsenide (GaAs) and gallium nitride (GaN) materials, lattice-matched HEMTs and pseudomorphic HEMTs (pHEMTs), single- (S-H) and double-heterojunction (D-H) HEMTs, and both virgin and multi-layer (ML) devices. The photos of the studied transistors are shown in Fig. 1. The details of the devices are: $0.5 \times (2 \times 100) \mu\text{m}^2$ S-H GaAs HEMT (see Fig. 1(a)), $0.5 \times (2 \times 75) \mu\text{m}^2$ S-H GaAs HEMT (see Fig. 1(b)), $0.5 \times (2 \times 100) \mu\text{m}^2$ D-H virgin GaAs pHEMT (see Fig. 1(c)), $0.5 \times (2 \times 100) \mu\text{m}^2$ D-H ML GaAs pHEMT (see Fig. 1(d)), $0.25 \times (2 \times 100) \mu\text{m}^2$ GaN HEMT (see Fig. 1(e)), and $0.15 \times (4 \times 50) \mu\text{m}^2$ GaN HEMT (see Fig. 1(f)).




Fig. 1. Illustration of the six studied HEMTs.

The studied devices have been characterized by using a thermal probe station coupled to an HP4142B DC source and an HP8510C vector network analyzer (VNA).

III. EXPERIMENTS AND DISCUSSION

Figs. 2-4 report the frequency dependence of the magnitude of S_{21} for the six tested devices at three different temperature conditions: -40°C , 25°C , and 150°C . The analysis is performed over the full studied frequency range (i.e., 45 MHz – 50 GHz) and at an operating bias point in the saturation region. A higher temperature leads to a significant reduction of the magnitude of S_{21} . Although this reduction can be observed practically at all frequencies, it is pronounced especially at low frequencies. This is due to the strict link between S_{21} and the transconductance, which is stronger at lower frequencies. As a matter of fact, at relatively low frequencies S_{21} can be defined as follows [12]:

$$S_{21} = -g_{m\text{Extr}}(R_0 \parallel R_{ds\text{Extr}}), \quad (1)$$

where R_0 is 50Ω , $g_{m\text{Extr}}$ is the RF transconductance, and $R_{ds\text{Extr}}$ is the RF drain-source resistance.

It is worthy to mention that the magnitude of S_{21} is reduced at higher frequencies, since the reactive element contributions play a more dominant role when the frequency is increased, thereby making the link between S_{21} and the transconductance less tight.




Fig. 2. Magnitude of S_{21} versus frequency under three different temperature conditions for two S-H GaAs HEMTs at $V_{ds} = 3 \text{ V}$ and $V_{gs} = 0.3 \text{ V}$: (a) $0.5 \times (2 \times 100) \mu\text{m}^2$, (b) $0.5 \times (2 \times 75) \mu\text{m}^2$.




Fig. 3. Magnitude of S_{21} versus frequency under three different temperature conditions for two D-H GaAs pHEMTs at $V_{ds} = 3 \text{ V}$ and $V_{gs} = -0.2 \text{ V}$: (a) Virgin: $0.5 \times (2 \times 100) \mu\text{m}^2$, (b) multi-layer: $0.5 \times (2 \times 100) \mu\text{m}^2$.




Fig. 4. Magnitude of S_{21} versus frequency under three different temperature conditions for two GaN HEMTs at $V_{ds} = 15 \text{ V}$ and $V_{gs} = -4.8 \text{ V}$: (a) $0.25 \times (2 \times 100) \mu\text{m}^2$, (b) $0.15 \times (4 \times 50) \mu\text{m}^2$.

In order to focus the analysis on the behaviour S_{21} at low frequency, we investigate the data at 45 MHz, which is the lowest available frequency. Figs. 5-7 report the magnitude of S_{21} at 45 MHz versus the gate-source voltage for the six investigated devices at three different temperature conditions: -40°C , 25°C , and 150°C .

As can be clearly observed from the data in Figs. 5-7, the four studied GaAs-based HEMTs exhibit an operating bias point at which the low-frequency magnitude of S_{21} is temperature insensitive, which can be linked to the so called transconductance zero temperature coefficient point [8], whereas the two studied GaN-based HEMTs show a degradation in the magnitude of S_{21} at low frequency for all the considered values of V_{gs} .

The result for the GaAs-based HEMTs can be explained by the fact that the resultant impact of the temperature on the device behaviour can be ascribed to two effects acting in opposite directions when the temperature is increased: the degradation of the carrier transport properties, which plays a more dominant role by increasing V_{gs} , and the threshold voltage (V_{TH}) shift towards more negative values, which has a more dominant role by lowering V_{gs} . In case of the GaN-based HEMTs, the worsening in the transport properties of the carriers is the predominant temperature-dependent effect for all the studied values of V_{gs} . However, it should be highlighted that for both GaAs and GaN devices, the highest value of the low-frequency magnitude of S_{21} is reduced by increasing the temperature, as the higher values are located far from the pinch-off condition.




Fig. 5. Magnitude of S_{21} at 45 MHz versus V_{GS} under three different temperature conditions for two S-H GaAs HEMTs at $V_{ds} = 3$ V: (a) $0.5 \times (2 \times 100) \mu\text{m}^2$, (b) $0.5 \times (2 \times 75) \mu\text{m}^2$.




Fig. 6. Magnitude of S_{21} at 45 MHz versus V_{GS} under three different temperature conditions for two D-H GaAs pHEMTs at $V_{ds} = 3$ V: (a) Virgin: $0.5 \times (2 \times 100) \mu\text{m}^2$, (b) multi-layer: $0.5 \times (2 \times 100) \mu\text{m}^2$.




Fig. 7. Magnitude of S_{21} at 45 MHz versus V_{GS} under three different temperature conditions for two GaN HEMTs at $V_{ds} = 15$ V: (a) $0.25 \times (2 \times 100) \mu\text{m}^2$, (b) $0.15 \times (4 \times 50) \mu\text{m}^2$.

IV. CONCLUSIONS

A measurement-based study has been developed to examine the temperature effects on the HEMT behaviour. This study has considered various HEMT technologies, including GaAs and GaN materials, lattice-matched and pseudomorphic HEMTs, single- and double-heterojunction HEMTs, and both virgin and multi-layer devices. The analysis has been focused on the forward transmission coefficient, which is a key figure of merit. Particular attention has been given to the low-frequency magnitude of S_{21} as this quantity can be tightly correlated to the transconductance. The reported experiments have shown that the temperature effects can strongly vary depending on the technology and bias condition.

REFERENCES

- [1] A. Belache, A. Vanovershelde, G. Salmer, and M. Wolny, "Experimental analysis of HEMT behavior under low-temperature conditions", *IEEE Trans. Electron Dev.*, vol. 38, no. 1, pp. 3-13, Jan. 1991.
- [2] S. Nuttinck, E. Gebara, J. Laskar, and H.M. Harris, "Study of selfheating effects, temperature-dependent modeling, and pulsed load-pull measurements on GaN HEMTs", *IEEE Trans. Microw. Theory Techn.*, vol. 49, no. 12, pp. 2413-2420, Dec. 2001.
- [3] Z. Marinković and V. Marković, "Temperature-dependent models of low-noise microwave transistors based on neural networks", *Int. J. RF Microw. Comput.-Aided Eng.*, vol. 15, no. 6, pp. 567-577, Nov. 2005.
- [4] A. Caddemi, G. Crupi, and N. Donato, "Temperature effects on DC and small signal RF performance of AlGaAs/GaAs HEMTs", *Microelectron. Reliab.*, vol. 46, no. 1, pp. 169-173, Jan. 2006.
- [5] M.A. Alim, A.A. Rezazadeh, and C. Gaquiere, "Temperature effect on DC and equivalent circuit parameters of 0.15- μ m gate length GaN/SiC HEMT for microwave applications", *IEEE Trans. Microw. Theory Techn.*, vol. 64, no. 11, pp. 3483-3491, Nov. 2016.
- [6] G. Crupi, A. Raffo, V. Vadalà, G. Avolio, D.M. M.-P. Schreurs, G. Vannini, and A. Caddemi, "Technology-independent analysis of the double current-gain peak in millimeter-wave FETs", *IEEE Microw. Wirel. Compon. Lett.*, vol. 28, no. 4, pp. 326-328, Apr. 2018.
- [7] G. Crupi, A. Raffo, V. Vadalà, G. Vannini, and A. Caddemi, "High-periphery GaN HEMT modeling up to 65 GHz and 200°C", *Solid-State Electron.*, vol. 152, pp. 11-16, Feb. 2019.
- [8] Y. Chen, Y. Xu, J. Zhou, Y. Kong, T. Chen, Y. Zhang, B. Yan, and R. Xu, "Temperature-dependent small signal performance of GaN-on-diamond HEMTs", *Int. J. Numer. Model. Electron. Netw. Dev. Field.*, vol. 33, no. 3, e2620, May/June 2020.
- [9] M.A. Alim, A.A. Rezazadeh, and G. Crupi, "Experimental insight into the temperature effects on DC and microwave characteristics for a GaAs pHEMT in multilayer 3-D MMIC technology", *Int. J. RF Microw. Comput.-Aided Eng.*, vol. 30, no. 10, e22379, Oct. 2020.
- [10] A. Majumdar, S. Chatterjee, S. Chatterjee, S.S. Chaudhari, and D.R. Poddar, "An ambient temperature dependent small signal model of GaN HEMT using method of curve fitting", *Int. J. RF Microw. Comput.-Aided Eng.*, vol. 30, no. 12, e22434, Dec. 2020.
- [11] A.H. Jarndal, M.A. Alim, A. Raffo, and G. Crupi, "2-mm-gate-periphery GaN HEMTs on SiC and Si substrates: A comparative analysis from a small-signal standpoint", *Int. J. RF Microw. Comput.-Aided Eng.*, vol. 31, no. 6, e22642, Jun. 2021.
- [12] G. Crupi, G. Avolio, A. Raffo, P. Barmuta, D.M. M.-P. Schreurs, A. Caddemi, and G. Vannini, "Investigation on the thermal behavior for microwave GaN HEMTs", *Solid-State Electron.*, vol. 64, no. 1, pp. 28-33, Oct. 2011.