



HAL
open science

Corrections to “Design-Oriented All-Regime All-Region 7-Parameter Short-Channel MOSFET Model Based on Inversion Charge”

Dayana Andrea Pino Monroy, Patrick Scheer, Mohamed Khalil Bouchoucha, Carlos Galup-Montoro, Manuel Barragan, Philippe Cathelin, Jean-Michel Fournier, Andreaia Cathelin, Sylvain Bourdel

► **To cite this version:**

Dayana Andrea Pino Monroy, Patrick Scheer, Mohamed Khalil Bouchoucha, Carlos Galup-Montoro, Manuel Barragan, et al.. Corrections to “Design-Oriented All-Regime All-Region 7-Parameter Short-Channel MOSFET Model Based on Inversion Charge”. *IEEE Access*, 2023, 11, 10.1109/ACCESS.2023.3267218 . hal-03759715v1

HAL Id: hal-03759715

<https://hal.science/hal-03759715v1>

Submitted on 22 Oct 2023 (v1), last revised 24 Aug 2022 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L’archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d’enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution - NonCommercial 4.0 International License

COMMENTS AND CORRECTIONS

Corrections to “Design-Oriented All-Regime All-Region 7-Parameter Short-Channel MOSFET Model Based on Inversion Charge”

DAYANA A. PINO-MONROY^{1,2}, (Student Member, IEEE), PATRICK SCHEER¹, (Member, IEEE), MOHAMED KHALIL BOUCHOUCHA^{1,2}, (Graduate Student Member, IEEE), CARLOS GALUP-MONTORO^{1,3}, (Life Senior Member, IEEE), MANUEL J. BARRAGAN^{1,2}, (Member, IEEE), PHILIPPE CATHELIN¹, JEAN-MICHEL FOURNIER², ANDREIA CATHELIN¹, (Senior Member, IEEE), AND SYLVAIN BOURDEL², (Member, IEEE)

¹STMicroelectronics, 38920 Crolles, France

²TIMA Laboratory, CNRS, Grenoble INP, Université Grenoble Alpes, 38000 Grenoble, France

³Department of Electrical and Electronics Engineering, Universidade Federal de Santa Catarina, Florianópolis 88040-900, Brazil

Corresponding author: Sylvain Bourdel (sylvain.bourdel@univ-grenoble-alpes.fr)

In the above article [1], equations (33) and (36) had a typing error. The correct equations are:

$$\frac{\partial q_D}{\partial v_d} = \left(\frac{\sigma}{n} - 1\right) \frac{q_D}{q_D + 1}, \tag{33}$$

$$\frac{\partial q_S}{\partial v_s} = \left(\frac{\sigma}{n} - 1\right) \frac{q_S}{q_S + 1}. \tag{36}$$

Equation (37) was incomplete. The complete equation is:

$$g_m = \frac{\partial i_d}{\partial v_g} = \frac{2}{nB} \left[q_S - q_D - i_d \frac{\theta}{4} \left(\frac{q_S}{1 + q_S} + \frac{q_D}{1 + q_D} \right) \right] \tag{37}$$

Equation (38) has a typing error. The correct equation is:

$$\frac{\partial i_{dsat}}{\partial v_x} = \frac{\partial i_{dsat}}{\partial q_S} \frac{\partial q_S}{\partial v_x} = 2 \frac{E}{D + \frac{\theta}{2} E} \frac{\partial q_S}{\partial v_x} \tag{38}$$

Equations (41) and (42) were incomplete. The complete equations are:

$$g_{m2} = \frac{\partial^2 i_d}{\partial v_g^2} = \frac{2}{n^2 B} \left[\frac{q_S}{1 + q_S} - \frac{q_D}{1 + q_D} - \frac{\theta}{4} \left[2ng_m \left(\frac{q_S}{1 + q_S} + \frac{q_D}{1 + q_D} \right) \right] \right]$$

$$+ i_d \left(\frac{q_S}{(1 + q_S)^3} + \frac{q_D}{(1 + q_D)^3} \right) \tag{41}$$

$$g_{m3} = \frac{\partial^3 i_d}{\partial v_g^3} = \frac{2}{n^3 B} \left[\frac{q_S}{(1 + q_S)^3} - \frac{q_D}{(1 + q_D)^3} - \frac{\theta}{4} \left[3n^2 g_{m2} \left(\frac{q_S}{1 + q_S} + \frac{q_D}{1 + q_D} \right) + 3ng_m \left(\frac{q_S}{(1 + q_S)^3} + \frac{q_D}{(1 + q_D)^3} \right) + i_d \left(\frac{q_S (1 - 2q_S)}{(1 + q_S)^5} + \frac{q_D (1 - 2q_D)}{(1 + q_D)^5} \right) \right] \right] \tag{42}$$

The authors request this correction to provide the correct equations, as they may be useful to the community for future work on the subject.

REFERENCES

[1] D. A. Pino-Monroy, P. Scheer, M. K. Bouchoucha, C. Galup-Montoro, M. J. Barragan, P. Cathelin, J.-M. Fournier, A. Cathelin, and S. Bourdel, “Design-oriented all-regime all-region 7-parameter short-channel MOSFET model based on inversion charge,” *IEEE Access*, vol. 10, pp. 86270–86285, 2022, doi: 10.1109/ACCESS.2022.3198644.

...