HAL open science

Scattering parameters of a non-reciprocal magneto-optical integrated coupler used as an isolator

Yann G. Boucher, Yuliya Dadoenkova, Florian Bentivegna

To cite this version:

Yann G. Boucher, Yuliya Dadoenkova, Florian Bentivegna. Scattering parameters of a non-reciprocal magneto-optical integrated coupler used as an isolator. EOS Annual Meeting (EOSAM 2022), Sep 2022, Porto, Portugal. pp.01004, 10.1051/epjconf/202226601004 . hal-03825177

HAL Id: hal-03825177

https://hal.science/hal-03825177

Submitted on 20 Jan 2023

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

EPJ Web of Conferences **266**, 01004 (2022) https://doi.org/10.1051/epjconf/202226601004
EOSAM 2022

Scattering parameters of a non-reciprocal magneto-optical integrated coupler used as an isolator

Yann G. Boucher[1,2], *Yuliya S.* Dadoenkova[3,*], and *Florian F. L.* Bentivegna[3]

[1]Institut FOTON, UMR 6082, CNRS, 22305 Lannion Cedex, France
[2]École Nationale d'Ingénieurs de Brest, 29238 Brest Cedex 3, France
[3]Lab-STICC, UMR 6285, CNRS, ENIB, 29238 Brest Cedex 3, France

Abstract. We theoretically investigate a non-reciprocal magneto-optical integrated slab directional coupler. The scattering parameters of the structure are derived in the frame of the Coupled-Mode Theory ~~(CMT)~~. By properly designing the coupler, it is possible to achieve a perfect non-reciprocity (with 100% contrast) between the two directions of propagation. Other operating points can also be defined, especially since modal dispersion in the spectral domain is naturally taken into consideration.

1 Introduction

Couplers are important components of photonic circuits. Using magneto-optical materials as constituents of such systems allows one to design non-reciprocal devices, such as nonreciprocal Mach-Zehnder interferometers or nonreciprocal directional isolators [1, 2]. In this communication, we discuss the principle and the operating conditions of such an isolator based on two coupled magneto-optical waveguides with opposite directions of magnetization.

2 Magneto-optical coupler

The coupler consists of two parallel slab waveguides of equal thickness h made of a bigyrotropic magnetic medium B. Both the spacer of thickness d separating the waveguides and the surrounding space are made of the same isotropic, non-magnetic medium A (Fig. 1). Propagation occurs over a coupling length L along the z-axis. Time dependence is taken as $\exp(+i\omega t)$. Both guides are magnetized at saturation along the y-axis, in an "anti-parallel" transverse configuration.



Fig. 1. System of two coupled bigyrotropic slab waveguides (1) in the "anti-parallel" transverse magnetic configuration. The width of both magnetic guiding layers (B) is h, that of the dielectric isotropic spacer (A) is d. L denotes the interaction length. The input-output ports are numbered from (1) to (4).

In the frame of the Coupled-Mode Theory, the coupling constant χ between two phase-matched slab waveguides can be retrieved by evaluating the modal propagation constants β_e and β_o of the *even* (slow) and *odd* (fast) super-modes, since $\chi = (\beta_e - \beta_o)/2$.

According to previous calculations reported in [3], a system made of coupled bigyrotropic slab waveguides in the anti-parallel transverse magnetic configuration becomes non-reciprocal: the two waveguides remain perfectly phase-matched, but the coupling constant depends on the direction of propagation. Let us call χ^+ and χ^- the coupling constants along the z-axis from the left to the right or from the right to the left, respectively. In a non-dissipative system, they are real and positive, with $\chi^+ < \chi^-$.

Besides, considering the spectral effects of modal dispersion, we derive an expression for χ^+ and χ^- that can be linearized around a given operating wavelength.

3 Non-reciprocal *S*-parameters

3.1 *S*-parameters and signal flow-graph

The scattering matrix expresses output fields (b_p) in terms of input fields (a_p). The signal flow graph is the graphical representation of the same connections (Fig. 2).



Fig. 2. Signal flow-graph of the directional coupler, in the general case. Input/output fields at port p are denoted (a_p, b_p).

* Corresponding author: dadoenkova@enib.fr

© The Authors, published by EDP Sciences. This is an open access article distributed under the terms of the Creative Commons Attribution License 4.0 (http://creativecommons.org/licenses/by/4.0/).

Since the coupler is directional, no reflection (either direct or cross) is experienced:

$$S_{11} = S_{22} = S_{33} = S_{44} = 0, \quad (1a)$$

$$S_{13} = S_{31} = S_{24} = S_{42} = 0. \quad (1b)$$

The remaining S-parameters are: from the left to the right, $S_{21} = S_{43} = t^+$, $S_{41} = S_{23} = k^+$; from the right to the left, $S_{12} = S_{34} = t^-$, $S_{14} = S_{32} = k^-$. We get eventually:

$$\begin{pmatrix} b_2 \\ b_4 \end{pmatrix} = \begin{pmatrix} t^+ & k^+ \\ k^+ & t^+ \end{pmatrix} \begin{pmatrix} a_1 \\ a_3 \end{pmatrix} \text{ and } \begin{pmatrix} b_1 \\ b_3 \end{pmatrix} = \begin{pmatrix} t^- & k^- \\ k^- & t^- \end{pmatrix} \begin{pmatrix} a_2 \\ a_4 \end{pmatrix} \quad (2)$$

with

$$t^+ = \cos(\chi^+ L) \exp(-i\,\beta^+ L), \quad (3a)$$

$$k^+ = -i \sin(\chi^+ L) \exp(-i\,\beta^+ L), \quad (3b)$$

$$t^- = \cos(\chi^- L) \exp(-i\,\beta^- L), \quad (3c)$$

$$k^- = -i \sin(\chi^- L) \exp(-i\,\beta^- L), \quad (3d)$$

where $\beta^+ = (\beta_e^+ + \beta_o^+)/2$ stands for the average propagation constant from the left to the right; similarly, from the right to the left, $\beta^- = (\beta_e^- + \beta_o^-)/2$. Numerical calculations show that the values of β^+ and β^- are almost identical, but anyway, they appear only as a global phase term.

It is possible to design the waveguide width h and/or the gap d (as well as the interaction length L) in order to ensure that, for a given wavelength λ_0, $(\chi^+ L)$ and $(\chi^- L)$ are adjusted at will, so that

$$\frac{\chi^+}{\chi^-} = \frac{2q}{2q+1}, \quad \text{with } q \in \mathbb{N}, \quad (4)$$

which ensures that the coupler behaves as a perfect directional isolator.

3.2 Perfect directional isolator

For GGG and Bi:YIG as materials A and B, the condition expressed by Eq. (4) can for instance be satisfied (and perfect isolation be achieved) at $\lambda_0 = 1.5$ µm with $h = 0.62$ µm, $d = 0.155$ µm, and $L = 206.5$ µm, so that:

$$(\chi^+ L) \approx 10\pi, (\chi^- L) \approx 10.5\pi. \quad (5)$$



Fig. 3. Illustration of high-contrast non-reciprocity: the material parameters of the coupler can be adjusted in such a way that, for a given operating wavelength, the structure works as a perfect isolator.

As a result, the system becomes highly non-reciprocal, as schematically illustrated in Fig. 3, since

$$|S_{21}|^2 = |S_{43}|^2 = 1, \; |S_{41}|^2 = |S_{23}|^2 = 0, \quad (6a)$$

$$|S_{12}|^2 = |S_{34}|^2 = 0, \; |S_{14}|^2 = |S_{32}|^2 = 1. \quad (6b)$$

3.3 Chromatic dispersion and consequences

Once the coupler is designed as a perfect isolator for a given operating wavelength λ_{op}, the knowledge of chromatic dispersion (both modal and material) enables one to assess the bandwidth over which the behaviour remains close to ideal. Around λ_{op}, we write:

$$\chi^{(\pm)} = \chi^{(\pm)}(\lambda_{op}) + (\lambda - \lambda_{op})\,(\partial\chi/\partial\lambda), \quad (7)$$

since both coupling constants χ^+ and χ^- exhibit roughly the same value of $(\partial\chi/\partial\lambda)$. Let us start from:

$$\chi^+ L = q\pi + \theta \quad (q \in \mathbb{N}), \quad (8a)$$

$$\chi^- L = q\pi + \pi/2 + \theta, \quad (8b)$$

$$\theta = (\lambda - \lambda_{op})\,(\partial\chi/\partial\lambda)\,L. \quad (8c)$$

Then we get:

$$|S_{21}|^2 = \cos^2\theta, \; |S_{12}|^2 = \sin^2\theta. \quad (9)$$

If we strive to maintain $\sin^2\theta < 0.01$ (which means $|\theta| < 0.1$), then the corresponding bandwitdth $\Delta\lambda$ is:

$$\Delta\lambda \approx \frac{0.2}{(\partial\chi L/\partial\lambda)} \quad (10)$$

Assuming $(\partial\chi/\partial\lambda) \approx 0.07$ µm^{-2}, $\lambda_{op} = 1.5$ µm and $L \approx 206.5$ µm, we get $\Delta\lambda \approx 14$ nm (or, in frequency terms, $\Delta\nu \approx 1.8 \times 10^{12}$ Hz = 1.8 THz).

The same element can also be seen as a building-block to be inserted into more complex structures, such as a non-reciprocal Mach-Zehnder interferometer.

This work is supported in part by École Nationale d'Ingénieurs de Brest, France, and Collège de France (programme PAUSE).

References

1. Y. Hadj Aissa Fekhar, F. Salah-Belkhodja, D. Vincent, E. Bronchalo, W. Tebboune, R. Naoum. J. Electromagn. Waves Appl. **34**, 623 (2020)
2. N. Bahlmann, M. Lohmeyer, O. Zhuromskyy, H. Dötsch, P. Hertel, Opt. Communications **161**, 330 (1999)
3. Y.G. Boucher, F.F.L. Bentivegna, Y.S. Dadoenkova, IEEE J. Quantum Electron. **54**, 6200208 (2018)