



HAL
open science

Correlation functions for realistic continuous quantum measurement

Pierre Guilmin, Pierre Rouchon, Antoine Tilloy

► **To cite this version:**

Pierre Guilmin, Pierre Rouchon, Antoine Tilloy. Correlation functions for realistic continuous quantum measurement. 2023. hal-03882949v2

HAL Id: hal-03882949

<https://hal.science/hal-03882949v2>

Preprint submitted on 7 Aug 2023 (v2), last revised 9 Jan 2024 (v3)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Correlation functions for realistic continuous quantum measurement

Pierre Guilmin^{1,2,*}, Pierre Rouchon² and Antoine Tilloy²

¹*Alice & Bob, 53 Bd du Général Martial Valin, 75015 Paris, France*

²*Laboratoire de Physique de l'École Normale Supérieure, Mines Paris,*

Inria, ENS, Université PSL, Sorbonne Université, Paris, France

May 22, 2023 [†]

We propose a self-contained and accessible derivation of an exact formula for the n -point correlation functions of the signal measured when continuously observing a quantum system. The expression depends on the initial quantum state and on the Stochastic Master Equation (SME) governing the dynamics. This derivation applies to both jump and diffusive evolutions and takes into account common imperfections of realistic measurement devices. We show how these correlations can be efficiently computed numerically for commonly filtered and integrated signals available in practice.

1. INTRODUCTION

Experiments studying quantum systems generally follow the *prepare, evolve and measure* pattern: the system is first prepared in a known quantum state, then it evolves unobserved for a certain period of time, and finally a projective measurement is performed. However, it was discovered in the 1990s that certain experimental setups allow to continuously measure a quantum system while it evolves [1]. Nowadays, continuous measurements are frequently used by experimenters, notably in superconducting quantum circuits [2, 3]. In these experiments, the observer is constantly acquiring information about the state of the system, and the impact of the measurement back-action must be taken into account at every time. The dynamics of such a continuously measured quantum system is described by the *Stochastic Master Equation* (SME) formalism.

The quantum state and/or parameters can be reconstructed from the measured signal via quantum filtering [1], but this is usually computationally too expensive. In practice, the experimenters have direct access to the measured signal, so they can trivially calculate its n -point correlation functions. We show in this paper how these functions can be expressed explicitly from the SME modelling the system. Thus, albeit not optimal from a Bayesian point of view, they are an alternative and more practical approach than quantum filtering for quantum state reconstruction or for parameter estimation (see *e.g.* [4, 5]).

Several recent and older works calculate these functions analytically in restricted cases [1, 6–12], and a general derivation in the case of the diffusive SME was discovered independently by [13] and [14] in 2018. Related calculations can also be found in the field of condensed matter physics, which focuses on full counting statistics, cumulants and

spectral representation [15–17]. This paper combines the general method developed in [14] to derive n -point correlations for diffusive SME with their discrete-time formulations presented in [18]. It provides explicit formulae of n -point correlations for both jump and diffusive SME: formulae (49) and (50) for 2-point; (51) and (52) for n -point. Computing these formulae for realistic signals involve solutions of modified Lindblad master equations as shown in equations (63) to (66). As far as we know, such calculations are not available in the literature, in particular for the jump SME. Furthermore, we detail all the ingredients necessary for the practical calculation of these n -point correlation functions on arbitrary quantum systems, including detector imperfections and for realistic (binned or filtered) experimental data. For clarity, the presentation focuses mainly on a single detector, but we also give the formula to derive n -point correlations between diffusive and/or jump signals coming from multiple different detectors.

This paper is organised as follows. In section 2, we recall the structure of continuous-time jump or diffusive SMEs, and we present their discrete-time formulations based on partial Kraus maps. In section 3, we derive the general correlations formula from the underlying SME and classical post-filtering. This derivation is almost straightforward in the discrete-time formulation, and it directly provides explicit formulae in the continuous-time formulation. In section 4 we detail a novel numerical method for practically computing the correlation functions. Section 5 briefly introduces an example application.

2. THE SME FORMALISM

A SME is a *non-linear and non-deterministic* differential equation which determines the evolution of the system

*pierre.guilmin@alice-bob.com

[†]© 2023 the authors. This work has been accepted to IFAC for publication under a Creative Commons Licence CC-BY-NC-ND.

state ρ_t at time t , conditioned on the detector measurement record. Different measurement schemes lead to different types of evolution: the state can evolve discontinuously, with sudden jumps at random time, which is modeled by a *jump* SME, or continuously in state space, which is modeled by a *diffusive* SME. In quantum optics for instance, the first situation corresponds to photon counting schemes [19] and the second to homodyne or heterodyne detection schemes [20].

In this section, we first introduce the jump and diffusive SMEs, then we give an equivalent discrete-time formulation, and we conclude by explaining the link between SMEs and the *linear and deterministic* Lindblad master equation describing unobserved quantum systems.

2.1. Jump SME

When the result of the measurement at time t is either a detection event or a no-detection event, the system state undergoes abrupt jumps from one state to another upon detection. The *discrete-valued continuous-time* stochastic process driving the SME is the increment dN_t , taking the value 0 for no-detection and 1 for detection with probabilities depending on the system state at time t :

$$\mathbb{P}[dN_t = 0] = 1 - \mathbb{P}[dN_t = 1], \quad (1)$$

$$\mathbb{P}[dN_t = 1] = (\theta + \eta \text{Tr}[L\rho_t L^\dagger]) dt, \quad (2)$$

where L is an arbitrary operator characterising the detector, $\theta \geq 0$ is the dark count rate and $0 < \eta \leq 1$ is the detector efficiency.

The evolution of ρ_t is described by the jump SME [18]:

$$d\rho_t = -i[H, \rho_t]dt + \mathcal{D}[L](\rho_t)dt + \mathcal{G}[L](\rho_t) (dN_t - (\theta + \eta \text{Tr}[L\rho_t L^\dagger]) dt), \quad (3)$$

where H is the system Hamiltonian, $\mathcal{D}[L](\rho) = L\rho L^\dagger - \frac{1}{2}L^\dagger L\rho - \frac{1}{2}\rho L^\dagger L$ is the standard dissipator, and the superoperator $\mathcal{G}[L]$ describing the back-action of the measurement is defined by:

$$\mathcal{G}[L](\rho) = \frac{\theta\rho + \eta L\rho L^\dagger}{\theta + \eta \text{Tr}[L\rho L^\dagger]} - \rho. \quad (4)$$

The *continuous-time signal* measured by the detector is $I_t = dY_t/dt$, where dY_t is directly defined as the stochastic increment in the case of the jump SME:

$$dY_t = dN_t. \quad (5)$$

The signal I_t is the rate of change of the counting process N_t , which counts the number of jumps that occurred in the time interval $[0, t]$.

An experiment corresponds to a specific realisation of the stochastic process dN_t , giving rise to a *quantum trajectory* which describes the path followed by the state of the

quantum system over time. This trajectory is conditioned on the measurement results: we can replace the stochastic term dN_t by the measured signal values at each time in (3), and thus reconstruct ρ_t from the measurement record.

2.2. Diffusive SME

When the result of the measurement at time t takes a continuous range of values, the system state evolves continuously in state space. The *real-valued continuous-time* stochastic process driving the SME is the Wiener process dW_t , taking independent Gaussian distributed increment.

The evolution of ρ_t is described by the diffusive SME in Itô form [21]:

$$d\rho_t = -i[H, \rho_t]dt + \mathcal{D}[L](\rho_t)dt + \sqrt{\eta}\mathcal{M}[L](\rho_t)dW_t, \quad (6)$$

where the superoperator $\mathcal{M}[L]$ describing the back-action of the measurement is defined by:

$$\mathcal{M}[L](\rho) = L\rho + \rho L^\dagger - \text{Tr}[(L + L^\dagger)\rho]\rho. \quad (7)$$

Similarly, the continuous-time signal measured by the detector $I_t = dY_t/dt$ verifies:

$$dY_t = \sqrt{\eta}\text{Tr}[(L + L^\dagger)\rho_t]dt + dW_t. \quad (8)$$

Sometimes the signal is defined with a different but equivalent normalisation $dY'_t = dY_t/(2\sqrt{\eta})$.

As for the jump SME, an experiment corresponds to a specific realisation of the stochastic process dW_t , giving rise to a quantum trajectory that can be reconstructed from the measured signal.

2.3. Discrete-time formulation

We can derive both SMEs by taking the limit of infinitely frequent and infinitely weak projective measurements [22, 23]. We use such a discrete-time picture with a slightly different formulation as described in [18].

In this formulation, the measurement process is described by a *quantum instrument*, which combines a quantum measurement characterised by a *positive operator-valued measure* (POVM) and a classical uncertainty on the measurement result accounting for imperfections of the detector. A map depending on the measurement result is applied at each small time step dt :

$$\rho_{k+1} = \frac{K_{r_{k+1}}(\rho_k)}{\text{Tr}[K_{r_{k+1}}(\rho_k)]}, \quad (9)$$

where ρ_k is the state of the system at step k (at time $t = kdt$), and $K_{r_{k+1}}$ is a linear map depending on r_{k+1} , the measurement result at step $k + 1$.

For both SMEs, we define the corresponding quantum instrument by specifying the linear map K_r associated with

each possible measurement result r . The continuous-time formulations (3) and (6) are recovered by taking the limit of infinitesimally small time step, and expanding the expression $\rho_{k+1} - \rho_k \sim \rho_{t+dt} - \rho_t = d\rho_t$ to first order in dt .

Jump SME – For the jump SME, the measurement result is either 0 or 1, and the corresponding maps are:

$$K_0(\rho) = (1 - \theta dt)M_0\rho M_0^\dagger + (1 - \eta)M_1\rho M_1^\dagger, \quad (10)$$

$$K_1(\rho) = \theta dt M_0\rho M_0^\dagger + \eta M_1\rho M_1^\dagger, \quad (11)$$

with

$$M_0 = \mathbb{I} - iHdt - \frac{1}{2}L^\dagger Ldt, \quad (12)$$

$$M_1 = L\sqrt{dt}. \quad (13)$$

The probability of obtaining the measurement result r at step $k + 1$ depends only on the preceding state ρ_k :

$$\mathbb{P}[r_{k+1} = r | \rho_k] = \text{Tr}[K_r(\rho_k)]. \quad (14)$$

We can evaluate the probability of obtaining the measurement record $\{r_1, r_2\}$ knowing the initial state ρ_0 :

$$\mathbb{P}[r_1, r_2 | \rho_0] = \mathbb{P}[r_1 | \rho_0] \times \mathbb{P}[r_2 | r_1, \rho_0].$$

The first term is given by (14): $\mathbb{P}[r_1 | \rho_0] = \text{Tr}[K_{r_1}(\rho_0)]$. To evaluate the second term we use (9) to write the state at step $k = 1$ conditioned on the measurement result r_1 : $\rho_1 = K_{r_1}(\rho_0)/\text{Tr}[K_{r_1}(\rho_0)]$. Then using (14) again:

$$\mathbb{P}[r_2 | r_1, \rho_0] = \text{Tr}[K_{r_2}(\rho_1)] = \text{Tr}\left[K_{r_2}\left(\frac{K_{r_1}(\rho_0)}{\text{Tr}[K_{r_1}(\rho_0)]}\right)\right].$$

Combining the two terms, we get:

$$\mathbb{P}[r_1, r_2 | \rho_0] = \text{Tr}[K_{r_2}K_{r_1}(\rho_0)]. \quad (15)$$

This result directly extends to the probability of obtaining the measurement record $\{r_1, \dots, r_N\}$:

$$\mathbb{P}[r_1, \dots, r_N | \rho_0] = \text{Tr}[K_{r_N} \dots K_{r_1}(\rho_0)]. \quad (16)$$

Diffusive SME – For the diffusive SME, the measurement result takes a continuous range of values and the map corresponding to the measurement result r is:

$$K_r(\rho) = M_r\rho M_r^\dagger + (1 - \eta)L\rho L^\dagger dt, \quad (17)$$

with

$$M_r = \mathbb{I} - iHdt - \frac{1}{2}L^\dagger Ldt + \sqrt{\eta}Lr. \quad (18)$$

The equivalent of (14) is given by the probability density to get a measurement result in $[r, r + dr]$ at step $k + 1$ knowing the state ρ_k :

$$d\mathbb{P}[r_{k+1} \in [r, r + dr] | \rho_k] = d\mu(r)\text{Tr}[K_r(\rho_k)], \quad (19)$$

where $d\mu(r)$ is the Gaussian measure centered on 0 with variance dt [18, 21]:

$$d\mu(r) = \frac{1}{\sqrt{2\pi dt}} \exp\left(\frac{-r^2}{2dt}\right) dr. \quad (20)$$

The same calculations as for the jump SME give the probability density to get the measurement record $\{r_1, \dots, r_N\}$:

$$d\mathbb{P}[r_1, \dots, r_N | \rho_0] = d\mu(r_1) \dots d\mu(r_N) \text{Tr}[K_{r_N} \dots K_{r_1}(\rho_0)]. \quad (21)$$

2.4. Unconditioned evolution

When the measurement results are unknown to the observer, for example for a purely dissipative process or for unread measurements, the system dynamics is deterministic. The evolution of the *unconditioned state* $\bar{\rho}_t$ is recovered by averaging over all possible quantum trajectories — or equivalently over all possible measurement records — weighted by their probability of occurrence:

$$\bar{\rho}_t = \mathbb{E}[\rho_t], \quad (22)$$

where \mathbb{E} denotes the statistical average over the stochastic process driving the SME. Note that the unconditioned state does not depend on the stochastic process averaged over (jump or diffusive): different types of stochastic evolution lead to the same ensemble average trajectory.

The evolution of $\bar{\rho}_t$ is then described by the *linear and deterministic Lindblad master equation* [24]:

$$\frac{d\bar{\rho}_t}{dt} = -i[H, \bar{\rho}_t] + \mathcal{D}[L](\bar{\rho}_t) = \mathcal{L}(\bar{\rho}_t), \quad (23)$$

where \mathcal{L} is the system Lindbladian, the superoperator generating the evolution of the system when the observer does not know the measured signal. For time-independent Lindbladian, the formal solution reads:

$$\bar{\rho}_t = e^{t\mathcal{L}}(\rho_0). \quad (24)$$

For time-dependent Lindbladian \mathcal{L}_t , the solution is written using the time-ordered exponential:

$$\bar{\rho}_t = \mathcal{T} \exp\left(\int_0^t \mathcal{L}_{t'} dt'\right)(\rho_0), \quad (25)$$

where \mathcal{T} is the time-ordering symbol.

Similarly to the jump and diffusive SME, the Lindblad master equation has a discrete-time formulation. The general evolution of an *unobserved open quantum system* between two time steps is characterised by a *completely positive trace preserving* (CPTP) linear map K (also called *quantum channel* or *dynamical map*):

$$\bar{\rho}_{k+1} = K(\bar{\rho}_k). \quad (26)$$

In this discrete-time formulation, we also recover the unconditioned evolution by averaging over all possible measurement outcomes at each step:

$$\bar{\rho}_{k+1} = \mathbb{E}[\rho_{k+1} | \bar{\rho}_k]. \quad (27)$$

As in the continuum, we find the same CPTP map K , that is the same unconditioned state dynamics, when averaging over either of the stochastic processes (jump or diffusive):

$$K(\rho) = K_0(\rho) + K_1(\rho) = \int_{-\infty}^{\infty} d\mu(r) K_r(\rho). \quad (28)$$

In the continuous-time limit we recover the evolution generated by the system Lindbladian \mathcal{L} .

3. CORRELATION FUNCTIONS

The statistics of the measured signal are fully characterised by its correlation functions. The n -point correlation function of the signal I_t is defined by:

$$C_{t_1, t_2, \dots, t_n} = \mathbb{E}[I_{t_1} I_{t_2} \dots I_{t_n} | \rho_0]. \quad (29)$$

The one-point correlation function is the signal mean, and the two-point correlation function is the signal autocorrelation.

The signal I_t is a singular quantity, in the case of the jump SME it can be loosely thought of as a series of Dirac delta distributions at the times of detection, and in the case of the diffusive SME as white noise with a trend. This quantity is better defined when it is integrated against a *smooth test function* f :

$$I_f = \int f_t dY_t. \quad (30)$$

In practice, the signal is obtained from a finite bandwidth detection chain, and is therefore effectively filtered. Experimentally, the smooth test function f then corresponds to the transfer function of the detection chain. In the following, we will refer to I_t as the *sharp* signal, and to I_f as the *filtered* signal.

The filtered signal I_f is the only quantity actually available to an experimenter. Thus, we are also interested in calculating its correlation functions:

$$C_{f_1, f_2, \dots, f_n} = \mathbb{E}[I_{f_1} I_{f_2} \dots I_{f_n} | \rho_0]. \quad (31)$$

The objective of this section is to give an analytical formula depending only on the SME for the correlation functions of the sharp and filtered signal. We first introduce the generating functional of the correlation functions, allowing us to evaluate both C_{t_1, \dots, t_n} and C_{f_1, \dots, f_n} . We then deduce the formula for the correlation functions using the discrete-time formulation and its continuous limit. The remainder of the section is devoted to examples of how to calculate basic correlation functions using this general formula, and we finally generalise the result to the case of multiple detectors and mixed jump-diffusive SME.

3.1. Generating functional

The sharp and filtered signal correlation functions can both be determined using the *generating functional* $\mathcal{Z}(j)$ defined by [14, 25]:

$$\mathcal{Z}(j) = \mathbb{E} \left[\exp \left(\int_{u=0}^{u=T} j_u dY_u \right) \middle| \rho_0 \right], \quad (32)$$

where j is a smooth test function and T is a large time, typically larger than any time involved in the correlation functions we wish to evaluate. This generating functional is defined analogously to the moment-generating function $M(t) = \mathbb{E}[e^{tX}]$ of a random variable X , whose n -th derivative yields the n -th moment of X :

$$\mathbb{E}[X^n] = \left. \frac{d^n}{dt^n} M(t) \right|_{t=0}. \quad (33)$$

Sharp signal correlations – The functional derivative of $\mathcal{Z}(j)$ with respect to j_t for $t \in [0, T]$ reads:

$$\frac{\delta}{\delta j_t} \mathcal{Z}(j) = \mathbb{E} \left[\frac{dY_t}{dt} \exp \left(\int_0^T j_u dY_u \right) \middle| \rho_0 \right]. \quad (34)$$

Thus for $t_1 < t_2 < \dots < t_n$, the sharp signal correlation function can be expressed as:

$$C_{t_1, \dots, t_n} = \left. \frac{\delta}{\delta j_{t_1}} \dots \frac{\delta}{\delta j_{t_n}} \mathcal{Z}(j) \right|_{j=0}. \quad (35)$$

The correlation functions involving *equal time contributions* are not well defined for the sharp signal, because they yield Dirac delta distribution. However, these contributions should not be missed when evaluating the filtered signal correlation functions.

Filtered signal correlations – The correlation functions of the filtered signals I_{f_1}, \dots, I_{f_n} are given by the standard partial derivative of $\mathcal{Z}(\alpha_1 f_1 + \dots + \alpha_n f_n)$ with respect to $\alpha_1, \dots, \alpha_n$:

$$C_{f_1, \dots, f_n} = \left. \frac{\partial}{\partial \alpha_1} \dots \frac{\partial}{\partial \alpha_n} \mathcal{Z}(\alpha_1 f_1 + \dots + \alpha_n f_n) \right|_{\alpha_1, \dots, \alpha_n=0}. \quad (36)$$

3.2. Derivation of the analytical formula

Our goal is to find an analytical formula for the generating functional $\mathcal{Z}(j)$. In this subsection we give the proof for the jump SME by using the discrete-time formulation, and explain how it extends to the diffusive SME. For a calculation in the diffusive case relying only on continuous stochastic calculus techniques without resorting to discretisation, see [14].

In the discrete-time formulation we divide the time T in N steps of duration $dt = T/N$, $\mathcal{Z}(j)$ then reads:

$$\mathcal{Z}(j) = \mathbb{E} \left[\exp \left(\sum_{k=1}^N j_k r_k \right) \middle| \rho_0 \right], \quad (37)$$

where j_k is the test function value at step k (at time $t = kdt$).

To evaluate the expectation value in $\mathcal{Z}(j)$, we need to average over all possible measurement records weighted by their probability of occurrence. In the case of the jump SME, the measurement result r_k at step k is either 0 or 1, so:

$$\mathcal{Z}(j) = \sum_{r_k \in \{0,1\}} \mathbb{P}[r_1, \dots, r_N | \rho_0] \exp \left(\sum_{k=1}^N j_k r_k \right). \quad (38)$$

The probability of a specific measurement record is given by (16): $\mathbb{P}[r_1, \dots, r_N | \rho_0] = \text{Tr}[K_{r_N} \dots K_{r_1}(\rho_0)]$. Now we split the exponential, reorder and regroup the terms to get the final result:

$$\mathcal{Z}(j) = \sum_{r_k \in \{0,1\}} \text{Tr}[K_{r_N} \dots K_{r_1}(\rho_0)] \prod_{k=1}^N \exp(j_k r_k) \quad (39)$$

$$= \text{Tr} \left[\left(\sum_{r_N \in \{0,1\}} K_{r_N} e^{j_N r_N} \right) \dots \right. \quad (40)$$

$$\left. \dots \left(\sum_{r_1 \in \{0,1\}} K_{r_1} e^{j_1 r_1} \right) (\rho_0) \right]$$

$$= \text{Tr}[(K_0 + K_1 e^{j_N}) \dots (K_0 + K_1 e^{j_1})(\rho_0)] \quad (41)$$

$$= \text{Tr}[\Phi_{j_N} \dots \Phi_{j_1}(\rho_0)], \quad (42)$$

with Φ_{j_k} a linear map defined by:

$$\begin{aligned} \Phi_{j_k}(\rho) &= (K_0 + K_1 e^{j_k})(\rho) \\ &= \rho + [\mathcal{L}(\rho) + (e^{j_k} - 1)(\theta\rho + \eta L_{\times}(\rho))] dt, \end{aligned} \quad (43)$$

where we defined the superoperator $L_{\times}(\rho) = L\rho L^{\dagger}$.

By taking the limit of infinitesimally small time step, we have:

$$\mathcal{Z}(j) = \text{Tr} \left[\mathcal{T} \exp \left(\int_0^T \mathcal{L}_{j_u} du \right) (\rho_0) \right], \quad (44)$$

with \mathcal{L}_{j_t} identified from (43) as the generator of the evolution:

$$\mathcal{L}_{j_t} = \mathcal{L} + (e^{j_t} - 1)(\theta\mathbb{I} + \eta L_{\times}). \quad (45)$$

The calculations are very similar in the case of the diffusive SME: replacing sums by integrals over the Gaussian measure (20) and using the partial Kraus map defined by (17)

and (18), we obtain the same formula for $\mathcal{Z}(j)$ where the generator of the evolution \mathcal{L}_{j_t} is now:

$$\mathcal{L}_{j_t} = \mathcal{L} + \sqrt{\eta} j_t L_{+} + \frac{j_t^2}{2} \mathbb{I}, \quad (46)$$

where we defined the superoperator $L_{+}(\rho) = L\rho + \rho L^{\dagger}$.

Note that the expression of $\mathcal{Z}(j)$ depends only on the initial state and on the SME describing the system.

3.3. Sharp signal correlation functions

In this subsection, we explain how to calculate the correlation functions of the sharp signal using the analytical formula for $\mathcal{Z}(j)$. The calculations for filtered signals are discussed in section 4.

We assume that the Lindbladian does not depend on time to simplify the expressions (the extension to time-dependent Lindbladian is straightforward). In the following calculations we also use the trace-preserving property of the Lindbladian evolution: $\text{Tr}[e^{t\mathcal{L}}(\rho)] = \text{Tr}[\rho] = 1$.

Signal mean – The one-point correlation function for the jump SME reads:

$$\begin{aligned} C_t &= \frac{\delta}{\delta j_t} \mathcal{Z}(j) \Big|_{j=0} \\ &= \text{Tr} \left[\mathcal{T} \exp \left(\int_t^T \mathcal{L}_{j_u} du \right) e^{j_t (\theta\mathbb{I} + \eta L_{\times})} \right. \\ &\quad \left. \mathcal{T} \exp \left(\int_0^t \mathcal{L}_{j_u} du \right) (\rho_0) \right] \Big|_{j=0} \\ &= \theta + \eta \text{Tr}[L_{\times} e^{t\mathcal{L}}(\rho_0)]. \end{aligned} \quad (47)$$

And for the diffusive SME:

$$C_t = \sqrt{\eta} \text{Tr}[L_{+} e^{t\mathcal{L}}(\rho_0)]. \quad (48)$$

Signal autocorrelation – For $t_1 < t_2$, the two-point correlation function for the jump SME reads:

$$\begin{aligned} C_{t_1, t_2} &= \frac{\delta}{\delta j_{t_1}} \frac{\delta}{\delta j_{t_2}} \mathcal{Z}(j) \Big|_{j=0} \\ &= \text{Tr} \left[(\theta\mathbb{I} + \eta L_{\times}) e^{(t_2 - t_1)\mathcal{L}} (\theta\mathbb{I} + \eta L_{\times}) e^{t_1 \mathcal{L}} (\rho_0) \right] \\ &= \theta^2 + \eta^2 \text{Tr}[L_{\times} e^{(t_2 - t_1)\mathcal{L}} L_{\times} e^{t_1 \mathcal{L}} (\rho_0)] \\ &\quad + \theta\eta (\text{Tr}[L_{\times} e^{t_1 \mathcal{L}} (\rho_0)] + \text{Tr}[L_{\times} e^{t_2 \mathcal{L}} (\rho_0)]). \end{aligned} \quad (49)$$

And for the diffusive SME:

$$C_{t_1, t_2} = \eta \text{Tr}[L_{+} e^{(t_2 - t_1)\mathcal{L}} L_{+} e^{t_1 \mathcal{L}} (\rho_0)]. \quad (50)$$

Multipoint correlation function – More generally for distinct times $t_1 < \dots < t_n$, the n -point correlation function

for the jump SME reads:

$$C_{t_1, \dots, t_n} = \text{Tr} \left[(\theta \mathbf{I} + \eta L_{\times}) e^{(t_n - t_{n-1}) \mathcal{L}} \dots \dots (\theta \mathbf{I} + \eta L_{\times}) e^{t_1 \mathcal{L}} (\rho_0) \right]. \quad (51)$$

And for the diffusive SME:

$$C_{t_1, \dots, t_n} = \eta^{n/2} \text{Tr} \left[L_{+} e^{(t_n - t_{n-1}) \mathcal{L}} \dots L_{+} e^{t_1 \mathcal{L}} (\rho_0) \right]. \quad (52)$$

The exact result is thus obtained by inserting specific super-operators at the correlation times ($\theta \mathbf{I} + \eta L_{\times}$ for the jump SME and $\sqrt{\eta} L_{+}$ for the diffusive SME), and evolving the system with the ensemble-averaged evolution in-between.

3.4. Generalisation to mixed jump-diffusive SME and multiple detectors

We generalise the analytical formula of $\mathcal{Z}(j)$ to the case of mixed jump-diffusive SME with multiple detectors, when the quantum system is continuously measured by n_{μ} detectors with discrete-valued measurement results, resulting in a jump-type evolution, and by n_{ν} detector with continuous-valued measurement results, resulting in a diffusive-type evolution.

The general jump-diffusive SME with multiple detectors reads:

$$\begin{aligned} d\rho_t = & -i[H, \rho_t]dt + \sum_{\mu} \mathcal{D}[V_{\mu}](\rho_t)dt + \sum_{\nu} \mathcal{D}[L_{\nu}](\rho_t)dt \\ & + \sum_{\mu} \mathcal{G}[V_{\mu}](\rho_t) (dN_{\mu,t} - (\theta_{\mu} + \eta_{\mu} \text{Tr}[V_{\mu} \rho_t V_{\mu}^{\dagger}] dt)) \\ & + \sum_{\nu} \sqrt{\eta_{\nu}} \mathcal{M}[L_{\nu}](\rho_t) dW_{\nu,t}, \end{aligned} \quad (53)$$

where $dN_{\mu,t}$ are independent stochastic increments and $dW_{\nu,t}$ are independent Wiener processes. The observer has access to $n_{\mu} + n_{\nu}$ signals:

$$\left\{ I_{\mu,t} = \frac{dY_{\mu,t}}{dt}, J_{\nu,t} = \frac{dZ_{\nu,t}}{dt} \right\}_{\mu \in [1, n_{\mu}], \nu \in [1, n_{\nu}]}, \quad (54)$$

with

$$dY_{\mu,t} = dN_{\mu,t}, \quad (55)$$

$$dZ_{\nu,t} = \sqrt{\eta_{\nu}} \text{Tr}[(L_{\nu} + L_{\nu}^{\dagger}) \rho_t] dt + dW_{\nu,t}. \quad (56)$$

The generating functional $\mathcal{Z}(j)$ has the same expression, where j is now the set of test functions each associated with a detector: $j = \{j_{\mu}, j_{\nu}\}_{\mu \in [1, n_{\mu}], \nu \in [1, n_{\nu}]}$. The generator of the evolution $\mathcal{L}_{j,t}$ reads:

$$\begin{aligned} \mathcal{L}_{j,t} = & \mathcal{L} + \sum_{\mu} (e^{j_{\mu,t}} - 1) (\theta_{\mu} \mathbf{I} + \eta_{\mu} V_{\mu, \times}) \\ & + \sum_{\nu} \left(\sqrt{\eta_{\nu}} j_{\nu,t} L_{\nu,+} + \frac{j_{\nu,t}^2}{2} \mathbf{I} \right). \end{aligned} \quad (57)$$

For example, the two-point correlation function for $t_1 < t_2$ between the jump-type detector indexed μ and the diffusive-type detector indexed ν reads:

$$\mathbb{E}[I_{\mu,t_1} J_{\nu,t_2}] = \text{Tr} \left[\sqrt{\eta_{\nu}} L_{\nu,+} e^{(t_2 - t_1) \mathcal{L}} (\theta_{\mu} \mathbf{I} + \eta_{\mu} V_{\mu, \times}) e^{t_1 \mathcal{L}} (\rho_0) \right]. \quad (58)$$

4. PRACTICAL COMPUTATION FOR REALISTIC DATA IN THE DIFFUSIVE CASE

In this section we detail a novel numerical method for practically computing analytical correlation functions on experimental data. We use a simple but easily generalisable example to explain the methodology.

In a common experimental setup, the detector consists of a chain of finite bandwidth amplifiers concluded by an analogue-to-digital converter (ADC), which converts the analogue signal into a discrete signal. This amplified and digitised output signal is usually integrated against a rectangular window of duration Δt much longer than the inverse of the ADC sampling rate. Thus from a practical point of view, the discrete-time signal I_k available to an experimenter is simply the integral of the continuous-time signal I_t against a rectangular window of duration Δt (a time bin):

$$I_k = \int_{k\Delta t}^{(k+1)\Delta t} dY_t. \quad (59)$$

Let us illustrate how to evaluate the two-point correlation function of this integrated signal in a slightly more general setting, when the integration windows partially overlap. This example illustrates the importance of not missing the equal time contributions when evaluating correlation functions of the filtered signal. We consider the signals I_1 integrated on some time interval Ω_1 and I_2 integrated on some time interval Ω_2 (see figure 1):

$$I_m = \int_{t \in \Omega_m} dY_t = \int \mathbf{1}_{\Omega_m}(t) dY_t, \quad (60)$$

where $\mathbf{1}_{\Omega}$ is the rectangular window defined by $\mathbf{1}_{\Omega}(t) = 1$ if $t \in \Omega$ and $\mathbf{1}_{\Omega}(t) = 0$ otherwise.




Figure 1: Overlapping integration windows

We consider a system whose evolution is described by a diffusive SME, and for simplicity we assume that the Lindbladian does not depend on time.

It is tempting to evaluate the two-point correlation function naively by taking partial derivatives of the generating func-

tional explicitly as in (36):

$$\begin{aligned}
C_{I_1, I_2} &= \partial_{\alpha_1} \partial_{\alpha_2} \mathcal{Z}(\alpha_1 \mathbb{1}_{\Omega_1} + \alpha_2 \mathbb{1}_{\Omega_2}) \Big|_{\alpha_1, \alpha_2=0} \\
&= \int_{\Omega_1 \cap \Omega_2} dt \\
&\quad + \eta \iint_{\Omega_1, \Omega_2, t_1 \leq t_2} dt_1 dt_2 \text{Tr} \left[L_+ e^{(t_2-t_1)\mathcal{L}} L_+ e^{t_1\mathcal{L}}(\rho_0) \right] \\
&\quad + \eta \iint_{\Omega_1, \Omega_2, t_1 > t_2} dt_1 dt_2 \text{Tr} \left[L_+ e^{(t_1-t_2)\mathcal{L}} L_+ e^{t_2\mathcal{L}}(\rho_0) \right],
\end{aligned}$$

where we use the abbreviated notation $\partial_\alpha = \frac{\partial}{\partial \alpha}$ for the partial derivative. Note the overlapping term for $t \in \Omega_1 \cap \Omega_2$ coming from the equal time contributions of the sharp signal. One could then evaluate this expression numerically by i) discretising the double integrals ii) evaluating the trace integrand at each quadrature point (*e.g.* by diagonalising \mathcal{L} and evaluating the exponentials exactly). This is prohibitively expensive for large Hilbert space dimensions and correlation functions involving more than two points.

We propose a faster way to compute such correlation functions, which requires no discretisation when the filter is a simple binning as we assume here. We go back to the generating functional and pull the derivatives inside the trace:

$$\begin{aligned}
C_{I_1, I_2} &= \partial_{\alpha_1} \partial_{\alpha_2} \text{Tr} \left[\mathcal{T} \exp \left(\int_0^T \mathcal{L}_{j_u} du \right) (\rho_0) \right] \Big|_{\alpha_1, \alpha_2=0} \\
&= \text{Tr} \left[\partial_{\alpha_1} \partial_{\alpha_2} \rho_T^j \Big|_{\alpha_1, \alpha_2=0} \right] = \text{Tr} \left[\rho_T^{(1,2)} \right], \quad (61)
\end{aligned}$$

where $j = \alpha_1 \mathbb{1}_{\Omega_1} + \alpha_2 \mathbb{1}_{\Omega_2}$ and ρ_t^j is the solution to the ordinary differential equation (ODE) $d\rho_t^j/dt = \mathcal{L}_{j_t}(\rho_t^j)$. To compute the derivatives of ρ_T^j with respect to α_1, α_2 , we simply (forward) differentiate the ODE:

$$\frac{d}{dt} \rho_t^{(1,2)} = \partial_{\alpha_1} \partial_{\alpha_2} \left(\mathcal{L}_{j_t}(\rho_t^j) \right) \Big|_{\alpha_1, \alpha_2=0}. \quad (62)$$

Introducing the partial derivatives

$$\rho_t^{(1)} = \partial_{\alpha_1} \rho_t^j \Big|_{\alpha_1, \alpha_2=0} \quad \text{and} \quad \rho_t^{(2)} = \partial_{\alpha_2} \rho_t^j \Big|_{\alpha_1, \alpha_2=0},$$

and using the explicit expression of \mathcal{L}_{j_t} from (46), we obtain the system of coupled linear ODEs describing the evolution of four fictitious states $\rho_t, \rho_t^{(1)}, \rho_t^{(2)}$ and $\rho_t^{(1,2)}$:

$$\frac{d}{dt} \rho_t = \mathcal{L}_{j_t}(\rho_t) \Big|_{\alpha_1, \alpha_2=0} = \mathcal{L}(\rho_t), \quad (63)$$

$$\begin{aligned}
\frac{d}{dt} \rho_t^{(1)} &= \partial_{\alpha_1} \left(\mathcal{L}_{j_t}(\rho_t^j) \right) \Big|_{\alpha_1, \alpha_2=0} \\
&= \mathcal{L}(\rho_t^{(1)}) + \mathbb{1}_{\Omega_1}(t) \sqrt{\eta} L_+(\rho_t), \quad (64)
\end{aligned}$$

$$\begin{aligned}
\frac{d}{dt} \rho_t^{(2)} &= \partial_{\alpha_2} \left(\mathcal{L}_{j_t}(\rho_t^j) \right) \Big|_{\alpha_1, \alpha_2=0} \\
&= \mathcal{L}(\rho_t^{(2)}) + \mathbb{1}_{\Omega_2}(t) \sqrt{\eta} L_+(\rho_t), \quad (65)
\end{aligned}$$

$$\begin{aligned}
\frac{d}{dt} \rho_t^{(1,2)} &= \partial_{\alpha_1} \partial_{\alpha_2} \left(\mathcal{L}_{j_t}(\rho_t^j) \right) \Big|_{\alpha_1, \alpha_2=0} \\
&= \mathcal{L}(\rho_t^{(1,2)}) + \mathbb{1}_{\Omega_1}(t) \sqrt{\eta} L_+(\rho_t^{(2)}) \\
&\quad + \mathbb{1}_{\Omega_2}(t) \sqrt{\eta} L_+(\rho_t^{(1)}) + \mathbb{1}_{\Omega_1 \cap \Omega_2}(t) \rho_t. \quad (66)
\end{aligned}$$

To obtain $\rho_T^{(1,2)}$, we solve this system linear ODE (which we see simply as a larger linear ODE) with initial condition $\rho_{t=0} = \rho_0$ and $\rho_{t=0}^{(1)} = \rho_{t=0}^{(2)} = \rho_{t=0}^{(1,2)} = 0$ from time 0 to T .

This is particularly economical numerically, because the generator of the linear ODE is piecewise constant. We may thus obtain the final state by four successive exponentiation of the generator, corresponding to the evolution before Ω_1 , on $\Omega_1 \setminus \Omega_2$, on $\Omega_1 \cap \Omega_2$ and finally on $\Omega_2 \setminus \Omega_1$ (the evolution for times after Ω_2 is trace-preserving and thus does not need to be computed).

For large Hilbert space dimensions, one does not need to compute the exponential explicitly, but simply its action on the initial state. This can be done efficiently using Krylov subspace methods. We propose an example implementation in an elementary Julia script available at [26] using the QuantumOptics.jl library [27] and the KrylovKit.jl library [28].

For more general filters, when the generator is not piecewise constant, our method remains practical and one may simply solve the time-dependent ODEs (63) to (66) with a high-order Runge-Kutta discretisation.

5. APPLICATION

The main practical application of these calculations is to infer, from n -point correlations given by experimental measurement data, some key parameters appearing in the modelling SME (*e.g.* typical transition frequency in the Hamiltonian H , detection efficiency η or dark count rate θ).

Our formulation enables efficient fitting and optimisation algorithms, based for example on gradient computations via adjoint methods. Moreover, imperfections of the detection chain can be directly included in the model via the filter function f . In the end, this makes the estimation of parameters from realistic experimental correlation functions practical, even for Hilbert space dimensions ~ 100 typically arising in bosonic problems.

ACKNOWLEDGMENTS

This project has received funding from the European Research Council (ERC) under the European Union's Horizon 2020 research and innovation program (grant agreement No. 884762).

REFERENCES

- [1] Howard M. Wiseman and Gerard J. Milburn. **Quantum Measurement and Control**. Cambridge University Press (2009).
- [2] Steven J. Weber, Kater W. Murch, Mollie E. Kimchi-Schwartz, Nicolas Roch, and Irfan Siddiqi. **Quantum trajectories of superconducting qubits**. *Comptes Rendus Physique*, 17.7 (2016).
- [3] Quentin Ficheux, Sébastien Jezouin, Zaki Leghtas, and Benjamin Huard. **Dynamics of a qubit while simultaneously monitoring its relaxation and dephasing**. *Nature Communications*, 9.1 (2018).
- [4] Philippe Campagne-Ibarcq, Pierre Six, Landry Bretheau, Alain Sarlette, Mazyar Mirrahimi, Pierre Rouchon, and Benjamin Huard. **Observing Quantum State Diffusion by Heterodyne Detection of Fluorescence**. *Physical Review X*, 6.1 (2016).
- [5] Pierre Six, Phillipe Campagne-Ibarcq, Landry Bretheau, Benjamin Huard, and Pierre Rouchon. **Parameter estimation from measurements along quantum trajectories**. *2015 54th IEEE Conference on Decision and Control (CDC), IEEE* (2015).
- [6] Alberto Barchielli and Viacheslav P. Belavkin. **Measurements continuous in time and a posteriori states in quantum mechanics**. *Journal of Physics A: Mathematical and General*, 24.7 (1991).
- [7] Alexander N. Korotkov. **Output spectrum of a detector measuring quantum oscillations**. *Physical Review B*, 63.8 (2001).
- [8] Qing Xu, Eliska Greplova, Brian Julsgaard, and Klaus Mølmer. **Correlation functions and conditioned quantum dynamics in photodetection theory**. *Physica Scripta*, 90.12 (2015).
- [9] Lajos Diósi. **Structural features of sequential weak measurements**. *Physical Review A*, 94.1 (2016).
- [10] Andrew N. Jordan, Areeya Chantasri, Pierre Rouchon, and Benjamin Huard. **Anatomy of fluorescence: quantum trajectory statistics from continuously measuring spontaneous emission**. *Quantum Studies: Mathematics and Foundations*, 3.3 (2016).
- [11] Neda Foroozani, Mahdi Naghiloo, Dian Tan, Klaus Mølmer, and Kater W. Murch. **Correlations of the Time Dependent Signal and the State of a Continuously Monitored Quantum System**. *Physical Review Letters*, 116.11 (2016).
- [12] Juan Atalaya, Shay Hacohen-Gourgy, Leigh S. Martin, Irfan Siddiqi, and Alexander N. Korotkov. **Multi-time correlators in continuous measurement of qubit observables**. *Physical Review A*, 97.2 (2018).
- [13] Daniel Hägele and Fabian Schefczik. **Higher-order moments, cumulants, and spectra of continuous quantum noise measurements**. *Physical Review B*, 98.20 (2018).
- [14] Antoine Tilloy. **Exact signal correlators in continuous quantum measurements**. *Physical Review A*, 98.1 (2018).
- [15] Christian Flindt, Tomáš Novotný, Alessandro Braggio, and Antti-Pekka Jauho. **Counting statistics of transport through Coulomb blockade nanostructures: High-order cumulants and non-Markovian effects**. *Physical Review B*, 82.15 (2010).
- [16] Markus Sifft, Annika Kurzmann, Jens Kerski, Rüdiger Schott, Arne Ludwig, Andreas D. Wieck, Axel Lorke, Michael R. Geller, and Daniel Hägele. **Quantum polyspectra for modeling and evaluating quantum transport measurements: A unifying approach to the strong and weak measurement regime**. *Physical Review Research*, 3.3 (2021).
- [17] Gabriel T. Landi, Michael J. Kewming, Mark T. Mitchison, and Patrick P. Potts. **Current fluctuations in open quantum systems: Bridging the gap between quantum continuous measurements and full counting statistics**. *arXiv preprint 2303.04270* (2023).
- [18] Pierre Rouchon. **A tutorial introduction to quantum stochastic master equations based on the qubit/photon system**. *Annual Reviews in Control*, 54 (2022).
- [19] Crispin Gardiner and Peter Zoller. **Quantum noise: a handbook of Markovian and non-Markovian quantum stochastic methods with applications to quantum optics**. Springer Science & Business Media (2004).
- [20] Howard M. Wiseman and Gerard J. Milburn. **Quantum theory of field-quadrature measurements**. *Physical Review A*, 47.1 (1993).
- [21] Kurt Jacobs and Daniel A. Steck. **A straightforward introduction to continuous quantum measurement**. *Contemporary Physics*, 47.5 (2006).
- [22] Stéphane Attal and Yan Pautrat. **From Repeated to Continuous Quantum Interactions**. *Annales Henri Poincaré*, 7.1 (2006).
- [23] Stéphane Attal and Clément Pellegrini. **Stochastic Master Equations in Thermal Environment**. *Open Systems & Information Dynamics*, 17.04 (2010).
- [24] Serge Haroche and Jean-Michel Raimond. **Exploring the Quantum**. Oxford University Press (2006).
- [25] Alberto Barchielli and Matteo Gregoratti. **Quantum Trajectories and Measurements in Continuous Time**. Springer (2009).
- [26] <https://github.com/pierreguilmin/continuous-quantum-measurement-correlations>
- [27] Sebastian Krämer, David Plankensteiner, Laurin Ostermann, and Helmut Ritsch. **QuantumOptics.jl: A Julia framework for simulating open quantum systems**. *Computer Physics Communications*, 227 (2018).
- [28] <https://github.com/Jutho/KrylovKit.jl>