



HAL
open science

Geometric optics expansions for hyperbolic corner problems II: from weak stability to violent instability

Antoine Benoit

► **To cite this version:**

Antoine Benoit. Geometric optics expansions for hyperbolic corner problems II: from weak stability to violent instability. *SIAM Journal on Mathematical Analysis*, In press, 49 (5), pp.3335-3395. 10.1137/16M1060145 . hal-01242899v4

HAL Id: hal-01242899

<https://hal.science/hal-01242899v4>

Submitted on 9 Mar 2017

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

1 **GEOMETRIC OPTICS EXPANSIONS FOR HYPERBOLIC CORNER PROBLEMS II :**
 2 **FROM WEAK STABILITY TO VIOLENT INSTABILITY.**

3 ANTOINE BENOIT*

4 **Abstract.** In this article we are interested in the rigorous construction of geometric optics expansions for weakly well-posed
 5 hyperbolic corner problems. More precisely we focus on the case where selfinteracting phases occur and where one of them is
 6 exactly the phase where the uniform Kreiss-Lopatinskii condition fails. We show that the associated WKB expansion suffers
 7 arbitrarily many amplifications before a fixed finite time. As a consequence, we show that such a corner problem can not be
 8 weakly well-posed even at the price of a huge loss of derivatives. The new result, in that framework, is that the violent instability
 9 (or Hadamard instability) does not come from the degeneracy of the weak Kreiss-Lopatinskii condition, but of the accumulation
 10 of arbitrarily many weak instabilities.

11 **Key words.** hyperbolic corner problems, geometric optics expansions, selfinteraction phases, violent instability

12 **AMS subject classifications.** 35L04, 78A05

13 **1. Introduction.** The main study in this article is the rigorous construction of geometric optics expan-
 14 sions for hyperbolic corner problem that is to say, problems reading :

$$15 \quad (1) \quad \begin{cases} L(\partial)u := \partial_t u + A_1 \partial_1 u + A_2 \partial_2 u = f, & \text{for } x_1, x_2 > 0 \\ B_1 u|_{x_1=0} = g_1, & \text{on } x_1 > 0, \\ B_2 u|_{x_2=0} = g_2, & \text{on } x_2 > 0, \\ u|_{t \leq 0} = 0, \end{cases}$$

16 where the matrices $A_i \in \mathbf{M}_N(\mathbb{R})$ and where $B_i \in \mathbf{M}_{p_i \times N}(\mathbb{R})$ (the values of p_1 and p_2 will be made precise in
 17 Assumption 2).

Under the uniform Kreiss-Lopatinskii condition

$$\ker B_1 \cap E_1^s(\zeta) = \{0\}, \text{ and } \ker B_2 \cap E_2^s(\zeta) = \{0\},$$

18 where the $E_1^s(\zeta)$ and $E_2^s(\zeta)$ are stable subspaces depending of a set of frequency parameters ζ (see Definition
 19 7 for a more precise definition). It is known that the associated initial boundary value problem in the half
 20 space is strongly well-posed (in the sense that we have existence and uniqueness of the solution and that this
 21 solution is as regular (in the L^2 -norm) as the source terms in (1)) if and only if the uniform Kreiss-Lopatinskii
 22 condition is satisfied.

23 The analogous result have not, in the author knowledge, been demonstrated yet for initial boundary value
 24 problems in the quarter space. However the results of [17]-[18] indicate that an extra condition of invertibility
 25 will be needed in the quarter space geometry and thus that imposing the uniform Kreiss-Lopatinskii condition
 26 on each side of the boundary will not be sufficient to ensure strong well-posedness.

27 However even if the well-posedness is not establish for corner problems, the geometric optics expansions
 28 have been studied in [19] and more recently by the author in [3] and [4]. More precisely in [19] the authors give
 29 precious intuitions and some elements of proof about this construction which are used in [3]-[4] to construct
 30 rigorously the expansions.

31
 32 In particular a new phenomenon, proper to the corner problem, has been investigated, the selfinter-
 33 action phenomenon. In more details, this phenomenon induces that some phases in the WKB expansion
 34 can generate themselves after a suitable number of reflections on the sides of the quarter space (see [3]-[4]).
 35 That is to say that some information lying on the side $\{x_1 = 0, x_2 > 0\}$ can be transported towards the side
 36 $\{x_1 > 0, x_2 = 0\}$, be reflected in the phase that send back the information towards $\{x_1 = 0, x_2 > 0\}$ and the
 37 same process is then repeated one more time. However it is possible that during the fourth rebound the
 38 obtained phase is exactly the one that was initially considered. So this phase will be generated several times.
 39 This was not the case for the half space geometry because a reflected phase automatically escapes to infinity.
 40 On one hand, in terms of the geometry of the characteristic variety, such systems contain a rectangle whose
 41 corners are elements of the characteristic variety (with suitable group velocities) and whose side are parallel

*Université Libre de Bruxelles, Département de Mathématiques, boulevard du triomphe 1050 Bruxelles Belgique Project-
 team MEPHYSTO, Inria Lille - Nord Europe 40, avenue Halley, 59650 Villeneuve d'Ascq, France antoine.benoit@inria.fr, .

42 to the axis of the frequency space. On the other hand, in terms of the resolution of the WKB cascade, a new
 43 amplitude equation, whose provenance is intrinsically linked with the uniform Kreiss-Lopatinskii condition
 44 has to be solved to initialize the resolution of the cascade.

45

We are here interested in corner problems whose, one of the boundary condition, to fix the ideas, let
 us say B_1 , does not satisfy the uniform Kreiss-Lopatinskii condition that is that there exists at least one
 frequency parameter $\underline{\zeta}$ such that:

$$\ker B_1 \cap E_1^s(\underline{\zeta}) \neq \{0\}.$$

46 The other boundary condition is assumed to be as convenient as necessary, that is it satisfies the uniform
 47 Kreiss-Lopatinskii condition or even it is strictly dissipative see [6]. The litterature about the hyperbolic
 48 boundary value problem in the half space tells us that such problems can not be strongly well-posed because
 49 of the failure of the uniform Kreiss-Lopatinskii condition. However they can be weakly well-posed in the
 50 sense that we still have existence and uniqueness but that the solution of (1) is now less regular than the
 51 sources terms in (1). We also say that the solution suffers losses of derivatives.

52

The number of losses depends on the particular structure of $E_1^s(\underline{\zeta})$ at the considered $\underline{\zeta}$. There are four
 53 possible kinds of degeneracy of the uniform Kreiss-Lopatinskii condition relying on the structure of $E_1^s(\underline{\zeta})$
 54 at the frequency where the uniform Kreiss-Lopatinskii condition breaks down (see Definition 4). Namely, the
 55 degeneracies of the uniform Kreiss-Lopatinskii condition can occur in the so-called hyperbolic, elliptic, mixed
 56 or glancing regions. In terms of geometric optics expansions hyperbolic modes are associated to transport
 57 phenomenon whereas elliptic ones are associated to boundary layers.

58

Concerning boundary value problems in the half space for which the uniform Kreiss-Lopatinskii condition
 59 is violated, the construction of the associated geometric optics expansions has already been made in all but
 60 the glancing region. We refer to [8] for the construction when the degeneracy takes place in the hyperbolic
 61 region and to [2] and [14] for the construction associated to a degeneracy in the elliptic or in the mixed region.
 62 With this expansions it is then possible to saturate the energy estimates for the solution of (1) and to show
 63 that the obtained losses in the litterature are sharp.

64

We will here focus our attention on a degeneracy of the uniform Kreiss-Lopatinskii condition in the
 65 hyperbolic region, and thus for a frequency that induce a transport phenomenon. Such problems are refer as
 66 the *WR* class in the sense of [5]. Some conjectures about the behaviours of the geometric optics expansions
 67 when the degeneracy of the uniform Kreiss-Lopatinskii condition occurs in the elliptic or in the mixed region
 68 can be found in Section 9.

69

In [8], the authors construct the geometric optics expansions for such *WR* problems in the half space and
 show that if the source terms are of order one compared to the small parameter ε which encodes the high
 oscillating behaviour, then the leading term in the geometric optics expansion is of order zero compared to
 ε . Then, they used this construction to show that the energy estimate with losses of derivatives established
 by [7]:

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\Omega_T)}^2 \leq C_T \left(\|f\|_{L^2_{x_1}(H^1(\partial\Omega_{1,T}))}^2 + \|g|_{x_1=0}\|_{(H^1(\partial\Omega_{1,T}))}^2 \right),$$

71 is sharp in terms of losses of derivatives.

72

Concerning corner problems, the litterature is much more poor. Indeed, as already mentionned the full
 74 characterization of strongly well-posed problems is, to our knowledge, not achieved yet. So, the full charac-
 75 terization of weakly well-posed corner problems seems, in the author opinion, to be a long range problem. As
 76 a consequence the fact that we construct the geometric optics expansions for these (expected to be) weakly
 77 well-posed problems can be seen as a "Majda's project" (see [1] and [13]). That is to say, that the author
 78 believes that the use of geometric optics expansions can give some intuition about what can be the good
 79 number of losses of derivatives in the associated corner problems.

80

In this article, we will focus our attention on the particular case of corner problems in the *WR* where the
 82 frequency of degeneracy is one of the selfinteracting phases. Our purpose is thus to construct the geometric
 83 optics expansion for such a corner problem. As we will see in Section 7, for any arbitrarily large $M \in \mathbb{N}$, the
 84 fact that the phase for which the uniform Kreiss-Lopatinskii condition breaks down is generated an arbitrarily
 85 number of times will imply a leading term in the geometric optics expansion of order zero, compared with

86 the small parameter ε , when one considers a source term on the boundary $\{x_1 = 0\}$ of order $M+1$ in terms of ε .
87

88 Using this geometric optics expansion, we will show that such a corner problem can not be weakly well-
89 posed on a finite interval of time because it loses an arbitrarily large number of derivatives before the time
90 T . In terms of losses of derivatives, it is the worst case that we can imagine because we have a violent or
91 Hadamard's instability.
92

93 The paper is organized as follows : in Section 2, we precise the terms of the previous discussion on an
94 example. The analysis made in Section 2 is purely formal and aims to illustrate the amplification and the
95 self-interaction phenomenons. Then Section 3 gives some classical definitions and introduce some notations.
96 In Section 4 we give a formal study of our problem and we describe what are the expected phases and the
97 associated amplitudes in the WKB expansion. Then in Section 6, we give a general framework in which the
98 previous formal discussion becomes rigorous. This section uses the same tools as these introduced in [4] to
99 describe, with precision, the set of expected phases in the WKB expansion. However, we believe that it is
100 important to recall these tools for the sake of completeness.

101 Section 7 is devoted to the construction of the geometric optics expansion and is the main section of
102 the paper. The most difficult part of the construction is to find a way to initialize the resolution of the
103 WKB cascade of equations. Indeed in [4] a new amplitude equation whose resolution permits to initialize
104 the WKB expansion was derived from the uniform Kreiss-Lopatinskii condition. However the obtention of
105 this new equation is intrinsically linked with the uniform Kreiss-Lopatinskii condition. As a consequence to
106 initialize the resolution of the WKB cascade when the uniform Kreiss-Lopatinskii condition degenerates, we
107 need a new amplitude equation. This equation comes from an adaptation of the method described in [8]. The
108 hardest point to handle with is that in [8], due to the "nice" geometry of the half space, it was possible to
109 determine all the outgoing phases (which act as source terms in the equation determining the amplitude for
110 which the uniform Kreiss-Lopatinskii breaks down) before all the others. However, this is not true anymore
111 in the quarter space geometry. But we found a new equation for the initialization of the WKB, which one
112 is given in paragraph 7.1. The resolution of this equation is made in subparagraphs 7.1.4 and 7.1.6. The
113 resolution is made after a "necessary" reformulation of this equation, in view to show that this equation can
114 in fact be rewritten under the particular form $(I - \mathbb{T})u = G$, for some operator \mathbb{T} . This rewriting is made in
115 paragraph 7.1.2.¹
116

117 Section 8 contains the proof of our main result, that is that a corner problem in the WR class for one
118 side which admits a loop in the section of its characteristic variety and for which one of the element of the
119 loop violates the uniform Kreiss-Lopatinskii condition can not be even weakly well-posed. It is not really a
120 positive result because it tells us that, in such a framework, there is no hope to solve the corner problem.
121 However, the author believes that this result is interesting in itself because it gives the first examples, in
122 our knowledge, of ill-posed hyperbolic boundary value problems for which the ill-posedness is due to the
123 accumulation of weak instabilities and not to the failure of the weak Kreiss-Lopatinskii condition. Moreover
124 the instability phenomenon in this framework is much more subtle.
125

126 At last, Section 9 gives examples of such ill-posed corner problems and some (more optimistic) conjectures
127 about what should be the leading order sizes (and so the number of losses of derivatives) in the more favorable
128 cases where the uniform Kreiss-Lopatinskii condition breaks down outside the loop.

129 **2. Example and formal discussion.** We start this an illustrative example. We consider the following
130 corner problem:

$$131 \quad (2) \quad \begin{cases} L(\partial)u^\varepsilon := \partial_t u^\varepsilon + A_1 \partial_1 u^\varepsilon + A_2 \partial_2 u^\varepsilon = 0, & \text{for } x_1, x_2 > 0, \\ B_1 u^\varepsilon|_{x_1=0} = \varepsilon g^\varepsilon, & \text{for } x_1 = 0, \\ B_2 u^\varepsilon|_{x_2=0} = 0, & \text{for } x_2 = 0, \\ u^\varepsilon|_{t \leq 0} = 0, & \text{for } x_1, x_2 > 0, \end{cases}$$

¹Let us note that the particular structure $(I - \mathbb{T})u = G$ was already the structure obtained in [4]. Moreover, this structure will be very important in the following proof because it permits to write the solution u as the sum of compositions of \mathbb{T} and thus to express the solution u in terms of the sum of wave packets.

where the coefficients in the interior are given by

$$A_1 := \begin{bmatrix} 0 & \sqrt{5} & 0 \\ \sqrt{5} & -4 & 0 \\ 0 & 0 & -\frac{5}{7} \end{bmatrix}, \text{ and } A_2 := \begin{bmatrix} -1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}.$$

And where the boundary matrices are given by:

$$B_1 := [-\sqrt{5} \quad \frac{7}{3} \quad 1], \text{ and } B_2 := \begin{bmatrix} -\frac{1}{\sqrt{5}} & 1 & 0 \\ -\frac{1}{\sqrt{5}} & 0 & 1 \end{bmatrix}.$$

132 The source term $g^\varepsilon(t, x_2) := e^{\frac{i}{\varepsilon}(t-8x_2)}g(t, x_2)$, where g is zero for negative times and is also zero for all
133 $x_2 \leq 1$.

134

Let \mathcal{L} be the symbol of $L(\partial)$ it is defined for all $(\tau, \xi_1, \xi_2) \in \mathbb{R}^3$ by:

$$\mathcal{L}(\tau, \xi_1, \xi_2) := \tau I + \xi_1 A_1 + \xi_2 A_2.$$

It what follows it will be convenient to introduce the characteristic variety of $L(\partial)$, that is:

$$V := \{(\tau, \xi_1, \xi_2) \in \mathbb{R}^3 \mid \det \mathcal{L}(\tau, \xi_1, \xi_2) = 0\},$$

and as the time frequency in g^ε will be constant equals to one, we introduce $\mathbf{V} := V \cap \{\tau := 1\}$. The section \mathbf{V} is given by:

$$V_{\{\tau=1\}} = \left\{ (\xi_1, \xi_2) \in \mathbb{R}^2 \setminus \left(1 - \frac{5}{7}\xi_1 + \xi_2 \right) (1 - 4\xi_1 + 4\xi_1\xi_2 - 5\xi_1^2 - \xi_2^2) = 0 \right\},$$

135 and is composed of an ellipse and a line (see Figure 1).

136

137 The aim of the following paragraph is to give a formal discussion based on the explicit example (2)
138 illustrating the phenomenon of repetition of the instabilities mentioned in the introduction. The remaining
139 of the article aims to give a rigorous justification of this formal discussion.

140

141 The corner problem (2) is hyperbolic so it has a finite speed of propagation. As a consequence the
142 information supported by g^ε can not hit immediately the boundary $\{x_2 = 0\}$. So in a very formal way, we
143 will forget the quarter space geometry and work in the half space $\{x_1 \geq 0, x_2 \in \mathbb{R}\}$. The problem now reads:

144

$$145 \quad (3) \quad \begin{cases} \partial_t u^\varepsilon + A_1 \partial_1 u^\varepsilon + A_2 \partial_2 u^\varepsilon = 0, & \text{for } x_1 \in \mathbb{R}_+, x_2 \in \mathbb{R}, \\ B_1 u^\varepsilon|_{x_1=0} = \varepsilon g^\varepsilon, & \text{for } x_1 = 0, x_2 \in \mathbb{R}, \\ u^\varepsilon|_{t \leq 0} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \end{cases}$$

146 and we are looking for an approximation solution of (3) via a WKB expansion.

147 We thus postulate exactly the same ansatz as in the half space:

$$148 \quad (4) \quad u^\varepsilon \sim \sum_{n \geq 0} e^{\frac{i}{\varepsilon}\varphi_1(t,x)} \varepsilon^n u_{1,n} + \sum_{n \geq 0} e^{\frac{i}{\varepsilon}\varphi_4(t,x)} \varepsilon^n u_{4,n} + \sum_{n \geq 0} e^{\frac{i}{\varepsilon}\varphi_0(t,x)} \varepsilon^n u_{0,n},$$

149 where the phases functions, φ_0 , φ_1 and φ_4 are given by: In particular, we remark that there is a loop
150 with phases $\varphi_1, \dots, \varphi_4$ defined by:

$$151 \quad \varphi_0(t, x) := t - \frac{49}{5}x_1 - 8x_2, \quad \varphi_1(t, x) := t - \frac{21}{5}x_1 - 8x_2, \quad \text{and } \varphi_4(t, x) := t - 3x_1 - 8x_2,$$

152 and we remark that the points $(-\frac{49}{5}, -8)$, $(-\frac{21}{5}, -8)$ and $(-3, -8)$ are the three points of intersection between
153 \mathbf{V} and the line $\{\xi_2 = 8\}$.

154 Plugging the ansatz (4) in the boundary value problem in the half space (3) gives the cascade of equations
155 in the interior:

$$156 \quad (5) \quad \begin{cases} \mathcal{L}(d\varphi_k)u_{0,k} = 0, & \text{for } k \in \{0, 1, 4\}, \\ i\mathcal{L}(d\varphi_k)u_{n+1,k} + L(\partial)u_{n,k} = 0, & \forall n \in \mathbb{N}, k \in \{0, 1, 4\}, \end{cases}$$

157 the boundary conditions:

$$158 \quad (6) \quad B_1 \left[\sum_{k \in \{0,1,4\}} u_{n,k} \right]_{|x_1=0} = \delta_{n,1}g, \quad \forall n \in \mathbb{N},$$

159 and finally the initial conditions:

$$160 \quad (7) \quad u_{n,k}|_{x_1=0} = 0, \quad \forall n \in \mathbb{N}, k \in \{0, 1, 4\}.$$

161 The first equation of (5) implies that $u_{0,k} \in \ker \mathcal{L}(d\varphi_k)$, $k \in \{0, 1, 4\}$ (recall that by definition of φ_k this
162 kernel is non-trivial). This is the so-called polarization condition.

We introduce P^k the projector upon $\ker \mathcal{L}(d\varphi_k)$ and Q^k the projector on $A_1 \ker \mathcal{L}(d\varphi_k)$ (we will not give
a precise definition of this projectors here, we refer to Definition 25). We have $\ker Q^k = \text{Ran } \mathcal{L}(d\varphi_k)$. Thus
multiplying the second equation of (5) written for $n = 1$ and using the polarization condition $P^k u_{0,k} = u_{0,k}$
we obtain:

$$Q^k L(\partial)P^k u_{0,k} = 0.$$

163 We can then use Lax's lemma [11] which establishes that the previous equation is in fact a transport equation,
164 that is:

$$165 \quad (8) \quad (\partial_t + v_k \cdot \nabla_x)u_{0,k} = 0,$$

166 where the velocity of the transport v_k is the so-called group velocity. Note that the group velocity is by
167 definition (see Definition 5) olinear to the inner normal to \mathbf{V} computed at (ξ_1^k, ξ_2^k) (where (ξ_1^k, ξ_2^k) is the
168 spatial frequency of φ_k).

169 We have easily:

$$170 \quad (9) \quad v_0 := \begin{bmatrix} -\frac{5}{7} \\ 1 \end{bmatrix}, \quad v_1 := \begin{bmatrix} 3 \\ -\frac{2}{5} \end{bmatrix}, \quad \text{and } v_4 := \begin{bmatrix} -\frac{5}{7} \\ 1 \end{bmatrix},$$

171 The interesting point here is that the first component of v_1 is strictly positive while the second component
172 of each v_0 and v_4 are strictly negative. As a consequence, for $k = 1$ the transport in (12) goes from the
173 boundary to the interior and it is thus needed to know the value of $u_{0,1}$ at the boundary. But for $k = 0, 4$
174 the transport in (12) goes from the interior to the boundary and consequently no boundary condition have
175 to be imposed on the boundary.

176 From this observation we deduce that for $k = 0, 4$, $u_{0,k}$ solves the homogeneous transport equation:

$$177 \quad (10) \quad \begin{cases} (\partial_t + v_k \cdot \nabla_x)u_{0,k} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \\ u_{0,k}|_{t \leq 0} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \end{cases}$$

178 and we thus have: $u_{0,k} \equiv 0$ for $k = 0, 4$ and it only remains to determine $u_{0,1}$. To do this we need to know
179 its trace on $\{x_1 = 0\}$. To determine this trace we use the boundary condition (6) which reads:

$$180 \quad (11) \quad B_1 u_{0,1}|_{x_1=0} = 0.$$

However there is an issue. Indeed, from the polarization condition we can write $u_{0,1} = \nu e$ where e is a generator
of $\ker \mathcal{L}(1, -\frac{21}{5}, -8)$. An easy computation gives:

$$e := \begin{bmatrix} \frac{7}{3} \\ \sqrt{5} \\ 0 \end{bmatrix},$$

181 and we remark that $B_1 e = 0$. As a consequence $\ker \mathcal{L}(1, -\frac{21}{5}, -8) \cap \ker B_1 = \text{vect} \{e\}$, the boundary condition
 182 (11) is trivially satisfied and does not give any information about $u_{0,1}|_{x_1=0}$. It is this situation that we referred
 183 to the failure of the uniform Kreiss-Lopatinskii condition in the introduction, more precisely as this failure
 184 happens for a phase with real values we say that we are in the WR class.
 185

To obtain the value of $u_{0,1}|_{x_1=0}$ we study the only other equation in which $u_{0,1}|_{x_1=0}$ appears that is the
 boundary condition (6) written for $n = 1$:

$$B_1 u_{1,1}|_{x_1=0} = g - B_1 \left[\sum_{k \in \{0,4\}} u_{1,k} \right]_{|x_1=0},$$

in which we make the decomposition $u_{1,k} = P^k u_{1,k} + (1 - P^k) u_{1,k}$ to obtain:

$$B_1 P^1 u_{1,1}|_{x_1=0} = g - B_1 \left[\sum_{k \in \{0,4\}} P^k u_{1,k} + \sum_{k \in \{0,4\}} (I - P^k) u_{1,k} \right]_{|x_1=0} - B_1 (I - P^1) u_{1,1}|_{x_1=0},$$

186 and recall that the left hand side is zero.

To make this equation more explicit we first determine the $(I - P^k) u_{1,k}$, that is the unpolarized part.
 To do this we introduce the pseudo-inverse characterized by:

$$R^k \mathcal{L}(d\varphi_k) = I - P^k, \text{ and } P^k R^k = R^k Q^k = 0,$$

and we compose the second equation of the cascade (5) written for $n = 0$ by R^k . It follows:

$$(I - P^k) u_{1,k} = i R^k L(\partial) u_{0,k}.$$

187 In particular for $k = 0, 4$ (recall that $u_{0,k} \equiv 0$) we obtain that $(I - P^k) u_{1,k} \equiv 0$. To determine $P^k u_{1,k}$ we use
 188 again Lax's lemma to show that the polarized part satisfies the transport equation:

$$189 \quad (12) \quad \begin{cases} (\partial_t + v_k \cdot \nabla_x) Q^k P^k u_{1,k} = -Q^k L(\partial) (I - P^k) u_{1,k} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \\ P^k u_{1,k}|_{t \leq 0} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \end{cases}$$

which implies that $P^k u_{1,k} \equiv 0$ for $k = 0, 4$. So the boundary condition of order one in fact reads:

$$(B_1 R^1 L(\partial) u_{0,1})_{|x_1=0} = -ig.$$

190 And with the notation $u_{0,1}(t,x) = \nu(t,x)e$ we obtain:

$$191 \quad (13) \quad (R^1 e \partial_t \nu + R^1 A_1 e \partial_1 \nu + R^1 A_2 e \partial_2 \nu)_{|x_1=0} = -ig,$$

which is a transport equation in ν . However to solve (13) we have to make its coefficients more explicit.
 After some computations we obtain:

$$P^1 = \begin{bmatrix} \frac{7}{2} & \frac{7}{6}\sqrt{5} & 0 \\ -\frac{3}{2}\sqrt{5} & -\frac{5}{2} & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad Q^1 = \begin{bmatrix} \frac{7}{2} & -\frac{3}{2}\sqrt{5} & 0 \\ \frac{7}{6}\sqrt{5} & -\frac{5}{2} & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad \text{and } R^1 = \begin{bmatrix} \frac{25}{36} & \frac{5}{12}\sqrt{5} & 0 \\ \frac{5}{12}\sqrt{5} & \frac{5}{4} & 0 \\ 0 & 0 & -\frac{1}{7} \end{bmatrix}.$$

And consequently:

$$B_1 R^1 e = \frac{16}{9} \frac{5}{6} \sqrt{5}, \quad B_1 R^1 A_2 e = \frac{2}{9} \frac{5}{6} \sqrt{5} \text{ and } B_1 R^1 A_1 e = 0.$$

192 The transport equation (13) in its final form reads:

$$193 \quad (14) \quad \begin{cases} \left(\partial_t + \frac{1}{8} \partial_2 \right) \nu|_{x_1=0} = -\frac{27}{40\sqrt{5}} ig, & \text{for } (t, x_2) \in \mathbb{R}^2, \\ \nu|_{x_1=0}|_{t \leq 0} = 0, & \text{for } x_2 \in \mathbb{R}, \end{cases}$$

194 and we can solve this equation by integration along the characteristics to obtain the value of $\nu|_{x_1=0}$ and then
 195 integrate along the characteristics the transport equation for $u_{0,1}$:

$$196 \quad (15) \quad \begin{cases} (\partial_t + v_1 \cdot \nabla_x)u_{0,1} = 0, & \text{for } (t, x_1, x_2) \in \mathbb{R} \times \mathbb{R}_+ \times \mathbb{R}, \\ u_{0,1}|_{x_1=0} = \nu|_{x_1=0}e, & \text{for } (t, x_2) \in \mathbb{R}^2, \\ u_{0,1}|_{t \leq 0} & \text{for } (x_1, x_2) \in \mathbb{R} \times \mathbb{R}_+, \end{cases}$$

197 to obtain the value of $u_{0,1}$.

198

199 An important remark is that from (14), the leading order term $u_{0,1}$ is not zero. But one have to recall
 200 that in (3) the source term on the boundary $\{x_1 = 0\}$ is of order one compared to ε . As a consequence,
 201 the leading order of the WKB expansion is of order zero for a source term of order one. It is exactly the
 202 amplification phenomenon that we introduced in the introduction. An other remark is that the coefficient in
 203 front of the x_2 -derivative in (14) is nothing but $\frac{1}{\varepsilon^2}$.

204

205 Then we study the behaviour of the amplitude $u_{0,1}$ as v_1 as a negative second component, the transported
 206 information hits the boundary $\{x_2 = 0\}$ after some times. When its happens we formally consider (recall that
 207 $u_{0,1}|_{x_2=0}$ has its support away from $x_1 = 0$) the boundary value problem in the half space $\{x_1 \in \mathbb{R}, x_2 \geq 0\}$
 208 whose information on the boundary has been turned on by $u_{0,1}$:

$$209 \quad (16) \quad \begin{cases} \partial_t u^\varepsilon + A_1 \partial_1 u^\varepsilon + A_2 \partial_2 u^\varepsilon = 0, & \text{for } x_1 \in \mathbb{R}, x_2 \in \mathbb{R}_+, \\ B_2 u^\varepsilon|_{x_2=0} = -B_2 u_{0,1}|_{x_2=0}, & \text{for } x_2 = 0, x_1 \in \mathbb{R}, \\ u^\varepsilon|_{t \leq 0} = 0, & \text{for } x_1 \in \mathbb{R}, x_2 \in \mathbb{R}_+, \end{cases}$$

and we thus add in the ansatz (4) the amplitudes $u_{n,2}$ associated to the phase φ_2 defined by:

$$\varphi_2(t, x) := t - \frac{21}{5}x_1 - 4x_2.$$

And the amplitude $u_{n,5}$ associated to the phase φ_5 defined by:

$$\varphi_5(t, x) := t - \frac{21}{5}x_1 - \frac{44}{5}x_2.$$

This new phases correspond to the intersection of \mathbf{V} with the line $\{\xi_1 = -\frac{21}{5}\}$. Note that the group velocity
 for the phase φ_2 is given by:

$$v_2 := \begin{bmatrix} -\frac{5}{7} \\ 1 \end{bmatrix},$$

210 while the group velocity v_5 has both its components positive. From Lax's lemma we have to solve the
 211 transport equation:

$$212 \quad (17) \quad \begin{cases} (\partial_t + v_2 \cdot \nabla_x)Q^2 P^2 u_{0,2} = 0, & \text{for } x_2 > 0, x_1 \in \mathbb{R}, \\ B_2 [u_{0,2} + u_{0,5}]|_{x_2=0} = -B_2 u_{0,1}|_{x_2=0}, & \text{for } x_2 = 0, x_1 \in \mathbb{R}, \\ P^2 u_{0,2}|_{t \leq 0} = 0, & \text{for } x_2 > 0, x_1 \in \mathbb{R}, \end{cases}$$

to determine $u_{0,2}$. However, this time we have $\ker \mathcal{L}(1, -\frac{21}{5}, -4) = \text{vect}\{e_2\}$ and $\ker \mathcal{L}(1, -\frac{21}{5}, -\frac{44}{5}) = \text{vect}\{e_5\}$ with

$$e_2 := \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix}, \text{ and } e_5 := \begin{bmatrix} \sqrt{5} \\ \frac{7}{3} \\ 0 \end{bmatrix},$$

and we remark that the matrix B_2 restricted to $\text{vect}\{e_2, e_5\}$ is invertible. This is the uniform Kreiss-
 Lopatinskii condition mentioned in the introduction. More precisely this inverse is given by:

$$\phi^2 := \begin{bmatrix} \frac{3}{7}\sqrt{5} & 0 \\ 1 & 0 \\ 0 & 1 \end{bmatrix},$$

213 So we can apply ϕ^2 in the boundary condition and project upon $\ker \mathcal{L}(1, -\frac{21}{5}, -4)$ to obtain the value of the
 214 trace of $u_{0,2}|_{x_2=0}$. This permits to solve (17) by integration along the characteristics to determine $u_{0,2}$. The
 215 determination of $u_{0,5}$ is similar and will not be describe here.
 216

We now repeat the same process, the group velocity v_5 has both its components positive, so when one
 solves the associated transport equation, the transported information spreads to infinity. It will never hits the
 boundary $\{x_1 = 0\}$, will never be reflected and consequently it will never creates a new phase by reflection.
 However the information carried by $u_{0,2}$ will hits the boundary $\{x_1 = 0\}$ and it will be reflected in a new
 amplitude. To determine this new amplitude we consider again the boundary value problem in the half space
 $\{x_1 \geq 0, x_2 \in \mathbb{R}\}$ and we add in the ansatz (4) the amplitudes $u_{n,3}$ associated to the phase φ_3 defined by:

$$\varphi_3(t, x) := t - 3x_1 - 4x_2,$$

with group velocity:

$$v_3 := \begin{bmatrix} 5 \\ -2 \end{bmatrix}.$$

217

$$218 \quad (18) \quad \varphi_4(t, x) := t - 3x_1 - 8x_2, \quad v_2 := \begin{bmatrix} 5 \\ -2 \end{bmatrix}.$$

219 To determine $u_{0,3}$ we have to solve the transport equation:

$$220 \quad (19) \quad \begin{cases} (\partial_t + v_3 \cdot \nabla_x) Q^3 P^3 u_{0,2} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \\ B_1 u_{0,3}|_{x_1=0} = -B_1 u_{0,2}|_{x_1=0}, & \text{for } x_1 = 0, x_2 \in \mathbb{R}, \\ P^3 u_{0,2}|_{t \leq 0} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \end{cases}$$

221 and we remark that compared to (12), this time $B_1 e_3$, where e_3 is a generator of $\ker \mathcal{L}(1, -3, -4)$ is not zero.
 222 As a consequence from the uniform Kreiss-Lopatinskii condition we can invert B_1 in the boundary condition
 223 of (19) to obtain the value of $u_{0,3}|_{x_1=0}$ and solve (19). An important remark is that this time the amplitude
 224 $u_{0,3}$ is not amplified and remains of order $O(1)$ compared with ε .

The information transported by (19) will hit the boundary $\{x_2 = 0\}$ so it leads us to study the boundary
 value problem in the half space $\{x_1 \in \mathbb{R}, x_2 \geq 0\}$ whose source term on the boundary has been turned on by
 the amplitude $u_{0,3}$. So we add in the ansatz the amplitudes for the phases associated to the intersections
 between \mathbf{V} and the line $\{\xi_1 = -3\}$ that is:

$$\varphi_6(t, x) := t - 3x_1 - \frac{22}{7}x_2,$$

and φ_4 . It is interesting to remark that even if the amplitude $u_{0,4}$ has been initially removed of the ansatz
 (because it was initially zero) nothing prevent that this amplitude has to be considered after several rebounds.
 To dedetermine $u_{0,4}$ we have to solve a transport equation and to do this we need the value of $u_{0,4}|_{x_2=0}$. Once
 again we remark that $\ker \mathcal{L}(1, -3, -8) = \text{vect}\{e_4\}$ and $\ker \mathcal{L}(1, -3, -\frac{22}{7}) = \text{vect}\{e_6\}$, with

$$e_4 := \begin{bmatrix} \sqrt{5} \\ 3 \\ 0 \end{bmatrix}, \quad \text{and} \quad e_6 := \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix},$$

and consequently by the uniform Kreiss-Lopatinskii condition, the matrix B_2 restricted to $\text{vect}_4, e_6\}$ is
 invertible. The inverse is given by:

$$\phi^4 := \begin{bmatrix} \frac{1}{3}\sqrt{5} & 0 \\ 1 & 0 \\ 0 & 1 \end{bmatrix},$$

225 which permits to determine the traces $u_{0,4}|_{x_2=0}$ and to solve the associated transport equation. The trans-
 226 ported information will hit the side $\{x_1 = 0, x_2 \in \mathbb{R}\}$ and we have to determine its rebounds. To do this we
 227 add in the ansatz (4) the phases associated to the intersection point between \mathbf{V} and the line $\{\xi_2 = -8\}$.
 228

It is there interesting to remark that one of these points gives exactly the phase φ_1 . As a consequence, the associated amplitude is generated a second time. This phenomenon is referred to selfinteraction phenomenon because it means that some phases can regenerated themselves after a suitable number of rebounds. We thus consider the boundary value problem in the half space $\{x_1 \geq 0, x_2 \in \mathbb{R}\}$ whose source term on the boundary as been turned on by the amplitude $u_{0,4}$ and we add in the ansatz (4) a new contribution for the phase φ_1 . The ansatz now reads:

$$u^\varepsilon \sim \sum_{n \geq 0} \sum_{k=1}^6 e^{\frac{i}{\varepsilon} \varphi_k(t,x)} \varepsilon^n u_{n,k} + \sum_{n \geq -1} e^{\frac{i}{\varepsilon} \varphi_1(t,x)} \varepsilon^n \tilde{u}_{n,1}.$$

229 To determine the new amplitude $\tilde{u}_{-1,1}$ we again apply Lax's lemma which leads us to solve the transport
230 equation:

$$231 \quad (20) \quad \begin{cases} (\partial_t + v_1 \cdot \nabla_x) \tilde{u}_{0,1} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}, \\ \tilde{u}_{0,1}|_{t \leq 0} = 0, & \text{for } x_1 > 0, x_2 \in \mathbb{R}. \end{cases}$$

232 Once again to solve this equation it is needed to determine first the value of the trace $\tilde{u}_{-1,1}|_{x_1=0}$. To do
233 this we reiterate the computations made for $u_{0,1}$. That is we consider the equation for $\tilde{u}_{0,1}|_{x_1=0}$. We thus
234 obtain that $\tilde{u}_{-1,1}|_{x_1=0}$ solves the transport equation (14) but with a source term depending on $u_{0,4}|_{x_1=0}$ and
235 consequently the amplitude $\tilde{u}_{-1,1}$ is not zero. So we obtain that the leading order in the WKB expansion is
236 now of order $O(\varepsilon^{-1})$ while the source term on the boundary g^ε is of order $O(\varepsilon)$. There are consequently two
237 amplifications in the WKB expansion.

238

239 Then we can reiterate exactly the same computations to determine the new amplitudes $\tilde{u}_{-1,k}$, $k = 2, \dots, 4$.
240 They do not suffer any amplification due to the Kreiss-Lopatinskii condition, but when one study the rebound
241 of $\tilde{u}_{-1,4}$. The phase φ_1 is generated again, this induce a new amplification and one has to add in the ansatz
242 a term of order $O(\varepsilon^{-2})$ and so on. This process can be repeating an arbitratly number of times to obtain a
243 WKB expansion with M amplifications where M is arbitrarily large.

244

245 Of course the previous discussion is totally formal. Indeed, at each step of the computations we restrict
246 ourselves to boundary value problems in the half space and we are not considering boundary value problems
247 in the quarter space as we should. However this discussion has the advantage of simplicity and illustrates the
expected phenomenons. The aim of what follows is to give a rigorous justification of this formal analysis.




FIG. 1. The characteristic variety for the corner problem (2).

248

249 **3. Notations and assumptions.**

250 **3.1. About the operator $L(\partial)$.** Let

251
$$\Omega := \{(x_1, x_2) \in \mathbb{R}^2 \mid x_1 \geq 0, x_2 \geq 0\}, \partial\Omega_1 := \Omega \cap \{x_1 = 0\}, \text{ and } \partial\Omega_2 := \Omega \cap \{x_2 = 0\},$$

252 be the quarter space and both of its edges. For $T > 0$, we will denote:

253
$$\Omega_T :=]-\infty, T] \times \Omega, \partial\Omega_{1,T} :=]-\infty, T] \times \partial\Omega_1, \text{ and } \partial\Omega_{2,T} :=]-\infty, T] \times \partial\Omega_2.$$

254 Hereof \mathcal{L} will be the symbol of the differential operator $L(\partial)$. It is defined for $\tau \in \mathbb{R}$ and $\xi \in \mathbb{R}^2$ by:

255
$$\mathcal{L}(\tau, \xi) := \tau I + \sum_{j=1}^2 \xi_j A_j.$$

256 The characteristic variety V of $L(\partial)$ is thus given by:

257
$$V := \{(\tau, \xi) \in \mathbb{R} \times \mathbb{R}^2 \mid \det \mathcal{L}(\tau, \xi) = 0\}.$$

258 In this article we choose to restrict our subject, in view to save some notations, to strictly hyperbolic oper-
 259 ators. The following constructions of the geometric optics expansions should also operate in the framework
 260 of constantly hyperbolic operators. However this simplifying assumption will make the analysis of Section 5
 261 slightly easier. We will give in the core of the proof some comments about the expected modifications about
 262 the proof for constantly hyperbolic operators. We thus assume the following property on $L(\partial)$:

263 *Hypothesis 1.* There exist N real valued functions, denoted by λ_j , analytic on $\mathbb{R}^2 \setminus \{0\}$ such that:

264
$$\forall \xi \in \mathbb{S}^1, \det \mathcal{L}(\tau, \xi) = \prod_{j=1}^N (\tau + \lambda_j(\xi)),$$

265 where the eigenvalues $\lambda_j(\xi)$ satisfy $\lambda_1(\xi) < \dots < \lambda_N(\xi)$.

266 We also assume that the boundary of Ω is non-characteristic, and that the matrices B_1 and B_2 induce the
 267 good number of boundary conditions, that is to say :

268 *Hypothesis 2.* The matrices A_1, A_2 are invertible. Moreover p_1 (resp. p_2), the number of lines of B_1
 269 (resp. B_2), equals the number of strictly positive eigenvalues of A_1 (resp. A_2). At last B_1 and B_2 are
 270 assumed to be of maximal rank.

271 One can easily convince himself that they are effectively the good number of conditions by considering the
 272 case $d = 1$ in which (1) is equivalent to solve N scalar transport equations.

273 Under Hypothesis 2, we can define the resolvent matrices with are obtained by taking the Laplace
 274 transform of the evolution equation of (1) and Fourier transform in one of the space variable:

275
$$\mathcal{A}_1(\zeta) := -A_1^{-1}(\sigma I + i\eta A_2) \text{ and } \mathcal{A}_2(\zeta) := -A_2^{-1}(\sigma I + i\eta A_1),$$

276 where ζ denotes an element of the frequency space :

277
$$\Xi := \{\zeta := (\sigma = \gamma + i\tau, \eta) \in \mathbb{C} \times \mathbb{R}, \gamma \geq 0\} \setminus \{(0, 0)\}.$$

For convenience, we also introduce Ξ_0 the boundary of Ξ :

$$\Xi_0 := \Xi \cap \{\gamma = 0\}.$$

and the notation :

$$\text{for } j = 1, 2, \zeta_j := (\sigma, \xi_{3-j}),$$

278 For $j = 1, 2, \zeta_j \in (\Xi \setminus \Xi_0)$, we denote by $E_j^s(\zeta_j)$ the stable subspace of $\mathcal{A}_j(\zeta_j)$ and $E_j^u(\zeta_j)$ its unstable
 279 subspace. These spaces are well-defined according to [9]. For all $\zeta_j \in (\Xi \setminus \Xi_0)$, the stable subspace $E_j^s(\zeta_j)$
 280 has dimension p_j , while the space $E_j^u(\zeta_j)$ has dimension $N - p_j$. Let us recall the following theorem due to
 281 Kreiss [10]² :

²For constantly (resp. geometrically regular) hyperbolic operators, this Theorem still holds, see [15] (resp. [16]).

282 THEOREM 3. Under Hypothesis 1 and 2, for all $\underline{\zeta} \in \Xi$, there exist a neighborhood \mathcal{V} of $\underline{\zeta}$ in Ξ , integers
 283 $L_1, L_2 \geq 1$, two partitions $N = \nu_{1,1} + \dots + \nu_{1,L_1} = \nu_{2,1} + \dots + \nu_{2,L_2}$ with $\nu_{1,l}, \nu_{2,l} \geq 1$, and two invertible
 284 matrices T_1, T_2 , regular on \mathcal{V} such that:

$$285 \quad \forall \zeta \in \mathcal{V}, \quad T_1(\zeta)^{-1} \mathcal{A}_1(\zeta) T_1(\zeta) = \text{diag}(\mathcal{A}_{1,1}(\zeta), \dots, \mathcal{A}_{1,L_1}(\zeta)),$$

$$286 \quad T_2(\zeta)^{-1} \mathcal{A}_2(\zeta) T_2(\zeta) = \text{diag}(\mathcal{A}_{2,1}(\zeta), \dots, \mathcal{A}_{2,L_2}(\zeta)),$$

287 where the blocks $\mathcal{A}_{j,l}(\zeta)$ have size $\nu_{j,l}$ and satisfy one of the following alternatives:

- 288 i) All the elements in the spectrum of $\mathcal{A}_{j,l}(\zeta)$ have positive real part.
 289 ii) All the elements in the spectrum of $\mathcal{A}_{j,l}(\zeta)$ have negative real part.
 290 iii) $\nu_{j,l} = 1$, $\mathcal{A}_{j,l}(\zeta) \in i\mathbb{R}$, $\partial_\gamma \mathcal{A}_{j,l}(\zeta) \in \mathbb{R} \setminus \{0\}$, and $\mathcal{A}_{j,l}(\zeta) \in i\mathbb{R}$ for all $\zeta \in \mathcal{V} \cap \Xi_0$.
 291 iv) $\nu_{j,l} > 1$, $\exists k_{j,l} \in i\mathbb{R}$ such that

$$292 \quad \mathcal{A}_{j,l}(\underline{\zeta}) = \begin{bmatrix} k_{j,l} & i & 0 \\ & \ddots & i \\ 0 & & k_{j,l} \end{bmatrix},$$

293 the coefficient in the lower left corner of $\partial_\gamma \mathcal{A}_{j,l}(\underline{\zeta})$ is real and non-zero, and moreover $\mathcal{A}_{j,l}(\zeta) \in i\mathbf{M}_{\nu_{j,l}}(\mathbb{R})$
 294 for all $\zeta \in \mathcal{V} \cap \Xi_0$.

295 Thanks to Theorem 3 it is possible to describe the four kinds of frequencies, for each part of the boundary
 296 $\partial\Omega$:

297 DEFINITION 4. For $j = 1, 2$, we denote by:

298 1) \mathcal{E}_j the set of elliptic frequencies, that is to say the set of $\underline{\zeta} \in \Xi_0$ such that Theorem 3 for the matrix
 299 $\mathcal{A}_j(\underline{\zeta})$ is satisfied with one block of type i) and one block of type ii) only.

300 2) \mathcal{H}_j the set of hyperbolic frequencies, that is to say the set of $\underline{\zeta} \in \Xi_0$ such that Theorem 3 for the
 301 matrix $\mathcal{A}_j(\underline{\zeta})$ is satisfied with blocks of type iii) only.

302 3) $\mathcal{E}\mathcal{H}_j$ the set of mixed frequencies, that is to say the set of $\underline{\zeta} \in \Xi_0$ such that Theorem 3 for the matrix
 303 $\mathcal{A}_j(\underline{\zeta})$ is satisfied with one block of type i), one of type ii) and at least one of type iii), but without block of
 304 type iv).

305 4) \mathcal{G}_j the set of glancing frequencies, that is to say the set of $\underline{\zeta} \in \Xi_0$ such that Theorem 3 for the matrix
 306 $\mathcal{A}_j(\underline{\zeta})$ is satisfied with at least one block of type iv).

307 Thus, by definition, Ξ_0 admits the following decomposition:

$$308 \quad \Xi_0 = \mathcal{E}_j \cup \mathcal{E}\mathcal{H}_j \cup \mathcal{H}_j \cup \mathcal{G}_j.$$

309 The study made in [10] shows that the subspaces $E_1^s(\zeta_j)$ and $E_2^s(\zeta_j)$ admit a continuous extension up to the
 310 boundary of the frequency set Ξ_0 . Moreover, for $j = 1, 2$, for $\underline{\zeta}_j \in \Xi_0 \setminus (\mathcal{G}_1 \cup \mathcal{G}_2)$ one can decompose:

$$311 \quad (27) \quad \mathbb{C}^N = E_j^s(i\underline{\tau}, \underline{\xi}_{3-j}) \oplus E_j^u(i\underline{\tau}, \underline{\xi}_{3-j}),$$

312 where the spaces E_j^s and E_j^u can also be decomposed in the following way:

$$313 \quad E_j^s(i\underline{\tau}, \underline{\xi}_{3-j}) = E_j^{s,e}(i\underline{\tau}, \underline{\xi}_{3-j}) \oplus E_j^{s,h}(i\underline{\tau}, \underline{\xi}_{3-j}), \text{ and } E_j^u(i\underline{\tau}, \underline{\xi}_{3-j}) = E_j^{u,e}(i\underline{\tau}, \underline{\xi}_{3-j}) \oplus E_j^{u,h}(i\underline{\tau}, \underline{\xi}_{3-j}).$$

314 Here $E_j^{s,e}(i\underline{\tau}, \underline{\xi}_{3-j})$ (resp. $E_j^{u,e}(i\underline{\tau}, \underline{\xi}_{3-j})$) is the generalized eigenspace associated with eigenvalues of the ma-
 315 trix $\mathcal{A}_j(i\underline{\tau}, \underline{\xi}_{3-j})$ with negative (resp. positive) real part, and where spaces $E_j^{s,h}(i\underline{\tau}, \underline{\xi}_{3-j})$ and $E_j^{u,h}(i\underline{\tau}, \underline{\xi}_{3-j})$
 316 are sums of eigenspaces of $\mathcal{A}_j(i\underline{\tau}, \underline{\xi}_{3-j})$ associated with some purely imaginary eigenvalues of $\mathcal{A}_j(i\underline{\tau}, \underline{\xi}_{3-j})$.
 317

318 Moreover since the matrices A_1 and A_2 are invertible we can also write (27) in the following way :for
 319 $j = 1, 2$

$$320 \quad (28) \quad \mathbb{C}^N = A_j E_j^s(i\underline{\tau}, \underline{\xi}_{3-j}) \oplus A_j E_j^u(i\underline{\tau}, \underline{\xi}_{3-j}),$$

In fact, it is possible to give a more precise decomposition of the spaces $E_j^{s,h}(\underline{\zeta}_j)$ and $E_j^{u,h}(\underline{\zeta}_j)$. Indeed,
 let $\omega_{m,j}$ be a purely imaginary eigenvalue of $\mathcal{A}_j(\underline{\zeta}_j)$, that is satisfying:

$$\det(\underline{\tau} + \underline{\eta} A_1 + \omega_{m,2} A_2) = \det(\underline{\tau} + \omega_{m,1} A_1 + \underline{\eta} A_2) = 0.$$

321 Then, using Hypothesis 1, we deduce that there exists an index $k_{m,j}$ satisfying:

$$322 \quad \tau + \lambda_{k_{m,2}}(\eta, \underline{\omega}_{m,2}) = \tau + \lambda_{k_{m,1}}(\underline{\omega}_{m,1}, \eta) = 0,$$

323 where $\lambda_{k_{m,j}}$ is smooth in both variables. Let us then introduce the following classification :

324 **DEFINITION 5.** • *The set of incoming (resp. outgoing) phases for the side $\partial\Omega_1$, denoted by \mathfrak{I}_1 (resp.*
 325 \mathfrak{D}_1), *is the set of indices m such that the group velocity $v_m := \nabla\lambda_{k_{m,1}}(\underline{\omega}_{m,1}, \eta)$ satisfies $\partial_1\lambda_{k_{m,1}}(\underline{\omega}_{m,1}, \eta) > 0$*
 326 *(resp. $\partial_1\lambda_{k_{m,1}}(\underline{\omega}_{m,1}, \eta) < 0$).*

327 • *The set of incoming (resp. outgoing) phases for the side $\partial\Omega_2$, denoted by \mathfrak{I}_2 (resp. \mathfrak{D}_2 , is the*
 328 *set of indices m such that the group velocity $v_m := \nabla\lambda_{k_{m,2}}(\eta, \underline{\omega}_{m,2})$ satisfies $\partial_2\lambda_{k_{m,2}}(\eta, \underline{\omega}_{m,2}) > 0$ (resp.*
 329 *$\partial_2\lambda_{k_{m,2}}(\eta, \underline{\omega}_{m,2}) < 0$).*

330 • *The set of incoming-incoming (resp. outgoing-outgoing) phases \mathcal{I}_{ii} (resp. \mathcal{I}_{oo}) is defined by $I_{ii} :=$*
 331 $\mathfrak{I}_1 \cap \mathfrak{I}_2$ (resp. $\mathcal{I}_{oo} := \mathfrak{D}_1 \cap \mathfrak{D}_2$).

332 • *The set of incoming-outgoing (resp. outgoing-incoming) phases \mathcal{I}_{io} (resp. \mathcal{I}_{oi}) is defined by $\mathcal{I}_{io} :=$*
 333 $\mathfrak{I}_1 \cap \mathfrak{D}_2$ (resp. $\mathcal{I}_{oi} := \mathfrak{D}_1 \cap \mathfrak{I}_2$).

334 Note that we do not considered the phases whose one of the component of the group velocity vanishes. This
 335 phases correspond to glancing modes and the construction of the geometric optics expansions is much more
 336 technical when we consider these phases [20].

337

338 Thanks to Definition 5, we can write the following decomposition of the stable and unstable components
 339 $E_j^{s,h}(\zeta)$ and $E_j^{u,h}(\zeta)$:

340 **LEMMA 6.** *For all $\zeta \in \mathcal{H}_j \cup \mathcal{E}\mathcal{H}_j$, $j = 1, 2$ we have*

$$341 \quad (30) \quad E_1^{s,h}(\zeta) = \oplus_{m \in \mathfrak{I}_1} \ker \mathcal{L}(\tau, \underline{\omega}_{m,1}, \eta), \quad E_1^{u,h}(\zeta) = \oplus_{m \in \mathfrak{D}_1} \ker \mathcal{L}(\tau, \underline{\omega}_{m,1}, \eta),$$

$$342 \quad (31) \quad E_2^{s,h}(\zeta) = \oplus_{m \in \mathfrak{I}_2} \ker \mathcal{L}(\tau, \eta, \underline{\omega}_{m,2}), \quad E_2^{u,h}(\zeta) = \oplus_{m \in \mathfrak{D}_2} \ker \mathcal{L}(\tau, \eta, \underline{\omega}_{m,2}).$$

343 We refer, for example, to [8] or [20] for a proof of this lemma.

344

345 **3.2. About the boundary conditions.** Let us introduce the initial boundary value problem in the
 346 half space $\{x_1 \geq 0, x_2 \in \mathbb{R}\}$:

$$347 \quad (32) \quad \begin{cases} L(\partial)u = f, \text{ on } \{x_1 \geq 0, x_2 \in \mathbb{R}\} \\ B_1 u|_{x_1=0} = g_1, \\ u|_{t \leq 0} = 0. \end{cases}$$

348 We recall the following result due to Kreiss [10] which establishes that the boundary value problem (32) is
 349 strongly well-posed if and only if it satisfies the following condition:

DEFINITION 7 (Uniform Kreiss-Lopatinskii condition). *We say that the system (32) satisfies the uniform Kreiss-Lopatinskii condition if we have:*

$$\forall \zeta \in \Xi, \ker B_1 \cap E_1^s(\zeta) = \{0\},$$

350 where $E_1^s(\zeta)$ still denotes the continuation of the stable subspace of the resolvent matrix $\mathcal{A}_1(\zeta)$ up to Ξ_0 .

351 **DEFINITION 8.** *We denote by Υ the set of frequencies for which the ibvp (32) does not satisfy the uniform*
 352 *Kreiss-Lopatinskii condition i.e.*

$$353 \quad \Upsilon := \{\zeta_1 \in \Xi : \ker B_1 \cap E_1^s(\zeta_1) \neq \{0\}\}.$$

354 If $\Upsilon \cap (\Xi \setminus \Xi_0) \neq \emptyset$ then we say that this problem does not satisfy the Kreiss-Lopatinskii condition and it
 355 is a well-known fact, we refer for example to [10] or [6], that such problem can not be strongly or weakly
 356 well-posed. As a consequence, the only possible frequencies where the uniform Kreiss-Lopatinskii can fail
 357 without causing ill-posedness of the problem are located on Ξ_0 .

358 The kind of degeneracy that we will consider in this article are thus on Ξ_0 and correspond to hyperbolic
 359 frequencies that is that $\mathcal{A}_1(\zeta)$ is diagonalizable with only imaginary eigenvalues. We recall that these fre-
 360 quencies induce a transport of the information. More precisely we will use the following definition due to [5]:

361

362 DEFINITION 9. The *ibvp* (32) is in the *WR* class if it satisfies the following conditions:

363 i) The *ibvp* (32) satisfies the weak Kreiss-Lopatinskii condition i.e. $\Upsilon \cap (\Xi \setminus \Xi_0) = \emptyset$.

364 ii) $\Upsilon \neq \emptyset$ and $\Upsilon \subset \mathcal{H}_1^\circ$.

365 iii) For all $\zeta \in \Upsilon$, there is a neighborhood \mathcal{V} of ζ in Ξ , a regular basis $(E_{1,1}^s, \dots, E_{1,p_1}^s)(\zeta)$ of $E_1^s(\zeta)$ on \mathcal{V} ,
366 an invertible $p_1 \times p_1$ matrix $P(\zeta)$, regular on \mathcal{V} and a smooth real valued function Θ such that

$$367 \quad \forall \zeta \in \mathcal{V}, B_1 [E_{1,1}^s, \dots, E_{1,p_1}^s](\zeta) = P(\zeta) \text{diag}(\gamma + i\Theta(\zeta), 1, \dots, 1).$$

368 In particular, one can find a Lopatinskii's determinant under the form:

$$369 \quad \forall \zeta \in \mathcal{V}, \Delta(\zeta) = (\gamma + i\Theta(\zeta)) \det P(\zeta).$$

370 These definitions about hyperbolic boundary value problems in the half space motivate the following
371 definition for the corner problem:

372 DEFINITION 10. We say that the corner problem (1) is in the *WR* class for the side $\partial\Omega_1$ if the boundary
373 value problem (32) is in the *WR* class.

374 In all this paper, the boundary condition for the side $\partial\Omega_1$ will not satisfy the uniform Kreiss-Lopatinskii
375 condition (precisely we will then work with corner problem in the *WR* class for the side $\partial\Omega_1$) and so weak
376 well-posedness is expected. While, as mentioned in the introduction, the boundary condition for the side
377 $\partial\Omega_2$ will be chosen as convenient as possible in terms of well-posedness. However, we will see in Theorem
378 14 that even if the boundary condition on $\partial\Omega_2$ is in the most favorable class of strictly dissipative boundary
379 conditions (see [6]), it can not compensate the "bad" boundary condition on $\partial\Omega_1$.

380

381 To make things more precise, let us thus assume the following :

Hypothesis 11. The corner problem (1) is in the *WR* class for the side $\partial\Omega_1$ and the boundary condition
on the side $\partial\Omega_2$ is strictly dissipative or satisfies (at least) the uniform Kreiss-Lopatinskii condition. In the
first case, that is to say that the following inequality holds:

$$\forall v \in \ker B_2, \langle A_2 v, v \rangle < 0.$$

While in the second case, it means that $\forall \zeta \in \Xi$, we have:

$$\ker B_2 \cap E_2^s(\zeta) = \{0\}.$$

382 In both cases (we refer to [6] for a proof that strict dissipativity implies the uniform Kreiss-Lopatinskii
383 condition) the restriction of B_2 to $E_2^s(\zeta)$ is invertible. We denote this inverse by $\phi_2(\zeta)$.

384 When one studies geometric optics expansion for weakly well-posed boundary value problems, it is useful
385 to define the following vectors (this definition comes from [8] and was also used later in [2]) :

386 DEFINITION 12. Let (1) be in the *WR* class for the side $\partial\Omega_1$, then there exist:

387 \diamond a vector $e \in \mathbb{C}^N \setminus \{0\}$ such that $\ker B_1 \cap E_1^s(\zeta) = \text{vect}(e)$.

388 \diamond A vector $b \in \mathbb{C}^{p_1} \setminus \{0\}$ such that $b \cdot Bw = 0$, for all $w \in E_1^s(\zeta)$.

389 **4. Formal phase generation process.** In this paragraph we briefly discuss the expected phases in
390 the WKB expansion and the associated amplitudes for corner problem in the *WR* class for the side $\partial\Omega_1$. We
391 will not here give a precise description of the phase generation process in itself (we refer to [4] and [19] for a
392 complete discussion) but we will focus on the expected sizes of the amplitudes according to the small param-
393 eter ε . More especially we will also discuss after how many time of travel the amplifications are expected.

394

395 Let us consider the hyperbolic corner problem:

$$396 \quad (35) \quad \begin{cases} L(\partial)u^\varepsilon = 0, & \text{on } \Omega_T \\ B_1 u^\varepsilon|_{x_1=0} = g^\varepsilon, & \text{on } \partial\Omega_{1,T}, \\ B_2 u^\varepsilon|_{x_2=0} = 0, & \text{on } \partial\Omega_{2,T}, \\ u^\varepsilon|_{t \leq 0} = 0, \end{cases}$$

and we assume that (35) satisfies Assumptions 1-2 and 11. We also suppose that this corner problem admits
four selfinteracting planar phases (see Assumption 21 or [4] for more details) namely

$$\varphi_{n_j}(t, x) := \underline{t} + \xi_1^{n_j} x_1 + \xi_2^{n_j} x_2, \quad j = 1, \dots, 4.$$

To be considered as selfinteracting these phases have firstly to satisfy

$$\xi_1^{n_1} = \xi_1^{n_2}, \xi_2^{n_2} = \xi_2^{n_3}, \xi_1^{n_3} = \xi_1^{n_4}, \text{ and } \xi_2^{n_4} = \xi_2^{n_1},$$

in other words it is possible to draw a rectangle whose vertices are on the characteristic variety. We will also impose that the phase φ_{n_1} and φ_{n_3} are incoming-outgoing whereas φ_{n_2} and φ_{n_4} are outgoing-incoming in view to have the good velocities for a selfinteraction.

We also choose the source term g^ε in (35) in such a way that it "turns on" the phase φ_{n_1} . Finally we assume that the phase φ_{n_1} is associated to the only frequency for which the uniform Kreiss-Lopatinskii condition is violated.

Let us choose g^ε , zero for negative times, with compact support away from the corner for all positive times (or at least a function which is zero on a neighborhood of the corner for all positive times). Then by finite speed of propagation arguments, the information carried by g^ε can not hit the side $\partial\Omega_2$ immediately. So, at least during a short time, we can forget the boundary condition on $\{x_1 > 0, x_2 = 0\}$ and see the corner problem (35) as a problem in the *WR* class for the half space $\{x_1 > 0, x_2 \in \mathbb{R}\}$. It is thus natural to start by taking the ansatz for this problem lying in the half space. This ansatz involves the phases φ_j defined by:

$$\varphi_j(t, x) := \tau t + \xi_1^j x_1 + \xi_2^{n_1} x_2, \quad j = 1, \dots, N,$$

where the (ξ_1^j) are the roots in the ξ_1 variable of the dispersion relation:

$$\det \mathcal{L}(\tau, \xi_1, \xi_2^{n_1}) = 0,$$

associated to incoming-outgoing or incoming-incoming group velocities (see [4] for more details). Let us stress that, by assumption, the phase φ_{n_1} is contained in the $\{\varphi_j\}_j$ and that since the corner problem (35) is in the *WR* class, in particular $(i\tau, \xi_2^{n_1}) \in \mathcal{H}_1$, then there is exactly N roots in the ξ_1 variable of the dispersion relation $\det \mathcal{L}(\tau, \xi_1, \xi_2^{n_1}) = 0$.

However the analysis of [8] tells us that when the uniform Kreiss-Lopatinskii condition breaks down, due to a transport phenomenon along the side $\partial\Omega_1$, the leading order is one order less than the order of the source term on the boundary $\{x_1 = 0, x_2 > 0\}$. More precisely, if the source term is of order one, then the leading order in the WKB expansion is of order zero. This transport phenomenon along the side $\partial\Omega_1$, in the presence of a source term on the boundary, is immediately turned on. We thus expect that this property which comes from the study of the problem in the half space remains true for the corner problem (35), at least during a short time.

In all this paper, we will assume that the transport along the side $\partial\Omega_1$ spreads the information away from the corner. If it is not the case then the information will hit the corner in finite time. Until now, we are not able to construct geometric optics expansions if such a situation occurs and we thus have a maximal time of existence for the geometric optics expansions corresponding to the time of impact. However as first noticed in [8], in the particular framework $d = 2$, then the velocity of the transport along the side $\partial\Omega_1$ is explicitly computable. More precisely it is given by $-\frac{\tau}{\xi_2^{n_1}}$ (see [8]). So in this particular setting ask that the transport phenomenon along the side $\partial\Omega_1$ spreads the information away from the corner is equivalent to ask that τ and $\xi_2^{n_1}$ have opposite signs, which is easily verifiable in practice.

The rays associated to the phase φ_j are incoming-outgoing or incoming-incoming. As a consequence if the phase φ_j the information that it carried will hit the boundary $\partial\Omega_2$ after some time of travel and we will have to determine its reflections or if it is incoming-incoming then it escapes to infinity and it will never be reflected. Let us now study the reflections of the incoming-outgoing ones. More precisely we will only describe the reflections φ_{n_1} which are the capital ones for our current discussion. We refer to [4] for a precise description of the reflections for the other rays.

The ray associated to the phase φ_{n_1} is incoming-outgoing so it hits the side $\partial\Omega_2$ after a finite time of travel. However, when it happens, the striking ray still have its support away from the corner. Thus, once again, by finite speed of propagation arguments, at least during a small time, we can see the corner problem (35) as a problem in the half space $\{x_1 \in \mathbb{R}, x_2 > 0\}$ for which the information on the side $\partial\Omega_2$ has been

”turned on” by the incoming-outgoing phase φ_{n_1} . We thus add in the ansatz the amplitudes associated with the phases

$$\varphi_j(t, x) := \underline{\tau}t + \xi_1^{n_1}x_1 + \xi_2^j x_2, \quad j = 1, \dots, N_2,$$

where the (ξ_2^j) are the roots in the ξ_2 variable of the dispersion relation :

$$\det \mathcal{L}(\underline{\tau}, \xi_1^{n_1}, \xi_2) = 0.$$

433 Note that φ_{n_2} is included in this set.

434 Let us here insist on the fact that there can be less than N roots for this dispersion relation and that
435 these roots can be complex valued. Indeed, the boundary value problem in the half space $\{x_1 \in \mathbb{R}, x_2 > 0\}$
436 is not assumed to be in the WR class. According to [4] we only consider the real roots associated with
437 outgoing-incoming or incoming-incoming group velocities and a class representative of the complex valued
438 roots with positive imaginary part (see Section 6 or [4] for more details).

439

440 As the boundary condition on the side $\partial\Omega_2$ is assumed to satisfy the uniform Kreiss-Lopatinskii condi-
441 tion, this time there is no transport phenomenon along the boundary and the leading order of the WKB
442 expansion remains of order zero (for a source term on the boundary $\partial\Omega_1$ of order one).

443

444 We can then repeat exactly the same arguments to show that the phases φ_{n_3} and φ_{n_4} are generated
445 when we consider the reflections of the ray associated to φ_{n_2} on $\partial\Omega_1$ ³ and the reflection of the ray associated
446 to φ_{n_3} on $\partial\Omega_2$.

447

448 It is then interesting to study the reflection of the ray associated to φ_{n_4} against the side $\partial\Omega_1$. This
449 reflection starts after a strictly positive time t_0 at a strictly positive distance of the corner y_0 (the precise
450 values of this parameters are given in Section 7 and will be fundamental in our proof). By selfinteraction
451 phenomenon, we know that during this reflection the phase φ_{n_1} is regenerated. However due to the degen-
452 eracy of the uniform Kreiss-Lopatinskii condition for the phase φ_{n_1} , a new transport along the boundary is
453 expected and shall induce a new amplification phenomenon. All the amplitudes in the ansatz then should
454 lose one power of ε , that is to say that the amplitude of order zero becomes of order -1 , the amplitude of
455 order one becomes of order zero and so on.

456

457 As a consequence, if one starts with a source term of order two in ε then before the time t_0 , the leading
458 order of the geometric optics expansion is expected to be of order one, but after the time t_0 , the leading order
459 in this expansion is expected to be of order zero. Moreover the traces of the amplitudes associated to the
460 phase φ_{n_1} are now expected to be zero for x_2 less than y_0 . We can then repeat exactly the same arguments.
461 That is to say that after another complete circuit around the loop, the amplitude associated to φ_{n_4} hits again
462 the side $\partial\Omega_1$ and regenerates the phase φ_{n_1} . A new amplification thus happens and all the amplitudes lose
463 one order in terms of ε . The leading order in the geometric optics expansion is now expected to be of order
464 zero for a source term on the boundary of order three.

465

466 So if one wants to construct a geometric optics expansion with $M + 1$ amplifications before a fixed time
467 T , it will be sufficient to choose the support of the source term g close enough of the corner to ensure that
468 the rays have made M complete circuits around the loop before the time T .

469

470 Moreover, the fact that we choose to work with a fixed maximal time of resolution T and with a source
471 term g having its support away from the corner permits us to assume that the number of generated phases in
472 the phase generation process is finite and avoid the technical difficulties pointed in [4]. Indeed, in [4] it was
473 shown that the phase generation process consists of considering sequences of phases with incoming-outgoing
474 and then outgoing-incoming group velocities and to stop the sequence when we meet a phase with incoming-
475 incoming group velocity. However, here each transport phenomenon from one side to the other takes some
476 (explicitly computable) time because the transported information has its support away from the corner. So
477 when we apply the phase generation process we can stop the sequence as soon as the sum of the time needed
478 to generate the considered phase exceeds the fixed maximal time T .

479

480 **5. Main result.** In this paragraph we describe the main result of this paper. Roughly speaking, this
481 result states that when one deals with a corner problem that does not satisfy the uniform Kreiss-Lopatinskii

³Let us stress that during this reflection on the side $\partial\Omega_1$ there is no amplification because the considered phases are φ_{n_2} and φ_{n_3} but not φ_{n_1} .

condition on each boundary then he should be careful. Indeed, Theorem 14 demonstrates that such a problem can, in some situations depending on the geometry of the characteristic variety, be ill-posed. The violent instability is, in this framework, caused by an accumulation of weak instabilities and differs from the failure of the weak Kreiss-Lopatinskii condition which is, to our knowledge, the only known example of violent instability for hyperbolic boundary value problem. Before to state the main theorem, let us define more precisely the terms of the previous discussion:

DEFINITION 13. *The corner problem (1) is said to be weakly well-posed (or to generate a weak instability) if there exists $(K, K_1, K_2) \in \mathbb{R}_+^3 \setminus \{0\}$ such that for all source terms $f \in H^K(\Omega_T)$, $g_1 \in H^{K_1}(\partial\Omega_{1,T})$, $g_2 \in H^{K_2}(\partial\Omega_{2,T})$, the corner problem (1) admits a unique solution $u \in L^2(\Omega_T)$ with traces $u|_{x_1=0} \in L^2(\partial\Omega_{1,T})$, $u|_{x_2=0} \in L^2(\partial\Omega_{2,T})$ satisfying the energy estimate:*

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{H^K(\Omega_T)}^2 + \|g_1\|_{H^{K_1}(\partial\Omega_{1,T})}^2 + \|g_2\|_{H^{K_2}(\partial\Omega_{2,T})}^2 \right),$$

for some positive constant C_T .

The corner problem (1) is said to be ill-posed (or to generate a violent instability) if it is not strongly well-posed and if such integers do not exist.

The main theorem of this paper is the following :

THEOREM 14. *Let (1) be a corner problem satisfying Hypothesis 1-2-21 and 22 then (1) can not be weakly well-posed. In other words, for all $K, K_2 \in \mathbb{N}$, $f \in H^K(\Omega_T)$, $g_2 \in H^{K_2}(\Omega_T)$ and for all $K_1 \in \mathbb{N}^*$ one can find $g_1 \in H^{K_1}(\partial\Omega_{1,T})$, such that the energy estimate*

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{H^K(\Omega_T)}^2 + \|g_1\|_{H^{K_1}(\partial\Omega_{1,T})}^2 + \|g_2\|_{H^{K_2}(\partial\Omega_{2,T})}^2 \right),$$

is violated.

The proof of Theorem 14 is given in Section 8. This proof is based on the rigorous construction of geometric optics expansions for the corner problem (1) with an arbitrary number of amplifications compared to the source term on the side $\partial\Omega_1$. This construction, which is the technical part of the proof, is made in Section 7.

6. General framework. In this section we recall some notations and definitions used in [4] to describe rigorously the set of phases obtained by reflection against the side of the quarter space.

6.1. Definition of the frequency set and first properties. Let us start with the definition of what we mean by a frequency set:

DEFINITION 15. *Let \mathcal{I} be a subset of \mathbb{N} and $\tau \in \mathbb{R}$, $\tau \neq 0$. A set indexed by \mathcal{I} ,*

$$\mathcal{F} := \{f^i := (\tau, \xi_1^i, \xi_2^i), i \in \mathcal{I}\},$$

will be a frequency set for the corner problem (1) if for all $i \in \mathcal{I}$, f_i satisfies

$$\det \mathcal{L}(f^i) = 0,$$

and one of the following alternatives:

- i) $\xi_1^i, \xi_2^i \in \mathbb{R}$.
- ii) $\xi_1^i \in (\mathbb{C} \setminus \mathbb{R})$, $\xi_2^i \in \mathbb{R}$ and $\text{Im } \xi_1^i > 0$.
- iii) $\xi_2^i \in (\mathbb{C} \setminus \mathbb{R})$, $\xi_1^i \in \mathbb{R}$ and $\text{Im } \xi_2^i > 0$.

In all what follows, if \mathcal{F} is a frequency set for the corner problem (1), we will define:

$$\begin{aligned} \mathcal{F}_{os} &:= \{f^i \in \mathcal{F} \text{ satisfying i)\}, \\ \mathcal{F}_{ev1} &:= \{f^i \in \mathcal{F} \text{ satisfying ii)\}, \\ \mathcal{F}_{ev2} &:= \{f^i \in \mathcal{F} \text{ satisfying iii)\}. \end{aligned}$$

It is clear that the sets \mathcal{F}_{os} , \mathcal{F}_{ev1} and \mathcal{F}_{ev2} give a partition of \mathcal{F} . Moreover to each $f^i \in \mathcal{F}_{os}$, we can associate a group velocity $v_i := (v_{i,1}, v_{i,2})$. Let us recall that the group velocity v_i has been introduced in

515 Definition 5. The set \mathcal{F}_{os} can thus be decomposed as follows:

$$\begin{aligned}
516 \quad \mathcal{F}_{ii} &:= \{f^i \in \mathcal{F}_{os} \setminus v_{i,1}, v_{i,2} > 0\}, \quad \mathcal{F}_{io} := \{f^i \in \mathcal{F}_{os} \setminus v_{i,1} > 0, v_{i,2} < 0\}, \\
517 \quad \mathcal{F}_{oi} &:= \{f^i \in \mathcal{F}_{os} \setminus v_{i,1} < 0, v_{i,2} > 0\}, \quad \mathcal{F}_{oo} := \{f^i \in \mathcal{F}_{os} \setminus v_{i,1}, 0, v_{i,2} < 0\}. \\
518 \quad \mathcal{F}_g &:= \{f^i \in \mathcal{F}_{os} \setminus v_{i,1} = 0 \text{ or } v_{i,2} = 0\}.
\end{aligned}$$

519 The partition of \mathcal{F} induces the following partition of \mathcal{I} :

$$520 \quad \mathcal{I} = \mathcal{I}_g \cup \mathcal{I}_{oo} \cup \mathcal{I}_{io} \cup \mathcal{I}_{oi} \cup \mathcal{I}_{ii} \cup \mathcal{I}_{ev1} \cup \mathcal{I}_{ev2},$$

521 where we have denoted by \mathcal{I}_{io} (resp. $g, oo, oi, ii, ev1, ev2$) the set of indices $i \in \mathcal{I}$ such that the corresponding
522 frequency $f^i \in \mathcal{F}_{io}$ (resp. $g, oo, oi, ii, ev1, ev2$).

523
524 From now on, the source term g_1^ε on the $\partial\Omega_1$ boundary in (1) reads :

$$525 \quad (36) \quad g_1^\varepsilon(t, x_2) := e^{\frac{i}{\varepsilon}(\tau t + \xi_2 x_2)} \varepsilon^{M+1} g(t, x_2),$$

526 for some fixed integer M and where the amplitude g has its support in space away from the corner and is
527 zero for negative times.

528 The following definition gives a precise framework for the phase generation process described in paragraph
529 4. More precisely, this definition qualifies the frequency set that contains all (and only) the frequencies linked
530 with the expected non-zero amplitudes in the WKB expansion:

531 DEFINITION 16. *The corner problem (1) is said to be complete for reflections if there exists a set of*
532 *frequencies \mathcal{F} satisfying the following properties:*

i) \mathcal{F} contains the real roots (in the variable ξ_1) associated with incoming-outgoing or incoming-incoming
group velocities and the complex roots with positive imaginary part, to the dispersion relation

$$\det \mathcal{L}(\tau, \xi_1, \xi_2) = 0.$$

533 *ii) $\mathcal{F}_g = \emptyset$.*

534

535 *iii) If $(\tau, \xi_1^i, \xi_2^i) \in \mathcal{F}_{io}$, then \mathcal{F} contains all the roots (in the ξ_2 -variable), denoted by ξ_2^p , to the dispersion*
536 *relation $\det \mathcal{L}(\tau, \xi_1^i, \xi_2) = 0$, that satisfy one of the following two alternatives:*

537 *iii') $\xi_2^p \in \mathbb{R}$ and the frequency (τ, ξ_1^i, ξ_2^p) is associated with an outgoing-incoming group velocity or an*
538 *incoming-incoming group velocity.*

539 *iii'') $\text{Im } \xi_2^p > 0$.*

540

541 *iv) If $(\tau, \xi_1^i, \xi_2^i) \in \mathcal{F}_{oi}$, then \mathcal{F} contains all the roots (in the ξ_1 -variable), denoted by ξ_1^p , to the dispersion*
542 *relation $\det \mathcal{L}(\tau, \xi_1, \xi_2^i) = 0$, that satisfy one of the following two alternatives:*

543 *iv') $\xi_1^p \in \mathbb{R}$ and the frequency (τ, ξ_1^p, ξ_2^i) is associated with an incoming-outgoing or an incoming-incoming*
544 *group velocity.*

545 *iv'') $\text{Im } \xi_1^p > 0$.*

546

547 *v) \mathcal{F} is minimal (for the inclusion) for the four preceding properties.*

548 Point *i)* imposes that the frequency set \mathcal{F} contains all (and only all) the incoming phases for $\partial\Omega_1$ that are
549 induced by the source term g_1^ε .

550 Point *iii)* (resp. *iv)*) explains the generation by reflection on the side $\partial\Omega_2$ (resp. $\partial\Omega_1$) of a wave packet
551 that emanates from the side $\partial\Omega_1$ (resp. $\partial\Omega_2$).

552 An immediate consequence of the minimality of \mathcal{F} is that \mathcal{F}_{oo} is empty. Moreover let us stress that
553 according to the discussion made in paragraph 4, because we are dealing with finite time and a source term
554 which has its support away from the corner, without loss of generality we can assume that $\#\mathcal{F} < +\infty$.

555

556 Let us recall that if the corner problem is complete for reflections, one can define two applications, defined
557 on the index set \mathcal{I} and which give, in the output, the indices "in the direct vicinity" of the input index:

$$558 \quad \Phi, \Psi : \mathcal{I} \longrightarrow \mathcal{P}_N(\mathcal{I}),$$

559 where $\mathcal{P}_N(\mathcal{I})$ denotes the power set of \mathcal{I} with at most N elements. More precisely, the definitions of Φ
560 and Ψ are: for $i \in \mathcal{I}$, $f^i = (\underline{\tau}, \xi_1^i, \xi_2^i)$,

$$561 \quad \Phi(i) := \left\{ j \in \mathcal{I} \mid \xi_2^j = \xi_2^i \right\} \text{ and } \Psi(i) := \left\{ j \in \mathcal{I} \mid \xi_1^j = \xi_1^i \right\}.$$

562 For convenience let us introduce the short-hand notations:

$$563 \quad \Phi^*(i) := \Phi(i) \setminus \{i\} \text{ and } \Psi^*(i) := \Psi(i) \setminus \{i\}.$$

564 Thanks to these functions, the index set \mathcal{I} can be seen as a graph. This graph structure will be more abstract
565 than the description of \mathcal{I} based on the wave packet reflections, but it will be easier to handle with when we
566 will construct the WKB expansion. This graph structure is defined by the following relation : two points
567 $i, j \in \mathcal{I}$ are linked by an edge if and only if $i \in \Phi(j)$ or $i \in \Psi(j)$.

568 In terms of wave packet reflection, the set $\Phi(i)$ (resp. $\Psi(i)$) is the set of all indices of the phases that are
569 considered in the reflection of the wave packet with phase f^i on $\partial\Omega_2$. Let us stress that the index i is not
570 necessarily the index of an incident ray but can be the index of one of the reflected rays.

571 Applications Φ and Ψ satisfy the following properties:

572 PROPOSITION 17. *If the corner problem (1) is complete for reflections, then Φ and Ψ satisfy:*

573

$$574 \quad i) \forall i \in \mathcal{I}, i \in \Psi(i), i \in \Phi(i).$$

575

$$576 \quad ii) \forall i \in \mathcal{I}, \forall j \in \Psi(i), \forall k \in \Phi(i) \text{ we have } \Psi(i) = \Psi(j) \text{ and } \Phi(i) = \Phi(k).$$

577

$$578 \quad iii) \forall i \in \mathcal{I}, \Phi(i) \cap \mathcal{I}_{ev2} = \emptyset \text{ and } \Psi(i) \cap \mathcal{I}_{ev1} = \emptyset. \text{ And, } \forall i \in \mathcal{I}_{ev1}, \forall j \in \mathcal{I}_{ev2}, \text{ we have } \Psi(i) \subset \mathcal{I}_{ev1},$$

579 $\Phi(i) \subset \mathcal{I}_{ev2}.$

580

$$581 \quad iv) \forall i \in \mathcal{I}_{os}, \#(\Phi(i) \cap \mathcal{I}_{ev1} \cap \mathcal{I}_{io} \cap \mathcal{I}_{ii}) \leq p_1, \text{ and } \#(\Psi(i) \cap \mathcal{I}_{ev2} \cap \mathcal{I}_{oi} \cap \mathcal{I}_{ii}) \leq p_2.$$

582

$$583 \quad v) \forall i \in \mathcal{I}, \text{ we have on the one hand } \forall i_1, i_2 \in \Phi(i), i_1 \neq i_2:$$

584

$$\Phi(i) \cap \Psi(i_1) = \{i_1\} \text{ and } \Psi(i_1) \cap \Psi(i_2) = \emptyset,$$

585 and on the other hand, $\forall j_1, j_2 \in \Psi(i), j_1 \neq j_2 :$

586

$$\Psi(i) \cap \Phi(j_1) = \{j_1\} \text{ and } \Phi(j_1) \cap \Phi(j_2) = \emptyset.$$

587 We refer to [4] for a proof of this proposition.

588 Thanks to applications Φ and Ψ it is easy to define the notion of two linked indices in the graph structure
589 of \mathcal{I} :

590 DEFINITION 18. *If $\underline{i} \in \mathcal{I}_{io}$, we say that the index $j \in \mathcal{I}_{io} \cup \mathcal{I}_{ev1}$ (resp. $j \in \mathcal{I}_{oi} \cup \mathcal{I}_{ev2}$) is linked with the
591 index \underline{i} , if there exist $p \in 2\mathbb{N} + 1$ (resp. $p \in 2\mathbb{N}$) and a sequence of indices $\ell = (\ell_1, \ell_2, \dots, \ell_p) \in \mathcal{I}^p$ such that:
592 $\alpha')$ $\ell_1 \in \Psi(\underline{i}) \cap \mathcal{I}_{oi}, \ell_2 \in \Phi(\ell_1) \in \mathcal{I}_{io}, \dots, j \in \Phi(\ell_p)$ (resp. $j \in \Psi(\ell_p)$).*

593

594 *We say that the index $j \in \mathcal{I}_{ii}$ is linked with the index \underline{i} , if there is a sequence of indices $\ell = (\ell_1, \ell_2, \dots, \ell_p) \in$
595 \mathcal{I}^p such that:*

$$596 \quad \beta') \ell_1 \in \Psi(\underline{i}) \cap \mathcal{I}_{oi}, \ell_2 \in \Phi(\ell_1) \cap \mathcal{I}_{io}, \dots, \begin{cases} j \in \Phi(\ell_p), & p \text{ is odd,} \\ j \in \Psi(\ell_p), & p \text{ is even.} \end{cases}$$

597

598 *If $\underline{i} \in \mathcal{I}_{oi}$, we say that the index $j \in \mathcal{I}_{io} \cup \mathcal{I}_{ev1}$ (resp. $j \in \mathcal{I}_{oi} \cup \mathcal{I}_{ev2}$) is linked with the index \underline{i} , if there
599 exist $p \in 2\mathbb{N}$ (resp. $p \in 2\mathbb{N} + 1$) and a sequence of indices $\ell = (\ell_1, \ell_2, \dots, \ell_p) \in \mathcal{I}^p$ such that:*

$$600 \quad \alpha'') \ell_1 \in \Phi(\underline{i}) \cap \mathcal{I}_{io}, \ell_2 \in \Psi(\ell_1) \in \mathcal{I}_{oi}, \dots, j \in \Phi(\ell_p)$$
 (resp. $j \in \Psi(\ell_p)$).

601

602 *We say that the index $j \in \mathcal{I}_{ii}$ is linked with the index \underline{i} , if there exists a sequence of indices $\ell =$
603 $(\ell_1, \ell_2, \dots, \ell_p) \in \mathcal{I}^p$ such that:*

$$604 \quad \beta'') \ell_1 \in \Phi(\underline{i}) \cap \mathcal{I}_{io}, \ell_2 \in \Psi(\ell_1) \cap \mathcal{I}_{oi}, \dots, \begin{cases} j \in \Psi(\ell_p), & p \text{ is odd,} \\ j \in \Phi(\ell_p), & p \text{ is even.} \end{cases}$$

605

606 Finally, if $\underline{i} \in \mathcal{I}_{ii} \cup \mathcal{I}_{ev1} \cup \mathcal{I}_{ev2}$, we say that there is no element of \mathcal{I} linked with \underline{i} .

607

608 Moreover, we will say that an index $j \in \mathcal{I}$ is linked with the index \underline{i} by a sequence of type H (for
609 "horizontal") (resp. V (for "vertical")) and we will note $i \xrightarrow{H} j$ (resp. $i \xrightarrow{V} j$) if the sequence $(\underline{i}, \ell_1, \ell_2, \dots, \ell_p, j)$
610 satisfies α'') or β'') (resp. α') or β')).

611 Applications Φ and Ψ also enable us to define a set of class of representative for the complex valued
612 frequencies (or evanescent frequencies) in view to treat these frequencies in a "monoblock" way as it is done
613 in [12]. That is to say that for an index $\underline{i} \in \mathcal{I}_{ev1}$ (resp. $\underline{i} \in \mathcal{I}_{ev2}$), all the elements $j \in \mathcal{I}_{ev1} \cap \Phi(\underline{i})$ (resp.
614 $j \in \mathcal{I}_{ev2} \cap \Psi(\underline{i})$) will contribute to a single vector valued amplitude. To write off the ansatz and to describe
615 with enough precision the boundary conditions, it is useful to introduce the two equivalence relations \sim_{Φ} and
616 \sim_{Ψ} defined by:

617

$$i \sim_{\Phi} j \iff j \in \Phi(i), \text{ and } i \sim_{\Psi} j \iff j \in \Psi(i).$$

618 Let \mathfrak{C}_1 (resp. \mathfrak{C}_2) be the set of equivalence classes for the relation \sim_{Φ} (resp. \sim_{Ψ}), and \mathcal{R}_1 (resp. \mathcal{R}_2), be
619 a set of class representative for \mathfrak{C}_1 (resp. \mathfrak{C}_2). So \mathcal{R}_1 (resp. \mathcal{R}_2) is a set of indices which includes all the
620 possible values for ξ_2 (resp. ξ_1) of the different frequencies. We also define \mathfrak{R}_1 and \mathfrak{R}_2 by:

621 (41)

$$\mathfrak{R}_1 := \{i \in \mathcal{R}_1 \setminus \Phi(i) \cap \mathcal{I}_{ev1} \neq \emptyset\},$$

622 (42)

$$\mathfrak{R}_2 := \{i \in \mathcal{R}_2 \setminus \Psi(i) \cap \mathcal{I}_{ev2} \neq \emptyset\}.$$

623 \mathfrak{R}_1 (resp. \mathfrak{R}_2) is a set of class representative of the values in ξ_2 (resp. ξ_1) for which there is an evanescent
624 mode for the side $\partial\Omega_1$ (resp. $\partial\Omega_2$). At last, without loss of generality, we can always assume that $n_1 \in \mathcal{R}_2$,
625 in other words, we choose n_1 as a class representative of its own equivalence class.

626

627 To conclude, let us recall the following proposition which is an immediate consequence of Definitions 4.2
628 and 4.3.

PROPOSITION 19. Let \mathcal{F} be a complete for reflections frequency set indexed by \mathcal{I} . Let \mathcal{I}_0 be the set of
indices in \mathcal{I} generated by the source term g_1^{ε} , that is to say:

$$\mathcal{I}_0 := \{i \in \mathcal{I}_{io} \cup \mathcal{I}_{ii} \cup \mathcal{I}_{ev1} \setminus \det \mathcal{L}(\underline{\tau}, \xi_1^i, \xi_2) = 0\}.$$

Let $\mathcal{I}_{\mathcal{R}}$ be the set of indices in \mathcal{I} linked with one of the elements of \mathcal{I}_0 . Then

$$\mathcal{I}_{\mathcal{R}} = \mathcal{I}.$$

629 **6.2. Frequency sets with loop.** As in [4] we will assume that the considered corner problem admits a
630 unique selfinteraction loop⁴. Let us now give the definition of the loop that has been mentioned in Section
631 4:

632

DEFINITION 20. Let $i \in \mathcal{I}$, $p \in 2\mathbb{N} + 1$ and $\ell = (\ell_1, \dots, \ell_p) \in \mathcal{I}^p$.

633

• We say that the index $i \in \mathcal{I}$ admits a loop if there exists a sequence ℓ satisfying :

634

$$\ell_1 \in \Phi(i), \ell_2 \in \Psi(\ell_1), \dots, i \in \Psi(\ell_p).$$

635 • A loop for an index i is said to be simple if the sequence ℓ does not contain a periodically repeated subse-
636 quence.

637 • An index $i \in \mathcal{I}_{io}$ (resp. $i \in \mathcal{I}_{oi}$) admits a selfinteraction loop if i admits a simple loop and if the sequence
638 (i, ℓ, i) is of type V (resp. H) according to Definition 18.

639

Let us assume that :

Hypothesis 21. Let (1) be complete for reflections, we assume that the frequency set \mathcal{F} contains a unique
loop, of size 3 and that this loop is a selfinteraction loop. More precisely, we ask that the following properties
are satisfied:

vi) $\exists (n_1, n_3) \in \mathcal{I}_{io}^2, (n_2, n_4) \in \mathcal{I}_{oi}^2$ such that

$$n_2 \in \Psi(n_1), n_3 \in \Phi(n_2), n_4 \in \Psi(n_3), n_1 \in \Phi(n_4).$$

640

vii) Let $i \in \mathcal{I}$ an index with a loop $\ell = (\ell_1, \dots, \ell_p)$. Then $p = 3$ and $\{i, \ell_1, \ell_2, \ell_3\} = \{n_1, n_2, n_3, n_4\}$.

⁴Compared to [4], for convenience, we have exchanged the indices n_2 and n_4 . It is due to the fact that here we are more
interested in a precise description in terms of wave packets reflection than in [4].




FIG. 2. The coefficients of the loop's elements.

641 We now fix the notations for the f^{n_j} , the frequencies associated to the loop's elements. For $j = 1, \dots, 4$ we
 642 write :

$$643 \quad (44) \quad f^{n_1} := (\underline{\tau}, \underline{\xi}_1, \bar{\xi}_2), \quad f^{n_2} := (\underline{\tau}, \underline{\xi}_1, \underline{\xi}_2), \quad f^{n_3} := (\underline{\tau}, \bar{\xi}_1, \underline{\xi}_2) \text{ and, } f^{n_4} := (\underline{\tau}, \bar{\xi}_1, \bar{\xi}_2).$$

644 We also assume that the only index of \mathcal{S} for which uniform Kreiss-Lopatinskii condition is violated is n_1 . We
 645 summarize the previous requests on the set of indices for the corner problem (1) in the following Hypothesis
 646 (which specifies Hypothesis 2.3):

647 *Hypothesis 22.* The corner problem (1) is in the class WR for the side $\partial\Omega_1$ and satisfies the uniform
 648 Kreiss-Lopatinskii condition on the side $\partial\Omega_2$. The set where the uniform Kreiss-Lopatinskii condition for the
 649 side $\partial\Omega_1$ breaks down Υ (see Definition 8) is given by $\Upsilon = \{\tilde{f}^{n_1} := (i\underline{\tau}, \underline{\xi}_1, \bar{\xi}_2)\}$.

650 Moreover to make sure that the transport along the boundary spreads the information away from the
 651 corner we will ask that $\underline{\tau}$ and $\bar{\xi}_2$ have opposite signs.

652 To conclude let us remark that when the frequency set \mathcal{F} , indexed by \mathcal{S} , is complete for the reflections
 653 and that when it admits a unique loop, then it follows from the definition of linked indices 18 that we have
 654 the following propositions: Firstly

655 **PROPOSITION 23.** *Let $i \in \mathcal{S}$ then there exists a unique type V sequence linking n_1 to i .*

656

657 *Moreover, one can write $\mathcal{S} \setminus \{n_1, n_2, n_3, n_4\}$ as a partition:*

$$658 \quad (45) \quad (\mathcal{S} \setminus \{n_1, n_2, n_3, n_4\}) = (\cup_{l \leq \mathfrak{C}_1} A_{a_l}) \cup (\cup_{m \leq \mathfrak{C}_2} B_{b_m}) \cup (\cup_{q \leq \mathfrak{C}_3} C_{c_q}) \cup (\cup_{r \leq \mathfrak{C}_4} D_{d_r}),$$

659 where A_{a_l} denotes the set of indices $i \in \mathcal{S}$ from which the type V sequence linking n_1 to i starts by a_l , B_{b_m}
 660 denotes the set of indices $i \in \mathcal{S}$ from which the type V sequence linking n_1 to i starts by (n_2, b_l) , C_{c_q} denotes
 661 the set of indices $i \in \mathcal{S}$ from which the type V sequence linking n_1 to i starts by (n_2, n_3, c_q) and D_{d_r} is the
 662 set of indices $i \in \mathcal{S}$ such that the type V sequence linking n_1 to i starts by (n_2, n_3, n_4, d_r) .

663 Secondly

664 **PROPOSITION 24.** *Let \mathcal{F} be complete for the reflections, under Assumption 21. Let \mathcal{S} be the index set ;
 665 then Φ and Ψ satisfy, in addition to the properties of Proposition 17, the four extra properties:*

666 *viii)*

$$667 \quad \Phi(n_1) \setminus \{n_2\} \subset \mathcal{S}_{io} \cup \mathcal{S}_{ii} \cup \mathcal{S}_{ev1}, \quad \Psi(n_1) \setminus \{n_1\} \subset \mathcal{S}_{oi} \cup \mathcal{S}_{ii} \cup \mathcal{S}_{ev2},$$

$$668 \quad \Phi(n_4) \setminus \{n_4\} \subset \mathcal{S}_{io} \cup \mathcal{S}_{ii} \cup \mathcal{S}_{ev1}, \quad \Psi(n_3) \setminus \{n_3\} \subset \mathcal{S}_{oi} \cup \mathcal{S}_{ii} \cup \mathcal{S}_{ev2}.$$

669 *ix) Let $i \in \mathcal{S}_{ii} \cup \mathcal{S}_{ev1}$ and $j \in \mathcal{S}_{ii} \cup \mathcal{S}_{ev2}$ then*


$$670 \quad i \in \Phi(n_1) \implies \Psi(i) = \{i\}, \quad j \in \Psi(n_1) \implies \Phi(j) = \{j\},$$

$$671 \quad i \in \Phi(n_4) \implies \Psi(i) = \{i\}, \quad j \in \Psi(n_3) \implies \Phi(j) = \{j\}.$$

672 Let $\underline{j} \in A_{\underline{a}} \setminus \{\underline{a}\}$, we denote by $\ell = (\ell_1, \dots, \ell_p)$ the sequence of type H linking \underline{j} to \underline{a} . Then, according to
 673 the parity of p , we have:

674 *x') If $p \in 2\mathbb{N}$, then $\underline{j} \notin \mathcal{S}_{oi}$. Moreover, if $\underline{j} \in \mathcal{S}_{ev1} \cup \mathcal{S}_{ii}$ then $\Psi(\underline{j}) = \{\underline{j}\}$.*

675 *x'') If $p \in 2\mathbb{N} + 1$, then $\underline{j} \notin \mathcal{S}_{io}$. Moreover, if $\underline{j} \in \mathcal{S}_{ev2} \cup \mathcal{S}_{ii}$ then $\Phi(\underline{j}) = \{\underline{j}\}$.*

FIG. 3. "Tree structure" of the frequency set \mathcal{F} .

676 Propositions 23 and 24 then permit to show that the set of indices \mathcal{I} has the "tree" structure depicted
 677 in the figure 2.

678

679 To conclude this section we define the following matrices which will be useful during the construction of
 680 the geometric optics expansions.

681 DEFINITION 25. For $j = 1, 2$ and $k \in \mathfrak{R}_j$. Let $f^k = (\underline{\tau}, \xi_1^k, \xi_2^k)$ be the associated frequency with the index
 682 k . We define $P_{ev,j}^k$ (resp. $Q_{ev,j}^k$) the projector on $E_j^{s,e}(i\underline{\tau}, \xi_{3-j}^k)$ (resp. $A_j E_j^{s,e}(i\underline{\tau}, \xi_{3-j}^k)$) with respect to the
 683 decomposition (27) (resp. (28)).

684 For $j = 1, 2$ and $k \in \mathcal{I}_{os}$. Let $f^k = (\underline{\tau}, \xi_1^k, \xi_2^k)$ be the associated frequency with the index k . We define
 685 P_j^k (resp. Q_j^k) the projector on $\ker \mathcal{L}(f^k)$ (resp. $A_j \ker \mathcal{L}(f^k)$) with respect to the decomposition (27) (resp.
 686 (28)). We also define R_j^k the partial-inverse of $\mathcal{L}(f^k)$ uniquely determined by:

$$687 \quad (46) \quad R_j^k \mathcal{L}(f^k) = I - P_j^k, \quad P_j^k R_j^k = R_j^k Q_j^k = 0.$$

688 **7. Geometric optics expansions for selfinteracting problems in the WR class.** The corner
 689 problem that we are now interested in reads:

$$690 \quad (47) \quad \begin{cases} L(\partial)u^\varepsilon = 0, & \text{on } \Omega_T, \\ B_1 u^\varepsilon|_{x_1=0} = g_M^\varepsilon, & \text{on } \partial\Omega_{1,T}, \\ B_2 u^\varepsilon|_{x_2=0} = 0, & \text{on } \partial\Omega_{2,T}, \\ u^\varepsilon|_{t \leq 0} = 0, & \text{on } \Omega, \end{cases}$$

691 where the source term g_M^ε is given by:

$$692 \quad (48) \quad g_M^\varepsilon(t, x_2) := \varepsilon^{M+1} e^{\frac{i}{\varepsilon}(\underline{\tau}t + \bar{\xi}_2 x_2)} g(t, x_2),$$

with $\underline{\tau} > 0$ fixed, $\bar{\xi}_2 < 0$ defined in (44) and where $M \in \mathbb{N} \setminus \{0\}$ is fixed⁵. The function g is zero for negative times and has its support in space away from the corner for all positive times. More precisely, there exists $y_0 > 0$ such that:

$$\forall t \in \mathbb{R}_+, \forall x_2 < y_0, g(t, x_2) = 0.$$

⁵The case $M = 0$ corresponds to the boundary value problem in the half space and will not be discussed here. We refer to [8] for a study in such a configuration.

693 The aim of this section is to construct the geometric optics expansion associated to the corner problem
 694 (47) up to a fixed time $T > 0$. More precisely, we want to show that, up to choose the support of the function
 695 g close enough to the corner, the geometric optics expansion suffers a number of amplifications that can be ar-
 696 bitrarily large. Indeed, due to the presence of the loop, the amplification arising for the amplitude associated
 697 to n_1 will be repeated at each cycle around the loop. More precisely, if one sets M in (48) and wants to show
 698 that the leading order in the WKB expansion is of order zero then it will be sufficient to choose g such that
 699 its support is close enough to the corner to ensure that M complete circuits has been made before the time T .
 700

Let us give more details about these times of travel. We fix a point $(0, \underline{y}^0) \in \partial\Omega_1$ such that $g(0, \underline{y}^0) \neq 0$
 and we draw the characteristic with group velocity v_{n_1} passing through $(0, \underline{y}^0)$. This characteristic intersects
 $\partial\Omega_2$ in a point $(\underline{x}^0, 0)$ after a certain time of travel $t_1(\underline{y}^0)$. In a second time we draw the characteristic
 with group velocity v_{n_2} passing through $(\underline{x}^0, 0)$. It intersects $\partial\Omega_1$ in a point $(0, \underline{y}^1)$ after a time $t_2(\underline{y}^0)$. We
 repeat the same process for the characteristics with group velocities v_{n_3} and v_{n_4} . Let $(\underline{x}^1, 0)$, $(0, \underline{y}^2)$ be
 the corresponding points of intersection and $t_3(\underline{y}^0)$, $t_4(\underline{y}^0)$ be the corresponding times of travel. An easy
 computation shows that:

$$\underline{y}^2 := \beta \underline{y}^0, \text{ and, } T_1(\underline{y}^0) := \sum_{j=1}^4 t_j(\underline{y}^0) = \alpha \underline{y}^0,$$

701 where the scalars α and β are given by:

$$702 \quad (49) \quad \alpha := -\frac{1}{v_{n_1,2}} \left(1 - \frac{v_{n_1,1}}{v_{n_2,1}} + \frac{v_{n_1,1}v_{n_2,2}}{v_{n_2,1}v_{n_3,2}} - \frac{v_{n_1,1}v_{n_2,2}v_{n_3,1}}{v_{n_2,1}v_{n_3,2}v_{n_4,1}} \right),$$

703

$$704 \quad (50) \quad \beta := \prod_{j=1}^4 \beta_j, \text{ with, } \beta_j := \begin{cases} \frac{v_{n_j,1}}{v_{n_j,2}}, & \text{if } j \text{ is odd,} \\ \frac{v_{n_j,2}}{v_{n_j,1}}, & \text{if } j \text{ is even,} \end{cases}$$

705 and where the $v_{n_j} := [v_{n_j,1} \ v_{n_j,2}]$ are the group velocities for the indices of the loop.

After $m \in \mathbb{N}^*$ circuits around the loop the initial point $(0, \underline{y}^0)$ comes back on $\partial\Omega_1$ in $(0, \underline{y}^{2m})$ after a total
 time of travel \underline{T}_m . It is easy to show that :

$$\underline{y}^{2m} := \beta^m \underline{y}^0, \text{ and, } \underline{T}_m = \underline{T}_m(\underline{y}^0) := \alpha \underline{y}^0 \sum_{k=0}^{m-1} \beta^k.$$

706 We point the fact that if $\beta < 1$, that is to say when the rays get closer and closer to the corner, the limit
 707 of the sum defining \underline{T}_m when m goes to infinity is finite. In other words, the rays reach the corner in a finite
 708 time $T_{max} := \alpha \underline{y}^0 \sum_{k=0}^{\infty} \beta^k$. In this particular situation we will thus assume that $T < T_{max}$.

It is clear that one can always choose \underline{y}^0 in such a way that:

$$\underline{T}_M \leq T < \underline{T}_{M+1}.$$

709 As already mentioned, if $t \in [\underline{T}_k, \min(\underline{T}_{k+1}, T)[$ one expects all the amplitudes of order less than $M-k+1$
 710 to be zero. Moreover it is also expected that the traces on $\partial\Omega_1$ of the amplitudes associated to the index n_1
 711 vanish for $x_2 < \underline{y}^{2k}$. Indeed, for $t \in [\underline{T}_k, \min(\underline{T}_{k+1}, T)[$, the information has only make k complete circuits
 712 around the loop, so it can not have been amplified more than k times and can not have been transported
 713 under the threshold \underline{y}^{2k} . This observation motivates the following definition:

DEFINITION 26. *Let us write, for $n \in \mathbb{N}$,*

$$u_{n,n_1}(t, x) := \nu_{n,n_1}(t, x)e + \check{v}_n(t, x),$$

714 where the vector e has been introduced in Definition 12 (this decomposition will be explained in paragraph
 715 7.1) and where $\check{v}_n \in \oplus_{j \in \Phi^*(n_1)} \ker \mathcal{L}(f^j)$. For $M \in \mathbb{N}$ we distinguish the two following subcases:

- 716 \diamond if $\beta \leq 1$, we say that the sequence of amplitudes $(u_{n,n_1})_{n \in \mathbb{N}}$ is in \mathcal{P}_{\leq} if for all $n \in \mathbb{N}$, $\nu_{n,n_1}|_{x_1=0}$ is in
 717 $\mathcal{P}_{b, \leq}^{M-n}$. Where the space $\mathcal{P}_{b, \leq}^{M-n}$ is the set of functions $\mu \in \mathcal{C}^\infty(]-\infty, T[, \mathcal{D}(\mathbb{R}_+))$ satisfying:
 718 $\dot{\imath}$ If $M-n > 0$, then for $-\infty < t < \underline{T}_{M-n}$, $\mu(t, x_2) = 0 \ \forall x_2 \in \mathbb{R}_+$, and for all k such that $M-n \leq k \leq M$,
 719 if $\underline{T}_k \leq t < \min(T, \underline{T}_{k+1})$, $\mu(t, x_2) = 0 \ \forall x_2 < \underline{y}^{2k}$.

720 ii) If $M - n \leq 0$, then μ is zero for negative times, and for all k such that $0 \leq k \leq M$, if $\underline{T}_k \leq t <$
 721 $\min(T, \underline{T}_{k+1})$, $\mu(t, x) = 0 \forall x_2 < \underline{y}^{2k}$.

722 iii) If $n \leq -1$ then $\mathcal{P}_b^{M-n} = \{0\}$.

723

724 \diamond If $\beta > 1$, we say that the sequence of amplitudes $(u_{n,n_1})_{n \in \mathbb{N}}$ is in $\mathcal{P}_>$ if for all $n \in \mathbb{N}$, $\nu_{n,n_1|x_1=0}$ is in
 725 $\mathcal{P}_{b,>}^{M-n}$. Where the space $\mathcal{P}_{b,>}^{M-n}$ is the set of functions $\mu \in \mathcal{C}^\infty(]-\infty, T[, \mathcal{D}(\mathbb{R}_+))$ satisfying:

726 i) If $M - n > 0$, then for $-\infty < t < \underline{T}_{M-n}$, $\mu(t, x_2) = 0 \forall x \in \mathbb{R}_+$, and for all k such that $M - n \leq k \leq M$,
 727 if $\underline{T}_k \leq t < \min(T, \underline{T}_{k+1})$, $\mu(t, x_2) = 0 \forall x < \underline{y}_0$.

728 ii) If $n \leq -1$ then $\mathcal{P}_b^{M-n} = \{0\}$.

729 The fact that we distinguish the profile space for $\beta \leq 1$ and for $\beta > 1$ is due to technical reasons which will
 730 be explained in paragraph 7.1.4. Notice that by definition we have $\mathcal{P}_{b,\leq}^{M-n} = \mathcal{P}_{b,\leq}^0$ for all $n > M$.

731

732 We are now able to describe the expected space of profiles:

733 DEFINITION 27. When $\beta \leq 1$, a sequence $(u_{n,k})_{n \in \mathbb{N}, k \in \mathcal{I}_{os}}$ is said to be in the space of profiles $\mathbb{P}_{os,\leq}$ if
 734 $(u_{n,n_1}) \in \mathcal{P}_\leq$ and if for all $k \in \mathcal{I}_{os} \setminus \{n_1\}$, for all $n \in \mathbb{N}$, $u_{n,k}$ lies in $H^\infty(\Omega_T)$.

735 When $\beta > 1$, a sequence $(u_{n,k})_{n \in \mathbb{N}, k \in \mathcal{I}_{os}}$ is said to be in the space of profiles $\mathbb{P}_{os,<}$ if $(u_{n,n_1}) \in \mathcal{P}_<$ and
 736 if for all $k \in \mathcal{I}_{os} \setminus \{n_1\}$, for all $n \in \mathbb{N}$, $u_{n,k}$ lies in $H^\infty(\Omega_T)$.

737

738 For $i = 1, 2$, the set $\mathbb{P}_{ev,i}$ of evanescent profiles for the side $\partial\Omega_i$ is the set of $U(t, x, X_i) \in H^\infty(\Omega_T \times \mathbb{R}_+)$
 739 for which there exists a positive δ such that $e^{\delta X_i} U(t, x, X_i) \in H^\infty(\Omega_T \times \mathbb{R}_+)$.

740 As already mentioned, we will have to consider three kinds of phases, the oscillating ones, the evanescent
 741 ones for the side $\partial\Omega_1$ and the evanescent ones for the side $\partial\Omega_2$. According to their kind the phases be denoted
 742 by:

$$\begin{aligned} 743 \quad \varphi_k(t, x) &:= \langle (t, x), f^k \rangle, \quad f^k \in \mathcal{F}_{os}, \\ 744 \quad \psi_{k,1}(t, x_2) &:= \langle (t, 0, x_2), f^k \rangle, \quad f^k \in \mathcal{F}_{ev1} \cup \mathcal{F}_{os}, \\ 745 \quad \psi_{k,2}(t, x_1) &:= \langle (t, x_1, 0), f^k \rangle, \quad f^k \in \mathcal{F}_{ev2} \cup \mathcal{F}_{os}. \end{aligned}$$

746 Once the expected phases are defined, we postulate the ansatz:

$$\begin{aligned} 747 \quad (51) \quad u^\varepsilon(t, x) &\sim \sum_{n \geq 0} \sum_{k \in \mathcal{I}_{os}} \varepsilon^n e^{\frac{i}{\varepsilon} \varphi_k(t, x)} u_{n,k}(t, x) \\ 748 \quad &+ \sum_{n \geq 0} \sum_{k \in \mathfrak{R}_1} \varepsilon^n e^{\frac{i}{\varepsilon} \psi_{k,1}(t, x_2)} U_{n,k,1} \left(t, x, \frac{x_1}{\varepsilon} \right) + \sum_{n \geq 0} \sum_{k \in \mathfrak{R}_2} \varepsilon^n e^{\frac{i}{\varepsilon} \psi_{k,2}(t, x_1)} U_{n,k,2} \left(t, x, \frac{x_2}{\varepsilon} \right), \end{aligned}$$

749 where $(u_{n,k})_{n \in \mathbb{N}, k \in \mathcal{I}_{os}} \in \mathbb{P}_{os,\leq}$ (resp. $\mathbb{P}_{os,<}$) for $\beta \leq 1$ (resp. $\beta > 1$), and for all $n \in \mathbb{N}, \forall k \in \mathfrak{R}_1$ (resp. \mathfrak{R}_2),
 750 $U_{n,k,1}$ (resp. $U_{n,k,2}$) is in $\mathbb{P}_{ev,1}$ (resp. $\mathbb{P}_{ev,2}$).

751

752 Plugging the ansatz (51) into the evolution equation of (47) leads us to the following cascade of equations
 753 in the interior :

$$(52) \quad \begin{cases} \mathcal{L}(d\varphi_k)u_{0,k} = 0, & \forall k \in \mathcal{I}_{os}, \\ i\mathcal{L}(d\varphi_k)u_{n+1,k} + L(\partial)u_{n,k} = 0, & \forall n \in \mathbb{N}, \forall k \in \mathcal{I}_{os}, \\ L_k(\partial_{X_1})U_{0,k,1} = 0, & \forall k \in \mathfrak{R}_1, \\ L_k(\partial_{X_1})U_{n+1,k,1} + L(\partial)U_{n,k,1} = 0, & \forall n \in \mathbb{N}, \forall k \in \mathfrak{R}_1, \\ L_k(\partial_{X_2})U_{0,k,2} = 0, & \forall k \in \mathfrak{R}_2, \\ L_k(\partial_{X_2})U_{n+1,k,2} + L(\partial)U_{n,k,2} = 0, & \forall n \in \mathbb{N}, \forall k \in \mathfrak{R}_2, \end{cases}$$

755 where the operators of differentiation in the fast variables $L_k(\partial_{X_1})$ and $L_k(\partial_{X_2})$ are defined by:

$$756 \quad (53) \quad L_k(\partial_{X_1}) := A_1(\partial_{X_1} - \mathcal{A}_1(\underline{T}, \xi_2^k)) \text{ for } k \in \mathfrak{R}_1,$$

$$757 \quad (54) \quad L_k(\partial_{X_2}) := A_2(\partial_{X_2} - \mathcal{A}_2(\underline{T}, \xi_1^k)) \text{ for } k \in \mathfrak{R}_2.$$

758 Then, plugging the ansatz (51) in the boundary conditions on $\partial\Omega_1$ and on $\partial\Omega_2$ gives:

$$759 \quad (55) \quad \begin{cases} B_1 \left[\sum_{j \in \Phi(n_1)} u_{n,j} \right]_{|x_1=0} = \delta_{n,M+1} g, & \forall n \in \mathbb{N} \\ B_1 \left[\sum_{j \in \Phi(k) \cap \mathcal{I}_{os}} u_{n,j} + U_{n,k,1} \right]_{|x_1=0} = 0, & \forall n \in \mathbb{N}, \forall k \in (\mathcal{R}_1 \setminus \{n_1\}) \cap \mathfrak{R}_1, \\ B_1 \left[\sum_{j \in \Phi(k)} u_{n,j} \right]_{|x_1=0} = 0, & \forall n \in \mathbb{N}, \forall k \notin (\mathcal{R}_1 \setminus \{n_1\}) \cap \mathfrak{R}_1, \\ B_2 \left[\sum_{j \in \Psi(k) \cap \mathcal{I}_{os}} u_{n,j} + U_{n,k,2} \right]_{|x_2=0} = 0, & \forall n \in \mathbb{N}, \forall k \in \mathfrak{R}_2, \\ B_2 \left[\sum_{j \in \Psi(k)} u_{n,j} \right]_{|x_2=0} = 0, & \forall n \in \mathbb{N}, \forall k \in \mathcal{R}_2 \setminus \mathfrak{R}_2, \end{cases}$$

760 where $\delta_{n,p}$ denotes the Kronecker symbol.

761 Finally, plugging the ansatz (51) into the initial condition of (47), gives:

$$762 \quad (56) \quad \forall n \in \mathbb{N}, \quad \begin{cases} u_{n,k}|_{t=0} = 0, & \forall k \in \mathcal{I}_{os}, \\ U_{n,k,1}|_{t=0} = 0, & \forall k \in \mathfrak{R}_1, \\ U_{n,k,2}|_{t=0} = 0, & \forall k \in \mathfrak{R}_2. \end{cases}$$

763 Thanks to the cascades of equations (52)-(55) and (56) we are now able to state our main result about
764 the construction of the geometric optics expansions:

765 **THEOREM 28.** *Let $T > 0$ and assume that the corner problem (47) satisfies Assumptions 1-2-21 and 22.*

766 \diamond *If $\beta > 1$, then for all $M \in \mathbb{N}$ the corner problem (47) admits a WKB expansion under the form (51).
767 More precisely there exist sequences of functions $(u_{n,k})_{n \in \mathbb{N}, k \in \mathcal{I}_{os}} \in \mathbb{P}_{os,>}$, $(U_{n,k,1}) \in \mathbb{P}_{ev1}$, and $(U_{n,k,2}) \in \mathbb{P}_{ev2}$
768 satisfying the cascades of equations (52)-(55) and (56). Moreover one can always choose g in such a way
769 that the leading order in (51) is not identically zero.*

770

771 \diamond *If $\beta \leq 1$, assume that $T < T_{max}$ if $\beta < 1$, then for all $M \in \mathbb{N}$ the corner problem (47) admits a WKB
772 expansion under the form (51). More precisely there exist sequences of functions $(u_{n,k})_{n \in \mathbb{N}, k \in \mathcal{I}_{os}} \in \mathbb{P}_{os,\leq}$,
773 $(U_{n,k,1}) \in \mathbb{P}_{ev1}$, and $(U_{n,k,2}) \in \mathbb{P}_{ev2}$ satisfying the cascades of equations (52)-(55) and (56). Moreover one
774 can always choose g in such a way that the leading order in (51) is not identically zero.*

775

776 The question is now to solve the cascades of equations (52)-(55) and (56). More precisely, to solve the
777 cascades, we are looking for an order of resolution of the different equations and an equation which can be
778 solved before all the others in view to initialize the resolution.

779

780 In [4] it is shown that to construct any amplitude in one of the "trees" (that is the sets composing the
781 partition (45) of \mathcal{S} depicted in Figure 2) it is in fact sufficient, thanks to the uniqueness of the type V
782 sequence linking any index of the "tree" to its root (see Proposition 23) and the uniform Kreiss-Lopatinskii
783 condition, to know the amplitude associated to the root. This is also the case here because this determination
784 only uses the uniform Kreiss-Lopatinskii condition which holds outside of the loop. Then it is shown that to
785 know the amplitudes associated to the roots it is sufficient to know the amplitudes associated to the loop's
786 indices. Thus the order of resolution will be exactly the same as in [4]. And also has in [4] the first amplitudes
787 that should be determined are the loop's amplitudes. So we need a new amplitude equation to determine the
788 loop's amplitudes and to initialize the resolution of the cascades of equations.

789

790 The first equation of the cascade (52) implies that we have the well-known polarization condition for the
791 oscillating amplitudes $u_{0,k}$, in particular for $k = n_1$, we have $u_{0,n_1} \in \ker \mathcal{L}(d\varphi_{n_1})$, in other words we can
792 write:

$$793 \quad (57) \quad P_1^{n_1} u_{0,n_1} = u_{0,n_1}.$$

794 But, thanks to Assumption 1, $\ker \mathcal{L}(d\varphi_{n_1})$ is one dimensional. Assumption 22 then permits to write:

$$795 \quad (58) \quad u_{0,n_1}(t, x) = \nu_{0,n_1}(t, x)e,$$

796 for some unknown scalar function ν_{0,n_1} and where e is the vector defined in 12.6 For other indices $k \in \mathcal{I}_{os}$

⁶Let us remark that (58) is not true anymore if the operator $L(\partial)$ is hyperbolic with constant multiplicity. In that framework,

797 we can always write:

$$798 \quad (59) \quad u_{0,k} = \nu_{0,k} e_k,$$

799 where $\nu_{0,k}$ is a scalar function and where e_k is a generator of $\ker \mathcal{L}(d\varphi_k)$.

800

801 More generally for any n let us introduce the notation:

$$802 \quad (60) \quad P_1^{n_1} u_{n,n_1}(t, x) = \nu_n(t, x) e,$$

803 where e is defined in Definition 12.

804

Next let us study the second equation of the cascade (52) written for $n = 0$ and $k = n_1$. If we compose this equation by $Q_1^{n_1}$ and use the fact that $\ker Q_1^{n_1} = \text{Ran} \mathcal{L}(d\varphi_{n_1})$ thanks to the polarization condition (57) we obtain that u_{0,n_1} satisfies the equation :

$$Q_1^{n_1} L(\partial) P_1^{n_1} u_{0,n_1} = 0.$$

805 From Lax's lemma [11], we have:

$$806 \quad (61) \quad Q_1^{n_1} L(\partial) P_1^{n_1} u_{0,n_1} = (\partial_t + v_{n_1} \cdot \nabla_x) \nu_{0,n_1} = 0,$$

807 where we used the fact that $Q_1^{n_1}$ induces an isomorphism from $\text{Ran} P_1^{n_1}$ to $\text{Ran} Q_1^{n_1}$. Using the fact that the
808 group velocity v_{n_1} is incoming-outgoing, to solve equation (61) we only need to determine the trace of ν_{0,n_1}
809 on $\{x_1 = 0\}$.

810

811 However, the degeneracy of the uniform Kreiss-Lopatinskii condition prevents to determine this trace by
812 the easy classical way. Indeed because without the uniform Kreiss-Lopatinskii condition we can not invert
813 the matrix B_1 upon the stable subspace $\ker \mathcal{L}(d\varphi_1)$ to recover the value of this trace. The only equation
814 where the trace of ν_{0,n_1} on $\partial\Omega_1$ seems to appear is the boundary condition (55) written for $n = 0$ that is:

$$815 \quad B_1 \left[\sum_{j \in \Phi(n_1)} u_{0,j} \right]_{|x_1=0} = 0.$$

816 From (58) and the fact that, by definition $e \in \ker B_1$, the boundary condition reads:

$$817 \quad B_1 \left[\sum_{j \in \Phi^*(n_1)} u_{0,j} \right]_{|x_1=0} = 0,$$

818 where we recall that $\Phi^*(n_1)$ stands for $\Phi(n_1) \setminus \{n_1\}$. As a consequence this equation does not give any infor-
819 mation about $\nu_{0,n_1}|_{x_1=0}$. So it seems that we shall find another way to determine $\nu_{0,n_1}|_{x_1=0}$. To do that, we
820 will start by using the method of [8] which has been introduced to construct the geometric optics expansion
821 for the initial boundary value problem belonging to the WR class in the half space and we will see how to
822 adapt this method.

823

824 Before to recall the main ideas of the method of determination of $\nu_{0,n_1}|_{x_1=0}$ by [8], let us remark the
825 following fact. If one assumes that $\nu_{0,n_1}|_{x_1=0}$ is known and write, once again in view to simplify the notations:
826

$$827 \quad (64) \quad \nu_{0,n_1}|_{x_1=0}(t, x_2) := \mu_0(t, x_2),$$

(58) has to be replaced by a decomposition reading :

$$u_{0,n_1}(t, x) = \nu_{0,n_1}(t, x) e + \check{v}(t, x),$$

where \check{v} lies in some subspace of $E_1^s(i_{\mathcal{I}}, \bar{\xi}_2)$. We can still apply Kreiss-Lopatinskii condition on this subspace. However, it seems that in that case, one can always determine \check{v} by reiterating the arguments of [4] which lead to ask for the invertibility of an operator reading under the form $(I - \mathbb{T})$.

828 then it is easy to determine the others amplitudes $u_{0,k}$, for $k = n_2, \dots, n_4$. Indeed, the transport equation
829 determining ν_{0,n_1} reads:

$$830 \quad \begin{cases} (\partial_t + v_{n_1} \cdot \nabla_x) \nu_{0,n_1} = 0, & \text{on } \Omega_T, \\ \nu_{0,n_1}|_{x_1=0} = \mu_0, & \text{on } \partial\Omega_{1,T}, \\ \nu_{0,n_1}|_{t \leq 0} = 0, & \text{on } \Omega. \end{cases}$$

831 Integrating along the characteristics we obtain the explicit formula:

$$832 \quad (66) \quad \nu_{0,n_1}(t, x_1, x_2) = \mu_0 \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right).$$

In particular, the trace of u_{0,n_1} on $\{x_2 = 0\}$ is given by

$$u_{0,n_1}|_{x_2=0} = \nu_{0,n_1}(t, x_1, 0)e,$$

so, thanks to the uniform Kreiss-Lopatinskii condition for the boundary condition (55) written for $n = 0$ and $k = n_2$ we are able to determine the trace on $\{x_2 = 0\}$ of ν_{0,n_2} . More precisely, from *viii*) Proposition (24), the boundary condition for u_{0,n_2} reads:

$$B_2 \left[\sum_{j \in (\Psi(n_2) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} + U_{0,n_2,2}|_{x_2=0} \right]_{|x_2=0} = -B_2 u_{0,n_1}|_{x_2=0}, \quad \text{if } n_2 \in \mathfrak{A}_2,$$

and

$$B_2 \left[\sum_{j \in (\Psi(n_2) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} \right]_{|x_2=0} = -B_2 u_{0,n_1}|_{x_2=0}, \quad \text{if } n_2 \in \mathfrak{B}_2 \setminus \mathfrak{A}_2,$$

Note that in both case the vector in the left hand side is an element of $E_2^s(i\tau, \underline{\xi}_1)$ so we can apply the uniform Kreiss-Lopatinskii condition. Recall that the inverse of B_2 on $E_2^s(i\tau, \underline{\xi}_1)$ is denoted by $\phi_2^{n_2}$, we apply this inverse and obtain:

$$\left[\sum_{j \in (\Psi(n_2) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} + U_{0,n_2,2}|_{x_2=0} \right]_{|x_2=0} = -\phi_2^{n_2} B_2 u_{0,n_1}|_{x_2=0}, \quad \text{if } n_2 \in \mathfrak{A}_2,$$

and

$$\left[\sum_{j \in (\Psi(n_2) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} \right]_{|x_2=0} = -\phi_2^{n_2} B_2 u_{0,n_1}|_{x_2=0}, \quad \text{if } n_2 \in \mathfrak{B}_2 \setminus \mathfrak{A}_2.$$

We then apply $P_2^{n_2}$ and recall the value of $u_{0,n_1}|_{x_2=0}$ to obtain that in both case:

$$u_{0,n_2}|_{x_2=0} = \nu_{0,n_2}|_{x_2=0} e_2 = -\nu_{0,n_1}|_{x_2=0} P_2^{n_2} \phi_2^{n_2} B_2 e.$$

We then write the vector in the right hand side of the previous equation as:

$$P_2^{n_2} \phi_2^{n_2} B_2 e = \mathcal{S}^{n_2} e_2,$$

833 to obtain the value of $\nu_{0,n_2}|_{x_2=0}$. Apply again Lax's Lemma we deduce that $\nu_{0,n_2}|_{x_2=0}$ solve the transport
834 equation (recall that n_2 is outgoing-incoming so only the boundary condition on $\partial\Omega_2$ is needed):

$$835 \quad \begin{cases} (\partial_t + v_{n_2} \cdot \nabla_x) \nu_{0,n_2} = 0, & \text{on } \Omega_T, \\ \nu_{0,n_2}|_{x_2=0} = -\mathcal{S}^{n_2} \mu_0, & \text{on } \partial\Omega_{2,T}, \\ \nu_{0,n_1}|_{t \leq 0} = 0, & \text{on } \Omega. \end{cases}$$

836 By integration along the characteristics we obtain:

$$837 \quad (68) \quad \nu_{0,n_2}(t, x_1, x_2) = -\mu_0(\mathbf{t}_2(t, x_1, x_2), \mathbf{x}_2(x_1, x_2)) \mathcal{S}_{n_2},$$

838 where

$$839 \quad (69) \quad \mathbf{t}_2(t, x_1, x_2) := t - \frac{1}{v_{n_1,1}} x_1 - \left[\frac{1}{v_{n_2,2}} - \frac{\beta_2^{-1}}{v_{n_1,1}} \right] x_2, \quad \mathbf{x}_2(x_1, x_2) := -\beta_1^{-1}(x_1 - \beta_2^{-1}x_2).$$

840 We can repeat exactly the same reasoning, applied to the amplitude u_{0,n_3} and then to the amplitude
841 u_{0,n_4} . We thus obtain their values in terms of the unknown trace μ_0 . More precisely we have:

$$842 \quad (70) \quad \nu_{0,n_3}(t, x_1, x_2) = \mu_0(\mathbf{t}_3(t, x_1, x_2), \mathbf{x}_3(x_1, x_2)) \mathcal{S}_{n_3},$$

843

$$844 \quad (71) \quad \nu_{0,n_4}(t, x_1, x_2) = -\mu_0(\mathbf{t}_4(t, x_1, x_2), \mathbf{x}_4(x_1, x_2)) \mathcal{S}_{n_4},$$

845 where we set for ν_{0,n_3} :

$$846 \quad (72) \quad \mathcal{S}^{n_3} := \mathbb{S}^{n_3} \mathcal{S}^{n_2},$$

$$847 \quad (73) \quad \mathbf{t}_3(t, x_1, x_2) := t - Ax_1 - \left[\frac{1}{v_{n_2,2}} - \frac{\beta_2^{-1}}{v_{n_1,1}} \right] x_2, \quad \text{and, } \mathbf{x}_3(x_1, x_2) := \prod_{j=1}^2 \beta_j^{-1}(x_2 - \beta_3^{-1}x_1),$$

848 with A a non-meaningful parameter introduced to simplify the notations. It is precisely given by:

$$849 \quad (74) \quad A := \frac{1}{v_{n_3,1}} - \beta_3^{-1} \left(\frac{1}{v_{n_2,2}} - \frac{\beta_2^{-1}}{v_{n_1,1}} \right).$$

850 And for ν_{0,n_4} :

$$851 \quad (75) \quad \mathcal{S}^{n_4} := \mathbb{S}^{n_4} \mathcal{S}^{n_3},$$

852

$$853 \quad (76) \quad \mathbf{t}_4(t, x_1, x_2) := t - Ax_1 - \left[\frac{1}{v_{n_4,2}} - \beta_4^{-1}A \right] x_2, \quad \text{and, } \mathbf{x}_4(x_1, x_2) := -\prod_{j=1}^3 \beta_j^{-1}(x_1 - \beta_4^{-1}x_2).$$

And finally where the scalars \mathbb{S}^{n_3} and \mathbb{S}^{n_4} appearing in (72) and (75) are defined by the relations:

$$P_1^{n_3} \phi_1^{n_3} B_1 e_2 := \mathbb{S}^{n_3} e_3, \quad \text{and } P_2^{n_4} \phi_2^{n_4} B_2 e_3 := \mathbb{S}^{n_4} e_4.$$

854 An important observation for what follows is to remark that the trace $\nu_{0,n_4|_{x_1=0}}$ depends on the particular
855 values, $\mathbf{t}_4(t, 0, x_2)$ and $\mathbf{x}_4(0, x_2)$. An easy computation shows that the constant in front of x_2 in $\mathbf{t}_4(t, 0, x_2)$
856 can in fact be expressed in terms of the parameters α and β , introduced in (49) and (50) and which encode
857 the time needed to make one complete circuit around the loop. More precisely, we have:

$$858 \quad (77) \quad \mathbf{t}(t, x_2) := \mathbf{t}_4(t, 0, x_2) = t - \alpha\beta^{-1}x_2, \quad \text{and, } \mathbf{x}(x_2) := \mathbf{x}_4(0, x_2) = \beta^{-1}x_2.$$

859 Let us also notice, because it will be important in paragraph 7.1.5, that the knowledge of u_{0,n_4} allows us
860 to express all the amplitudes in $\Phi^*(n_1)$ in terms of μ_0 . Indeed, Proposition 17 implies that these amplitudes
861 (except n_4) are in $\mathcal{S}_{ii} \cup \mathcal{S}_{io}$. So, let $\underline{i} \in \Phi^*(n_1) \setminus \{n_4\}$ to determine $u_{0,\underline{i}}$ for $\underline{i} \in \mathcal{S}_{io}$ (resp. $\underline{i} \in \mathcal{S}_{ii}$) we have
862 to solve the transport equation:

$$863 \quad (78) \quad \begin{cases} (\partial_t + v_{\underline{i}} \cdot \nabla_x) u_{0,\underline{i}} = 0, & \text{on } \Omega_T, \\ B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} u_{0,j} \right]_{|x_1=0} = -B_1 u_{0,n_4|_{x_1=0}}, & \text{on } \partial\Omega_{1,T}, \\ u_{0,\underline{i}|_{t \leq 0}} = 0, & \text{on } \Omega, \end{cases}$$

$$864 \quad (79) \quad \left(\text{resp. } \begin{cases} (\partial_t + v_{\underline{i}} \cdot \nabla_x) u_{0,\underline{i}} = 0, & \text{on } \Omega_T, \\ B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} u_{0,j} \right]_{|x_1=0} = -B_1 u_{0,n_4|_{x_1=0}}, & \text{on } \partial\Omega_{1,T}, \\ B_2 \left[\sum_{j \in \Psi(n_2)} u_{0,j} \right]_{|x_2=0} = 0, & \text{on } \partial\Omega_{2,T} \\ u_{0,\underline{i}|_{t \leq 0}} = 0, & \text{on } \Omega. \end{cases} \right)$$

However, by assumption, the index \underline{i} is associated with a frequency for which the uniform Kreiss-Lopatinskiĭ condition holds, so the boundary condition(s) of (78) (resp.(78)-(79)) can be written under the form:

$$u_{0,\underline{i}|_{x_1=0}} = -P_1^{\underline{i}}\phi_1^{\underline{i}}B_1u_{0,n_4|_{x_1=0}}, \left(\text{resp.} \begin{cases} u_{0,\underline{i}|_{x_1=0}} = -P_1^{\underline{i}}\phi_1^{\underline{i}}B_1u_{0,n_4|_{x_1=0}}, \\ u_{0,\underline{i}|_{x_2=0}} = 0. \end{cases} \right)$$

865 Using the expression of $u_{0,n_4|_{x_1=0}}$ and integrating along the characteristics we obtain the explicit expression:
866

$$867 \quad (80) \quad u_{0,\underline{i}}(t, x) = \mu_0 \left(\underline{\mathbf{t}} - \frac{1}{v_{\underline{i},1}}x_1, \underline{\mathbf{x}} - \frac{v_{\underline{i},2}}{v_{\underline{i},1}}x_1 \right) \mathcal{S}^{n_4} P_1^{\underline{i}}\phi_1^{\underline{i}}B_1e_4.$$

868 **7.1. Initialization of the resolution, determination of the loop's indices .** As already mentioned
869 in the previous paragraph to determine μ_0 we will adapt the method of [8] from the half space to the quarter
870 space geometry.

871 We study the boundary condition for the amplitude u_{1,n_1} that is (55) written for $n = 1$. This is a
872 natural choice because it is the only equation involoving $u_{0,n_1|_{x_1=0}}$. This boundary condition reads (recall
873 that $M \geq 1$):

$$874 \quad (81) \quad B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} P_1^j u_{1,j} \right]_{|_{x_1=0}} = -B_1 u_{1,n_4} - B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} (I - P_1^j) u_{1,j} \right]_{|_{x_1=0}}.$$

875 Thanks to Proposition 17, we know that $\Phi(n_1) \setminus \{n_4\}$ is included in $\mathcal{S}_{io} \cup \mathcal{S}_{ii}$, so the left hand side term is
876 in $B_1 E_1^s(i_{\mathcal{I}}, \bar{\xi}_2)$. By definition of b (see Definition 12) multiply by b in the left makes this term vanish. We
877 thus have:

$$878 \quad (82) \quad b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} (I - P_1^j) u_{1,j} \right]_{|_{x_1=0}} = -b \cdot B_1 u_{1,n_4}.$$

879
880

To make this equation more explicit in terms of μ_0 , we use the cascade of equation (52) written for $n = 0$.
Composing by the partial inverse R_1^k defined in Definition 25, leads us to the relation:

$$\forall j \in \Phi(n_1) \setminus \{n_4\}, (I - P_1^j) u_{1,j} = iR_1^j L(\partial) u_{0,j} = iR_1^j L(\partial) P_1^j u_{0,j},$$

881 where we used the polarization condition for $u_{0,j}$ in the right hand side. We thus can write (82) under the
882 form :

$$883 \quad (83) \quad b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) P_1^j u_{0,j} \right]_{|_{x_1=0}} = ib \cdot B_1 u_{1,n_4|_{x_1=0}}.$$

884 Let us recall the following proposition due to [8] :

885 PROPOSITION 29 ([8], Proposition 2). *For all $j \in \Phi(n_1) \setminus \{n_4\}$, and for all $k = 1, 2$ let P_k^j, Q_k^j and R_k^j
886 be defined in Definition 25 then we have $R_k^j A_k P_k^j = 0$.*

887 *Moreover let b be the vector introduced in Definition 12. Then there exists a nonzero real number κ such
888 that the following equality holds:*

$$889 \quad b \cdot B_1 \sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) P_1^j = \kappa (\Theta(i_{\mathcal{I}}, \bar{\xi}_2) \partial_t + \partial_{\xi_2} \Theta(i_{\mathcal{I}}, \bar{\xi}_2) \partial_2),$$

890 where Θ is defined in Definition 9. Moreover, $\partial_t \Theta(i_{\mathcal{I}}, \bar{\xi}_2) = 1$ and $\partial_{\xi_2} \Theta(i_{\mathcal{I}}, \bar{\xi}_2) = -\frac{\tau}{\xi_2} := \underline{c}$.

891 *Proof.* We refer to [8] for a complete proof. We will here just show that we have the equality $\partial_{\xi_2} \Theta(i_{\mathcal{I}}, \bar{\xi}_2) =$
892 $-\frac{\tau}{\xi_2}$. This equality was already shown in [[8], Lemma 7], but since it is important for our purpose, let us
893 give a proof for the sake of completeness.

Necessarily $\bar{\xi}_2 \neq 0$ otherwise the Kreiss-Lopatinskii condition will break down for $\gamma > 0$ and it would say that the boundary condition on $\partial\Omega_1$ does not satisfy the weak Kreiss-Lopatinskii condition. We then use the fact that $d = 2$ and the relation $R_1^j A_1 P_1^j = 0$. First we have :

$$\forall j \in \Phi(n_1) \setminus \{n_4\}, \mathcal{L}(d\varphi_j)P_1^j = \underline{\tau}P_1^j + \xi_1^j A_1 P_1^j + \bar{\xi}_2 A_2 P_1^j = 0,$$

we compose by R_1^j , the term $R_1^j A_1 P_1^j$ disappears. Then we sum over $j \in \Phi(n_1) \setminus \{n_4\}$ and multiply by $b \cdot B_1$ to obtain :

$$b \cdot B_1 \sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j A_2 P_1^j = -\frac{\underline{\tau}}{\bar{\xi}_2} b \cdot B_1 \sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j P_1^j.$$

894 A consequence of this proposition is to recover the transport phenomenon along the boundary already
895 observed in [8]. Moreover thanks to Proposition 29, the equation (83) can be expressed under the form:

$$896 \quad (85) \quad \left(\partial_t \mu_0 - \frac{\underline{\tau}}{\bar{\xi}_2} \mu_0 \right) = \frac{i}{\kappa} \left(b \cdot B_1 P_2^{n_4} u_{1,n_4|_{x_1=0}} + b \cdot B_1 (I - P_2^{n_4}) u_{1,n_4|_{x_1=0}} \right).$$

897 Thus to determine the unknown trace μ_0 , we want to solve the same transport equation as in [8]. But,
898 in the analysis of Coulombel and Guès the amplitude u_{1,n_4} which acts like a source term in (82) could be
899 determinated regardless μ_0 . Indeed, for the geometry of the half space u_{1,n_4} is an outgoing amplitude so it
900 satisfies a transport equation which does not require any boundary condition for its resolution (see [8] for
901 more details). As a consequence it can be determined just by integration along the characteristics of the
902 source term in the interior and the initial data (and is even zero if these terms vanish).

903 For the quarter space geometry it is not true anymore because u_{1,n_4} depends on u_{1,n_3} , which depends
904 on u_{1,n_2} and so on. However, equation (82) meets with the intuition that we gave in paragraph 4 because
905 this equation says that the amplification of order zero is "turned on" by the outgoing for the side $\partial\Omega_1$ (but
906 incoming for the side $\partial\Omega_2$) mode u_{1,n_4} . Moreover, we mentioned at the end of the previous paragraph that
907 amplitudes $u_{0,j}$ for $j = n_1, \dots, n_4$ can be expressed in terms of the unknown trace μ_0 .

908 So our purpose is now to express the amplitude u_{1,n_4} (which acts like a source term in (85)) in terms of
909 the unknown trace μ_0 . In view to do this, we will show in a first time that the unpolarized part $(I - P_2^{n_4})u_{1,n_4}$
910 can be expressed in terms of μ_0 . In a second time we will show that the polarized part $P_2^{n_4}u_{1,n_4}$ can be
911 expressed in terms of μ_0 and a new unknown trace μ_1 (which is just the unknown part of the polarized part
912 of the trace of u_{1,n_1} on the side $\partial\Omega_1$). The determination of the dependency on $(I - P_2^{n_4})u_{1,n_4}$ in terms of
913 μ_0 is made in the following paragraph.

914 **7.1.1. Unpolarized part of the terms of order one.** In a classical way, after composition of the
915 second equation of (52) (written for $n = 0$ and $k = n_j$, $j = 1, \dots, 4$) by the pseudo-inverse $R_1^{n_j}$ introduced in
916 Definition 25, we obtain that :

$$917 \quad (86) \quad (I - P_1^{n_j})u_{1,n_j} = iR_1^{n_j} L(\partial)u_{0,n_j}, \text{ if } j \text{ is odd, } (I - P_2^{n_j})u_{1,n_j} = iR_2^{n_j} L(\partial)u_{0,n_j}, \text{ if } j \text{ is even,}$$

918 where we used the fact that by definition $R_k^{n_j} \mathcal{L}(d\varphi_{n_j}) = I - P_k^{n_j}$, for $k = 1, \dots, 2$.

919
920 We then use the first equality in Proposition 29. Thanks to this lemma we can compute precisely the
921 values of the unpolarized part of the amplitudes of order one. Indeed for $(I - P_1^{n_1})u_{1,n_1}$ we thus have:

$$922 \quad (I - P_1^{n_1})u_{1,n_1} = -R_1^{n_1} [\partial_t + A_1 \partial_1 + A_2 \partial_2] \mu_0 \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right) e,$$

$$923 \quad (87) \quad = -[(\partial_t \mu_0) R_1^{n_1} e + (\partial_2 \mu_0) R_1^{n_1} A_2 e] \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right),$$

924 where we used the fact that $P_1^{n_1} e = e$.

925 But as $e \in \ker \mathcal{L}(d\varphi_{n_1})$, we have $(\underline{\tau} + \xi_1 A_1 + \bar{\xi}_2 A_2)e = 0$. We compose by $R_1^{n_1}$, and we use Proposition
926 29 to show that:

$$927 \quad (88) \quad R_1^{n_1} A_2 e = -\frac{\underline{\tau}}{\bar{\xi}_2} R_1^{n_1} e.$$

928 This relation permits to reformulate (87) under the form :

$$929 \quad (89) \quad (I - P_1^{n_1})u_{1,n_1} = - \left[\partial_t \mu_0 - \frac{\underline{\tau}}{\bar{\xi}_2} \partial_2 \mu_0 \right] \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right) R_1^{n_1} e.$$

930 The fact that one restricts the study to corner problems (1) in only two space dimensions is used in a non
 931 trivial way to establish relation (88) which allows us to reformulate (87) under the form (89). We will see in
 932 a moment why this reformulation is so important in the proof.

933 We do not know if the restriction $d = 2$ is really necessary, however it has the advantage to make all the
 934 following computations much more simpler.

935 The same computations can be repeated to determine the unpolarized part of the amplitudes u_{1,n_j} , for
 936 $j = 2, \dots, 4$. Unfortunately, since our aim is to determine the exact value of the trace $u_{1,n_4|_{x_1=0}}$, we also need
 937 the exact values of the unpolarized part of the amplitudes u_{1,n_j} , for $j = 2, \dots, 4$. After some computations,
 938 we find:

$$939 \quad (90) \quad (I - P_2^{n_2})u_{1,n_2} = \mathcal{S}^{n_2} \left[\left(1 + \frac{\tau}{v_{n_1,1}\xi_1} \right) \partial_t \mu_0 + \frac{\tau}{\xi_1} \partial_2 \mu_0 \right] (\mathbf{t}_2, \mathbf{x}_2) R_2^{n_2} e_2,$$

$$940 \quad (91) \quad (I - P_1^{n_3})u_{1,n_3} = -\mathcal{S}^{n_3} \left[\left(1 - \frac{\tau}{v_{n_2,2}\xi_2} \left(1 - \frac{v_{n_2,1}}{v_{n_1,1}} \right) \right) \partial_t \mu_0 + \frac{\tau}{\xi_2} \beta_2^{-1} \beta_1^{-1} \partial_2 \mu_0 \right] (\mathbf{t}_3, \mathbf{x}_3) R_1^{n_3} e_3,$$

$$941 \quad (92) \quad (I - P_2^{n_4})u_{1,n_4} = \mathcal{S}^{n_4} \left[\left(1 + \frac{\tau}{\xi_1} A \right) \partial_t \mu_0 + \frac{\tau}{\xi_1} \prod_{j=1}^3 \beta_j^{-1} \partial_2 \mu_0 \right] (\mathbf{t}_4, \mathbf{x}_4) R_2^{n_4} e_4.$$

942 At this step of the proof, the term depending on $(I - P_2^{n_4})u_{1,n_4}$ appearing in the right hand side of (85)
 943 is expressed in terms of the function μ_0 . So we just have to do the same for the term $P_2^{n_4}u_{1,n_4}$. In paragraph
 944 7.1.3 we will see how the knowledge of the unpolarized part of the amplitudes of order one enables us to
 945 determine the polarized part of the amplitudes of order one. However, before to do this determination, it
 946 is useful (because it will simplify a lot the computations) to express the unpolarized part of the amplitudes
 947 of order one in terms of the transport operator along the boundary. Moreover, as we will see in paragraph
 948 7.1.4, this reformulation will also be essential for the resolution of the initializing equation (85).

949 **7.1.2. Reformulation of equations (90)-(91) and (92).** The following lemma which is just an al-
 950 ggebraic property based on a simple computation is however fundamental for our analysis. Indeed it will
 951 permit to reformulate equation (85) in a much more pleasant and simple form. The fact that we are able to
 952 reformulate (85) in a particular form (more precisely under the form $(I - \tilde{T})(\mathcal{T}\mu_0)$ see (131) for more details)
 953 is not anodyne at all when one wants to solve (85) in view to determine μ_0 . Indeed it will permit to express
 954 $\mathcal{T}\mu_0$ as a sum of iterations of the transport operator along the boundary corresponding to the number of
 955 complete circuits that have been made.

956 LEMMA 30. *If $d = 2$, we have the following equalities:*

$$957 \quad (93) \quad 1 + \frac{\tau}{\xi_1 v_{n_1,1}} = -\frac{\bar{\xi}_2}{\xi_1} \beta_1^{-1},$$

$$958 \quad (94) \quad \left(1 - \frac{\tau}{v_{n_2,2}\xi_2} \left(1 - \frac{v_{n_2,1}}{v_{n_1,1}} \right) \right) = \frac{\bar{\xi}_2}{\xi_2} \beta_1^{-1} \beta_2^{-1},$$

$$959 \quad (95) \quad 1 + \frac{\tau}{\xi_1} A = -\frac{\bar{\xi}_2}{\xi_1} \beta_1^{-1} \beta_2^{-1} \beta_3^{-1},$$

960 where we recall that the parameter A appearing in (95) is defined in (74).

961 *Proof.* We will only demonstrate (95), the proofs of the two other equalities are simpler and follow exactly
 962 the same kind of computations.

963 First let us develop :

$$964 \quad (96) \quad 1 + \frac{\tau}{\xi_1} A = \frac{1}{\xi_1} \left[\bar{\xi}_1 + \frac{\tau}{v_{n_3,1}} \left(1 - \frac{v_{n_3,2}}{v_{n_2,2}} \left(1 - \frac{v_{n_2,1}}{v_{n_1,1}} \right) \right) \right],$$

$$965 \quad = \frac{1}{v_{n_3,1} v_{n_2,2} v_{n_1,1} \bar{\xi}_1} [v_{n_3,1} v_{n_2,2} v_{n_1,1} \bar{\xi}_1 + v_{n_2,2} v_{n_1,1} \tau - v_{n_3,2} v_{n_1,1} \tau + v_{n_3,2} v_{n_2,1} \tau].$$

We recall that for all $(\tau, \xi_1, \xi_2) \in V$, we have

$$\tau + \lambda(\xi_1, \xi_2) = 0.$$

966 Using the fact that λ is homogeneous of degree one, Euler's formula implies that:

$$967 \quad (97) \quad \tau + (\xi_1, \xi_2) \cdot \nabla_{\xi} \lambda(\xi_1, \xi_2) = 0.$$

968 In particular, applying (97) to $f^{n_1} = (\underline{\tau}, \underline{\xi}_1, \bar{\xi}_2)$, $f^{n_2} = (\underline{\tau}, \underline{\xi}_1, \underline{\xi}_2)$ and $f^{n_3} = (\underline{\tau}, \bar{\xi}_1, \underline{\xi}_2)$ we obtain respec-
969 tively:

$$970 \quad (98) \quad \underline{\tau} + v_{n_1,1} \underline{\xi}_1 + v_{n_1,2} \bar{\xi}_2 = 0,$$

$$971 \quad (99) \quad \underline{\tau} + v_{n_2,1} \underline{\xi}_1 + v_{n_2,2} \underline{\xi}_2 = 0,$$

$$972 \quad (100) \quad \underline{\tau} + v_{n_3,1} \bar{\xi}_1 + v_{n_3,2} \underline{\xi}_2 = 0.$$

973 From (100) we deduce that:

$$974 \quad (101) \quad v_{n_3,1} v_{n_2,2} v_{n_1,1} \bar{\xi}_1 = -v_{n_2,2} v_{n_1,1} \underline{\tau} - v_{n_2,2} v_{n_1,1} v_{n_3,2} \underline{\xi}_2.$$

975 Using (99) the second term in the right hand side of (101) this equation can be reformulate under the form:

$$976 \quad (102) \quad v_{n_2,2} v_{n_1,1} v_{n_3,2} \underline{\xi}_2 = v_{n_1,1} v_{n_3,2} \underline{\tau} + v_{n_2,1} v_{n_1,1} v_{n_3,2} \underline{\xi}_1.$$

977 We then use (98) in the second term in the right hand side of (102). We obtain:

$$978 \quad (103) \quad v_{n_2,1} v_{n_1,1} v_{n_3,2} \underline{\xi}_1 = -v_{n_2,1} v_{n_3,2} \underline{\tau} - v_{n_1,2} v_{n_2,1} v_{n_3,2} \bar{\xi}_2.$$

979 Combining equations (101), (102) and (103) it follows that:

$$980 \quad (104) \quad v_{n_3,1} v_{n_2,2} v_{n_1,1} \bar{\xi}_1 = -v_{n_2,2} v_{n_1,1} \underline{\tau} + v_{n_3,2} v_{n_1,1} \underline{\tau} - v_{n_3,2} v_{n_2,1} \underline{\tau} - v_{n_1,2} v_{n_2,1} v_{n_3,2} \bar{\xi}_2.$$

981 Equality (95) follows from (96) combined with (104).

982 \square

\square

983 For simplicity we introduce the notation:

$$984 \quad (105) \quad \mathcal{T} := \partial_t - \frac{\tau}{\xi_2} \partial_2,$$

985 which is the same transport operator along the boundary as in [8].

986

987 Thanks to Lemma 30 formulas (90)-(91) and (92), which give the unpolarized part of the amplitudes
988 u_{1,n_i} , for $i = 2, \dots, 4$, can be written under the following more pleasant form:

$$989 \quad (106) \quad (I - P_2^{n_2}) u_{1,n_2} = -\mathcal{S}^{n_2} \frac{\bar{\xi}_2}{\xi_1} \beta_1^{-1}(\mathcal{T} \mu_0)(\mathbf{t}_2, \mathbf{x}_2) R_2^{n_2} e_2,$$

$$990 \quad (107) \quad (I - P_1^{n_3}) u_{1,n_3} = -\mathcal{S}^{n_3} \frac{\bar{\xi}_2}{\xi_2} \prod_{j=1}^2 \beta_j^{-1}(\mathcal{T} \mu_0)(\mathbf{t}_3, \mathbf{x}_3) R_1^{n_3} e_3,$$

$$991 \quad (108) \quad (I - P_2^{n_4}) u_{1,n_4} = -\mathcal{S}^{n_4} \frac{\bar{\xi}_2}{\xi_1} \prod_{j=1}^3 \beta_j^{-1}(\mathcal{T} \mu_0)(\mathbf{t}_4, \mathbf{x}_4) R_2^{n_4} e_4.$$

992 We thus remark that the unpolarized part of the amplitudes u_{1,n_j} , $j = 1, \dots, 4$ depend of the same trans-
993 port operator which is precisely the transport operator applied to μ_0 in equation (85).

994

995 Let us conclude this paragraph by the determination of the unpolarized part of the amplitudes $u_{1,j}$ for
996 $\underline{j} \in \Phi(n_1)^* \setminus \{n_4\}$. The knowledge of these amplitudes will be useful in paragraph 7.1.5. From (80) and the
997 relation (86), one easily obtains, that after the reformulation of $(I - P_{n_4}) u_{1,n_4}$, we have:

$$998 \quad (109) \quad (I - P_1^{\underline{j}}) u_{1,\underline{j}|_{x_1=0}} = i \left[\mathcal{S}^{n_4} R_1^{\underline{j}} L(\partial) \mu_0(\mathbf{t}_4, \mathbf{x}_4) P_1^{\underline{j}} \phi_1^{\underline{j}} B_1 e_4 \right]_{|_{x_1=0}},$$

999 from which we deduce that up to some derivatives and scalar multiplications, $(I - P_1^{\underline{j}}) u_{1,\underline{j}|_{x_1=0}}$ depends on
1000 $\mu_0(\underline{\mathbf{t}}, \underline{\mathbf{x}})$.

1001 **7.1.3. Polarized part of the terms of order one.** The knowledge of the unpolarized part of the
 1002 amplitudes of order one enables us to determine the polarized part of the amplitudes of order one, and will
 1003 conclude the determination of the right hand side in equation (85).

1004 Indeed, let us consider equation (52) written for $n = 1$ and $k = n_j, j = 1, \dots, 4$. This equation reads:

$$1005 \quad i\mathcal{L}(d\varphi_{n_j})u_{2,n_j} + L(\partial)P_1^{n_j}u_{1,n_j} = -L(\partial)(I - P_1^{n_j})u_{1,n_j}, \text{ for } j \text{ odd,}$$

$$1006 \quad i\mathcal{L}(d\varphi_{n_j})u_{2,n_j} + L(\partial)P_2^{n_j}u_{1,n_j} = -L(\partial)(I - P_2^{n_j})u_{1,n_j}, \text{ for } j \text{ even.}$$

1007 We compose by $Q_1^{n_1}, Q_1^{n_3}$ in the first equation, by $Q_2^{n_2}, Q_2^{n_4}$ in the second one. This makes the term depending
 1008 of u_{2,n_j} disappears and from Lax's lemma we obtain that the polarized parts of order one satisfy the transport
 1009 equations:

$$1010 \quad (110) \quad (\partial_t + v_{n_j} \cdot \nabla_x)Q_1^{n_j}P_1^{n_j}u_{1,n_j} = -Q_1^{n_j}L(\partial)(I - P_1^{n_j})u_{1,n_j}, \text{ if } j = 1, 3,$$

$$1011 \quad (111) \quad (\partial_t + v_{n_j} \cdot \nabla_x)Q_2^{n_j}P_2^{n_j}u_{1,n_j} = -Q_2^{n_j}L(\partial)(I - P_2^{n_j})u_{1,n_j}, \text{ if } j = 2, 4,$$

1012 with initial and boundary conditions given by (55)-(56). A preliminary to obtain the exact values of the
 1013 solutions of (110)-(111) is thus to determine the source terms. This can be done thanks to the reformulation
 1014 made in paragraph 7.1.2. Let us start with the term $Q_1^{n_1}L(\partial)(I - P_1^{n_1})u_{1,n_1}$, from equation (89), an explicit
 1015 computation gives:

$$1016 \quad (112) \quad Q_1^{n_1}L(\partial)(I - P_1^{n_1})u_{1,n_1} = - \left[Q_1^{n_1}R_1^{n_1}e \left(\partial_{tt}^2\mu_0 - \frac{\tau}{\xi_2}\partial_{t2}^2\mu_0 \right) + Q_1^{n_1}A_2R_1^{n_1}e \left(\partial_{t2}^2\mu_0 - \frac{\tau}{\xi_2}\partial_{22}^2\mu_0 \right) \right]$$

$$1017 \quad \left(t - \frac{1}{v_{n_1,1}}x_1, x_2 - \beta_1^{-1}x_1 \right).$$

1018 Where we used the fact that $Q_1^{n_1}A_1R_1^{n_1}e = 0$ (see Proposition 29 for more details).

1019

1020 To make this equation more explicit in terms of μ_0 , as it has been done for the determination of the
 1021 unpolarized parts of order one, we are looking for a relation linking $Q_1^{n_1}R_1^{n_1}e$ and $Q_1^{n_1}A_2R_1^{n_1}e$ in view to
 1022 factorize (112).

1023 We recall that $\ker Q_1^{n_1} = \text{Ran } \mathcal{L}(d\varphi_{n_1})$ so for all $X \in \mathbb{C}^N$ we have $Q_1^{n_1}\mathcal{L}(d\varphi_{n_1})X = 0$. In particular, for
 1024 $X = R_1^{n_1}e$ we obtain:

$$1025 \quad (113) \quad \tau Q_1^{n_1}R_1^{n_1}e + \xi_1 Q_1^{n_1}A_1R_1^{n_1}e + \bar{\xi}_2 Q_1^{n_1}A_2R_1^{n_1}e = 0 \implies Q_1^{n_1}A_2R_1^{n_1}e = -\frac{\tau}{\xi_2}Q_1^{n_1}R_1^{n_1}e.$$

1026 Using this relation in (112) gives:

$$1027 \quad (114) \quad Q_1^{n_1}L(\partial)(I - P_1^{n_1})u_{1,n_1} = - \left[Q_1^{n_1}R_1^{n_1}e \left(\partial_{tt}^2\mu_0 - 2\frac{\tau}{\xi_2}\partial_{t2}^2\mu_0 + \left(\frac{\tau}{\xi_2} \right)^2 \partial_{22}^2\mu_0 \right) \right]$$

$$1028 \quad \left(t - \frac{1}{v_{n_1,1}}x_1, x_2 - \beta_1^{-1}x_1 \right),$$

$$1029 \quad = - [Q_1^{n_1}R_1^{n_1}e\mathcal{F}^2\mu_0] \left(t - \frac{1}{v_{n_1,1}}x_1, x_2 - \beta_1^{-1}x_1 \right),$$

1030

1031 where we recall that the transport operator \mathcal{F} is defined in (105).

1032 Let us remark that, exactly as for the unpolarized part of the amplitudes of order one, the source term
 1033 in (110) expresses in terms of the transport operator \mathcal{F} . However this time (114) involves some power of the
 1034 operator \mathcal{F} .

1035

1036 We then repeat the same kind of computations for the terms $Q_2^{n_2}L(\partial)(I - P_2^{n_2})u_{1,n_2}$, $Q_1^{n_3}L(\partial)(I -$
 1037 $P_1^{n_3})u_{1,n_3}$ and $Q_2^{n_4}L(\partial)(I - P_2^{n_4})u_{2,n_4}$. Using analogous relations as (113), more precisely:

$$1038 \quad (115) \quad Q_2^{n_2}A_1R_2^{n_2}\mathcal{F}^{n_2}e = -\frac{\tau}{\xi_1}Q_2^{n_2}R_2^{n_2}\mathcal{F}^{n_2}e,$$

$$1039 \quad (116) \quad Q_1^{n_3}A_2R_1^{n_3}\mathcal{F}^{n_3}e = -\frac{\tau}{\xi_2}Q_1^{n_3}R_1^{n_3}\mathcal{F}^{n_3}e,$$

$$1040 \quad (117) \quad Q_2^{n_4}A_1R_2^{n_4}\mathcal{F}^{n_4}e = -\frac{\tau}{\xi_1}Q_2^{n_4}R_2^{n_4}\mathcal{F}^{n_4}e,$$

1041 and Lemma 30 in equations (106)-(107) and (108), some tedious (but explicit) computations give:

$$1042 \quad (118) \quad Q_2^{n_2} L(\partial)(I - P_2^{n_2})u_{1,n_2} = \mathcal{S}^{n_2} \beta_1^{-2} \left(\frac{\bar{\xi}_2}{\bar{\xi}_1} \right)^2 (\mathcal{T}^2 \mu_0)(\mathbf{t}_2, \mathbf{x}_2)_2^{n_2} R_2^{n_2} e_2,$$

$$1043 \quad (119) \quad Q_1^{n_3} L(\partial)(I - P_1^{n_3})u_{1,n_3} = -\mathcal{S}^{n_3} \beta_1^{-2} \beta_2^{-2} \left(\frac{\bar{\xi}_2}{\bar{\xi}_2} \right)^2 (\mathcal{T}^2 \mu_0)(\mathbf{t}_3, \mathbf{x}_3) Q_1^{n_3} R_1^{n_3} e_3,$$

$$1044 \quad (120) \quad Q_2^{n_4} L(\partial)(I - P_2^{n_4})u_{1,n_4} = \mathcal{S}^{n_4} \prod_{j=1}^3 \beta_j^{-2} \left(\frac{\bar{\xi}_2}{\bar{\xi}_1} \right)^2 (\mathcal{T}^2 \mu_0)(\mathbf{t}_4, \mathbf{x}_4) Q_2^{n_4} R_2^{n_4} e_4.$$

1045 More details about those computations can be find in Appendix 9.2.

1046

1047 Now that the source term in equation (110) is express in terms of $\mathcal{T}^2 \mu_0$, we can solve this equation in
1048 terms of $\mathcal{T}^2 \mu_0$. From the strict dissipativity of (1), we have $\ker B_1 = E_1^s(i_{\mathcal{I}}, \bar{\xi}_2) = \text{vect} \{e\}$. So we write as
1049 in the beginning of paragraph 7.1:

$$1050 \quad (121) \quad P_1^{n_1} u_{1,n_1}(t, x_2) := \nu_{1,n_1}(t, x_2)e = \mu_1(t, x_2)e.$$

1051 The transport equation (110) becomes :

$$1052 \quad (122) \quad \begin{cases} (\partial_t + v_{n_1} \cdot \nabla_x) \nu_{1,n_1} = -\widetilde{Q}_1^{n_1} Q_1^{n_1} L(\partial)(I - P_1^{n_1})u_{1,n_1}, \\ \nu_{1,n_1}|_{x_1=0} = \mu_1(t, x_2) \\ \nu_{1,n_1}|_{t \leq 0} = 0, \end{cases}$$

1053 where $\widetilde{Q}_1^{n_1}$ denotes the inverse of the restriction of $Q_1^{n_1}$ to $\text{Ran} P_1^{n_1}$ and where the trace function μ_1 is an
1054 unknown. Then integrating along the characteristics gives the exact value of ν_{1,n_1} (and thus also of $P_1^{n_1} u_{1,n_1}$)
1055 in terms of the unknown traces μ_0, μ_1 . More precisely, we have to study two separates cases:

1056

1057 • $t - \frac{1}{v_{n_1,1} x_1} < 0$. Then the transported information is above the characteristic, the transported condition
1058 is the initial one. Moreover, as the function μ_0 is assumed to satisfy $\mu_{0|_{t \leq 0}} = 0$, one can check on (114) that the
1059 transport associated to the source term in the interior is zero. Consequently the associated solution is zero.

1060

1061 • $t - \frac{1}{v_{n_1,1} x_1} > 0$. Then the transported information is below the characteristic, the transported condition
1062 is the boundary condition and this time the transport associated to the source term in the interior does not
necessarily vanish. We Integrate along the characteristics to obtain the explicit value:

$$1063 \quad \nu_{1,n_1} = \mu_1 \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right) \\ 1064 \quad + c \int_0^{x_1} \mathcal{T}^2 \mu_0 \left(t - \frac{s}{v_{n_1,1}} - \frac{s}{v_{n_1,1}} (x_1 - s), x_2 - \beta_1^{-1} s - \beta_1^{-1} (x_1 - s) \right) ds \\ 1065 \quad (123) \quad = \mu_1 \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right) + c x_1 \mathcal{T}^2 \mu_0 \left(t - \frac{s}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right),$$

1066 for some explicit constant c .

1067 To obtain (123), one has to use the explicit value of the source term given in (114), and check that the
1068 source term lies along the characteristics. So the integral term in (123) is just a multiplication by the length
1069 of the characteristic.

1070 From this formula, and the formula giving the unpolarized part of u_{1,n_1} , we finally obtain the following
1071 value for u_{1,n_1} :

$$1072 \quad u_{1,n_1} = P_1^{n_1} u_{1,n_1} + (I - P_1^{n_1})u_{1,n_1} \\ 1073 \quad = [\mu_1 e + c x_1 \mathcal{T}^2 \mu_0 e - \mathcal{T} \mu_0 R_1^{n_1} e] \left(t - \frac{1}{v_{n_1,1}} x_1, x_2 - \beta_1^{-1} x_1 \right),$$

1074 from which, we deduce the value of $u_{1,n_1}|_{x_2=0}$ in terms of $\mathcal{T} \mu_0$ and μ_1 :

$$1075 \quad (124) \quad u_{1,n_1}|_{x_2=0} = [\mu_1 e + c x_1 \mathcal{T}^2 \mu_0 e - \mathcal{T} \mu_0 R_1^{n_1} e] \left(t - \frac{1}{v_{n_1,1}} x_1, -\beta_1^{-1} x_1 \right).$$

1076 where c stands for an explicitly computable constant.
1077

The knowledge of this trace enable us to determine the amplitude u_{1,n_2} (recall that $u_{1,n_1}|_{x_2=0}$ acts as a boundary source term in the transport equation determining u_{1,n_2}). Thus we can evaluate $u_{1,n_2}|_{x_1=0}$ and then determine the amplitude u_{1,n_3} . Finally the knowledge of $u_{1,n_3}|_{x_2=0}$ permits to determine the amplitude u_{1,n_4} and more precisely its trace on $\{x_1 = 0\}$ which appears in equation (85). Indeed, thanks to paragraph 7.1.1, to fully determine the u_{1,n_j} , $j = 2, \dots, 4$ it only remains to determine their polarized parts. Let us define:

$$P_2^{n_j} u_{1,n_j}(t, x) = \nu_{1,n_j}(t, x) e_j, \text{ for } j = 2, 4 \text{ and } P_1^{n_3} u_{1,n_3}(t, x) = \nu_{1,n_3}(t, x) e_3,$$

1078 then, thanks to the uniform Kreiss-Lopatinskii condition and the fact that $n_2 \in \mathcal{S}_{oi}$, ν_{1,n_2} satisfies the
1079 transport equation:

$$1080 \quad (125) \quad \begin{cases} (\partial_t + v_{n_2} \cdot \nabla_x) \nu_{1,n_2} = -\widetilde{Q}_2^{n_2} Q_2^{n_2} L(\partial)(I - P_2^{n_2}) u_{1,n_2}, \\ \nu_{1,n_2}|_{x_2=0} = -\mathcal{S}^{n_2} u_{1,n_1}|_{x_2=0} - \mathcal{S}^{n_2} (I - P_2^{n_2}) u_{1,n_2}|_{x_2=0}, \\ \nu_{1,n_2}|_{t \leq 0} = 0, \end{cases}$$

1081 where as for ν_{1,n_2} , $\widetilde{Q}_2^{n_2}$ denotes the inverse of the restriction of $Q_2^{n_2}$ to $\text{Ran} P_2^{n_2}$. The source terms in (125)
1082 are given by (118), (124) and (106). We integrate along the characteristics, once again there are two cases
1083 to separate:

1084 • $t - \frac{1}{v_{n_2,2x_2}} \leq 0$. The transported information comes from the initial condition. Noticing that the source
1085 term in the interior is evaluated in $\mathbf{t}_2(t, x) \leq t - \frac{1}{v_{n_2,2x_2}}$ (we recall that \mathbf{t}_2 is defined in (69)) we deduce that
1086 the transport of the source term in the interior is also zero.

1087 • $t - \frac{1}{v_{n_2,2x_2}} > 0$. The transported information comes from the boundary condition. We integrate along
1088 the characteristics. This gives:

$$1089 \quad (126) \quad \nu_{1,n_2} = -\mathcal{S}^{n_2} [\mu_1 + cx_1 \mathcal{I}^2 \mu_0 e - \mathcal{I} \mu_0 R_1^{n_1} e] (\mathbf{t}_2, \mathbf{x}_2) + c_2 x_2 \mathcal{I}^2 \mu_0 (\mathbf{t}_2, \mathbf{x}_2),$$

1090 where $c_2 := \beta_1^{-2} \left(\frac{\xi_2}{\xi_1} \right)^2 \widetilde{Q}_2^{n_2} Q_2^{n_2} R_2^{n_2} \mathcal{S}^{n_2} e$, however this value is not really important in the end of the proof.
1091 Once again the multiplication by the factor x_2 in the last term of the right hand side of (126) comes from
1092 the fact that the source term in the interior of (125) lies on the characteristics.

1093 So we now have an explicit formula for the polarized part of the amplitude $u_{n_2,1}$, from which we deduce
1094 the value of its trace on $\partial\Omega_1$. We then solve the transport equation and determine the trace of $u_{n_2,1}$ on $\partial\Omega_2$.
1095 Then we use this trace in the transport equation determining ν_{1,n_3} . Integrating along the characteristics
1096 we obtain the trace of $P_1^{n_3} u_{n_3,1}$. The important fact is that (as in the resolution of the resolution of (122)
1097 and (125)), the source term in the interior already lies along the characteristics so its contribution to the
1098 transport phenomenon is just a multiplication by x_1 of itself. Moreover equations (107) and (119) tell us that
1099 the source terms in the transport equation determining ν_{1,n_3} depends on μ_1 , $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$, all evaluated
1100 in $(\mathbf{t}_2, \mathbf{x}_2)$. As a consequence $P_1^{n_3} u_{1,n_3}$ depends on μ_1 , $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$, all evaluated in $(\mathbf{t}_3, \mathbf{x}_3)$, then from
1101 equation (107) so do u_{1,n_3} .

1102

1103 To conclude, we compute the trace of u_{1,n_3} on $\partial\Omega_2$ and we use it as a source term in the transport
1104 equation determining ν_{1,n_4} . Repeating exactly the same arguments we show that the $P_2^{n_4} u_{1,n_4}$ depends on
1105 μ_1 , $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$, all evaluated in $(\mathbf{t}_4, \mathbf{x}_4)$. This implies that $P_2^{n_4} u_{1,n_4}|_{x_1=0}$ depends on μ_1 , $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$,
1106 all evaluated in $(\mathbf{t}_4, \mathbf{x}_4)$.

1107

1108 Consequently the right hand side of (85) (because it only involves $P_2^{n_4} u_{1,n_4}|_{x_1=0}$ and $(I - P_2^{n_4} u_{1,n_4}|_{x_1=0})$)
1109 has been expressed in terms of μ_1 , $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$, all evaluated in (\mathbf{t}, \mathbf{x}) (recall the notation $(\mathbf{t}, \mathbf{x}) = (\mathbf{t}_4, \mathbf{x}_4)$),
1110 more precisely (85) reads:

$$1111 \quad (127) \quad (\mathcal{I} \mu_0)(t, x_2) - (\mathbb{T} \mu_0)(t, x_2) = \frac{i}{\kappa} \mathcal{S}^{n_4} e \mu_1(\mathbf{t}, \mathbf{x}),$$

1112 where \mathbb{T} is up to multiplications by some (possibly complicated functions) the sum of $\mathcal{I} \mu_0$ and $\mathcal{I}^2 \mu_0$ followed

1113 by the evaluation in $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ more precisely it reads: where the operator \mathbb{T} reads⁷:

1114 (128)
$$(\mathbb{T}u)(t, x_2) := c_1 u(\underline{\mathbf{t}}(t, x_2), \underline{\mathbf{x}}(x_2)) + c_2(t, x_2)(\mathcal{T}u)(\underline{\mathbf{t}}(t, x_2), \underline{\mathbf{x}}(x_2)).$$

This reformulation is the keystone of our construction because it permits to factorize the transport phenomenon along the boundary in the left hand side to rewrite (85) under the form :

$$[(I - \mathbb{T})(\mathcal{T}\mu_0)](t, x_2) = \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}),$$

1115 where we set $\tilde{\mu}_1 := \frac{i}{\kappa} \mathcal{S}^{n_4} e\mu_1$ and then drop the tilde and where we did the same operation (up to the sign)
1116 for \tilde{g}^8 .

1117

1118 In the following paragraph, we explain how this particular structure for equation (85) permits us to
1119 determine the unknown μ_0 .

1120 **7.1.4. Resolution of equation (85), preliminary study.** The resolution of equation (85) is based
1121 upon the study of the influence of the change of variables $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ on the profile spaces. We recall that these
1122 spaces are not defined in the same way depending on the value of the dilatation parameter β . That is why
1123 the resolution of equation (85) needs to be discussed in two distinct frameworks.

1124 *The case $\beta \leq 1$, the information gets closer of the corner or admits a periodic pattern.* Before to solve
1125 equation (85) we give a useful property of the behaviour spaces of profiles $\mathcal{P}_{b, \leq}^{M-n}$ compared with the change
1126 of variables $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$. More precisely this property states that if a function μ is one of the $\mathcal{P}_{b, \leq}^{M-n}$, which
1127 essentially means that it starts to be non-zero only after a certain time (corresponding to n complete circuits
1128 around the loop), then $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ will be non-zero only after the time corresponding to $n + 1$ complete circuits.
1129 If we use formally this result in (127) this means that the one order unknown trace can only affect the one
1130 order unknown trace after one complete circuit. This formally meets the intuition given in Section 4 which
1131 claims that the zero order amplitude in the WKB expansion has been turned on by the one order amplitude
1132 after it has made one complete circuit around the loop.

1133 **PROPOSITION 31.** *If $\mu \in \mathcal{P}_{b, \leq}^{M-n}$ then $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}}) \in \mathcal{P}_{b, \leq}^{M-n+1}$.*

1134 *Proof.* We assume that $M - n > 0$, the other possible values of $M - n > 0$ are treated similarly and will
1135 not be demonstrated here.

1136 In a first time we show that $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ is zero for $t \in]-\infty, \underline{T}_{M-n+1}[$.

1137 Firstly if $t < \underline{T}_{M-n}$ then so do $\underline{\mathbf{t}} < \underline{T}_{M-n}$ and the result is automatic. So we assume that $\underline{T}_{M-n} < t <$
1138 \underline{T}_{M-n+1} and $\underline{\mathbf{t}} < \underline{T}_{M-n+1}$. By definition of \mathcal{P}_b^{M-n} , $\mu(\underline{\mathbf{t}}, x)$ is zero if $x_2 < \beta^{M-n} \underline{y}_0$. Thus we restrict our
1139 attention to the case $x_2 \geq \beta^{M-n} \underline{y}_0$. We thus have that:

1140
$$\underline{\mathbf{t}} < \underline{T}_{M-n+1} - \alpha \beta^{M-n} \underline{y}_0 = \underline{T}_{M-n},$$

1141 from which it follows that $\mu(\underline{\mathbf{t}}, \cdot)$ is zero.

1142 Now, let k be such that $M - n + 1 \leq k \leq M$ and fix $t \in [\underline{T}_k, \min(\underline{T}_{k+1}, T)[$, we will distinguish three
1143 cases depending on the value of $\underline{\mathbf{t}}$:

1144 *i)* If $\underline{\mathbf{t}} < \underline{T}_{k-1}$ then it follows that:

1145 (130)
$$\underline{T}_k < t < \alpha \beta^{-1} x_2 + \underline{T}_{k-1},$$

1146 from which we deduce that $x_2 > \beta^k \underline{y}_0$. Consequently it is, in fact, not useful to study this case to show that
1147 $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ is zero for $x_2 < \beta^k \underline{y}_0$.

1148 *ii)* If $\underline{T}_{k-1} < \underline{\mathbf{t}} < \underline{T}_k$ then by definition of $\mathcal{P}_{b, \leq}^{M-n}$, $\mu(\underline{\mathbf{t}}, x)$ is zero for $x_2 < \beta^{k-1} \underline{y}_0$ and as a consequence
1149 $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ is zero for $x_2 < \beta^k \underline{y}_0$.

1150 *iii)* If $\underline{T}_k < \underline{\mathbf{t}}$ then we can repeat the argument applied in equation (130) to show that, this time,
1151 necessarily we have $\underline{y}_0 \beta^{k+1} > x_2$ for which we deduce that $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ is zero.

1152 \square \square

⁷Notice that the precise values of the constant c_1 and of the function c_2 can be exactly expressed from equations (108) and explicit computations in the resolution of the transport equations mentioned in paragraph 7.1.3. However, it is useless for our purpose.

⁸Let us stress that the operator \mathbb{T} of this paper has nothing in common with the operator \mathbb{T} of [4]. Indeed, the operator \mathbb{T} of [4] is of order zero and necessitates to be well-defined the uniform Kreiss-Lopatinskii condition.

1153 We also give a useful proposition concerning the influence of the change of variables (\mathbf{t}, \mathbf{x}) on the source
 1154 term g . This proposition shows that even if g is not in some \mathcal{P}_b^k the change of variable (\mathbf{t}, \mathbf{x}) has good
 1155 properties on the support of g . More precisely this proposition states that the change of variable (\mathbf{t}, \mathbf{x}) has
 1156 essentially the same influence on g that if it was a function in some \mathcal{P}_b^k .

PROPOSITION 32. *Let g be a smooth function which is zero for negative times and satisfying*

$$\forall t > 0, g(t, x) = 0 \text{ if } x < \underline{y}_0.$$

1157 *Then for all $l \in \mathbb{N}^*$, $g(\mathbf{t}^l, \mathbf{x}^l) \in \mathcal{P}_{b, \leq}^l$.*

1158 *Proof.* The proof picks up some ideas from the proof of Proposition 31. However, we give it for the sake
 1159 of completeness.

First let us show that $g(\mathbf{t}^l, \mathbf{x}^l) \in \mathcal{P}_{b, \leq}^l$ is zero for $t < \underline{T}_l$. If $\mathbf{t}^l < 0$, it is trivial so we assume that $\mathbf{t}^l \geq 0$
 and that $\mathbf{x}^l \geq \underline{y}_0$, then for $t < \underline{T}_l$ we have the following bound :

$$\mathbf{t}^l < \alpha \underline{y}_0 \left(\sum_{j=0}^{l-1} \beta^j - \beta^l \sum_{j=1}^l \beta^{-j} \right) < 0,$$

1160 which is a contradiction.

1161 Now let fix k such that $l \leq k \leq M$ and a time $t \in [\underline{T}_k, \min(T, \underline{T}_{k+1})[$. Once again let us assume that
 1162 $\mathbf{t}^l > 0$, so $g(\mathbf{t}^l, \mathbf{x}^l)$ is zero if $\mathbf{x}^l < \underline{y}_0$, from the support property of g . In other words $g(\mathbf{t}^l, \mathbf{x}^l)$ is zero for
 1163 $x < \beta^l \underline{y}_0$. But using the fact that $\beta \leq 1$ and that $l \leq k$ it follows, in particular, that $g(\mathbf{t}^l, \mathbf{x}^l)$ is zero for
 1164 $x < \beta^k \underline{y}_0$.

1165 \square

1166 With Propositions 31 and 32 in hand we now turn to the study of equation (85). At the end of the
 1167 previous paragraph we explained why (85) could be rewritten as:

$$1168 \quad (131) \quad [(I - \mathbb{T})(\mathcal{T}\mu_0)](t, x_2) = \mu_1(\mathbf{t}, \mathbf{x}),$$

1169 where we recall that \mathbb{T} is an operator reading under the form (128).

1170

1171 The idea of the resolution is to remark that the operator \mathbb{T} is expressed in the variables (\mathbf{t}, \mathbf{x}) and thus
 1172 the composition by \mathbb{T} "costs" in terms of time of travel the time needed to make one complete circuit around
 1173 the loop. Thus as we arrange the things in such a way that we can only make M turns around the loop,
 1174 one can always invert $I - \mathbb{T}$ by taking the Neumann serie expansion. Indeed, the terms associated with \mathbb{T}^j
 1175 with j large enough "cost too much time" to appear and consequently are zero. Then we show that we can
 1176 repeat exactly the same reasoning to show that we can express μ_0 in terms of μ_2 (the scalar component of
 1177 the unknown trace u_{2, n_1}) and so on to express μ_0 in terms of some μ_k (the scalar component of the unknown
 1178 trace u_{k, n_1}) for k arbitrarily large and in terms of the source term g . However, the trace μ_0 in fact does
 1179 not depend on μ_k for k arbitrarily large, because this should say that we have made an arbitrary number of
 1180 complete circuits around the loop. We thus determine μ_0 in terms of g only.

1181

1182 Formally, we can always invert the operator $(I - \mathbb{T})$ appearing in equation (131) by taking its Neumann
 1183 serie expansion. This gives the following formal value of $\mathcal{T}\mu_0$:

$$1184 \quad (132) \quad (\mathcal{T}\mu_0)(t, x_2) = \sum_{j \geq 0} \mathbb{T}^j \mu_1(\mathbf{t}, \mathbf{x}).$$

1185 Let us remark that the second sum in the right hand side of (132) reads :

$$1186 \quad (133) \quad \sum_{j \geq 1} (F_j(\mu_1))(\mathbf{t}^j, \mathbf{x}^j),$$

where the operators $F_j(\mu_1)$ are some explicitly computable operators and where \mathbf{t}^j and \mathbf{x}^j denote that we
 made the change of variables $(t, x) \rightarrow (\mathbf{t}^j(t, x_2), \mathbf{x}^j(x_2))$ j times that is:

$$\mathbf{t}^j = \mathbf{t}^j(t, x_2) := t - \alpha \sum_{l=0}^j \beta^{-l} x \text{ and } \mathbf{x}^j = \mathbf{x}^j(x) := \beta^{-j} x_2.$$

1187 Now remember that by definition of the profiles spaces (see Definition 27) we are looking for μ_1 to be
 1188 in $\mathcal{P}_{b,\leq}^{M-1}$, so using the fact that the operators F_j are sums of derivatives (up to some multiplication by
 1189 known functions), it follows that the $F_j(\mu_1)$ are in $\mathcal{P}_{b,\leq}^{M-1}$. Proposition 31 shows that $F_j(\mu_1)(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j)$ is in
 1190 $\mu_1 \in \mathcal{P}_{b,\leq}^{M-1+j}$.

1191 As a consequence, equation (132) in fact reads:

$$1192 \quad (134) \quad (\mathcal{T}\mu_0)(t, x) = \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}),$$

1193 which gives a rigorous, because the Neumann expansion for $(I - \mathbb{T})$ is finite, value of $(\mathcal{T}\mu_0)$ in terms of the
 1194 (still) unknown function $\mu_1 \in \mathcal{P}_{b,\leq}^{M-1}$. In terms of wave packets propagation (134) tells us that μ_0 , compared
 1195 to the others terms in the WKB expansion, only depends on μ_1 which has made a complete circuit around
 1196 the loop. This fact agrees with the intuition given in paragraph 4 that the amplitude u_{0,n_1} does not depend
 1197 on the amplitudes u_{n,n_1} for $n \geq 2$. Indeed these amplitudes do not have achieved enough complete circuits
 1198 around the loop to suffer enough amplifications and consequently they remain of higher order in terms of ε .
 1199 Let us also stress that the term depending on \tilde{g} in the right hand side of (134) starts to be evaluated in (t, x)
 1200 while the term depending on μ_1 is evaluated in $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$. This will be a crucial point in the following.

1201

1202 If we assume that μ_1 is a known function in $\mathcal{P}_{b,\leq}^{M-1}$, then is it easy to compute μ_0 : indeed by definition
 1203 of the transport operator \mathcal{T} , μ_0 satisfies the transport equation:

$$1204 \quad (135) \quad \begin{cases} (\mathcal{T}\mu)(t, x_2) = \left(\partial_t \mu_0 - \frac{\tau}{\xi_2} \partial_2 \mu_0 \right) (t, x_2) = \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}), & \text{for } (t, x_2) \in]-\infty, T] \times \mathbb{R}_+, \\ \mu_0|_{x_2=0} = 0, & \text{on } t \in]-\infty, T], \\ \mu_0|_{t \leq 0} = 0, & \text{on } x_2 \in \mathbb{R}_+, \end{cases}$$

1205 which can be integrated along the characteristics to obtain the value of μ_0 . Let us denote by \mathcal{K} the application
 1206 that to a given source term in the interior for the transport equation (135) associates the solution of the
 1207 transport equation (135). We can thus write:

$$1208 \quad (136) \quad \mu_0(t, x_2) = \mathcal{K}(\mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}})).$$

1209 We recall that we made the hypothesis that $\frac{\tau}{\xi_2} < 0$ (see Hypothesis 4.3), the transport operator \mathcal{T}
 1210 "pushes" the information away from the set $\{x_2 = 0\}$. As a consequence, integrating (135) along the
 1211 characteristics show that applying the operator \mathcal{K} does not destroy the property to be zero on the strip
 1212 $\{t \in]-\infty, T], 0 < x_2 < Y\}$, for some $Y > 0$. This remark justify the following proposition:

1213 **PROPOSITION 33.** *Let \mathcal{K} be the inverse of the transport operator \mathcal{T} defined previously. Then the profile*
 1214 *spaces are invariant sets under the action of \mathcal{K} . More precisely if $\mu \in \mathcal{P}_{b,\leq}^k$, for some $k \in \mathbb{N}$, then*
 1215 *$(\mathcal{K}\mu) \in \mathcal{P}_{b,\leq}^k$.*

1216 Consequently if $\mu_1 \in \mathcal{P}_{b,\leq}^{M-1}$ then equation (136) gives, as expected, a trace μ_0 in $\mathcal{P}_{b,\leq}^M$.

1217

1218 However (136) is not sufficient to determine μ_0 because the trace μ_1 is not a known function. That is
 1219 why in the following paragraph, we will study the unknown trace μ_1 . We will show that it can be expressed
 1220 in terms of the unknown trace μ_2 and μ_0 .

1221 But before that let us give some comments about the resolution of equation (85) in the case $\beta > 1$.

1222 *The case $\beta > 1$, the information does not approach the corner.* As for the case $\beta \leq 1$ we start by a
 1223 study of the influence of the change of variables $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ on the profile sets $\mathcal{P}_{b,>}^{M-n}$. The following proposition
 1224 is equivalent to Proposition 31 in the framework $\beta \leq 1$.

1225 **PROPOSITION 34.** *If $\mu \in \mathcal{P}_{b,>}^{M-n}$, then $\mu(\underline{\mathbf{t}}, \underline{\mathbf{x}}) \in \mathcal{P}_{b,>}^{M-n+1}$. In particular, $\mu(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j)$ is zero for $l \geq n + 1$.*

1226 The proof of this proposition is based on the same ideas than the proof of Proposition 31 but is simpler.
 1227 That is why we will not give a proof here.

1228

1229 Let us also note that thanks to the conditions imposed on the source term g , Proposition 32 is trivial in
 1230 the framework $\beta > 1$.

1231

1232 With Proposition 34 in hand it is then easy to show that the Neumann serie expansion associated with
 1233 equation (131) contains a finite number of non-zero terms. One can thus reiterate the arguments described

1234 in the framework $\beta \leq 1$, to show that (136) also holds for $\beta > 1$. Indeed in the framework $\beta \leq 1$ to establish
 1235 (136) we only use Proposition 31 and 32 but we do not use explicitly the fact that $\beta \leq 1$. Also remark that
 1236 Proposition 33 only uses the fact that $\frac{\tau}{\xi_2} < 0$ so this Proposition still holds for $\beta > 1$.

1237 **7.1.5. The equation on μ_n , $n > 0$.** In this paragraph we give an equation determining the unknown
 1238 scalar part of the trace $u_{n,n_1}|_{x_1=0}$ for all $n > 0$. As the reader may notice, this equation looks like equation
 1239 (85) determining the unknown trace of order zero μ_0 . However for $n > 0$, the equation involves some extra
 1240 terms. The appearance of these terms is due to the fact that, as already noticed in paragraph 7.1.1, the
 1241 amplitudes u_{n,n_1} are not polarized for $n > 0$.

1242 As it as been done at the beginning of Paragraph 7.1 for μ_0 , to obtain this new equation we study the
 1243 boundary condition (55) written for $j = n_1$:

$$1244 \quad B_1 \left[\sum_{j \in \Phi(n_1)} u_{n,j} \right]_{|x_1=0} = \delta_{n,M+1} g.$$

1245 And we decompose the amplitudes $\in \Phi(n_1) \setminus \{n_4\}$ and isolate the only outgoing-incoming phase n_4 to obtain:
 1246

$$1247 \quad (138) \quad B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} P_1^j u_{n,j} \right]_{|x_1=0} + B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} (I - P_1^j) u_{n,j} \right]_{|x_1=0} = \delta_{n,M+1} g - B_1 u_{n,n_4}|_{x_1=0}.$$

1248 According to Proposition 17, the first term in the left hand side of (138) is in $B_1 E_1^s(i_{\mathcal{T}}, \bar{\xi}_2)$. So take the
 1249 inner product of (138) by the vector b introduced in Definition 12 makes this term vanish. This gives:

$$1250 \quad (139) \quad b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} (I - P_1^j) u_{n,j} \right]_{|x_1=0} = \delta_{n,M+1} b \cdot g - b \cdot B_1 u_{n,n_4}|_{x_1=0}.$$

But let us recall that from the cascade of equations (52) we know that the unpolarized part of the amplitudes
 of order n are given by the polarized parts of the amplitudes of order $n - 1$. More precisely for all $j \in \mathcal{I}_{os}$
 we have:

$$(I - P_1^j) u_{n,j} = i R_1^j L(\partial) u_{n-1,j} = i R_1^j L(\partial) \left(P_1^j u_{n-1,j} + (I - P_1^j) u_{n-1,j} \right),$$

1251 and using this relation in equation (139) leads us to:

$$1252 \quad i b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) P_1^j u_{n-1,j} \right]_{|x_1=0} = b \cdot \delta_{n,M+1} g - b \cdot B_1 u_{n,n_4}|_{x_1=0}$$

$$1253 \quad (140) \quad - i b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) (I - P_1^j) u_{n-1,j} \right]_{|x_1=0}.$$

1254 We thus apply Proposition 29 to rewrite the left hand side in terms of the transport operator along the
 1255 boundary:

$$1256 \quad (141) \quad \mathcal{T} \mu_{n-1} = \delta_{n,M+1} b \cdot g - b \cdot B_1 u_{n,n_4}|_{x_1=0} - i b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) (I - P_1^j) u_{n-1,j} \right]_{|x_1=0},$$

1257 which tells us that the scalar unknown part of the amplitude u_{n-1,n_1} , namely μ_{n-1} , satisfies the same
 1258 transport equation as μ_0 up to the extra term $-i b \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial) (I - P_1^j) u_{n-1,j} \right]_{|x_1=0}$.

1259 However, we can reiterate the computations made in Paragraphs 7.1.1 and 7.1.3 to make the terms
 1260 $b \cdot B_1 u_{n,n_4}|_{x_1=0}$ explicit in terms of μ_{n-1} and μ_n . This shows that $b \cdot B_1 u_{n,n_4}|_{x_1=0}$ involves μ_n evaluated in

1261 $(\underline{t}, \underline{x})$ and also $\mathbb{T}(\mathcal{T}\mu_{n-1})$. We thus have:

$$1262 \quad (142) \quad [(I - \mathbb{T})(\mathcal{T}\mu_{n-1})](t, x_2) = \delta_{n, M+1} b \cdot g(t, x_2) + \mu_n(\underline{t}, \underline{x})$$

$$1263 \quad - ib \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial)(I - P_1^j) u_{n-1, j} \right]_{|x_1=0} (t, x_2),$$

1264 and we recover (85) up to the extra term $-ib \cdot B_1 \left[\sum_{j \in \Phi(n_1) \setminus \{n_4\}} R_1^j L(\partial)(I - P_1^j) u_{n-1, j} \right]_{|x_1=0}$ which involves
 1265 the $u_{n-1, j}$ for $j \in \Phi(n_1) \setminus \{n_4\}$ (and consequently μ_{n-1}) that is why we have to make this term more explicit
 1266 in terms of μ_{n-1} .

1267

To do this we reiterate the computations of paragraph 7.1.1 to treat the last term in the right hand side of (142). First we remark that the terms $(I - P_1^j)u_{n-1, j}$ for $j \neq n_1, n_4$ are given by equation (109) when $n = 2$. However the result is totally similar when $n > 2$. So after having applied the operator $R_1^j L(\partial)$ and taking the trace on $\{x_1 = 0\}$ one can show that the sum on $j \in \Phi^*(n_1) \setminus n_4$ appearing in the right hand side of (142) depends on $\mu_{n-2}(\underline{t}, \underline{x})$ (and possibly of the source term g). That is why we write:

$$\left[\sum_{j \in \Phi^*(n_1) \setminus \{n_4\}} R_1^j L(\partial)(I - P_1^j) u_{n-1, j} \right]_{|x_1=0} = (\Lambda_1 \mu_{n-2})(\underline{t}, \underline{x}),$$

1268 where Λ_1 is some explicitly computable operator which is a sum of derivatives and multiplications by scalar
 1269 functions. The exact expression of Λ_1 is not relevant for our discussion.

1270

The same argument holds for $(I - P_1^{n_1})u_{n-1, n_1}$. It is given by (89) in the case $n = 2$, but the computations are totally analogous when $n > 2$. We thus can write:

$$[R_1^{n_1} L(\partial)(I - P_1^{n_1})u_{n-1, n_1}]_{|x_1=0} = (\Lambda_0 \mu_{n-2})(t, x_2),$$

1271 where Λ_0 is an operator which acts like Λ_1 .

1272

1273 So (142) in its final form reads:

$$1274 \quad (143) \quad [(I - \mathbb{T})\mathcal{T}\mu_{n-1}](t, x_2) = \delta_{n, M+1} \tilde{g}(t, x_2) + \mu_n(\underline{t}, \underline{x}) + (\Lambda \mu_{n-2})(t, x_2),$$

1275 where we set $\tilde{g} := b \cdot g$ and $\Lambda u := (\Lambda_0 u)(t, x) + (\Lambda_1 u)(\underline{t}, \underline{x})$. The only point to keep in mind about Λ is that
 1276 the profile sets $\mathcal{P}_{b, \leq}^k$ and $\mathcal{P}_{b, >}^k$ are invariant sets for the operator Λ because this operator is a sum (up to
 1277 some multiplications) of derivatives and thus does not modify supports properties.

1278 **7.1.6. End of the resolution of equation (85).** In this paragraph we describe the end of the resolution
 1279 of equation (85) when $\beta \leq 1$. As we will see this resolution does not take into account the precise value of β
 1280 but only needs Proposition 31. Proposition 31 has its equivalent when $\beta > 1$ (that is to say Proposition 34).
 1281 So the proof given here will extend to the case $\beta > 1$.

1282 To save some notations, as β is not relevant in this discussion, we will denote \mathcal{P}_b^{M-n} in place of $\mathcal{P}_{b, \leq}^{M-n}$.

1283

1284 The end of paragraph 7.1.4 shows that (85) in fact reads:

$$1285 \quad (144) \quad \mu_0 = \mathcal{H}(\mu_1(\underline{t}, \underline{x})),$$

1286 from which we deduced that if $\mu_1 \in \mathcal{P}_b^{M-1}$ then $\mu_0 \in \mathcal{P}_b^M$. Because of the definition of the profile spaces
 1287 (see Definition 27) we assume that for all $1 \leq n \leq M+1$, $\mu_n \in \mathcal{P}_b^{M-n}$. Our aim is here to show that
 1288 equation (144) defines a unique $\mu_0 \in \mathcal{P}_b^M$ and to express this solution μ_0 as a function of the source term g .
 1289

1290 Using the analysis described in the previous paragraph we are now able to give more informations about
 1291 the unknown μ_1 . Indeed, (143) written for $n = 2$ reads:

$$1292 \quad (145) \quad [(I - \mathbb{T})\mathcal{T}\mu_1](t, x_2) = \delta_{M, 1} \tilde{g}(t, x_2) + \mu_2(\underline{t}, \underline{x}) + (\Lambda \mu_0)(t, x_2).$$

Using the fact that $\mu_0 \in \mathcal{P}_b^M$ and the fact that Λ keeps \mathcal{P}_b^M invariant we obtain that the term $(\Lambda\mu_0)(t, x)$ appearing in (145) is in \mathcal{P}_b^M . As in paragraph 7.1.4, we write the Neumann serie expansion associated to (145):

$$(\mathcal{T}\mu_1)(t, x_2) := \delta_{M,1} \sum_{j \geq 0} \mathbb{T}^j(\tilde{g}(t, x_2)) + \sum_{j \geq 0} \mathbb{T}^j(\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}})) + \sum_{j \geq 0} \mathbb{T}^j(\Lambda\mu_0(t, x_2)).$$

1293 Recall that each iteration of \mathbb{T} induces the evaluation in $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$. So from Proposition 31, $\mathbb{T}^j(\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}}))$ is zero
1294 for all $j \geq 2$ and $\mathbb{T}^j(\Lambda\mu_0(t, x_2))$ as soon as $j \geq 1$ (because $\mu_2 \in \mathcal{P}_b^{M-2}$ and $\Lambda\mu_0 \in \mathcal{P}_b^M$). From Proposition
1295 32, $\mathbb{T}^j(\tilde{g}(t, x_2))$ is zero for all $j \geq 2$. So the Neumann serie expansion only contains a finite number of terms
1296 and reads:

$$1297 \quad (146) \quad (\mathcal{T}\mu_1)(t, x_2) := \delta_{M,1}(\tilde{g}(t, x_2) + \mathbb{T}\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}})) + \mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mathbb{T}\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + (\Lambda\mu_0)(t, x_2).$$

1298 Up to the source term in the interior, μ_0 and μ_1 solve the same transport equation so we can write:

$$1299 \quad (147) \quad \mu_1(t, x_2) = \mathcal{K} \left(\delta_{M,1}(\tilde{g}(t, x_2) + \mathbb{T}\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}})) + \mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mathbb{T}\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + \Lambda\mu_0(t, x_2) \right).$$

1300 where we recall that \mathcal{K} is the operator that to a source term f associates the solution of the transport
1301 equation $\mathcal{T}u = f$. When we evaluate (147) in $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ we obtain, using Propositions 31 and 32, that:

$$1302 \quad (148) \quad \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}) = \mathcal{K} \left(\delta_{M,1}\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) \right).$$

1303 Let us stress that (148) written in this form is not true. Indeed in this formulation, we used the fact
1304 that \mathcal{K} and the evaluation $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ commute which is clearly false. However we are in this purpose only
1305 interested in the profile spaces in which the terms in the right hand side of (148) lie and we are not really
1306 interested in their precise values. As from Proposition 33, \mathcal{K} keeps the spaces \mathcal{P}_b^{M-n} invariant, our abuse
1307 of notations is not so important (as far as the spaces \mathcal{P}_b^{M-n} are concerned). But the reader has to keep in
1308 mind that if he really wants to compute the WKB expansion it is necessary to apply \mathcal{K} and then make the
1309 evaluation $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$.

1310

1311 From equations (144) and (148) we deduce that

$$1312 \quad (149) \quad \mu_0(t, x) = \mathcal{K} \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}) = \mathcal{K}^2 \left(\delta_{M,1}\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) \right).$$

1313 As a consequence μ_0 can be expressed in terms of μ_2 (and μ_2 only) evaluated in a time corresponding to two
1314 complete circuits around the loop. Once again this observation meets the intuition given in Section 4.

1315

1316 More generally, we can repeat exactly the same arguments for all $n \geq 1$ to obtain that: for all $n > 0$:

$$1317 \quad (150) \quad \mu_n(t, x_2) = \mathcal{K} \left(\delta_{n,M} \sum_{j=0}^M \mathbb{T}^j \tilde{g}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) + \sum_{j=1}^{\min(n+1, M)} \mathbb{T}^{j-1} \mu_{n+1}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) + \sum_{j=0}^{\min(n-1, M)} \mathbb{T}^j \Lambda \mu_{n-1}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) \right).$$

1318 If for all $0 < n \leq M+1$, $\mu_n \in \mathcal{P}_b^{M-n}$, these formulas make sense for $0 < n \leq M$ (because we can ensure that
1319 the Neumann serie expansion contains a finite number of terms). We deduce from (150) that for all $l \leq M$:

$$1320 \quad (151) \quad \mu_n(\underline{\mathbf{t}}^l, \underline{\mathbf{x}}^l) = \mathcal{K} \left(\delta_{n,M} \sum_{j=l}^M \mathbb{T}^j \tilde{g}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) + \sum_{j=l+1}^{\min(n+1, M)} \mathbb{T}^{j-1} \mu_{n+1}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) + \sum_{j=l}^{\min(n-1, M)} \mathbb{T}^j \Lambda \mu_{n-1}(\underline{\mathbf{t}}^j, \underline{\mathbf{x}}^j) \right),$$

1321 from which it follows that for all $n < M$, each $\mu_n(\underline{\mathbf{t}}^n, \underline{\mathbf{x}}^n)$ is equal to $\mu_{n+1}(\underline{\mathbf{t}}^{n+1}, \underline{\mathbf{x}}^{n+1})$, and that for $n = M$,
1322 $\mu_n(\underline{\mathbf{t}}^n, \underline{\mathbf{x}}^n)$ is equal to $g(\underline{\mathbf{t}}^M, \underline{\mathbf{x}}^M)$. A simple iteration in (149) shows that:

$$1323 \quad (152) \quad \mu_0(t, x_2) = \mathcal{K}^M \tilde{g}(\underline{\mathbf{t}}^M, \underline{\mathbf{x}}^M),$$

1324 equation determining in a unique way $\mu_0 \in \mathcal{P}_b^M$ in terms of the known source term g . This concludes the
1325 resolution of equation (85).

1326

1327 Let us point that (152) meets with the intuition described in Section 4 that μ_0 depends on the initial
 1328 information which has made M complete circuits around the loop.

1329

1330 Now that the value of the trace μ_0 is determine it end up the determination of the zero order amplitudes
 1331 of the loop indices. Indeed these four amplitudes are given by (66)-(68)-(70) and (71). The initialization of
 1332 the resolution of the cascades (52)-(55) and (56) is finished and we now have to determine all the others zero
 1333 order amplitudes in (51).

1334 **7.2. Determination of the others amplitudes in the WKB expansion.** Now that at least one
 1335 amplitude is determined to determine all the others it is sufficient to find an order of resolution. The main
 1336 feature in the quarter space geometry is that compared to the half space we do not have any natural order
 1337 of resolution. In fact we just have a partial order. However this partial order is sufficient to determine all
 1338 the others amplitudes in the WKB expansion.

1339 The construction and, in particular, the partial order of resolution used are exactly the same as in [4] so
 1340 we will not give all the details of this construction here. We refer to [4] for a complete proof.

1341 **7.2.1. Determination of the oscillating amplitudes.** Thanks to Proposition 23 the set of indices
 1342 $\mathcal{I}_{os} \setminus \{n_j\}$ can be expressed as a partition (see (45) and 3 for more details). We will here describe the
 1343 determination of an arbitrary oscillating amplitude associated to an index \underline{i} in one of the sets (or trees) let
 1344 us say A_{a_1} . The determination of the amplitudes in the others sets composing (45) is similar and will not be
 1345 discussed here.

1346

1347 Let us denote by $\ell_{\underline{i}} := (\ell_1, \ell_2, \dots, \ell_p)$ the type V sequence linking n_1 to \underline{i} (see Definition 18 and Proposition
 1348 23). By definition of the tree A_{a_1} (see again Definition 18), $\ell_1 = a_1$ and as a consequence ℓ_1 is associated to
 1349 an outgoing-incoming group velocity, ℓ_2 to an incoming-outgoing group velocity and so one (note that ℓ_p
 1350 is associated to an incoming-outgoing group velocity (resp. outgoing-incoming) if p is even (resp. odd)).

1351 Before to determine the amplitude associated to \underline{i} we will have to determine all the amplitudes in the
 1352 sequence $\ell_{\underline{i}}$. As it has been done to the loop's amplitudes (see Paragraph 7.1), thanks to the fact that u_{0,ℓ_1}
 1353 is polarized, we apply Lax's Lemma so u_{0,ℓ_1} satisfies the transport equation:

1354 (153)
$$(\partial_t + v_{\ell_1} \cdot \nabla_x)u_{0,\ell_1} = 0.$$

with homogeneous initial condition. As $\ell_1 \in \mathcal{I}_{oi}$ this transport equation needs a boundary condition on $\partial\Omega_2$
 to be solved. This boundary condition is given by cascade (55) written for $n = 0$ and $k = n_1$:

$$B_2 \left[\sum_{j \in (\Psi(n_1) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} + U_{0,n_1,2|_{x_2=0}} \right]_{|_{x_2=0}} = -B_2 u_{0,n_1|_{x_2=0}}, \text{ if } n_1 \in \mathfrak{R}_2,$$

or

$$B_2 \left[\sum_{j \in (\Psi(n_1) \cap \mathcal{I}_{os}) \setminus \{n_1\}} u_{0,j} \right]_{|_{x_2=0}} = -B_2 u_{0,n_1|_{x_2=0}}, \text{ if } n_1 \in \mathfrak{R}_2 \setminus \mathfrak{R}_2.$$

We reiterate the computations made for u_{0,n_2} (see the beginning of Section 7). We use the uniform Kreiss-
 Lopatinskii condition and then we multiply by $P_2^{\ell_1}$ to obtain in both cases:

$$u_{0,\ell_1|_{x_2=0}} = -P_2^{\ell_1} \phi_2^{n_1} B_2 u_{0,n_1|_{x_2=0}}.$$

1355 So we have to solve the transport equation:

1356
$$\begin{cases} (\partial_t + v_{\ell_1} \cdot \nabla_x)u_{0,\ell_1} = 0, & \text{in } \Omega_T, \\ u_{0,\ell_1|_{x_2=0}} = -P_2^{\ell_1} \phi_2^{n_1} B_2 u_{0,n_1|_{x_2=0}}, & \text{on } \partial\Omega_{2,T}, \\ u_{0,\ell_1 t \leq 0} = 0, & \text{on } \Omega, \end{cases}$$

1357 this equation can be integrate along the characteristics (because u_{0,n_1} and its trace on $\partial\Omega_{2,T}$ are known) to
 1358 determine u_{0,ℓ_1} . It is interesting to remark that if $t < \underline{T}_M$ then u_{0,n_1} is zero and so do u_{0,ℓ_1} . As a consequence
 1359 the amplification of order $M + 1$ only spreads to the amplitudes away from the loop for $t \geq \underline{T}_M$ (that is after

1360 M complete circuits). Also note that as $u_{0,n_1|x_2=0}$ vanishes in a neighborhood of $x_1 = 0$ so do $u_{0,\ell_1|x_2=0}$ and
 1361 by resolution of the transport equation $u_{0,\ell_1|x_1=0}$ is zero near $x_2 = 0$.

1362

1363 Then we construct u_{0,ℓ_2} . In view of the definition of the tree A_{ℓ_1} , $\ell_2 \in \mathcal{S}_{i_0}$ so u_{0,ℓ_2} is solution of:

$$1364 \quad \begin{cases} (\partial_t + v_{\ell_2} \cdot \nabla_x) u_{0,\ell_2} = 0, & \text{in } \Omega_T, \\ u_{0,\ell_2|x_1=0} = -P_1^{\ell_2} \phi_1^{\ell_1} B_1 u_{0,\ell_1|x_1=0}, & \text{on } \partial\Omega_{1,T}, \\ u_{0,\ell_2|t \leq 0} = 0, & \text{on } \Omega. \end{cases}$$

1365 This equation uniquely determines u_{0,ℓ_2} because $u_{0,\ell_1|x_1=0}$ is known and we have $u_{0,\ell_1|x_2=0} = 0$ for x_1 small
 1366 enough. We then proceed recursively to determine all the u_{0,ℓ_k} , $3 \leq k \leq p$.

1367

1368 We now turn to the construction of $u_{0,\underline{i}}$. We have to distinguish two cases according to the parity of p .
 1369 Let us assume that p is even. Then by definition of A_{ℓ_1} we have $\underline{i} \in \mathcal{S}_{oi} \cup \mathcal{S}_{ii}$. If $\underline{i} \in \mathcal{S}_{oi}$ the amplitude $u_{0,\underline{i}}$
 1370 solves:

$$1371 \quad \begin{cases} (\partial_t + v_{\underline{i}} \cdot \nabla_x) u_{0,\underline{i}} = 0, & \text{in } \Omega_T, \\ u_{0,\underline{i}|x_2=0} = -P_2^{\ell_2} \phi_2^{\ell_p} B_2 u_{0,\ell_p|x_2=0}, & \text{on } \partial\Omega_{2,T}, \\ u_{0,\underline{i}|t \leq 0} = 0, & \text{on } \Omega, \end{cases}$$

1372 if $\underline{i} \in \mathcal{S}_{oi}$ and we proceed as for u_{0,ℓ_1} .

If $\underline{i} \in \mathcal{S}_{ii}$, then $u_{0,\underline{i}}$ solves the same transport equation but this time it needs boundary conditions
 on both sides of the boundary. The boundary condition on $\partial\Omega_2$ is unchanged. Concerning the boundary
 condition on $\partial\Omega_1$ it reads (recall that incoming-incoming phases do not create new phases):

$$B_1 u_{0,\underline{i}|x_1=0} = 0.$$

1373 As $\underline{i} \in \mathcal{S}_{ii}$, $u_{0,\underline{i}|x_1=0} \in E_1^s(i_T, \xi_2^{\underline{i}})$, where $\xi_2^{\underline{i}}$ is the ordinate of $f^{\underline{i}}$, so thanks to the uniform Kreiss-Lopatinskii
 1374 we obtain $u_{0,\underline{i}|x_1=0} = 0$. Consequently $u_{0,\underline{i}}$ solves :

$$1375 \quad \begin{cases} (\partial_t + v_{\underline{i}} \cdot \nabla_x) u_{0,\underline{i}} = 0, & \text{in } \Omega_T, \\ u_{0,\underline{i}|x_1=0} = 0, & \text{on } \partial\Omega_{1,T}, \\ u_{0,\underline{i}|x_2=0} = -P_2^{\ell_2} \phi_2^{\ell_p} B_2 u_{0,\ell_p|x_2=0}, & \text{on } \partial\Omega_{2,T}, \\ u_{0,\underline{i}|t \leq 0} = 0, & \text{on } \Omega. \end{cases}$$

1376 This equation can be solved with a highly regular solution (which is needed to compute the higher order
 1377 amplitudes $u_{n,\underline{i}}$ as they involve derivatives of $u_{0,\underline{i}}$) because $u_{0,\ell_p|x_2=0}$ is zero at $x_1 = 0$. If $u_{0,\ell_p|x_2=0}$ is not
 1378 zero at $x_1 = 0$ then we only recover $u_{0,\underline{i}} \in L^2(\Omega)$ (see [4] for more details).

1379 **7.2.2. Determination of the evanescent amplitudes.** In this paragraph we conclude the construc-
 1380 tion of the leading order of the geometric optics expansion by giving elements of proof to construct an
 1381 arbitrary evanescent amplitude associated to the index \underline{i} lying in the tree A_{a_1} . Without loss of generality we
 1382 assume that this amplitude is evanescent for the side $\partial\Omega_1$. Proposition 24 implies that the type V sequence
 1383 $\ell_{\underline{i}} := (\ell_1, \ell_2, \dots, \ell_p)$ linking n_1 to \underline{i} has an odd number of terms. Moreover, from the previous paragraph all the
 1384 ℓ_j has already been constructed. We then recall the following lemma due to [12] which states that evanescent
 1385 equations in the cascade (52) can be solved in the profile space $\mathbb{P}_{ev,1}$:

1386 LEMMA 35. For $j = 1, 2$, and $\underline{k} \in \mathfrak{R}_i$, let

$$1387 \quad (158) \quad \mathbb{P}_{ev,j}^{\underline{k}} U(X_j) := e^{X_j \mathcal{A}_j(\underline{\tau}, \xi_{3-j}^{\underline{k}})} P_{s,j}^{\underline{k}} U(0),$$

$$1388 \quad (159) \quad \mathbb{Q}_{ev,j}^{\underline{k}} F(X_j) := \int_0^{X_j} e^{(X_j-s) \mathcal{A}_j(\underline{\tau}, \xi_{3-j}^{\underline{k}})} P_{s,j}^{\underline{k}} A_j^{-1} F(s) ds - \int_{X_j}^{+\infty} e^{(X_j-s) \mathcal{A}_j(\underline{\tau}, \xi_{3-j}^{\underline{k}})} P_{u,j}^{\underline{k}} A_i^{-1} F(s) ds.$$

1389 Then, for all $F \in \mathbb{P}_{ev,j}$ the equation:

$$1390 \quad L_{\underline{k}}(\partial_{X_j}) U = F,$$

1391 admits a solution in $\mathbb{P}_{ev,i}$. Moreover, this solution reads:

$$1392 \quad U = \mathbb{P}_{ev,i}^k U + \mathbb{Q}_{ev,i}^k F.$$

This lemma tells us that to construct any evanescent amplitude for the side $\partial\Omega_1$ it is in fact sufficient to know the value of the trace the solution on $\{X_1 = 0\}$. Following [12], to determine this trace we study the boundary condition (55) written for $k = \underline{i}$ and $n = 0$ from which we deduce the value of the "double" trace on $\{X_1 = x_1 = 0\}$. Indeed thanks to the uniform Kreiss-Lopatinskii condition we obtain:

$$U_{0,\underline{i},k|_{X_1=x_1=0}} = -P_{ev,1}^{\underline{i}} \phi_1^{\underline{i}} B_1 u_{0,\ell_p|_{x_1=0}},$$

1393 where we recall that the right hand side has already been determined.

Then as in [12], we are free to straighten the "double" trace into a "single" one by setting (for example):

$$U_{0,\underline{i},k|_{X_1=0}} = -\chi(x_1) S_{ev,1}^{\underline{i}} B_1 u_{0,\ell_p|_{x_1=0}},$$

1394 where χ is some function in $\mathcal{D}(-1, +\infty[)$ satisfying $\chi(0) = 1$.

1395

1396 It is interesting to remark that evanescent amplitudes suffer the same amplification as the oscillating ones
1397 and this even if the degeneracy of the uniform Kreiss-Lopatinskii condition is in the hyperbolic region and
1398 thus not related to complex phases. Such a behaviour is not observable for the hyperbolic boundary value
1399 problem in the half space because the possible evanescent modes are "turned on" by the source term and can
1400 not be "turned on" by oscillating modes. As for the oscillating amplitudes, one can show that evanescent
1401 amplitudes of order zero are zero for $t < \underline{T}_M$.

1402 **7.3. Construction of the higher order terms and summary.** As for the construction of the leading
1403 order of the WKB expansion, we have to distinguish the case $\beta \leq 1$ and the case $\beta > 1$. But once again we
1404 only need Proposition 31 (resp. Proposition 34) to conclude if $\beta \leq 1$ (resp. $\beta > 1$) so the proof is the same
1405 in both cases. We will assume that $\beta \leq 1$ and we continue to note \mathcal{P}_b^{M-n} for $\mathcal{P}_{b,\leq}^{M-n}$.

1406 **7.3.1. The term of order one.** Once the amplitudes of order zero, and more precisely the keystone
1407 μ_0 , are determined we can repeat our method of construction to determine the amplitudes of order one. As
1408 for the leading order, we start by the determination of the indices of the loop, that is the n_j for $j = 1, \dots, 4$.
1409 We remark that equations (89)-(106)-(107) and (108) give the unpolarized part of the u_{1,n_j} , $j = 1, \dots, 4$
1410 in terms of μ_0 (which at this step of the proof is a known function). Similarly the values of the polarized parts
1411 are determined in terms of the unknown trace μ_1 .

1412 So it remains to determine the unknown trace μ_1 to construct the amplitudes of order one for the loop's
1413 elements. Noticing that the unpolarized part of the amplitudes for the indices outside of the loop are deter-
1414 mined (because from (86) they only depend on the associated amplitude of order zero) and reiterating the
1415 same computations as in paragraph 7.2 determines their polarized part in terms of μ_1 . As a consequence we
1416 just have to determine μ_1 to construct all the oscillating amplitudes of order one.

1417

1418 To do this from paragraph 7.1.4, μ_1 satisfies equation (147), that is:

$$1419 \quad (162) \quad (\mathcal{T}\mu_1)(t, x_2) := \delta_{M,1} (\tilde{g}(t, x_2) + \mathbb{T}\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mathbb{T}^2\tilde{g}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)) + (\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \mathbb{T}\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)) + \Lambda\mu_0(t, x_2).$$

1420 where μ_2 , appearing in the right hand side, is assumed to be \mathcal{P}_b^{M-2} and where we used the notations of
1421 paragraph 7.1.4. From (162), after integration along the characteristics, we deduce that:

$$1422 \quad (163) \quad \mu_1(t, x) = \mathcal{K} \left(\delta_{M,1} \sum_{k=0}^1 \mathbb{T}^k \tilde{g}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) + \Lambda\mu_0(t, x) \right) + \delta_{M \geq 2} \mathcal{K} \left(\sum_{k=1}^{\min(M,2)} \mathbb{T}^{k-1} \mu_2(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) \right).$$

1423 In this equation the first term in the right hand side is a known function which only depends on \tilde{g} . So
1424 to express μ_1 in terms of \tilde{g} we just have to express $\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ and $\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)$ in terms of \tilde{g} . In view to do so, we
1425 use equation (143) written for $n = 3$ to obtain:

$$1426 \quad (164) \quad \mu_2(t, x) = \mathcal{K} \left(\delta_{M,2} \sum_{k=0}^2 \mathbb{T}^k \tilde{g}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) + \sum_{k=1}^{\min(M,3)} \mathbb{T}^{k-1} \mu_3(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) \right) + \mathcal{K} (\Lambda\mu_1(t, x) + \mathbb{T}\Lambda\mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}})),$$

1427 and a new difficulty appears in (164) compared to (136). Indeed in (164) two terms, while there is only one in
 1428 (136) (in terms of μ_0 , depend on μ_1 each of them lying respectively in \mathcal{P}_b^M and in \mathcal{P}_b^{M-1} . So *a priori* they
 1429 are not zero. However in (163) we are not interested in μ_2 but we are interested in $\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ and $\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)$.
 1430 A simple change of variables in (164) shows that these quantities are given by:

$$1431 \quad (165) \quad \mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}}) = \mathcal{K} \left(\delta_{M,2} \sum_{k=1}^2 \mathbb{T}^{k-1} \tilde{g}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) + \sum_{k=2}^{\min(M,3)} \mathbb{T}^{k-2} \mu_3(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) \right) + \mathcal{K} \Lambda \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}),$$

$$1432 \quad \mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) = \mathcal{K} (\delta_{M,2} \tilde{g}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + \delta_{M \geq 3} \mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)),$$

1433 where for $I \subset \mathbb{R}$, δ_I is the characteristic function of I . Now let us make the change of variables $(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ in
 1434 (163), it follows that :

$$1435 \quad \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}) = \delta_{M,1} \mathcal{K} (\tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}})) + \delta_{M \geq 2} \mathcal{K} \mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2).$$

1436 that is to say :

$$1437 \quad (167) \quad \mathcal{K} \Lambda \mu_1(\underline{\mathbf{t}}, \underline{\mathbf{x}}) = \begin{cases} \mathcal{K} \Lambda \mathcal{K} \tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}), & \text{if } M = 1, \\ \mathcal{K} \Lambda \mathcal{K}^2 (\delta_{M,2} \tilde{g}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + \delta_{M \geq 3} \mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)), & \text{if } M > 1, \end{cases}$$

1438 and we are free to reinject (167) in (165) and then to reinject (165) in (163) to obtain that :

$$1439 \quad (168) \quad \mu_1(t, x) = \begin{cases} \mathcal{K} (\tilde{g}(t, x) + \mathbb{T} \tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}) + \Lambda \mu_0(t, x)) + \mathcal{K}^2 \Lambda \mathcal{K} \tilde{g}(\underline{\mathbf{t}}, \underline{\mathbf{x}}), & \text{if } M = 1, \\ \mathcal{K} \Lambda \mu_0(t, x) \\ + \mathcal{K}^2 (\delta_{M,2} \sum_{k=1}^2 \mathbb{T}^{k-1} \tilde{g}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) + \sum_{k=2}^{\min(M,3)} \mathbb{T}^{k-2} \mu_3(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)) & \text{if } M > 1. \\ + \mathcal{K}^2 \Lambda \mathcal{K}^2 (\delta_{M,2} \tilde{g}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + \delta_{M \geq 3} \mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)) \\ + \mathcal{K} \mathbb{T} \mathcal{K} (\delta_{M,2} \tilde{g}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) + \delta_{M \geq 3} \mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)), & \end{cases}$$

1440 Equation (168) ends the discussion in the particular case $M = 1$. To treat the case $M > 1$, let us remark
 1441 that in (168) the unknown part of the right hand side of equation depends on $\mu_3(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)$ and possibly on
 1442 $\mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)$. So we are exactly in the same situation as in equation (163) with $\mu_3(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)$, $\mu_3(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)$ in place of
 1443 $\mu_2(\underline{\mathbf{t}}, \underline{\mathbf{x}})$, $\mu_2(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2)$ and we can thus repeat the same computations to express μ_1 in terms of $\mu_4(\underline{\mathbf{t}}^3, \underline{\mathbf{x}}^3)$ and
 1444 $\mu_4(\underline{\mathbf{t}}^4, \underline{\mathbf{x}}^4)$ and so on.

1445 A tedious (but not difficult) reiterative process shows that for all $M > 1$, μ_1 is given by :

$$1446 \quad \mu_1(t, x_2) = \mathcal{K} \Lambda \mu_0(t, x_2) + \mathcal{K}^M (\tilde{g}(\underline{\mathbf{t}}^{M-1}, \underline{\mathbf{x}}^{M-1}) + \mathbb{T} \tilde{g}(\underline{\mathbf{t}}^M, \underline{\mathbf{x}}^M))$$

$$1447 \quad (169) \quad + \sum_{k=0}^{M-1} \mathcal{K}^{M+1-k} \Lambda \mathcal{K}^{k+1} \tilde{g}(\underline{\mathbf{t}}^M, \underline{\mathbf{x}}^M) + \sum_{k=1}^{M-1} \mathcal{K}^k \mathbb{T} \mathcal{K}^{M-k} \tilde{g}(\underline{\mathbf{t}}^M, \underline{\mathbf{x}}^M),$$

1448 equation which determines in a unique way μ_1 in terms of \tilde{g} and the known operators Λ , \mathbb{T} . This completes
 1449 the construction of μ_1 and more generally of the amplitudes of order one in the *WKB* expansion.

1450 Moreover, all the terms composing (169) are in \mathcal{P}_b^M , except $\tilde{g}(\underline{\mathbf{t}}^{M-1}, \underline{\mathbf{x}}^{M-1})$ which is in \mathcal{P}_b^{M-1} . Thus
 1451 μ_1 defined by (169) is an element of \mathcal{P}_b^{M-1} , so it is in the good profile space. To conclude this discussion let
 1452 us remark that before the time $\underline{\mathbf{T}}_M$, μ_1 (and consequently the u_{1,n_j}) only depends on the information that
 1453 was initially present and which has made $M - 1$ complete circuits around the loop.

1454

1455 Once the amplitudes for indices associated to the loop are known, the construction of the amplitudes
 1456 which do not lie on the loop follows the same kind of arguments as those given in paragraph 7.2. A precise
 1457 construction will not be given here and we refer to [4] for more details.

1458 **7.3.2. Summary : the construction of higher order terms.** In this paragraph we sketch some
 1459 elements about the construction of the amplitudes of higher order in view to give a summary of the previous
 1460 construction. Let us assume that the amplitudes of order less than $n - 1$ have already been determined,
 1461 our aim is to construct the amplitude of order n .

1462

1463 *i)* First of all, from the cascade of equations (52), we know that the unpolarized part of the oscillating
 1464 amplitudes of order n is known. So we only have to determine the polarized part of the oscillating amplitudes.

1465 Moreover, from Lemma 35 and the definition of the operator \mathbb{Q}_{ev1} (resp. \mathbb{Q}_{ev2}), see (159), concerning the
 1466 evanescent amplitudes, we will only have to determine \mathbb{P}_{ev1} (resp. \mathbb{P}_{ev2}).
 1467

1468 *ii)* To determine the polarized part of the oscillating amplitudes of order n , we start, as it has been done
 1469 in paragraphs 7.1 and 7.3.1 by the determination of the loop's indices. We thus reiterate the computations
 1470 of paragraph 7.1 to show that to construct these polarized parts it is necessary and sufficient to construct
 1471 the scalar component of the trace on $\partial\Omega_1$ of the amplitude u_{n,n_1} , that is to say, μ_n .
 1472

1473 *iii)* The analysis of paragraphs 7.1.5 and 7.1.6 tells us that this trace has to satisfy equation (150). In
 1474 other words, μ_n depends on the unknown μ_{n+1} and the known functions μ_{n-1} (and possibly of \tilde{g}). More
 1475 precisely μ_n depends on the $\mu_{n+1}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$, for $k = 1, \dots, \min(n+1, M)$. Then applying again equation (150)
 1476 but for μ_{n+1} we obtain that μ_{n+1} depends on μ_n and μ_{n+2} . With more details, the $\mu_{n+1}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$, for
 1477 $k = 1, \dots, \min(n+1, M)$ admits the following dependencies :

$$1478 \quad (170) \quad \begin{array}{c} \mu_{n+1}(\underline{\mathbf{t}}, \underline{\mathbf{x}}) \\ \mu_{n+1}(\underline{\mathbf{t}}^2, \underline{\mathbf{x}}^2) \\ \vdots \\ \mu_{n+1}(\underline{\mathbf{t}}^{\min}, \underline{\mathbf{x}}^{\min}) \end{array} \left| \begin{array}{c} \mu_n(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) \\ k = 1, \dots, \underline{\min} \\ k = 2, \dots, \underline{\min} \\ \vdots \\ k \in \emptyset \end{array} \right. \begin{array}{c} \mu_{n+2}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k) \\ k = 2, \dots, \overline{\min} \\ k = 3, \dots, \overline{\min} \\ \vdots \\ k \in \emptyset \text{ or } k = M \end{array}$$

1479 where we denoted $\underline{\min} := \min(n, M)$, $\min := \min(n+1, M)$ and $\overline{\min} = \min(n+2, M)$. Let us study the
 1480 dependency on μ_n . The worst term is $\mu_n(\underline{\mathbf{t}}, \underline{\mathbf{x}})$, indeed the other terms will be eliminate before $\mu_n(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ (by
 1481 the same arguments) and are harmless. Using equation (151), we obtain that $\mu_n(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ in fact depends on
 1482 $\mu_{n+1}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$, for $k = 2, \dots, \min$. But the tabular (170) tells us that these traces depend, in fact, on $\mu_n(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$
 1483 for $k = 2, \dots, \underline{\min}$. As a consequence, $\mu_{n+1}(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ can be expressed in terms of the $\mu_n(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ for $k = 2, \dots, \underline{\min}$.
 1484 Repeating the same argument we obtain that $\mu_{n+1}(\underline{\mathbf{t}}, \underline{\mathbf{x}})$ can be expressed in terms of the $\mu_n(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ for
 1485 $k = 3, \dots, \underline{\min}$. Then if we repeat $\underline{\min}$ times this argument, we obtain that the $\mu_{n+1}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ for $k = 1, \dots, \min$
 1486 (and consequently μ_n) can be expressed in terms of $\mu_{n+2}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ for $k > 2$ only.
 1487

1488 We thus repeat exactly the same reasoning for $\mu_{n+2}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ to show that it can be expressed in terms of
 1489 the $\mu_{n+3}(\underline{\mathbf{t}}^k, \underline{\mathbf{x}}^k)$ for $k > 3$ and so on to determine μ_n in terms of \tilde{g} and μ_{n-1} (up to some compositions by
 1490 the operators \mathbb{T} and Λ) only, as it has already been made in paragraphs 7.1.6 and 7.3.1. This concludes the
 1491 construction of the trace μ_n and as a consequence, the construction of the amplitudes linked to the loop's
 1492 indices of order n .
 1493

1494 *iv)* The construction of the other polarized part of the oscillating (or equivalently of the $\mathbb{P}_{ev1}U$ (resp.
 1495 $\mathbb{P}_{ev2}U$) for the evanescent amplitudes for the side $\partial\Omega_1$ (resp. $\partial\Omega_2$) is then easy. Indeed these amplitudes
 1496 are linked to frequencies for which the uniform Kreiss-Lopatinskii condition holds and we can use the "tree"
 1497 structure of the frequency set to conclude (see [4] for a precise construction).

1498 **8. Proof of the main result.** With Theorem 28 in hand, it is now easy to show Theorem 14. We
 1499 argue by contradiction. We thus assume that the corner problem (1) is weakly (or strongly) well-posed in the
 1500 sense that there exists a positives integers K, K_1 and K_2 such that the corner problem (1) admits a solution
 1501 satisfying the energy estimate:

$$1502 \quad (171) \quad \|u\|_{L^2(\Omega_T)}^2 + \|u_{|x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u_{|x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{H^K(\Omega_T)}^2 + \|g_1\|_{H^{K_1}(\partial\Omega_{1,T})}^2 + \|g_2\|_{H^{K_2}(\partial\Omega_{2,T})}^2 \right),$$

1503 for $T > 0$ if $\beta \geq 1$ and $0 < T < T_{max}$ if $\beta < 1$. According to Theorem 28, for any $M \in \mathbb{N}$ one can always
 1504 construct a truncated geometric optics expansions for the corner problem (47). Here we only keep the $K+2$
 1505 first terms in the truncated expansion. It is given by:

$$1506 \quad (172) \quad u_{app}^\varepsilon := \sum_{n=0}^{K+1} \sum_{k \in \mathcal{I}_{os}} \varepsilon^n e^{\frac{i}{\varepsilon} \varphi_k(t,x)} u_{n,k}(t,x) \\ 1507 \quad + \sum_{n=0}^{K+1} \sum_{k \in \mathcal{R}_1} \varepsilon^n e^{\frac{i}{\varepsilon} \psi_{k,1}(t,x_2)} U_{n,k,1} \left(t, x, \frac{x_1}{\varepsilon} \right) + \sum_{n=0}^{K+1} \sum_{k \in \mathcal{R}_2} \varepsilon^n e^{\frac{i}{\varepsilon} \psi_{k,2}(t,x_1)} U_{n,k,2} \left(t, x, \frac{x_2}{\varepsilon} \right).$$

1508 Moreover one can always choose g in such a way that the leading order of u_{app}^ε is not identically zero.
 1509 Let u^ε be the solution of (47). The error $u^\varepsilon - u_{app}^\varepsilon$ satisfies the corner problem :

$$1510 \quad \begin{cases} L(\partial)(u^\varepsilon - u_{app}^\varepsilon) = f^\varepsilon, & \text{in } \Omega_T, \\ B_1(u^\varepsilon - u_{app}^\varepsilon)|_{x_1=0} = 0, & \text{on } \partial\Omega_{1,T}, \\ B_2(u^\varepsilon - u_{app}^\varepsilon)|_{x_2=0} = 0, & \text{on } \partial\Omega_{2,T}, \\ (u^\varepsilon - u_{app}^\varepsilon)|_{t \leq 0} = 0, & \text{on } \Omega, \end{cases}$$

1511 where :

$$1512 \quad f^\varepsilon := \varepsilon^{K+1} \left[\sum_{k \in \mathcal{I}_{os}} e^{i\frac{\varphi_k}{\varepsilon}} L(\partial)u_{K+1,k} \right. \\ 1513 \quad \left. + \sum_{k \in \mathfrak{R}_1} e^{i\frac{\psi_{k,1}}{\varepsilon}} (L(\partial)U_{K+1,k,1})|_{X_1=\frac{x_1}{\varepsilon}} + \sum_{k \in \mathfrak{R}_2} e^{i\frac{\psi_{k,2}}{\varepsilon}} (L(\partial)U_{K+1,k,2})|_{X_2=\frac{x_2}{\varepsilon}} \right].$$

1514 From the energy estimate (171) we have:

$$1515 \quad (174) \quad \|u^\varepsilon - u_{app}^\varepsilon\|_{L^2(\Omega_T)} \leq \|f^\varepsilon\|_{H^K(\Omega_T)}.$$

1516 It is then easy to see from its expression that f^ε is $O(\varepsilon)$ in $H^K(\Omega_T)$ (the worst term to handle with is the
 1517 one for which all the derivatives fall on the terms $e^{i\frac{\varphi_k}{\varepsilon}}$, $e^{i\frac{\psi_{k,1}}{\varepsilon}}$ or $e^{i\frac{\psi_{k,2}}{\varepsilon}}$). Consequently the error $u^\varepsilon - u_{app}^\varepsilon$
 1518 is $O(\varepsilon)$ in $L^2(\Omega_T)$. Using the fact that u^ε is a solution of (47) we obtain that:

$$1519 \quad (175) \quad \|u^\varepsilon\|_{L^2(\Omega_T)} \leq \|g^\varepsilon\|_{H^{K_1}(\Omega_T)},$$

1520 from which we deduce that u^ε is $O(\varepsilon^{M-K_1})$ in $L^2(\Omega_T)$. We choose $M > K_1$, by the triangle inequality and
 1521 inequalities (174) and (175), it follows that u_{app}^ε is at least $O(\varepsilon)$ which is a contradiction with the fact that
 1522 u_{0,n_1} is nonzero.

1523 9. Examples, conclusion and conjectures.

1524 **9.1. Examples.** Of course Theorem 14 to the corner problem (2) even if it may seem a bit abusive.
 1525 Indeed, Theorem 14 needs strict hyperbolicity while the corner problem (2) is clearly not strictly hyperbolic.
 1526 However, in the proof of Theorem 14, the only points where we used the hyperbolicity hypothesis were to
 1527 establish the block structure and to use Lax Lemma. It can be shown that these points are still true for geo-
 1528 metrically regular hyperbolic systems (see [16] for a precise definition) as soon as we are away from crossing
 1529 points, which is the case for (2) under this choice of the source term.

1530
 1531 A strictly hyperbolic example for which Theorem 14 applies is due to [19, paragraph 7]. In this example,
 1532 the authors construct a system whose characteristic variety is composed of two intersecting ellipses chosen
 1533 in such a configuration that a loop exists. The construction is the following a first ellipse is fixed and three
 1534 points A, B, D are chosen on this ellipse in such a way that:

- 1535 • \widehat{DAB} is a right angle
- 1536 • The group velocity in A is incoming-outgoing while the group velocities in B and D are outgoing-
 1537 incoming

1538 This determines a unique C such that $ABCD$ is a rectangle. Then we choose a second ellipse passing through
 1539 C such that the group velocity in this point is incoming-outgoing. Without loss of generality the loop can
 1540 be constructed in the half space $\{\xi_2 < 0\}$, to make sure that the velocity along the boundary has the good
 1541 sign. Then one chooses a boundary condition to make sure that the associated corner problem is in the WR
 1542 class. This point can be easily done because at this stage of the construction the system is composed of two
 1543 decoupled subsystems.

1544
 1545 To obtain a strictly hyperbolic system, it is sufficient to make the perturbation described in [19, paragraph
 1546 9]. The associated perturbed operator is strictly hyperbolic and remains in WR class, because this class is
 1547 stable by small perturbations (see [5]).

1548 **9.2. Conclusion and conjectures.** In this article, we constructed the rigorous geometric optics expansion for a corner problem for which the uniform Kreiss-Lopatinskii condition breaks down on a selfinteraction
 1549 frequency. We have shown that it was always possible to choose the source term with support close enough of
 1550 the corner problem to makes sure that the associated geometric optics expansion suffers $M + 1$ amplifications,
 1551 before a fixed time T , compared to the source term. M can be arbitrarily big, so this leads to the fact that such
 1552 a corner problem can not be weakly well-posed because it suffers an arbitrarily big number of losses of derivatives
 1553 and thus present an Hadamard's instability. In terms of well-posedness it is the worst possible situation.
 1554
 1555

1556 As a consequence we shown that for hyperbolic corner problem a weak instability can be repeated an
 1557 arbitrarily number of times to cause a violent instability which differs from the degeneracy of the Kreiss-
 1558 Lopatinskii condition.
 1559

1560 Nevertheless in the author opinion systems admitting a loop are not so widespread at least for small
 1561 values of N . Indeed, loops can not appear if $N = 2$ (see [19]) and at the present time the examples in this
 1562 article are, in the author knowledge, the only methods to construct a system with a loop (in particular we do
 1563 not know any physical example). But it also seems reasonable to think that for large values of N loops are
 1564 much more frequent. Indeed when N becomes large the geometry of the characteristic variety of the system
 1565 becomes really complicated and we can imagine that more the geometry is more there are possibilities to
 1566 have loops.

1567 However obtain a more rigorous answer about the occurence of loops (or a full characterization of systems
 1568 with loops) is a important question in the study of hyperbolic initial boundary value problems in the quarter
 1569 space which is left for future studies.
 1570

1571 In this article we treated a very particular kind of degeneracy of the uniform Kreiss-Lopatinskii condition
 1572 and many others are possible. In these cases, one should be more optimistic. Let us formulate the following
 1573 reasonable conjectures.
 1574

1575 First of all let us stress that when the failure of the uniform Kreiss-Lopatinskii condition happens away
 1576 from the loop then the weak instability can not be repeated an arbitrarily number of times and thus the
 1577 system should be weakly well-posed. More precisely:

◊ If the uniform Kreiss-Lopatinskii condition breaks down in the elliptic area, using the fact that evanescent modes for the side $\partial\Omega_1$ are not reflected on the side $\partial\Omega_2$, the amplification observed in the high frequency expansion for the boundary value problem in the half space should not be improved. So we believe that the leading order in the WKB expansion should be of order ε^0 with a source term in the interior of order ε and a source term on the side $\partial\Omega_1$ of order ε^0 . The associated corner problem should be weakly well-posed with an energy estimate reading:

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{L^2(\Omega_T)}^2 + \|g_1\|_{H^1(\partial\Omega_{1,T})}^2 + \|g_2\|_{L^2(\partial\Omega_{2,T})}^2 \right).$$

◊ When the uniform Kreiss-Lopatinskii condition is violated in the mixed area in such a way that $\ker B_1 \cap E_1^s(\zeta) = \ker B_1 \cap E_1^{s,e}(\zeta) = \text{span}\{e\}$, where $E_1^{s,e}(\zeta)$ denotes the "elliptic" component of $E_1^s(\zeta)$ (see [2] and [12]), then the same argument should apply. The conjecture is then that we have the same amplifications as for the boundary value problem in the half space. The expected energy estimate is:

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{H^{\frac{1}{2}}(\Omega_T)}^2 + \|g_1\|_{H^1(\partial\Omega_{1,T})}^2 + \|g_2\|_{L^2(\partial\Omega_{2,T})}^2 \right),$$

or

$$\|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \leq C_T \left(\|f\|_{L^2(\Omega_T)}^2 + \|g_1\|_{H^1(\partial\Omega_{1,T})}^2 + \|g_2\|_{L^2(\partial\Omega_{2,T})}^2 \right),$$

1578 depending of a technical assumption already discussed in [2].
 1579

◊ Finally when the uniform Kreiss-Lopatinskii condition fails in the hyperbolic region (but away from the loop) the conjecture is that the leading order in the geometric optics expansion is of order ε^0 for source terms of order ε^M , where M denotes the number of time that a ray has been amplified. More precisely M is defined by:

$$M := \max_{i \in \mathcal{I}_{os}} \#(\Upsilon \cap L_i),$$

1580 where L_i is the set containing the values of the type V sequence linking i to the first generated index in the
 1581 phase generation process. Indeed, an amplified ray should be amplified again if it contains in its reflections a
 1582 phase associated to a frequency of degeneracy of the uniform Kreiss-Lopatinskii condition. The conjectured
 1583 energy estimate is thus given by:
 1584

$$1585 \quad (176) \quad \|u\|_{L^2(\Omega_T)}^2 + \|u|_{x_1=0}\|_{L^2(\partial\Omega_{1,T})}^2 + \|u|_{x_2=0}\|_{L^2(\partial\Omega_{2,T})}^2 \\
 1586 \quad \leq C_T \left(\|f\|_{L^2_{x_1}(H^M(\partial\Omega_{1,T}))}^2 + \|g_1\|_{H^M(\partial\Omega_{1,T})}^2 + \|g_2\|_{L^2(\partial\Omega_{2,T})}^2 \right).$$

1588 As a consequence the WR class should remain a class where weak stability is observed as soon as there is
 1589 no loop or that the frequency of degeneracy is away from the loop. However in the WR class the loss of
 1590 derivatives should be more marked for the corner geometry than for the half space geometry.
 1591

1592 All the previous conjectures are made under the assumption that the transport along the boundary
 1593 spreads the information away from the corner. The energy estimates and the amplifications in the geometric
 1594 optics expansions when the transport along the boundary sends the information to the corner are left for
 1595 future studies.
 1596

1597 Appendix.

1598 **Details of the computations to establish equations (118)-(119) and (120).** Let us develop :

$$1599 \quad Q_1^{n_3} L(\partial)(I - P_1^{n_3})u_{1,n_3} = -\frac{\bar{\xi}_2}{\xi_2} \beta_1^{-1} \beta_2^{-1} \left[Q_1^{n_3} R_1^{n_3} \mathcal{S}^{n_3} e \left(\partial_{tt}^2 \mu_0 - \frac{\tau}{\xi_2} \partial_{t_2}^2 \mu_0 \right) \right. \\
 1600 \quad \quad \quad \left. + Q_1^{n_3} A_2 R_1^{n_3} \mathcal{S}^{n_3} e \left(\left(-\frac{1}{v_{n_2,2}} + \frac{\beta_2^{-1}}{v_{n_1,1}} \right) \partial_{tt}^2 \mu_0 + \beta_1^{-1} \beta_2^{-1} \partial_{t_2}^2 \mu_0 \right) \right. \\
 1601 \quad \quad \quad \left. - \frac{\tau}{\xi_2} \left(\left(-\frac{1}{v_{n_2,2}} + \frac{\beta_2^{-1}}{v_{n_1,1}} \right) \partial_{t_2}^2 \mu_0 + \beta_1^{-1} \beta_2^{-1} \partial_{22}^2 \mu_0 \right) \right] (\mathbf{t}_3, \mathbf{x}_3),$$

1602 where we used the fact that $Q_1^{n_3} A_1 R_1^{n_3} = 0$. We then use the relation between $Q_1^{n_3} R_1^{n_3} \mathcal{S}^{n_3} e$ and $Q_1^{n_3} A_2 R_1^{n_3} \mathcal{S}^{n_3} e$ given in
 1603 (116) to express $Q_1^{n_3} L(\partial)(I - P_1^{n_3})u_{1,n_3}$ in terms of $Q_1^{n_3} R_1^{n_3} \mathcal{S}^{n_3} e$ only :

$$1604 \quad (177) \quad Q_1^{n_3} L(\partial)(I - P_1^{n_3})u_{1,n_3} = -\frac{\bar{\xi}_2}{\xi_2} \beta_1^{-1} \beta_2^{-1} Q_1^{n_3} R_1^{n_3} \mathcal{S}^{n_3} e \left[\partial_{tt}^2 \mu_0 \left(1 + \frac{\tau}{\xi_2} \left(\frac{1}{v_{n_2,2}} - \frac{\beta_2^{-1}}{v_{n_1,1}} \right) \right) \right. \\
 1605 \quad \quad \quad \left. - C_3 \partial_{t_2}^2 \mu_0 + \partial_{22}^2 \mu_0 \beta_1^{-1} \beta_2^{-1} \frac{\tau^2}{\xi_2 \xi_2} \right] (\mathbf{t}_3, \mathbf{x}_3),$$

where

$$C_3 := \frac{\tau}{\xi_2} \left[1 + \frac{\tau}{\xi_2} \left(\frac{1}{v_{n_2,2}} - \frac{\beta_2^{-1}}{v_{n_1,1}} \right) \right] + \frac{\tau}{\xi_2} \beta_1^{-1} \beta_2^{-1}.$$

1606 From Lemma 30, we know that the first term in C_3 is $\frac{\bar{\xi}_2}{\xi_2} \beta_1^{-1} \beta_2^{-1}$. We thus obtain that $C_3 = 2 \frac{\tau}{\xi_2} \beta_1^{-1} \beta_2^{-1}$, and we can factorize
 1607 (177) to obtain (119).
 1608

1609 Using the fact that $Q_2^{n_4} A_2 R_2^{n_4} = 0$ we develop $Q_2^{n_4} L(\partial)(I - P_2^{n_4})u_{1,n_4}$ to obtain :

$$1610 \quad Q_2^{n_4} L(\partial)(I - P_2^{n_4})u_{1,n_4} = -\frac{\bar{\xi}_2}{\xi_1} \prod_{j=1}^3 \beta_j^{-1} \left[Q_2^{n_4} R_2^{n_4} \mathcal{S}^{n_4} e \left(\partial_{tt}^2 \mu_0 - \frac{\tau}{\xi_2} \partial_{t_2}^2 \mu_0 \right) \right. \\
 1611 \quad \quad \quad \left. + Q_2^{n_4} A_1 R_2^{n_4} \mathcal{S}^{n_4} e \left(-A \partial_{tt}^2 \mu_0 - \prod_{j=1}^3 \beta_j^{-1} \partial_{t_2}^2 \mu_0 \right) \right. \\
 1612 \quad \quad \quad \left. - \frac{\tau}{\xi_2} \left(-A \partial_{t_2}^2 \mu_0 - \prod_{j=1}^3 \beta_j^{-1} \partial_{22}^2 \mu_0 \right) \right] (\mathbf{t}_4, \mathbf{x}_4),$$

1613 where we recall that A is defined in (74). We then use (117) to express this equation in terms of $Q_2^{n_4} R_2^{n_4} \mathcal{S}^{n_4} e$ only :

$$1614 \quad Q_2^{n_4} L(\partial)(I - P_2^{n_4})u_{1,n_4} = -\frac{\bar{\xi}_2}{\xi_1} \prod_{j=1}^3 \beta_j^{-1} Q_2^{n_4} R_2^{n_4} \mathcal{S}^{n_4} e \left[\partial_{tt}^2 \mu_0 \left(1 + A \frac{\tau}{\xi_1} \right) + C_4 \partial_{t_2}^2 \mu_0 + \frac{\tau^2}{\xi_1 \xi_2} \prod_{j=1}^3 \beta_j^{-1} \partial_{22}^2 \mu_0 \right] (\mathbf{t}_4, \mathbf{x}_4),$$

where C_4 is defined by :

$$C_4 := -\frac{\tau}{\xi_2} \left(1 + A \frac{\tau}{\xi_1} \right) + \frac{\tau}{\xi_1} \prod_{j=1}^3 \beta_j^{-1}.$$

1615 Once again thanks to Lemma 30, we obtain that C_4 in fact reads $C_4 = 2 \frac{\tau}{\xi_1} \prod_{j=1}^3 \beta_j^{-1}$. As a consequence we obtain (120).

1616 **Acknowledgments.** The author acknowledges financial support from the European Research Council
 1617 under the European Community's Seventh Framework Programme (FP7/2014-2019 Grant Agreement
 1618 QUANTHOM 335410).

1619 The author also wishes to thank all the members, academic as well as administrative, of the "Laboratoire
 1620 de Mathématiques Jean Leray" of Nantes, and more specifically Jean-François Coulombel. Because the main
 1621 part of this research has been made in this department.

1622

REFERENCES

- 1623 [1] M. ARTOLA, A. MAJDA, *Nonlinear development of instabilities in supersonic vortex sheets. I. The basic kink modes*, Phys.
 1624 D, 28 (1987), pp. 253–281.
- 1625 [2] A. BENOIT, *Geometric optics expansions for linear hyperbolic boundary value problems and optimality of energy esti-*
 1626 *mates for surface waves*, Differential Integral Equations, 27 (2014), pp. 531–562, [http://projecteuclid.org/euclid.die/](http://projecteuclid.org/euclid.die/1396558096)
 1627 [1396558096](http://projecteuclid.org/euclid.die/1396558096).
- 1628 [3] A. BENOIT, *Problèmes aux limites, optique géométrique et singularités*, PhD thesis, Université de Nantes, 2015. <https://hal.archives-ouvertes.fr/tel-01180449v1>.
- 1629 [4] A. BENOIT, *Geometric optics expansions for hyperbolic corner problems, I: Self-interaction phenomenon*, Anal. PDE, 9
 1630 (2016), pp. 1359–1418, doi:10.2140/apde.2016.9.1359, <http://dx.doi.org/10.2140/apde.2016.9.1359>.
- 1631 [5] S. BENZONI-GAVAGE, F. ROUSSET, D. SERRE, AND K. ZUMBRUN, *Generic types and transitions in hyperbolic initial-*
 1632 *boundary-value problems*, Proc. Roy. Soc. Edinburgh Sect. A, 132 (2002), pp. 1073–1104.
- 1633 [6] S. BENZONI-GAVAGE, D. SERRE, *Multidimensional hyperbolic partial differential equations*, Oxford Mathematical Mono-
 1634 *graphs*, Oxford University Press, 2007.
- 1635 [7] J.-F. COULOMBEL, *Well-posedness of hyperbolic initial boundary value problems*, J. Math. Pures Appl. (9), 84 (2005),
 1636 pp. 786–818.
- 1637 [8] J.-F. COULOMBEL AND O. GUÈS, *Geometric optics expansions with amplification for hyperbolic boundary value problems:*
 1638 *linear problems*, Ann. Inst. Fourier (Grenoble), 60 (2010), pp. 2183–2233, [http://aif.cedram.org/item?id=AIF_2010__](http://aif.cedram.org/item?id=AIF_2010__60_6_2183_0)
 1639 [60_6_2183_0](http://aif.cedram.org/item?id=AIF_2010__60_6_2183_0).
- 1640 [9] R. HERSH, *Mixed problems in several variables*, J. Math. Mech., 12 (1963), pp. 317–334.
- 1641 [10] H.-O. KREISS, *Initial boundary value problems for hyperbolic systems*, Comm. Pure Appl. Math., 23 (1970), pp. 277–298.
- 1642 [11] P. D. LAX, *Asymptotic solutions of oscillatory initial value problems*, Duke Math. J., 24 (1957), pp. 627–646.
- 1643 [12] V. LESCARRET, *Wave transmission in dispersive media*, Math. Models Methods Appl. Sci., 17 (2007), pp. 485–535.
- 1644 [13] A. MAJDA, R. ROSALES, *A theory for spontaneous Mach stem formation in reacting shock fronts. I. The basic perturbation*
 1645 *analysis*, SIAM J. Appl. Math., 43 (1983), pp. 1310–1334.
- 1646 [14] A. MARCOU, *Rigorous weakly nonlinear geometric optics for surface waves*, Asymptot. Anal., 69 (2010), pp. 125–174.
- 1647 [15] G. MÉTIVIER, *The block structure condition for symmetric hyperbolic systems*, Bull. London Math. Soc., 32 (2000), pp. 689–
 1648 702.
- 1649 [16] G. MÉTIVIER AND K. ZUMBRUN, *Hyperbolic boundary value problems for symmetric systems with variable multiplicities*,
 1650 J. Differential Equations, 211 (2005), pp. 61–134, doi:10.1016/j.jde.2004.06.002, [http://dx.doi.org/10.1016/j.jde.2004.](http://dx.doi.org/10.1016/j.jde.2004.06.002)
 1651 [06.002](http://dx.doi.org/10.1016/j.jde.2004.06.002).
- 1652 [17] S. OSHER, *Initial-boundary value problems for hyperbolic systems in regions with corners. I*, Trans. Amer. Math. Soc., 176
 1653 (1973), pp. 141–164.
- 1654 [18] S. OSHER, *Initial-boundary value problems for hyperbolic systems in regions with corners. II*, Trans. Amer. Math. Soc.,
 1655 198 (1974), pp. 155–175.
- 1656 [19] L. SARASON AND J. A. SMOLLER, *Geometrical optics and the corner problem*, Arch. Rational Mech. Anal., 56 (1974/75),
 1657 pp. 34–69.
- 1658 [20] M. WILLIAMS, *Nonlinear geometric optics for hyperbolic boundary problems*, Comm. Partial Differential Equations, 21
 1659 (1996), pp. 1829–1895.
- 1660