



HAL
open science

A Kalman rank condition for the indirect controllability of coupled systems of linear operator groups

Thibault Liard, Pierre Lissy

► **To cite this version:**

Thibault Liard, Pierre Lissy. A Kalman rank condition for the indirect controllability of coupled systems of linear operator groups. 2016. hal-01298367v1

HAL Id: hal-01298367

<https://hal.science/hal-01298367v1>

Preprint submitted on 6 Apr 2016 (v1), last revised 28 Oct 2016 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

A Kalman rank condition for the indirect controllability of coupled systems of linear operator groups

Thibault Liard* Pierre Lissy†

April 5, 2016

Abstract

In this article, we give a necessary and sufficient condition of Kalman type for the indirect controllability of systems of groups of linear operators, under some “regularity and locality” conditions on the control operator that will be made precise later and fits very well the case of distributed controls. Moreover, in the case of first order in time systems, when the Kalman rank condition is not satisfied, we characterize exactly the initial conditions that can be controlled. Some applications to the control of systems of Schrödinger or wave equations are provided. The main tool used here is the *fictitious control method* coupled with the proof of an *algebraic solvability* property for some related underdetermined system and some regularity results.

Keywords: controllability of abstract linear semi-groups, indirect controllability of systems, fictitious control method, algebraic solvability.

MSC: 35F35, 35G35, 47D03, 93B05, 93B07.

1 Introduction

1.1 Presentation of the problem and main results

Let $T > 0$ and $\mathbb{K} = \mathbb{R}$ or \mathbb{C} . Let \mathcal{U}, \mathcal{H} two Hilbert spaces on \mathbb{K} (that will be always identified with their dual in what follows) and a linear continuous application $\mathcal{C} : \mathcal{U} \rightarrow \mathcal{H}$. We consider

- $\mathcal{L} : \mathcal{D}(\mathcal{L}) \subset \mathcal{H} \rightarrow \mathcal{H}$ a closed unbounded operator with dense domain, which is supposed to be the generator of a strongly continuous **group** on \mathcal{H} ,
- $\mathcal{Q} : \mathcal{D}(\mathcal{Q}) \subset \mathcal{H} \rightarrow \mathcal{H}$ another closed unbounded operator with dense domain, which is supposed to be **self-adjoint and negative with compact resolvent**.

Let $n \in \mathbb{N}^*$ with $n \geq 2$ and $m \in \mathbb{N}^*$, and let $(A, B) \in \mathcal{M}_n(\mathbb{K}) \times \mathcal{M}_{n,m}(\mathbb{K})$ two matrices. For every $k \in \mathbb{N}^*$, we introduce the operators $L_k : \mathcal{D}(\mathcal{L})^k \subset \mathcal{H}^k \rightarrow \mathcal{H}^k$, $Q_k : \mathcal{D}(\mathcal{Q})^k \subset \mathcal{H}^k \rightarrow \mathcal{H}^k$ and $C_k : \mathcal{U}^k \rightarrow \mathcal{H}^k$ such that, for every $\varphi \in \mathcal{D}(\mathcal{L})^k$ and $\psi \in \mathcal{U}^k$,

$$L_k(\varphi) = \begin{pmatrix} \mathcal{L}(\varphi_1) \\ \mathcal{L}(\varphi_2) \\ \vdots \\ \mathcal{L}(\varphi_k) \end{pmatrix}, \quad Q_k(\varphi) = \begin{pmatrix} \mathcal{Q}(\varphi_1) \\ \mathcal{Q}(\varphi_2) \\ \vdots \\ \mathcal{Q}(\varphi_k) \end{pmatrix} \quad \text{and} \quad C_k(\psi) = \begin{pmatrix} \mathcal{C}(\psi_1) \\ \mathcal{C}(\psi_2) \\ \vdots \\ \mathcal{C}(\psi_k) \end{pmatrix}. \quad (1.1)$$

*Université Pierre et Marie Curie (Univ. Paris 6), CNRS UMR 7598, Laboratoire Jacques-Louis Lions, F-75005, Paris, France (thibault.liard@upmc.fr).

†Ceremade, Université Paris-Dauphine, CNRS UMR 7534, Place du Maréchal de Lattre de Tassigny, 75775 Paris Cedex 16, France (pierre.lissy@ceremade.dauphine.fr).

We consider the (first and second order in time) systems of n linear equations

$$\partial_t Y = L_n(Y) + AY + BC_m V \quad \text{in } (0, T) \times \mathcal{H}^n, \quad (\text{Ord1})$$

and

$$\partial_{tt} Y = Q_n(Y) + AY + BC_m V \quad \text{in } (0, T) \times \mathcal{H}^n, \quad (\text{Ord2})$$

where $V := (v_1, \dots, v_m) \in \mathcal{U}^m$ is called a control. (Ord1) (resp. (Ord2)) can be seen as a “system” version of the “scalar” controlled equation $\partial_t z = \mathcal{L}z + \mathcal{C}u$ (resp. $\partial_{tt} z = \mathcal{L}z + \mathcal{C}u$), where we add some coupling terms of zero order through the matrix A and where we impose a precise structure on the control through the matrix B . Note that one may have $m < n$, which means that the number of controls can be strictly less than the number of equations, and notably some equations might be uncontrolled. In this setting, the structure of the coupling terms is crucial in order to obtain some controllability results, and in some sense these coupling terms can be used to act indirectly on the equations that are not controlled. This is why we call *indirect controllability* the study of the controllability properties of this kind of systems.

It is usual to write the second order system (Ord2) as a first order system (see section 3.1). However, we emphasize that (Ord2) is *not* a particular case of (Ord1), the reason being that if we transform (Ord2) into a first order system, we will not be able to find any matrix A such that (Ord2) can be written as (Ord1). Finding such a matrix would require that the coupling terms involve simultaneously Y and Y_t (see notably (3.3)), which is not the case here.

It is well-known that for the controllability of coupled systems like (Ord2), the natural state space $\mathcal{D}(\mathcal{Q}^{\frac{1}{2}})^n \times \mathcal{H}^n$ is not always possible. For instance taking zero as initial data we cannot reach any target state in $\mathcal{D}(\mathcal{Q}^{\frac{1}{2}})^n \times \mathcal{H}^n$ because of the regularity of solutions of (Ord2) (one might for example think of an upper triangular matrix A with a control acting only on the last equation, see [DLRL14]). The same phenomena does not occur for system like (Ord1), however, in both cases, we will always assume that the initial conditions are regular enough, namely $Y(0, \cdot) \in \mathcal{D}(\mathcal{L}^{n-1})^n$ (resp. $(Y(0, \cdot), \partial_t Y(0, \cdot)) \in \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \times \mathcal{D}(\mathcal{Q}^{n-1})^n$), which is enough to ensure that system (Ord1) (resp. (Ord2)) with initial condition in these spaces admits a unique solution in $C^0([0, T]; \mathcal{H}^n)$ (resp. in $C^0([0, T]; \mathcal{D}(\mathcal{Q}^{\frac{1}{2}})^n \times \mathcal{H}^n)$).

The main goal of this article is to analyze the null controllability of System (Ord1) and System (Ord2), which would (partially) generalize the results of [AKBDGB09a] in the case of conservative systems. Let us recall the definition of these notions. It will be said that

- System (Ord1) (resp. System (Ord2)) is *null controllable* at time T if for every initial condition $Y^0 \in \mathcal{D}(\mathcal{L}^{n-1})^n$ (resp. $(Y^0, Y^1) \in \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \times \mathcal{D}(\mathcal{Q}^{n-1})^n$), there exists a control $V \in C^0([0, T]; \mathcal{U}^m)$ such that the solution Y to System (Ord1) with initial condition $Y(0, \cdot) = Y^0$ (resp. to System (Ord2) with initial condition $(Y(0, \cdot), \partial_t Y(0, \cdot)) = (Y^0, Y^1)$) satisfies

$$Y(T) \equiv 0 \quad \text{in } \mathcal{H}^n \quad (\text{resp. } Y(T) \equiv 0 \text{ and } \partial_t Y(T) \equiv 0 \quad \text{in } \mathcal{H}^n \times \mathcal{H}^n).$$

- System (Ord1) (resp. System (Ord2)) is *exactly controllable* at time T if for every initial condition $Y^0 \in \mathcal{D}(\mathcal{L}^{n-1})^n$ (resp. $(Y^0, Y^1) \in \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \times \mathcal{D}(\mathcal{Q}^{n-1})^n$) and every $Y_T \in \mathcal{D}(\mathcal{L}^{n-1})^n$ (resp. $(Y_T, Z_T) \in \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \times \mathcal{D}(\mathcal{Q}^{n-1})^n$), there exists a control $V \in C^0([0, T]; \mathcal{U}^m)$ such that the solution Y to System (Ord1) with initial condition $Y(0, \cdot) = Y^0$ (resp. to System (Ord2) with initial condition $(Y(0, \cdot), \partial_t Y(0, \cdot)) = (Y^0, Y^1)$) satisfies

$$Y(T) \equiv Y_T \quad \text{in } \mathcal{D}(\mathcal{L}^{n-1})^n \quad (\text{resp. } Y(T) \equiv Y_T \quad \text{in } \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \text{ and } \partial_t Y(T) \equiv Z_T \quad \text{in } \mathcal{D}(\mathcal{Q}^{n-1})^n).$$

Let us remark that since L_n (resp. \hat{Q}_n defined in (3.2), see Section 3.1) is a generator of a group, then System (Ord1) (resp. System (Ord2)) is null controllable at time T if and only if it is exactly controllable at time T (see for example [Cor07, p. 55]). Hence, from now on, we will only concentrate on the null controllability of Systems (Ord1) and (Ord2).

Our main assumptions will be the following.

ASSUMPTIONS

There exists a linear continuous application $\bar{\mathcal{C}} : \mathcal{U} \rightarrow \mathcal{H}$ such that

ASSUMPTION 1.1. [Scalar null controllability]

Case (Ord1) The control system

$$\partial_t z = \mathcal{L}z + \bar{\mathcal{C}}u, \quad (1.2)$$

is exactly controllable at time T^* .

Case (Ord2) The control system

$$\partial_{tt} z = \mathcal{Q}z + \bar{\mathcal{C}}u, \quad (1.3)$$

is exactly controllable at time T^* .

ASSUMPTION 1.2. [Regularity and locality]

Case (Ord1) $\mathcal{L}^k(\bar{\mathcal{C}}\mathcal{C}^*\mathcal{D}(\mathcal{L}^{*k})) \subset \mathcal{C}(\mathcal{U})$ for all $k \in \{0, \dots, n-1\}$,

Case (Ord2) $\mathcal{Q}^{\frac{k}{2}}(\bar{\mathcal{C}}\mathcal{C}^*\mathcal{D}(\mathcal{Q}^{\frac{k}{2}})) \subset \mathcal{C}(\mathcal{U})$ for all $k \in \{0, \dots, 2n-2\}$.

Remark 1. 1. It might happen that the operator \mathcal{C} itself verify Assumptions 1.1 and 1.2, hence in some sense our assumptions are **more general** than just stating the same assumptions replacing $\bar{\mathcal{C}}$ by \mathcal{C} . However, the price to pay is that condition 1.1 is **stronger** than just having Assumption 1.1 with the control operator \mathcal{C} (see the next point).

2. Assumption 1.1 may seem quite artificial since it does not seem to be related to the controllability of systems

$$\partial_t z = \mathcal{L}z + \mathcal{C}u, \quad (1.4)$$

and

$$\partial_{tt} z = \mathcal{L}z + \mathcal{C}u, \quad (1.5)$$

that would be the natural minimum conditions one might expect.

However, one can easily prove that Assumptions 1.1 and 1.2 imply the controllability at time T^* of (1.4) and (1.5). Let us explain it for (1.4) (this exactly the same reasoning for equation (1.5)). Thanks to the Hilbert Uniqueness Method (HUM, see [Lio88]), we know that the control function u in (1.2) with minimal L^2 -norm is necessarily in $R(\bar{\mathcal{C}}^*)$ (where R denotes the range of an operator), which implies that $\bar{\mathcal{C}}u \in R(\bar{\mathcal{C}}\bar{\mathcal{C}}^*)$, hence thanks to Assumption 1.2 (with $k=0$), we obtain $\bar{\mathcal{C}}u \in R(\mathcal{C})$ and this proves that (1.4) is indeed controllable.

3. One consequence of Assumption 1.2 is that we have $\bar{\mathcal{C}}\mathcal{C}^*\mathcal{D}(\mathcal{L}^{*k}) \in \mathcal{D}(\mathcal{L}^k)$ for every $k \in \{0, \dots, n-1\}$, hence in some sense $\bar{\mathcal{C}}$ has to “preserve the regularity”, which is very natural in the context of conservative systems of second order like (Ord2) (see notably [DL09]). However, in many applications this is in general false for the operator \mathcal{C} itself (and it the main reason why we introduce $\bar{\mathcal{C}}$). For example, consider some open subset Ω of \mathbb{R}^N ($N \in \mathbb{N}^*$), and consider $\mathcal{H} = \mathcal{U} = L^2(\Omega)$. Assume that \mathcal{L} is a differential operator defined on some open subset Ω and the application $\mathcal{C} : L^2(\Omega) \rightarrow L^2(\Omega)$ is defined by $\mathcal{C}u = \mathbb{1}_\omega u$, where ω is some open subset of Ω . Then it is clear that the property $\mathcal{C}\mathcal{C}^*\mathcal{D}(\mathcal{L}^{*k}) \in \mathcal{D}(\mathcal{L}^k)$, which is equivalent to $\mathbb{1}_\omega u \mathcal{D}(\mathcal{L}^{*k}) \in \mathcal{D}(\mathcal{L}^k)$, is *always false* as soon as $k > 0$, \mathcal{L} is of order more than 1 and ω is different from Ω (because $\mathbb{1}_\omega \in L^2(\Omega)$ but does not belong to any higher order Sobolev space). Hence, roughly speaking, the linear application $\bar{\mathcal{C}}$ has to be thought as a “regularization” of the linear application \mathcal{C} . In the case of distributed control, a natural candidate for $\bar{\mathcal{C}}$ is $\bar{\mathcal{C}}u = \mathbb{1}_\omega u$,

where $\tilde{\mathbb{1}}_\omega \in \mathcal{C}_c^\infty(\Omega)$ is some ‘‘regularization’’ of the indicator function $\mathbb{1}_\omega$, defined for example such that

$$\tilde{\mathbb{1}}_\omega := \begin{cases} 1 & \text{on } \omega_0, \\ 0 & \text{on } \Omega \setminus \omega, \end{cases}$$

where ω_0 is some well-chosen open set included in ω . This will be explained into more details in Sections 4.1 and 4.2.

4. Adding the condition $\mathcal{L}^k(\overline{\mathcal{C}\mathcal{C}^*}\mathcal{D}(\mathcal{L}^{*k})) \subset \mathcal{C}(\mathcal{U})$ for all $k \in \{0, \dots, n-1\}$ is necessary in our method to prove that our control is in $(\mathcal{C}(\mathcal{U}))^m$. This notably ensures that the operator \mathcal{M} and $\tilde{\mathcal{M}}$ defined in (2.18) and (3.17) respectively are ‘‘local’’ in the sense that they send an element of the range of $\overline{\mathcal{C}\mathcal{C}^*}$ into an element of the range of \mathcal{C} .

In the sequel, we will denote by $[A|B] \in \mathcal{M}_{n,nm}(\mathbb{K})$ the Kalman matrix, which is given by

$$[A|B] = (B|AB|A^2B|\dots|A^{n-1}B). \quad (1.6)$$

Our result gives a necessary and sufficient condition for exact (or null) controllability of System (Ord1) and (Ord2).

THEOREM 1. *Let us assume that \mathcal{L} satisfies Assumptions 1.1 and 1.2. Let $Y^0 \in (\mathcal{D}(\mathcal{L})^{n-1})^n$. Then, for every $T > T^*$, there exists a control V in $C^0([0, T] \times \mathcal{U}^m)$ such that the solution of (Ord1) corresponding to the initial condition $Y(0) = Y^0$ in \mathcal{H}^n satisfies*

$$Y(T) \equiv 0 \quad \text{in } \mathcal{H}^n$$

if and only $Y^0 \in [A|B](\mathcal{H}^{nm})$.

Remark 2. Concerning Theorem 1, the reversibility of the equation allows us to obtain the same conclusion if we replace the final condition $Y(T, \cdot) = 0$ by $Y(T, \cdot) = Y^T$ for some $Y^T \in \mathcal{D}(\mathcal{L}^{n-1})^n \cap [A|B](\mathcal{H}^{nm})$.

When $\text{rank}([A|B]) = n$, Theorem 1 gives us a necessary and sufficient condition for the null controllability of System (Ord1).

Corollary 1.1. *Let us assume that \mathcal{L} satisfies Assumptions 1.1 and 1.2. Then, for every $T > T^*$, the control system (Ord1) is exactly controllable at time T if and only if $\text{rank}([A|B]) = n$.*

Concerning system (Ord2), we have the following result.

THEOREM 2. *Let us assume that \mathcal{Q} satisfies assumptions 1.1 and 1.2. Then, for every $T > T^*$, the control system (Ord2) is exactly controllable at time T if and only if $\text{rank}(B|AB|\dots|A^{n-1}B) = n$.*

Remark 3. We were not able to derive the same kind of result as in Theorem 1 in the case of second-order in time systems, so that we do not know it would be true in this context.

Using the transmutation technique (for instance the version given in [EZ11]) and Section 3.2, one can deduce easily the following result in the parabolic case, assuming that the corresponding ‘‘scalar’’ hyperbolic system is controllable.

Corollary 1.2. *Let us assume that \mathcal{Q} satisfies Assumptions 1.1 and 1.2. Then, for every $T > 0$, the control system*

$$\partial_t Y = Q_n(Y) + AY + BC_m V \quad \text{in } (0, T) \times \mathcal{H}^n,$$

is null controllable at time T if and only if $\text{rank}(B|AB|\dots|A^{n-1}B) = n$.

Remark 4. (a) $\text{rank}(B|AB|\dots|A^{n-1}B) = n$ is called the Kalman rank condition by analogy with the finite-dimensional case.

- (b) The assumption $T > T^*$ enables us to choose a regular control U in time for the analytic system (2.1) such that $U(0, \cdot) = U(T, \cdot) = 0$ (see [EZ10]). This is necessary to ensure that during the resolution of the Algebraic Problem, we can construct a solution X of (2.9) or (3.11) such that $X(0) = X(T) = 0$. However, many of the controllability results known in the literature are either results in arbitrary small time or with an “open” condition on the minimal time of control, hence in practice controlling at any time $T > T^*$ rather than at time exactly T^* will not provide a weaker result than in the scalar case.

Our paper is organized as follows. In Section 1.2, we recall some previous results and explain precisely the scope of the present contribution. In Section 1.3 we quickly present the main method used. In Section 1.4 we present some related open problems. Section 2 and 3 are respectively devoted to proving Theorem 1 and Theorem 2. In Section 4, we conclude with some applications, giving new results for the indirect controllability of Schrödinger equations and wave equations with internal control.

1.2 State of the art and precise scope of the paper

The question of controlling coupled systems of linear PDEs with a reduced number of control has drawn an increasing interest during the last decade, notably in the case of parabolic or hyperbolic systems. This issue is interesting from a theoretical point of view but also for potential applications. Moreover, as explained in details in [AB13, Section 1], indirect controllability is also closely related to insensitizing control and simultaneous control of coupled systems. In all what follows, we will mainly concentrate on systems coupled with zero order terms, on distributed controls and on null or exact controllability results. The case of boundary controls (which are unbounded) is not covered by our abstract setting. However, there is also a huge literature on boundary control, approximate controllability and high order coupling terms for coupled systems (see notably [GBdT10], [AKBGBdT11a], [BO14] or [DL16] for some recent contributions).

Concerning second-order parabolic equations, the case of coupled systems of heat equations with same diffusion coefficients and constant or time-dependent coupling terms is well-understood (see notably [AKBDGB09a], where an algebraic Kalman rank condition similar to the one of the current article is given). In the case of different diffusion coefficients, a necessary and sufficient condition involving some differential operator related to the Kalman matrix was also given in [AKBDGB09b]. This case was treated into more details in [AKBGBdT14]. However, as soon as the coupling coefficients depend on the space variable, the situation is far more intricate and in general we only have partial results, essentially with two equations, one control force and in the one-dimensional case (see [AKBGBdT15] for example) or in simple geometries like cylinders (see [BBGBO14]). Let us also mention that the non-linear (and even semi-linear) has not been investigated too much up to now (see for example [AKBD06], [GBPG06] and [CGR10]). For further informations on this topic, we refer to the recent survey [AKBGBdT11b].

The case of hyperbolic or dispersive systems seems to have been less studied and the results obtained are somehow quite different from the parabolic ones. Concerning the Schrödinger equation, the recent paper [LGMdT15] considers the case of a cascade system of 2 equations with one control force under the condition that the coupling region and the control region intersect and verify some technical conditions ensuring that a Carleman estimate can be proved. Concerning systems of wave equation, let us mention [AB13], where a result of controllability in sufficiently large time for second order in time cascade or bidiagonal systems under coercivity conditions on the coupling terms is given. Another related result is also [ABL13], where the case of two wave equations with one control and a coupling matrix A which is supposed to be symmetric and having some additional technical properties is investigated. Let us also mention a result in the one-dimensional and periodic case proved in [RdT11]. In this last article, the authors also prove a result for the Schrödinger equation in arbitrary dimension on the torus, however they only obtained a result in large time, which is rather counter-intuitive and should be only technical. The case of a cascade system of two wave equations with one

control on a compact manifold without boundary was treated in [DLRL14], where the author also give a necessary and sufficient condition of controllability depending on the geometry of the control domain and coupling region. Let us emphasize that in the four last references, the results obtained in the case of abstract systems of wave equations can be applied to get some interesting results in the case of abstract heat and Schrödinger equations thanks to the *transmutation method* (see [Phu01], [Mil06] or [EZ11]), leading however to strong (and in general artificial) geometric restrictions on the coupling region and control region. To finish, let us mention a recent result given in [ABCO15], which treats the case of some linear system of two periodic and one-dimensional non-conservative transport equations with same speed of propagation, space-time varying coupling matrix and one control and also a nonlinear case.

Regarding the previous presentation, let us precise the exact scope of this paper, which has a rather different spirit from most of the papers presented before concerning conservative systems.

- Our result is given in a very general setting, since we basically work on some group of operators (which are not necessarily differential operators) with a bounded control operator satisfying some technical conditions that appear to be verified in many cases in practice. Notably, our result fits very well (but is not restricted to) the case of conservative systems of PDEs with distributed control, where no general result was known in the case of constant coupling coefficients.
- Contrary to many results in the literature which concentrates on symmetric matrices, bi-diagonal matrices or cascade matrices, our result does not require any structural conditions on the coupling matrix A , nor on the matrix B which is often assumed to be acting only on the last(s) equations. Moreover, we do not have any restriction on the number of equations n we treat. Hence, most of the techniques used in the literature will fail in our case. Another important point is that we are able here to give a necessary and sufficient condition of controllability and we also are able in the one-order in time case to characterize precisely the initial conditions that can be controlled, which -as far as we know- was only known for the finite-dimensional case and for linear second order parabolic systems (see [AKBDGB09b]).
- The main restriction is that we work with constant coupling coefficients (this implies that the coupling is made everywhere), which do not cover some interesting cases, notably the case of space-varying coefficients described before. Despite this, we believe that the important degree of generality of the present paper compensates this restriction and that our contribution is of interest in order to have a deeper understanding of the controllability properties of coupled systems.

1.3 Strategy of the proof

The general method that we describe briefly in this section is sometimes called *fictitious control method* and was first introduced in [GBPG06]. It has been then used in different context notably in [ABCO15], [CL14] and [DL16]. Roughly speaking, the method can be described as follows: we first control our system of equations with n controls, one on each equation. This control is called a *fictitious control* because it is destined to disappear at the end of the reasoning. Then we try to eliminate this control thanks to algebraic manipulations and replace it by the control operator BC_m , which has a determined algebraic structure and may not act on all equations. The first step will be called *Analytic Problem*, whereas the second one will be called the *Algebraic Problem*. For more details concerning this method and its exact scope, we refer to [DL16, Section 2.3], [CL14, Section 3.1] and [Lis13, Section 1.3].

1.4 Some related open problems

Let us address some related open questions and possible extensions of this work.

- In the case of equation (Ord1), Assumption 1.2 and the regularity condition on the initial data do not seem to be necessary, and it would be natural to expect the same result by just assuming that Assumption 1.1 is true with $\bar{\mathcal{C}} = \mathcal{C}$, but the strategy used here prevented us to get this result. The case of admissible unbounded control operators $\mathcal{B} \in \mathcal{L}_c(U, \mathcal{D}((\mathcal{L}^*)'))$ is also still an open question.
- A natural extension of the Kalman rank condition is what is called the *Silverman-Meadows condition* (see [SM65]) in the case of matrix A and B depending on the time variable, that we did not manage to treat with the same strategy.
- Here the coupling terms are supposed to be constant. It would be interesting to replace them by more general coupling terms. A more challenging issue would be to find an abstract setting that would include conservative partial differential equations with coupling terms depending on the space and time variable, at least in the case where the coupling region intersect the control domain.
- Another interesting question is the case of the local controllability of semi-linear equations, the main difficulty being that due to the difference of regularity between the initial condition and the control, standard inverse mapping theorems or fixed-point theorems cannot be used. A possible remedy would be to use a fixed point strategy of Nash-Moser type as in [ABCO15].
- When systems of equations like (Ord1) and (Ord2) are concerned, a very natural question that might appear in many applications is what is called *partial controllability*, which means that we would like (for example) to bring only the first l ($l \in \llbracket 1, n-1 \rrbracket$) components of the state variable to 0 without imposing any conditions the $n-l+1$ last components. It would be interesting to see if general conditions like the one found in [FAKD16] can be derived.
- To finish, one could also investigate more general coupled systems of the form

$$\partial_t Y = DL_n(Y) + AY + BC_m V \quad \text{in } (0, T) \times \mathcal{H}^n$$

and

$$\partial_{tt} Y = DQ_n(Y) + AY + BC_m V \quad \text{in } (0, T) \times \mathcal{H}^n,$$

where D is some constant matrix, for example a diagonal matrix with (possibly) distinct coefficients and try to derive results similar to [AKBDGB09b].

2 Proof of Theorem 1

In the sequel, we focus our attention on the null-controllability of the system (Ord1). Suppose that Assumptions 1.1 and 1.2 are satisfied and let $T > T^*$. We will always consider some initial condition Y^0 belonging to $\mathcal{D}(\mathcal{L}^{n-1})^n$.

2.1 First part of the proof Theorem 1

In all this section, we assume Y^0 is in $[A|B](\mathcal{H}^{nm})$ and we want to prove that the solution to (Ord1) with initial condition Y^0 can be brought to 0 at time T .

Analytic problem:

We consider the control problem

$$\begin{cases} \partial_t Z = L_n(Z) + AZ + \bar{C}_n(U) & \text{in } (0, T) \times \mathcal{H}^n, \\ Z(0) = Y^0. \end{cases} \quad (2.1)$$

Let us emphasize that in this step we act on *all equations* with n distinct controls, one on each equation. U is here called a *fictitious control* because he will disappear at the end of the reasoning. Let us first prove that (2.1) is controllable and give some regularity results on the control and the solution.

PROPOSITION 2.1. *If Assumption 1.1 is satisfied, then for every $T > T^*$, the control system (2.1) is null controllable at time T . Moreover, one can choose a control U such that*

$$U(t, \cdot) \in [A|B](\mathcal{H}^{nm}) \text{ for every } t \in (0, T), \quad (2.2)$$

$$U \in H_0^{n-1}(0, T; \mathcal{U}^n) \cap \bigcap_{k=0}^{n-1} C^k([0, T]; \overline{C}_n^* \mathcal{D}((L_n^*)^{n-1-k})), \quad (2.3)$$

$$Z \in \bigcap_{k=0}^{n-1} C^k([0, T]; \mathcal{D}(L_n^{n-1-k})). \quad (2.4)$$

Proof of Proposition 2.1. Using the change of variables $Z = e^{tA} \tilde{Z}$ and $U = e^{tA} \tilde{U}$, we obtain that the solution Z of system (2.1) is null controllable at time T if and only if the system

$$\left\{ \begin{array}{l} \partial_t \tilde{Z} = L_n(\tilde{Z}) + \overline{C}_n(\tilde{U}) \quad \text{in } (0, T) \times \mathcal{H}^n, \end{array} \right. \quad (2.5)$$

is null controllable at time T . Remark that system (2.5) is totally uncoupled. Hence, since the control system (1.2) is controllable at time T , using the definitions of L_n and \overline{C}_n given in (1.1), we easily obtain that the control system (2.5) is controllable at time T .

Moreover $\overline{C}_n \in \mathcal{L}(\mathcal{U}^n, \mathcal{H}^n)$ and the operator L_n is a generator of a group on \mathcal{H}^n . Then, applying [EZ10, Corollary 1.5] (with $s = n - 1$), we deduce that there exists (\tilde{Z}, \tilde{U}) a solution of (2.5) such that $\tilde{Z}(T) = 0$ and

$$\tilde{Z} \in \bigcap_{k=0}^{n-1} C^k([0, T]; \mathcal{Z}_{n-1-k}),$$

where \mathcal{Z}_j is defined by induction by

$$\mathcal{Z}_0 = \mathcal{H}^n, \quad \mathcal{Z}_j = L_n^{-1}(\mathcal{Z}_{j-1} + \overline{C}_n \overline{C}_n^* (\mathcal{D}((L_n^*)^j))).$$

The spaces \mathcal{Z}_j are in general not known explicitly, however, in our case, using Assumption 1.2 (see also the second point of Remark 1), it is clear that notably

$$\overline{C}_n \overline{C}_n^* \mathcal{D}((L_n^*)^j) \subset \mathcal{D}(L_n^j),$$

from which we deduce easily by induction that for every $j \in \llbracket 1, n \rrbracket$, we have

$$\mathcal{Z}_j \subset \mathcal{D}(L_n^j),$$

which establishes (2.4).

Moreover, [EZ10, Theorem 1.4] (with $s = n - 1$) notably implies that one can choose \tilde{U} belonging to $H_0^{n-1}(0, T; \mathcal{U}^n)$. Finally, to prove (2.3), it is enough to prove that

$$\tilde{U} \in \bigcap_{k=0}^{n-1} C^k([0, T]; \overline{C}_n^* \mathcal{D}((L_n^*)^{n-1-k})),$$

which is an immediate consequence of the proof of Corollary 1.5 of [EZ10, Page 1387] (and notably equality (3.19) in this reference).

It remains us to prove (2.2). As in [EZ10, Equality (1.3)], we fix $\delta > 0$ such that $T - 2\delta > T^*$ and we consider $\eta \in C^{n-1}(\mathbb{R})$ such that

$$\eta(t) = \begin{cases} 0 & \text{if } t \in (0, T), \\ 1 & \text{if } t \in [\delta, T - \delta]. \end{cases}$$

Then, \tilde{U} can also be chosen as the one of minimal $L^2(0, T; dt/\eta; U)$ among all possible controls for which the solution of (2.1) satisfies $\tilde{Z}(T) = 0$, properties (2.3) and (2.4) being still verified.

Hence, using [EZ10, Proposition 1.3], \tilde{U} can be written as

$$\tilde{U} = \eta(t)\overline{C}_n^* e^{(T-t)L_n^*} G_n^{-1} e^{TL_n} Y^0,$$

where

$$G_n = \int_0^T e^{(T-t)L_n} \overline{C}_n \overline{C}_n^* e^{(T-t)L_n^*} dt.$$

Note that since (2.5) is null controllable, G_n is indeed an invertible linear application. Using that $Y^0 = [A|B]\hat{Y}^0$ with $\hat{Y}^0 \in \mathcal{H}^{nm}$, and the formulas

$$\begin{aligned} L_n[A|B] &= [A|B]L_{nm}, \\ \overline{C}_n^*[A|B] &= [A|B]\overline{C}_{nm}^*, \\ \overline{C}_n[A|B] &= [A|B]\overline{C}_{nm}, \end{aligned}$$

we deduce

$$\tilde{U} = [A|B]\eta(t)\overline{C}_{nm}^* e^{(T-t)L_{nm}^*} G_{nm}^{-1} e^{TL_{nm}} \hat{Y}^0,$$

where

$$G_{nm} = \int_0^T e^{(T-t)L_{nm}} \overline{C}_{nm} \overline{C}_{nm}^* e^{(T-t)L_{nm}^*} dt,$$

which is also invertible. Using that $\tilde{U} = e^{-tA}U$, we obtain

$$U = e^{tA}[A|B]\eta(t)\overline{C}_{nm}^* e^{(T-t)L_{nm}^*} G_{nm}^{-1} e^{TL_{nm}} \hat{Y}^0. \quad (2.6)$$

By the Cayley-Hamilton theorem, there exists $\beta = \begin{pmatrix} \beta_0 \\ \vdots \\ \beta_{n-1} \end{pmatrix} \in \mathbb{K}^n$ such that $A^n = \sum_{i=0}^{n-1} \beta_i A^i$. Let

$\psi = \begin{pmatrix} \psi_0 \\ \vdots \\ \psi_{n-1} \end{pmatrix} \in \mathcal{H}^{nm}$, we have

$$\begin{aligned} A[A|B]\psi &= (AB, A^2B, \dots, A^n B)\psi \\ &= (AB, A^2B, \dots, \sum_{i=0}^{n-1} \beta_i A^i B)\psi \\ &= [A, B]\hat{\psi} \end{aligned} \quad (2.7)$$

with

$$\hat{\psi} = \begin{pmatrix} \beta_0 \psi_{n-1} \\ \psi_0 + \beta_1 \psi_{n-1} \\ \vdots \\ \psi_{n-2} + \beta_{n-1} \psi_{n-1} \end{pmatrix} \in \mathcal{H}^{nm}.$$

Combining (2.6), (2.7) and using the fact that there exists $\alpha \in \mathbb{K}^n$ such that $e^{-tA} = \sum_{i=0}^{n-1} \alpha_i A^i$, we obtain (2.2) and the proof of Proposition 2.1 is complete. ■

Algebraic problem:

Now, we would like to come back to the original system (Ord1) by algebraic manipulations.

Using Proposition 2.1, there exists (Z, U) solution of (2.1) verifying moreover (2.2), (2.3) and (2.4). Notably, there exists $\tilde{U} \in \mathcal{U}^{nm}$ such that $\tilde{C}_n(U) = [A|B]\tilde{C}_{nm}(\tilde{U})$. From now on, we will call $f := \tilde{C}_{nm}(\tilde{U})$, that will be considered as a source term. Our goal will be to find a pair $(X, \tilde{W}) \in C^0([0, T]; \mathcal{D}(L_n)) \cap C^1([0, T]; \mathcal{H}^n) \times C^0([0, T]; \mathcal{U}^m)$ satisfying the following problem:

$$\begin{cases} \partial_t X = L_n(X) + AX + BC_m \tilde{W} + [A|B]f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = 0. \end{cases} \quad (2.8)$$

Calling $C_m \tilde{W} = W$, we will rather solve (the unknowns being the variables X and W) the following problem

$$\begin{cases} \partial_t X = L_n(X) + AX + BW + [A|B]f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = 0, \end{cases} \quad (2.9)$$

(the fact that $W \in C_m \mathcal{U}^m$ will be a consequence of our construction and our assumptions). Let us remark that system (2.9) is *underdetermined* in the sense that we have more unknowns than equations. Hence, one can hope to find a trajectory (X, W) verifying $X(0) = X(T) = 0$ (which is a *crucial point here*), which would not be necessarily possible if the system were well-posed. We will use the notion of *algebraic solvability*, which is based on ideas coming from [Gro86, Section 2.3.8] for differential systems and was already widely used in [ABCO15], [CL14] and [DL16]. The idea is to write System (2.9) as an underdetermined system in the variables X and W and to see f as a source term, so that we can write Problem (2.9) under the abstract form

$$\mathcal{P}(X, W) = [A|B]f, \quad (2.10)$$

where

$$\mathcal{P} : \begin{array}{l} \mathcal{D}(\mathcal{P}) \subset L^2(0, T; \mathcal{H}^{n+m}) \\ (X, W) \end{array} \rightarrow \begin{array}{l} L^2(0, T; \mathcal{H}^n) \\ \partial_t X - L_n X - AX - BW. \end{array} \quad (2.11)$$

The goal will be then to find an operator \mathcal{M} (involving time derivatives and powers of L_n) satisfying

$$\mathcal{P} \circ \mathcal{M} = [A|B]. \quad (2.12)$$

When (2.12) is satisfied, we say that System (2.9) is *algebraically solvable*. In this cas, one can choose as a particular solution of (2.9) $(X, W) = \mathcal{M}(\tilde{C}_{nm}(\tilde{U}))$. This exactly means that one can find a solution (X, W) of System (2.9) which can be written as a linear combination f , its derivatives in time, and some $L_n^k f$ with $k \in \mathbb{N}^*$. Let us prove the following Proposition:

PROPOSITION 2.2. *Let $(A, B) \in \mathcal{M}_n(\mathbb{K}) \times \mathcal{M}_{n,m}(\mathbb{K})$. There exists an operator \mathcal{M} such that the equality (2.12) is satisfied. Moreover, the operator \mathcal{M} is an operator of order at most*

$$\begin{cases} n - 2 & \text{for the } n \text{ first components} \\ n - 1 & \text{for the } m \text{ last components} \end{cases} \quad (2.13)$$

in time and in term of powers of L_n .

Proof of Proposition 2.2. We can remark that equality (2.12) is equivalent to

$$\mathcal{M}^* \circ \mathcal{P}^* = [A|B]^*. \quad (2.14)$$

The adjoint operator $\mathcal{P}^* : \mathcal{D}(\mathcal{P}^*) \subset L^2(0, T; \mathcal{H}^n) \rightarrow L^2(0, T; \mathcal{H}^n) \times L^2(0, T; \mathcal{H}^m)$ of the operator \mathcal{P} is given for all $\varphi \in \mathcal{D}(\mathcal{P}^*)$ by

$$\mathcal{P}^* \varphi := \begin{pmatrix} (P^* \varphi)_1 \\ \vdots \\ (P^* \varphi)_n \\ (P^* \varphi)_{n+1} \\ \vdots \\ (P^* \varphi)_{n+m} \end{pmatrix} = \begin{pmatrix} -\partial_t \varphi - L_n^* \varphi - A^* \varphi \\ -B^* \varphi \end{pmatrix}. \quad (2.15)$$

Since $(A, B) \in \mathcal{M}_n(\mathbb{K}) \times \mathcal{M}_{n,m}(\mathbb{K})$ are constant matrices, we have the following commutation properties:

$$B^*(A^*)^i L_n^* = L_m^* B^*(A^*)^i$$

and

$$B^*(A^*)^i \partial_t = \partial_t B^*(A^*)^i.$$

By definition, we have

$$B^* \varphi = - \begin{pmatrix} (P^* \varphi)_{n+1} \\ \vdots \\ (P^* \varphi)_{n+m} \end{pmatrix}.$$

Now, for $i = \{1, \dots, n-1\}$, applying $B^*(A^*)^{i-1}$ to $-\partial_t \varphi - L_n^* \varphi - A^* \varphi$, we have

$$B^*(A^*)^{i-1} \begin{pmatrix} (P^* \varphi)_1 \\ \vdots \\ (P^* \varphi)_n \end{pmatrix} = -(\partial_t + L_m^*)(B^*(A^*)^{i-1} \varphi) - B^*(A^*)^i \varphi, \text{ i.e.}$$

$$B^*(A^*)^i \varphi = -B^*(A^*)^{i-1} \begin{pmatrix} (P^* \varphi)_1 \\ \vdots \\ (P^* \varphi)_n \end{pmatrix} - (\partial_t + L_m^*)(B^*(A^*)^{i-1} \varphi).$$

By induction, we find, for every $i \in \{1, \dots, n-1\}$,

$$\begin{aligned} B^*(A^*)^i \varphi &= \sum_{j=0}^{i-1} (-1)^{j+1} \left((\partial_t + L_m^*)^j B^*(A^*)^{i-1-j} \begin{pmatrix} (P^* \varphi)_1 \\ \vdots \\ (P^* \varphi)_n \end{pmatrix} \right) \\ &\quad + (-1)^{i+1} (\partial_t + L_m^*)^i \begin{pmatrix} (P^* \varphi)_{n+1} \\ \vdots \\ (P^* \varphi)_{n+m} \end{pmatrix}. \end{aligned} \tag{2.16}$$

We introduce the operator $\mathcal{M}^* : \mathcal{D}(\mathcal{M}^*) \subset L^2(0, T; \mathcal{H}^{n+m}) \rightarrow L^2(0, T; \mathcal{H}^{nm})$ defined by

$$\mathcal{M}^* \begin{pmatrix} \psi_1 \\ \vdots \\ \psi_{n+m} \end{pmatrix} := \begin{pmatrix} -\psi_{n+1} \\ \vdots \\ -\psi_{n+m} \\ -B^* \begin{pmatrix} \psi_1 \\ \vdots \\ \psi_n \end{pmatrix} + (\partial_t + L_m^*) \begin{pmatrix} \psi_{n+1} \\ \vdots \\ \psi_{n+m} \end{pmatrix} \\ \vdots \\ \sum_{j=0}^{n-2} (-1)^{j+1} \left((\partial_t + L_m^*)^j B^*(A^*)^{n-2-j} \begin{pmatrix} \psi_1 \\ \vdots \\ \psi_n \end{pmatrix} \right) + (-1)^n (\partial_t + L_m^*)^{n-1} \begin{pmatrix} \psi_{n+1} \\ \vdots \\ \psi_{n+m} \end{pmatrix} \end{pmatrix}. \tag{2.17}$$

Thanks to (2.16) and (2.17), \mathcal{M}^* verifies equality (2.14). Using the definition of \mathcal{M}^* given in (2.17), we deduce that

$$\mathcal{M} : \mathcal{D}(\mathcal{M}) \subset L^2(0, T; \mathcal{H}^{nm}) \rightarrow L^2(0, T; \mathcal{H}^{n+m})$$

$$f = \begin{pmatrix} f_1 \\ \vdots \\ f_m \\ f_{m+1} \\ \vdots \\ f_{2m} \\ \vdots \\ f_{nm} \end{pmatrix} \mapsto \mathcal{M}f,$$

defined by

$$\mathcal{M}f = \begin{pmatrix} \sum_{i=1}^{n-1} \sum_{j=0}^{i-1} (-1)^{j+1} (-\partial_t + L_n)^j A^{i-1-j} B \begin{pmatrix} f_{jm+1} \\ \vdots \\ f_{(j+1)m} \end{pmatrix} \\ \sum_{i=0}^{n-1} (-1)^{i+1} (-\partial_t + L_m)^i \begin{pmatrix} f_{im+1} \\ \vdots \\ f_{(i+1)m} \end{pmatrix} \end{pmatrix}, \quad (2.18)$$

satisfies (2.12). Thus, in the n first components the higher order term is $(-\partial_t + \mathcal{L})^{n-2}$ and in the m last components the higher order term is $(-\partial_t + \mathcal{L})^{n-1}$, which concludes the proof. \blacksquare

Conclusion: combination of the Analytic and Algebraic Problems.

Thanks to Proposition 2.1, there exists (Z, U) solution of (2.1) verifying moreover (2.2), (2.3) and (2.4). One can notably write

$$\bar{C}_n(U) = [A|B]\bar{C}_{nm}(\hat{U}) \quad (2.19)$$

for some $\hat{U} \in L^2((0, T); \mathcal{U}^{nm})$. Using Proposition 2.2, we define (X, W) by

$$\begin{pmatrix} X \\ W \end{pmatrix} := \mathcal{M}(\bar{C}_{nm}\hat{U}), \quad (2.20)$$

where \hat{U} is defined in (2.19). Using (2.3), we know that

$$\bar{C}_n U \in H_0^{n-1}(0, T; \bar{C}_n(\mathcal{U}^n)) \cap \bigcap_{k=0}^{n-1} C^k([0, T]; \bar{C}_n \bar{C}_n^* \mathcal{D}((L_n^*)^{n-1-k})),$$

which implies using Assumption 1.2 that

$$\bar{C}_n U \in H_0^{n-1}(0, T; \bar{C}_n(\mathcal{U}^n)) \cap \bigcap_{k=0}^{n-1} C^k([0, T]; (\mathcal{D}(\mathcal{L}^{n-1-k}))^n).$$

Using now (2.19), we obtain

$$\bar{C}_{nm} \hat{U} \in H_0^{n-1}(0, T; \bar{C}_{nm}(\mathcal{U}^{nm})) \cap \bigcap_{k=0}^{n-1} C^k([0, T]; (\mathcal{D}(\mathcal{L}^{n-1-k}))^{nm}). \quad (2.21)$$

Using (2.20) together with (2.13) and (2.21), we obtain that

$$(X, W) \in \left(H_0^1(0, T; \bar{C}_n(\mathcal{U}^n)) \cap \bigcap_{k=0}^1 C^k([0, T]; \mathcal{D}(L_n^{1-k})) \right) \times \left(L^2(0, T; \bar{C}_m(\mathcal{U}^m)) \cap C^0([0, T]; \mathcal{H}^m) \right),$$

i.e.

$$(X, W) \in \left(H_0^1(0, T; \bar{C}_n(\mathcal{U}^n)) \cap \bigcap_{k=0}^1 C^k([0, T]; \mathcal{D}(L_n^{1-k})) \right) \times C^0([0, T]; \bar{C}_m(\mathcal{U}^m)). \quad (2.22)$$

Notably, there exists $\tilde{W} \in C^0([0, T]; \mathcal{U}^m)$ such that $W = C_m \tilde{W}$. Thus, coming back to (2.8), we infer that (X, \tilde{W}) is a solution to the problem

$$\begin{cases} \partial_t X = L_n(X) + AX + BC_m \tilde{W} + [A|B]f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = 0. \end{cases} \quad (2.23)$$

Hence, combining (2.1), (2.23) and the regularity results given in (2.4) and (2.22), the fictitious control f disappears and the pair $(Y, V) := (Z - X, -\tilde{W})$ is a solution to System (Ord1) in the space

$$C^0([0, T]; \mathcal{D}(L_n)) \cap C^1([0, T]; \mathcal{H}^n) \times C^0([0, T]; \mathcal{U}^m)$$

satisfying

$$\begin{aligned} Y(0) &= Y^0 \text{ in } \mathcal{D}(\mathcal{L}^{n-1})^n, \\ Y(T) &\equiv 0 \text{ in } \mathcal{H}^n, \end{aligned}$$

which concludes the first part of the proof of Theorem 1. ■

2.2 Second part of the proof of Theorem 1

In this section, we assume Y^0 is NOT in $[A|B](\mathcal{H}^{nm})$ and we want to prove that we cannot bring the solution of (Ord1) with initial Y^0 to 0. We argue by contradiction.

For the sake of completeness we mimic the proof of [AKBDGB09a, Theorem 1.5]. Without loss of generality we can only consider the case where we have one control force $m = 1$, that is to say $B \in \mathcal{M}_{n,1}(\mathbb{K})$ ($m = 1$), the general case being quite similar (see notably [AKBDGB09a, Lemma 3.1 and Page 14]).

Let $l \in \mathbb{N}$ such that $\text{rank}[A|B] = l < n$. By the Cayley-Hamilton theorem, $\{B, AB, \dots, A^{l-1}B\}$ is linearly independent. We introduce

$$X = \text{span}\{B, AB, \dots, A^{l-1}B\}.$$

Since $A^l B \in X$, we know that there exists $\alpha \in \mathbb{K}^l$ such that

$$A^l B = \alpha_1 B + \alpha_2 AB + \dots + \alpha_l A^{l-1} B. \quad (2.24)$$

Let p_{l+1}, \dots, p_n be $n - l$ vectors in \mathbb{K}^n such that the set

$$\{B, AB, \dots, A^{l-1}B, p_{l+1}, \dots, p_n\}$$

is a basis of \mathbb{K}^n . Introducing

$$P = (B|AB|\dots|A^{l-1}B|p_{l+1}|\dots|p_n),$$

we have $Pe_1 = B$ with $e_1 = \begin{pmatrix} 1 \\ 0 \\ \vdots \\ 0 \end{pmatrix}$ and

$$P^{-1}AP = \begin{pmatrix} D_{11} & D_{12} \\ 0 & D_{22} \end{pmatrix}$$

for some $D_{12} \in \mathcal{M}_{l,n-l}(\mathbb{K})$, $D_{22} \in \mathcal{M}_{n-l}(\mathbb{K})$ and $D_{11} \in \mathcal{M}_l$ which is given by

$$D_{11} = \begin{pmatrix} 0 & 0 & 0 & \cdots & \alpha_1 \\ 1 & 0 & 0 & \cdots & \alpha_2 \\ 0 & 1 & 0 & \cdots & \alpha_3 \\ \vdots & \vdots & \ddots & \ddots & \vdots \\ 0 & 0 & \cdots & 1 & \alpha_l \end{pmatrix}$$

By the change of variables $W = P^{-1}Y$ and using $L_n P^{-1} = P^{-1}L_n$ and $\partial_t P^{-1} = P^{-1}\partial_t$ we observe that there exists a control V in $L^2((0, T) \times \mathcal{H})$ such that the solution of (Ord1) corresponding to the initial condition $Y(0) = Y^0$ in \mathcal{H}^n satisfies $Y(T) \equiv 0$ in \mathcal{H}^n if and only if the solution $W = \begin{pmatrix} W_1 \\ W_2 \end{pmatrix}$ to

$$\begin{cases} \partial_t W = L_n W + \begin{pmatrix} D_{11} & D_{12} \\ 0 & D_{22} \end{pmatrix} W + C_1 V e_1, \\ W(0) = W^0 := P^{-1}Y^0 \end{cases} \quad (2.25)$$

verifies $W(T) \equiv 0$ in \mathcal{H}^n . Besides, it is easy to see that $Y^0 \in [A|B](\mathcal{H}^{nm})$ if and only if there exists $W_1^0 \in \mathcal{H}^l$ such that $Y^0 = P \begin{pmatrix} W_1^0 \\ 0 \end{pmatrix}$. If $Y^0 \notin [A|B](\mathcal{H}^{nm})$ then $Y^0 = P \begin{pmatrix} W_1^0 \\ W_2^0 \end{pmatrix}$ with $W_1^0 \in \mathcal{H}^l$, $W_2^0 \in \mathcal{H}^{n-l}$ and $W_2^0 \neq 0$. Thus, by uniqueness we conclude that $W_2(T) \neq 0$. Hence the solution W of (2.25) cannot be driven to zero at time T and (Ord1) cannot be driven from Y^0 at time T to 0 at time T , which concludes the proof. ■

3 Proof of Theorem 2

Let us recall that we consider here an operator \mathcal{Q} which is assumed to be self-adjoint, negative with compact resolvent. Suppose that Assumptions 1.1 and 1.2 are satisfied and let $T > T^*$. We will always consider some initial condition $(Y^0, Y^1) \in \mathcal{D}(\mathcal{Q}^{n-\frac{1}{2}})^n \times \mathcal{D}(\mathcal{Q}^{n-1})^n$.

During this section, we will assume that $\mathbb{K} = \mathbb{C}$ for the sake of simplicity. The case $\mathbb{K} = \mathbb{R}$ can then be easily deduced for example by complexifying the spaces \mathcal{H} and \mathcal{U} .

3.1 First part of the proof of Theorem 2

In this section, we assume that the Kalman rank condition is satisfied and we want to prove the controllability of (Ord2). We proceed as in the proof of Theorem 1. Let us emphasize that the main difference with the previous case is that the changing of variables exhibited during the proof of Proposition 2.1 does not work anymore, hence we have to change totally the proof of the analytic part, which will now rely on a classical compactness-uniqueness argument similar to the one given for example in [CT10, Section 3]. Concerning the algebraic part, the computations are essentially the same.

Analytic problem:

We consider the controlled system

$$\begin{cases} \partial_{tt} Z = Q_n(Z) + AZ + \bar{C}_n(U) & \text{in } (0, T) \times \mathcal{H}^n, \\ Z(0) = Z^0, \\ \partial_t Z(0) = Z^1. \end{cases} \quad (3.1)$$

Let us first introduce some notations and first-order framework. Let H_α be the Hilbert space defined by $\mathcal{H}_\alpha = \mathcal{D}(Q^\alpha)$ for any $\alpha \geq 0$ and $H_{-\alpha}$ is the dual space of H_α with respect to the pivot

space \mathcal{H} . We denote by $X = \left(\mathcal{H}_{\frac{1}{2}} \times \mathcal{H}\right)^n$ our state space. We introduce the operator $\hat{Q} : \mathcal{D}(\hat{Q}) = \left(\mathcal{H}_1 \times \mathcal{H}_{\frac{1}{2}}\right)^n \subset X \rightarrow X$ such that

$$\hat{Q} = \begin{pmatrix} A_{\mathcal{Q}} & 0 & \cdots & 0 \\ 0 & A_{\mathcal{Q}} & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & A_{\mathcal{Q}} \end{pmatrix} \quad \text{with} \quad A_{\mathcal{Q}} = \begin{pmatrix} 0 & I_d \\ \mathcal{Q} & 0 \end{pmatrix}. \quad (3.2)$$

The system (3.1) can be written as a first order system

$$\hat{Z}_t = (\hat{Q} + \hat{A})\hat{Z} + \hat{C}U, \quad (3.3)$$

$$\text{with } \hat{Z} = \begin{pmatrix} Z_1 \\ (Z_1)_t \\ \vdots \\ Z_n \\ (Z_n)_t \end{pmatrix}, \hat{C} \begin{pmatrix} u_1 \\ \vdots \\ u_n \end{pmatrix} = \begin{pmatrix} 0 \\ \bar{\mathcal{C}}u_1 \\ \vdots \\ 0 \\ \bar{\mathcal{C}}u_n \end{pmatrix} \text{ and } \hat{A} = \begin{pmatrix} 0 & 0 & 0 & \cdots & 0 & 0 \\ a_{11} & 0 & a_{12} & \cdots & 0 & a_{1n} \\ \vdots & \vdots & \vdots & \ddots & \vdots & \vdots \\ 0 & 0 & 0 & \cdots & 0 & 0 \\ a_{n1} & 0 & a_{n2} & \cdots & 0 & a_{nn} \end{pmatrix}.$$

Since we identify \mathcal{H} with its dual, we shall define $\left(\mathcal{H}_{\frac{1}{2}} \times \mathcal{H}\right)' = \mathcal{H} \times \mathcal{H}_{-\frac{1}{2}}$ and the duality product defined for $(y_0, y_1) \in \mathcal{H} \times \mathcal{H}_{-\frac{1}{2}}$, $(z_0, z_1) \in \mathcal{H}_{\frac{1}{2}} \times \mathcal{H}$ by

$$\left\langle \begin{pmatrix} y_0 \\ y_1 \end{pmatrix}, \begin{pmatrix} z_0 \\ z_1 \end{pmatrix} \right\rangle_{\left(\mathcal{H} \times \mathcal{H}_{-\frac{1}{2}}\right) \times \left(\mathcal{H}_{\frac{1}{2}} \times \mathcal{H}\right)} = \langle y_0, z_1 \rangle_H + \langle y_1, z_0 \rangle_{\mathcal{H}_{-\frac{1}{2}} \times \mathcal{H}_{\frac{1}{2}}}.$$

With this scalar product, we have

$$\hat{Q}^* = - \begin{pmatrix} A_{\mathcal{Q}^*} & 0 & \cdots & 0 \\ 0 & A_{\mathcal{Q}^*} & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & A_{\mathcal{Q}^*} \end{pmatrix} \quad \text{with} \quad \begin{cases} X' = (\mathcal{H} \times \mathcal{H}_{-\frac{1}{2}})^n, \\ \mathcal{D}(\hat{Q}^*) = \left(\mathcal{H}_{\frac{1}{2}} \times \mathcal{H}\right)^n, \end{cases}$$

and $\hat{C}^* : X^* \rightarrow \mathcal{U}^n$ is given by

$$\hat{C}^* \begin{pmatrix} x_1 \\ x_2 \\ \vdots \\ x_{2n} \end{pmatrix} = \begin{pmatrix} \bar{\mathcal{C}}^* x_1 \\ \bar{\mathcal{C}}^* x_3 \\ \vdots \\ \bar{\mathcal{C}}^* x_{2n-1} \end{pmatrix}. \quad (3.4)$$

Thus, $\hat{C}\hat{C}^* : X^* \rightarrow X$ is exactly

$$\hat{C}\hat{C}^* = \begin{pmatrix} B_{\bar{\mathcal{C}}} & 0 & \cdots & 0 \\ 0 & B_{\bar{\mathcal{C}}} & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & B_{\bar{\mathcal{C}}} \end{pmatrix} \quad \text{with} \quad B_{\bar{\mathcal{C}}} = \begin{pmatrix} 0 & 0 \\ \bar{\mathcal{C}}\bar{\mathcal{C}}^* & 0 \end{pmatrix}.$$

and for $i \in \mathbb{N}^*$, $\mathcal{D}(\hat{Q}^i) = \left(\mathcal{H}_{\frac{i+1}{2}} \times \mathcal{H}_{\frac{i}{2}}\right)^n$ and $\mathcal{D}((\hat{Q}^*)^i) = \mathcal{D}(\hat{Q}^{i-1})$.

We can now go back to the resolution of the analytic problem.

For any operator \mathcal{R} , we introduce the set

$$\begin{aligned} \mathcal{N}_{\mathcal{R}}(T) &:= \left\{ \begin{bmatrix} z^0 \\ z^1 \end{bmatrix} \in \mathcal{H}_{\frac{1}{2}} \times \mathcal{H} \mid C^* z_t = 0 \quad \forall t \in [0, T], \quad z \text{ solution of } \begin{cases} \partial_{tt} z = \mathcal{R} z \\ z(0) = z^0, \partial_t z(0) = z^1 \end{cases} \right\}, \\ &= \left\{ \begin{bmatrix} z^0 \\ z^1 \end{bmatrix} \in \mathcal{H}_{\frac{1}{2}} \times \mathcal{H} \mid (0, C^*) Z = 0 \quad \forall t \in [0, T], \quad Z \text{ solution of } \begin{cases} \partial_t Z = \begin{pmatrix} 0 & I_d \\ \mathcal{R} & 0 \end{pmatrix} Z \\ Z(0) = \begin{pmatrix} z^0 \\ z^1 \end{pmatrix} \end{cases} \right\}. \end{aligned} \quad (3.5)$$

The main proposition is the following.

PROPOSITION 3.1. *If Assumption 1.1 is satisfied, for every $T > T^*$, the control system (3.1) is null controllable at time T . Moreover, one can choose U such that*

$$U \in H_0^{2n-2}(0, T; \mathcal{U}^n) \cap \bigcap_{k=0}^{2n-2} C^k([0, T], \overline{C}^*(\mathcal{H}_{n-1-\frac{k}{2}})^n). \quad (3.6)$$

Proof of Proposition 3.1.

We will need the two following lemmas.

Lemma 3.1. *If $\mathcal{N}_{Q_n^* + A^*}(T) = \{0\}$ and if the system*

$$\partial_{tt} Z = Q_n(Z) + \overline{C}_n(U) \quad \text{in } (0, T) \times \mathcal{H}^n \quad (3.7)$$

is exactly controllable at time T then the system (3.1) is exactly controllable in time T .

Lemma 3.1 can be found in [CT10, Theorem 4] (with $\epsilon = 1$), its proof will then be omitted.

Lemma 3.2. *If $\mathcal{N}_{Q^*}(T) = \{0\}$ then $\mathcal{N}_{Q_n^* + A^*}(T) = \{0\}$.*

Let us temporarily admit this lemma and explain how we can deduce Proposition 3.1. By Assumption 1.1, we have a unique continuation property for the adjoint system of (3.7), from which we obtain that $\mathcal{N}_{Q^*}(T) = \{0\}$. Now, using Lemma 3.1 and Lemma 3.2, the system (3.1) is null controllable at time T . Since $\hat{C} \in \mathcal{L}(\mathcal{U}^n, X)$, the control system (3.3) is null controllable at time T and the operator $\hat{Q} + \hat{A}$ is a generator of strongly continuous group on X . Let $T > T^*$, combining one more time Theorem 1.4, Corollary 1.5 and the equality (3.19) in [EZ10] (with $s = 2n - 2$), if $Y_0 \in \mathcal{D}(\hat{Q}^{2n-2})$ one can choose U such that

$$U \in H_0^{2n-2}(0, T; \mathcal{U}^n) \cap \bigcap_{k=0}^{2n-2} C^k([0, T]; \hat{C}^* \mathcal{D}((\hat{Q}^*)^{2n-2-k})).$$

Since for $i \in \mathbb{N}^*$, $\mathcal{D}(\hat{Q}^i) = (\mathcal{H}_{\frac{i+1}{2}} \times \mathcal{H}_{\frac{i}{2}})^n$, $\mathcal{D}((\hat{Q}^*)^i) = \mathcal{D}(\hat{Q}^{i-1})$, and going back to the definition of \hat{C}^* given in (3.4), we obtain (3.6). ■

It remains us to prove Lemma 3.2. The proof is based on the following property.

Lemma 3.3. *Let $a \in \mathbb{K}$. If $\mathcal{N}_{Q^*}(T) = \{0\}$ then $\mathcal{N}_{Q^* + aI_{\mathcal{H}}}(T) = \{0\}$.*

Proof of Lemma 3.3. Let us decompose the proof into three steps.

- If $C^* \varphi \neq 0$ for every eigenvector φ of $Q^* + aI_{\mathcal{H}}$ then $\mathcal{N}_{Q^* + aI_{\mathcal{H}}} = \{0\}$.

To prove this property we refer to the proof of [CT10, Theorem 5] which relies on an easy compactness-uniqueness argument.

- If φ an eigenvector of \mathcal{Q}^* associated to the eigenvalue $-\lambda < 0$ and $\mathcal{N}_{\mathcal{Q}^*}(T) = 0$ then $C^*\varphi \neq 0$.

Indeed, in this case $\begin{pmatrix} \frac{\varphi}{i\sqrt{\lambda}} \\ \varphi \end{pmatrix}$ is an eigenvector of $\begin{pmatrix} 0 & I_d \\ \mathcal{Q}^* & 0 \end{pmatrix}$ associated to the eigenvalue $i\sqrt{\lambda}$. Let us assume that $(0, C^*) \begin{pmatrix} \frac{\varphi}{i\sqrt{\lambda}} \\ \varphi \end{pmatrix} = C^*\varphi = 0$. Let Z_φ be the solution of

$$\begin{cases} \partial_t Z_\varphi = \begin{pmatrix} 0 & I_d \\ \mathcal{Q}^* & 0 \end{pmatrix} Z_\varphi, \\ Z_\varphi(0) = \begin{pmatrix} \frac{\varphi}{i\sqrt{\lambda}} \\ \varphi \end{pmatrix}. \end{cases}$$

Thus for all $t \in (0, T)$, we have

$$Z(t) = e^{i\sqrt{\lambda}t} \begin{pmatrix} \frac{\varphi}{i\sqrt{\lambda}} \\ \varphi \end{pmatrix}.$$

By assumption $(0, C^*)Z(t) = e^{i\sqrt{\lambda}t}C^*\varphi = 0$. From the definition of $\mathcal{N}_{\mathcal{Q}^*}(T)$, $\varphi \in \mathcal{N}_{\mathcal{Q}^*}(T) = \{0\}$, whence the contradiction.

- For every φ eigenvector of $\mathcal{Q}^* + aI_{\mathcal{H}}$, $C^*\varphi \neq 0$.

Indeed, the couple (φ, λ) is a vector-eigenfunction of \mathcal{Q}^* if and only if the couple $(\varphi, \lambda + a)$ is a vector-eigenfunction of $\mathcal{Q}^* + aI_{\mathcal{H}}$, and we can use the previous point.

Combining these 3 arguments provides Lemma 3.3. ■

Proof of Lemma 3.2. Since $\mathbb{K} = \mathbb{C}$, A^* is triangularisable. Hence, There exists an invertible matrix P such that $A^* = P\mathcal{T}P^{-1}$ with $\mathcal{T} = (t_{ij})$ some lower triangular matrix. Using the change of variables $V = P^{-1}Z$, we deduce that $\mathcal{N}_{\mathcal{Q}_n^* + A^*}(T) = \{0\}$ if and only if $\mathcal{N}_{\mathcal{Q}_n^* + \mathcal{T}^*}(T) = \{0\}$. The system

$$\begin{cases} Z_{tt} = \mathcal{Q}_n^* Z + \mathcal{T}Z, \\ Z(0) = Z_0, \end{cases} \quad (3.8)$$

can be written as

$$\begin{cases} Z_{tt}^1 = \mathcal{Q}_n^* Z^1 + t_{11}Z^1, \\ Z_{tt}^2 = \mathcal{Q}_n^* Z^2 + t_{21}Z^1 + t_{22}Z^2, \\ \vdots \\ Z_{tt}^n = \mathcal{Q}_n^* Z^n + t_{n1}Z^1 + t_{n2}Z^2 + \cdots + t_{nn}Z^n, \\ Z(0) = Z_0. \end{cases} \quad (3.9)$$

Let $Z_0 = \begin{pmatrix} Z_0^1 \\ \vdots \\ Z_0^n \end{pmatrix} \in \mathcal{N}_{\mathcal{Q}_n^* + \mathcal{T}^*}(T)$. By definition $\bar{\mathcal{C}}_n^* Z = \begin{pmatrix} \bar{\mathcal{C}}^* Z^1 \\ \vdots \\ \bar{\mathcal{C}}^* Z^n \end{pmatrix} = 0$ with Z solution of (3.8),

hence $Z_0^1 \in \mathcal{N}_{\mathcal{Q}^* + t_{11}I_{\mathcal{H}}}$. Since $\mathcal{N}_{\mathcal{Q}^*}(T) = 0$ and using Lemma 3.3, we have $Z_0^1 = 0$. Thus the system can be written as

$$\begin{cases} Z_{tt}^2 = \mathcal{Q}_n^* Z^2 + t_{22}Z^2, \\ \vdots \\ Z_{tt}^n = \mathcal{Q}_n^* Z^n + t_{n2}Z^2 + \cdots + t_{nn}Z^n, \\ Z(0) = Z_0. \end{cases}$$

Using the same reasoning as before by replacing Z^1 by Z^2, Z^3, \dots, Z^n successively, we get by induction that $Z_0^2 = \dots = Z_0^n = 0$, thus we have $Z_0 = 0$ and we infer that $\mathcal{N}_{Q_n^* + \mathcal{T}^*}(T) = 0$, which concludes the proof thanks to Lemma 3.1. ■

Algebraic problem:

For $f := \overline{C}_n(U)$, we want find a pair $(X, \tilde{W}) \in C^0([0, T]; \mathcal{D}(Q_n)) \cap C^1([0, T]; \mathcal{D}(Q_n^{\frac{1}{2}})) \cap C^2([0, T]; \mathcal{H}^n) \times C^0([0, T]; \mathcal{U}^m)$ satisfying the following control problem:

$$\begin{cases} \partial_{tt}X = Q_n(X) + AX + BC_m\tilde{W} + f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = \partial_t X(0) = \partial_t X(T) = 0. \end{cases} \quad (3.10)$$

As in the proof of Theorem 1, we will solve instead

$$\begin{cases} \partial_{tt}X = Q_n(X) + AX + BW + f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = \partial_t X(0) = \partial_t X(T) = 0, \end{cases} \quad (3.11)$$

with $W \in \mathcal{C}_m(\mathcal{U}^m)$. We will mimick the proof of Proposition 2.2. In the same way we can write Problem (2.23) under the abstract form

$$\tilde{\mathcal{P}}(X, W) = f, \quad (3.12)$$

where

$$\tilde{\mathcal{P}} : \begin{array}{l} \mathcal{D}(\tilde{\mathcal{P}}) \subset L^2(0, T; \mathcal{H}^{n+m}) \\ (X, W) \end{array} \rightarrow \begin{array}{l} L^2(0, T; \mathcal{H}^n) \\ \partial_{tt}X - Q_nX - AX - BW. \end{array} \quad (3.13)$$

The goal will be then to find a partial differential operator \mathcal{M} satisfying

$$\tilde{\mathcal{P}} \circ \mathcal{M} = I_n. \quad (3.14)$$

PROPOSITION 3.2. *Let $(A, B) \in \mathcal{M}_n(K) \times \mathcal{M}_{n,m}(K)$. If $\text{rank}(B|BA|\dots|BA^{n-1}) = n$, $\tilde{\mathcal{P}}$ has a right inverse denoted by \mathcal{M} . Moreover, the operator \mathcal{M} is an operator of order*

$$\begin{cases} 2n - 4 & \text{for } n \text{ first components} \\ 2n - 2 & \text{for the } m \text{ last components} \end{cases} \quad (3.15)$$

in time and

$$\begin{cases} n - 2 & \text{for } n \text{ first components} \\ n - 1 & \text{for the } m \text{ last components} \end{cases} \quad (3.16)$$

in terms of powers of \mathcal{Q} .

Proof of Proposition 3.2. Changing ∂_t to ∂_{tt} in the proof of Proposition 2.2 we have

$$\tilde{\mathcal{P}} \circ \tilde{\mathcal{M}} = [A, B]$$

with

$$\tilde{\mathcal{M}} : \mathcal{D}(\tilde{\mathcal{M}}) \subset L^2(0, T; \mathcal{H}^{nm}) \rightarrow L^2(0, T; \mathcal{H}^{n+m})$$

$$f = \begin{pmatrix} f_1 \\ \vdots \\ f_m \\ f_{m+1} \\ \vdots \\ f_{2m} \\ \vdots \\ f_{nm} \end{pmatrix} \mapsto \tilde{\mathcal{M}}f,$$

defined by

$$\tilde{\mathcal{M}}f = \begin{pmatrix} \sum_{i=1}^{n-1} \sum_{j=0}^{i-1} (-1)^{j+1} (-\partial_{tt} + Q_n)^j A^{i-1-j} B \begin{pmatrix} f_{jm+1} \\ \vdots \\ f_{(j+1)m} \end{pmatrix} \\ \sum_{i=0}^{n-1} (-1)^{i+1} (-\partial_{tt} + Q_m)^i \begin{pmatrix} f_{im+1} \\ \vdots \\ f_{(i+1)m} \end{pmatrix} \end{pmatrix}. \quad (3.17)$$

Since $\text{rank}(B|AB| \cdots |A^{n-1}B) = n$, there exists $D \in \mathcal{M}_{nm,n}$ such that $[A|B]D = I_n$. Introducing the operator $\mathcal{M} := \tilde{\mathcal{M}}D$ we obtain (3.14). Moreover, in the n first components the higher order term is $(-\partial_{tt} + Q)^{n-2}$ and in the m last components the higher order term is $(-\partial_{tt} + Q)^{n-1}$, which concludes the proof. \blacksquare

Conclusion: combination of the Analytic and Algebraic Problems.

The proof is similar to the one-order case, so that we just give the main arguments here. Let (X, W) be defined by

$$\begin{pmatrix} X \\ W \end{pmatrix} := \mathcal{M}(\bar{C}_n U), \quad (3.18)$$

with $\bar{C}_n U \in H_0^{2n-2}(0, T; \bar{C}_n(\mathcal{U}^n)) \cap \cap_{k=0}^{2n-2} C^k([0, T]; \bar{C}_n \bar{C}_n^*(\mathcal{H}_{n-1-\frac{k}{2}}^n))$ constructed in Proposition 3.1. Using Proposition 3.2 and Assumption 1.2, we obtain that

$$(X, W) \in \left(H_0^2(0, T; (\bar{C}_n(\mathcal{U}^n))) \cap \cap_{k=0}^2 C^k([0, T]; \mathcal{H}_{1-\frac{k}{2}}^n) \right) \times C^0([0, T], \bar{C}_m(\mathcal{U}^m)).$$

Notably, there exists $\tilde{W} \in C^0([0, T], \mathcal{U}^m)$ such that $W = C_m \tilde{W}$. Moreover, using Proposition 3.1 we have $X(0, \cdot) = X(T, \cdot) = 0$ in \mathcal{H}^n and we remark that (X, \tilde{W}) is a solution to the problem

$$\begin{cases} \partial_{tt} X = Q_n(X) + AX + BC_m \tilde{W} + f & \text{in } (0, T) \times \mathcal{H}^n, \\ X(0) = X(T) = \partial_t X(0) = \partial_t X(T) = 0. \end{cases}$$

Thus the pair $(Y, V) := (Z - X, -\tilde{W})$ is a solution to System (Ord2) in $C^0([0, T]; \mathcal{D}(Q_n)) \cap C^1([0, T]; \mathcal{D}(Q_n^{\frac{1}{2}})) \cap C^2([0, T]; \mathcal{H}^n) \times C^0([0, T]; \mathcal{U}^m)$ and satisfies

$$\begin{aligned} Y(0, \cdot) = Y^0 \text{ in } \mathcal{D}(Q^{n-\frac{1}{2}})^n, \quad \partial_t Y(0, \cdot) = Y^1 \text{ in } \mathcal{D}(Q^{n-1})^n \\ Y(T, \cdot) \equiv 0 \text{ in } \mathcal{H}^n, \quad \partial_t Y(T, \cdot) \equiv 0 \text{ in } \mathcal{H}^n. \end{aligned}$$

\blacksquare

3.2 Second part of the proof of Theorem 2

In this section, we assume that the Kalman condition is NOT satisfied and we want to prove that the null controllability of (Ord2) fails. We will use an argument based on the *transmutation method* in order to go back to a parabolic one-order system. The ideas are then essentially the same as in Section 2.2.

Using the transmutation technique (as in [EZ11] for instance) we have the following lemma:

Lemma 3.4. *If the system*

$$\begin{cases} \partial_{tt} Y = Q_n Y + AY + BC_m U & \text{in } (0, T) \times \mathcal{H}^n, \end{cases} \quad (3.19)$$

is null controllable in some time T then at any time $\tilde{T} > 0$, the system

$$\left\{ \begin{array}{l} \partial_t Z = Q_n Z + AZ + BC_m V \\ \text{in } (0, \tilde{T}) \times \mathcal{H}^n, \end{array} \right. \quad (3.20)$$

is null controllable.

We assume that $\text{rank}(B|AB|\dots|A^{n-1}B) \neq n$. Thus, there exists $X = \begin{pmatrix} X_1 \\ \vdots \\ X_n \end{pmatrix} \in \mathcal{H}^n \setminus \{0\}$ such that $B^*X = B^*A^*X = \dots = B^*(A^*)^{n-1}X = 0$. We consider the following adjoint system of (3.20)

$$\left\{ \begin{array}{l} -\partial_t \varphi = Q_n^*(\varphi) + A^*\varphi \\ \varphi(T) = \varphi^T. \end{array} \right. \quad \text{in } (0, T) \times \mathcal{H}^n, \quad (3.21)$$

It is well-known that System (3.20) is null controllable at time T if and only if there exists a positive constant C_1 such that for all solution φ of (3.21)

$$\|\varphi(0)\|_{\mathcal{H}^n} \leq C_1 \int_0^T \|C_m^* B^* \varphi\|_{\mathcal{U}^m} dt, \quad (3.22)$$

for all $\varphi^T \in \mathcal{D}(L_n^*)$. Let φ_X the solution of (3.21) with $\varphi_X(T) = X$. Let $S = (S_t)_{t \in \mathbb{R}}$ be a strongly continuous group on \mathcal{H} , with generator $Q : \mathcal{D}(Q) \subset \mathcal{H} \rightarrow \mathcal{H}$. By the definition of Q_n given in (1.1),

we obtain $C_m^* B^* \varphi_X = C_m^* B^* e^{tA^*} \begin{pmatrix} S^*(T-t)X_1 \\ \vdots \\ S^*(T-t)X_n \end{pmatrix}$. Since $(A, B) \in \mathcal{M}_n(\mathbb{K}) \times \mathcal{M}_{n,m}(\mathbb{K})$, for all

$i \in \{0, \dots, n-1\}$, $B^*(A^*)^i \begin{pmatrix} S^*(T-t)X_1 \\ \vdots \\ S^*(T-t)X_n \end{pmatrix}$ is solution of

$$\left\{ \begin{array}{l} -\partial_t \varphi = Q_m^*(\varphi) \\ \varphi(T) = B^*(A^*)^i X = 0. \end{array} \right. \quad \text{in } (0, T) \times \mathcal{H}^m,$$

Thus

$$B^*(A^*)^i \begin{pmatrix} S^*(T-t)X_1 \\ \vdots \\ S^*(T-t)X_n \end{pmatrix} = 0.$$

Using the Cayley-Hamilton theorem, we obtain that $C_m^* B^* \varphi_X = 0$, from which we deduce that (3.22) is not satisfied. Thus, the System (3.20) is not controllable at time T . Using Lemma 3.4, we deduce that the system

$$\partial_{tt} Y = Q_n Y + AY + BC_m U \quad \text{in } (0, T) \times \mathcal{H}^n,$$

is not controllable, which concludes the proof. \blacksquare

4 Applications

In this section, we will give some examples of applications in the case of systems of Schrödinger and wave equations with internal control. Let Ω be a smooth bounded open subset of \mathbb{R}^N . We will denote by $L^2(\Omega)$ the set of square-integrable functions f defined on Ω with values in the complex plane \mathbb{C} .

We recall the following definition that will be widely used in what follows.

DEFINITION 4.1 (GCC). We say that ω verifies the Geometric Optics Condition (GCC in short) if there exists $T^* > 0$ such that any rays of Geometric Optics in Ω enter the open set ω in time smaller than T^* (see [BLR92]).

4.1 System of Schrödinger equations with internal control

Let us introduce the state space $\mathcal{H} = L^2(\Omega)$ and the control space $\mathcal{U} = L^2(\Omega) = \mathcal{H}$. We consider the linear continuous operator $\mathcal{C} : L^2(\Omega) \rightarrow L^2(\Omega)$ defined by $\mathcal{C}u = \mathbb{1}_\omega u$ with

$$\mathbb{1}_\omega = \begin{cases} 1 & \text{on } \omega, \\ 0 & \text{on } \Omega \setminus \omega. \end{cases}$$

We consider the following Schrödinger equation

$$\begin{cases} \partial_t z = i\Delta z + W(x)z + \mathbb{1}_\omega u, \\ z(0) = z_0, \end{cases} \quad (4.1)$$

where the potential W is in $C^\infty(\bar{\Omega}; \mathbb{K})$. It is well-known that the operator $i\Delta + W(x) : \mathcal{H}^2(\Omega) \cap \mathcal{H}_0^1(\Omega) \subset L^2(\Omega) \rightarrow L^2(\Omega)$ is a generator of a group on $L^2(\Omega)$. Let $n \in \mathbb{N}^*$, we have $\mathcal{D}((i\Delta + W(x))^n) = \mathcal{D}(((i\Delta + W(x))^*)^n) = H_{(0)}^{2n}(\Omega)$ where $H_{(0)}^{2n}(\Omega)$ is defined by

$$H_{(0)}^{2n}(\Omega) := \{v \in H^{2n}(\Omega) \text{ such that } v = \Delta v = \dots = \Delta^{n-1}v = 0 \text{ on } \partial\Omega\}. \quad (4.2)$$

We consider the control system

$$\begin{cases} \partial_t Y = i\Delta Y + W(x)Y + AY + \mathbb{1}_\omega BV & \text{in } (0, T) \times L^2(\Omega)^n, \\ Y(0) = Y^0, \end{cases} \quad (4.3)$$

with $(A, B) \in \mathcal{M}_n(\mathbb{K}) \times \mathcal{M}_{n,m}(\mathbb{K})$.

Our first result concerns the case where ω is strongly included in Ω .

THEOREM 3. *Let $T > 0$ and let us assume that the open set ω of Ω satisfy GCC and $\bar{\omega} \subset \Omega$, then there exists a control V in $C^0((0, T) \times (L^2(\Omega))^m)$ such that the solution of (4.3) with initial condition $Y(0) = Y^0$ in $(H_{(0)}^{2n-2}(\Omega))^n$ satisfies*

$$Y(T) \equiv 0 \quad \text{in } (L^2(\Omega))^n$$

if and only $Y^0 \in [A|B]((L^2(\Omega))^{nm})$.

Proof of Theorem 3. Since $\bar{\omega} \subset \Omega$, one can construct a function $\tilde{\mathbb{1}}_\omega \in C^\infty(\Omega)$ defined by

$$\tilde{\mathbb{1}}_\omega := \begin{cases} 1 & \text{on } \omega_0, \\ 0 & \text{on } \Omega \setminus \omega, \end{cases} \quad (4.4)$$



where ω_0 is some well-chosen open set strongly included in ω still verifying GCC, so that

$$\begin{cases} \partial_t z = (i\Delta + W(x))z + \tilde{\mathbb{1}}_\omega u, \\ z(0) = z_0, \end{cases} \quad (4.5)$$

is exactly controllable thanks to the result of [Leb92] (see Figure 1). Thus, we deduce that Assumption 1.1 is verified with $\bar{\mathcal{C}} : L^2(\Omega) \rightarrow L^2(\Omega)$ defined by $\bar{\mathcal{C}}u = \tilde{\mathbb{1}}_\omega u$.

To apply Theorem 1 we need to verify Assumption 1.2 where $\bar{\mathcal{C}}$ is described above. Let $\varphi \in \mathcal{D}(((i\Delta + W(x))^*)^k) = H_{(0)}^{2k}(\Omega)$, for all $k \in \{0, \dots, n-1\}$, by definition of $\tilde{\mathbb{1}}_\omega \in C_c^\infty(\Omega)$ we obtain $\bar{\mathcal{C}}\bar{\mathcal{C}}^* \varphi = \tilde{\mathbb{1}}_\omega^2 \varphi \in H_{(0)}^{2k}(\Omega)$ and $(i\Delta + W(x))^k (\bar{\mathcal{C}}\bar{\mathcal{C}}^* \mathcal{D}(((i\Delta + W(x))^*)^k)) \in C(L^2(\Omega))$. Thus, we can apply Theorem 1 whence the conclusion of the proof of Theorem 3. \blacksquare

Remark 5. One can obtain the same result as in Theorem 3 with exactly the same proof by replacing the open set Ω with some regular compact connected Riemannian manifold without boundary M , with ω any open subset of M verifying GCC.

Figure 1: An example when $\bar{\omega} \subset \Omega$.Figure 2: An example when $\omega \subset \bar{\Omega}$ is an open set such that $\omega \cap \partial\Omega \neq \emptyset$.

From now on we consider ω an open subset of $\bar{\Omega}$ such that $\omega \cap \partial\Omega \neq \emptyset$ (see Figure 2). In general it is impossible to construct a function $\tilde{\mathbb{1}}_\omega \in C^\infty(\Omega)$ as (4.4) such that the system (4.5) is controllable and $\tilde{\mathbb{1}}_\omega$ maps $H_{(0)}^{2k}(\Omega)$ into itself for all $k \in [3, \infty]$. More precisely, satisfying Assumption 1.2 would require that, for every $\varphi \in H_{(0)}^{2(n-1)}(\Omega)$, for every $k \leq n-2$, $\Delta^k(\tilde{\mathbb{1}}_\omega \varphi) = 0$ on $\partial\Omega$ which is not verified without additional conditions on $\tilde{\mathbb{1}}_\omega$. If $n = 2$ it is clear that $\tilde{\mathbb{1}}_\omega$ maps $L^2(\Omega, \mathbb{C})$ into itself. If $n = 3$, we need to assume moreover that $\nabla \tilde{\mathbb{1}}_\omega \cdot \vec{n} = 0$ with \vec{n} the unit normal vector. If $n > 3$, $\tilde{\mathbb{1}}_\omega$ has to satisfy strong global geometric conditions, for instance $\tilde{\mathbb{1}}_\omega$ can be chosen constant near any connected component of the boundary (for more informations we refer to [DL09, Section 4.2]). However, we cannot affirm anymore that the system (4.5) will still be controllable without loss of regularity or locality on the function $\tilde{\mathbb{1}}_\omega$, so that Assumption 1.2 will not be verified. Hence, we will focus our attention on some particular cases. We will first consider the case where the number of equations is less than or equal to three without additional conditions on Ω and then we will consider the case where Ω is the product of N open intervals in \mathbb{R}^N and the case where Ω is a unit disk.

THEOREM 4. *Let $T > 0$. Let ω be an open subset of $\bar{\Omega}$ such that $\omega \cap \partial\Omega \neq \emptyset$ and ω satisfies GCC. Let $n \leq 3$, then there exists a control V in $C^0([0, T]; (L^2(\Omega))^m)$ such that the solution of (4.3) corresponding to the initial condition $Y(0) = Y^0$ in $(H_{(0)}^{2n-2}(\Omega))^n$ satisfies*

$$Y(T) \equiv 0 \quad \text{in } (L^2(\Omega))^n,$$

if and only $Y^0 \in [A|B]((L^2(\Omega))^{nm})$.

Proof of Theorem 4. We can keep constructing a function $\tilde{\mathbb{1}}_\omega \in C^\infty(\Omega)$ defined by

$$\tilde{\mathbb{1}}_\omega := \begin{cases} 1 & \text{on } \omega_0, \\ 0 & \text{on } \Omega \setminus \omega, \end{cases} \quad (4.6)$$

where ω_0 is some well-chosen open set included in ω still verifying GCC such that $\nabla \tilde{\mathbb{1}}_\omega \cdot \vec{n} = 0$ and the system

$$\begin{cases} \partial_t z = i\Delta z + W(x)z + \tilde{\mathbb{1}}_\omega u, \\ z(0) = z_0, \end{cases} \quad (4.7)$$

is exactly controllable (see Figure 2). Moreover, using [DL09, Section 4.2] and $\nabla \tilde{\mathbb{1}}_\omega \cdot \vec{n} = 0$, we infer that $\mathbb{1}_\omega^2$ maps $H_{(0)}^{2k}(\Omega)$ into itself for $k \leq 2$ and by definition of $\tilde{\mathbb{1}}_\omega$, we have $(i\Delta + W(x))^k (\overline{\mathcal{C}}^* \mathcal{D}((i\Delta + W(x))^*)^k)) \in C(L^2(\Omega))$ for $k \leq 2$. Thus, Assumption 1.2 is verified and we can conclude as in the proof of Theorem 3. \blacksquare

It is well-known that GCC is only a sufficient condition to ensure the exact controllability of the Schrödinger equation, but is not always necessary in some particular geometries. Let us give two examples. If Ω is the product of N open intervals, we do not need to impose restrictions on ω and if Ω is a unit disk, ω has to touch the boundary of Ω .

THEOREM 5. *Let $T > 0$ and let us assume that the domain $\Omega \subset \mathbb{R}^N$ is the product of N open intervals, then there exists a control V in $C^0((0, T) \times (L^2(\Omega))^m)$ such that the solution of (4.3) corresponding to the initial condition $Y(0) = Y^0$ in $(H_{(0)}^{2n-2}(\Omega))^n$ satisfies*

$$Y(T) \equiv 0 \quad \text{in} \quad (L^2(\Omega))^n,$$

if and only $Y^0 \in [A|B]((L^2(\Omega))^{nm})$.

Proof of Theorem 5. From [KL05, Proposition 8.8], one can easily deduce that the system

$$\begin{cases} \partial_t z = i\Delta z + W(x)z + \mathbb{1}_{\tilde{\omega}} u, \\ z(0) = z_0, \end{cases}$$

is exactly controllable for any nonempty open $\tilde{\omega}$ subset of Ω . Consequently, without loss of generality we can assume that $\tilde{\omega} \subset \Omega$. Thus, we just have to copy the proof of Theorem 3 and we deduce the expected result. ■

THEOREM 6. *Let $T > 0$ and let us assume that the domain $\Omega \subset \mathbb{R}^2$ is the unit disk and let ω be an open subset of $\bar{\Omega}$ such that $\omega \cap \partial\Omega \neq \emptyset$. Let $n \leq 3$, then there exists a control V in $C^0([0, T]; (L^2(\Omega))^m)$ such that the solution of (4.3) corresponding to the initial condition $Y(0) = Y^0$ in $(H_{(0)}^{2n-2}(\Omega))^n$ satisfies*

$$Y(T) \equiv 0 \quad \text{in} \quad (L^2(\Omega))^n,$$

if and only $Y^0 \in [A|B]((L^2(\Omega))^{nm})$.

Proof of Theorem 6. Since the domain $\Omega \subset \mathbb{R}^2$ is the unit disk, from [ALM15, Theorem 1.2], we deduce that the equation

$$\begin{cases} \partial_t z = i\Delta z + W(x)z + \mathbb{1}_{\tilde{\omega}} u, \\ z(0) = z_0, \end{cases}$$

is exactly controllable for any open $\tilde{\omega}$ subset of $\bar{\Omega}$ such that $\tilde{\omega} \cap \partial\Omega \neq \emptyset$. Thus, we just mimick the proof of Theorem 4 and we have directly the expected result. ■

Remark 6. The same results can be obtained by replacing the Schrödinger equation by the plate equation (see for example [Leb92, Section 5]).

4.2 System of wave equations with internal control

We consider the state space and control space as in the previous section, i.e. $\mathcal{H} = \mathcal{U} = L^2(\Omega)$. We introduce the operator $\mathcal{C} : L^2(\Omega) \rightarrow L^2(\Omega)$ such that $\mathcal{C}u = \mathbb{1}_{\omega}u$. We consider the following wave equation

$$\begin{cases} \partial_{tt} z = \Delta z + W(x)z + \mathbb{1}_{\omega} u, \\ z(0) = z_0, \\ \partial_t z(0) = z_1, \end{cases} \quad (4.8)$$

where the potential W is in $C^\infty(\bar{\Omega}; \mathbb{K})$. It is well-known that the operator $\Delta + W(x) : \mathcal{H}^2(\Omega) \cap \mathcal{H}_0^1(\Omega) \subset L^2(\Omega) \rightarrow L^2(\Omega)$ is self-adjoint with compact resolvent, but it is not a negative operator in general. This is not a problem here because we know that for $\mu > 0$ large enough the operator $\Delta + W(x) - \mu$ becomes negative, hence we can adapt the results of Theorem 2 in this case. Moreover, we know that if ω verifies GCC, then (4.8) is controllable at any time $T > T^*$, where T^* is the minimal time

needed to ensure that all the rays of Geometric Optics in Ω enter the open set ω . Let $n \in \mathbb{N}^*$, we have $\mathcal{D}((\Delta + W(x))^n) = H_{(0)}^{2n}(\Omega)$ where $H_{(0)}^{2n}(\Omega)$ is defined in (4.2). We consider the control system

$$\begin{cases} \partial_{tt}Y = \Delta Y + W(x)Y + AY + \mathbb{1}_\omega BV & \text{in } (0, T) \times L^2(\Omega)^n, \\ Y(0) = Y^0, \\ \partial_t Y(0) = Y^1, \end{cases} \quad (4.9)$$

with $(A, B) \in \mathcal{M}_n(K) \times \mathcal{M}_{n,m}(K)$. Mimicking the proof of Theorem 3 and Theorem 4 we immediately obtain the following results:

THEOREM 7. *Let us assume that ω satisfies GCC and $\bar{\omega} \subset \Omega$. Let $(Y^0, Y^1) \in H_{(0)}^{2n-1}(\Omega) \times H_{(0)}^{2n-2}(\Omega)$. Then, for every $T > T^*$, the control system (4.9) is exactly controllable at time T if and only if $\text{rank}([B|A]) = n$.*

Remark 7. As in the case of the Schrödinger equation, one can obtain the same result as in Theorem 7 with exactly the same proof by replacing the open set Ω with some regular compact connected Riemannian manifold without boundary M , with ω any open subset of M verifying GCC.

THEOREM 8. *Let ω be an open subset of $\bar{\Omega}$ such that $\omega \cap \partial\Omega \neq \emptyset$ and ω satisfies GCC. Let $n \leq 3$. Let $(Y^0, Y^1) \in H_{(0)}^{2n-1}(\Omega) \times H_{(0)}^{2n-2}(\Omega)$, then, for every $T > T^*$, the control system (4.9) is exactly controllable at time T if and only if $\text{rank}([B|A]) = n$.*

Acknowledgements

The authors would like to thank Camille Laurent for interesting discussions concerning Section 4 of this work.

References

- [AB13] F. Alabau-Boussouira. A hierarchic multi-level energy method for the control of bidiagonal and mixed n -coupled cascade systems of PDE's by a reduced number of controls. *Adv. Differential Equations*, 18(11-12):1005–1072, 2013.
- [ABCO15] F. Alabau-Boussouira, J.-M. Coron, and G. Olive. Internal controllability of first order quasilinear hyperbolic systems with a reduced number of controls. *Submitted*, 2015.
- [ABL13] F. Alabau-Boussouira and M. Léautaud. Indirect controllability of locally coupled wave-type systems and applications. *J. Math. Pures Appl. (9)*, 99(5):544–576, 2013.
- [AKBD06] F. Ammar-Khodja, A? Benabdallah, and C. Dupaix. Null-controllability of some reaction-diffusion systems with one control force. *J. Math. Anal. Appl.*, 320(2):928–943, 2006.
- [AKBDGB09a] F. Ammar-Khodja, A. Benabdallah, C. Dupaix, and M. González-Burgos. A generalization of the Kalman rank condition for time-dependent coupled linear parabolic systems. *Differ. Equ. Appl.*, 1(3):427–457, 2009.
- [AKBDGB09b] F. Ammar-Khodja, A. Benabdallah, C. Dupaix, and M. González-Burgos. A Kalman rank condition for the localized distributed controllability of a class of linear parabolic systems. *J. Evol. Equ.*, 9(2):267–291, 2009.
- [AKBGBdT11a] F. Ammar-Khodja, A. Benabdallah, M. González-Burgos, and L. de Teresa. The Kalman condition for the boundary controllability of coupled parabolic systems. Bounds on biorthogonal families to complex matrix exponentials. *J. Math. Pures Appl. (9)*, 96(6):555–590, 2011.
- [AKBGBdT11b] F. Ammar-Khodja, A. Benabdallah, M. González-Burgos, and L. de Teresa. Recent results on the controllability of linear coupled parabolic problems: a survey. *Math. Control Relat. Fields*, 1(3):267–306, 2011.
- [AKBGBdT14] F. Ammar Khodja, A. Benabdallah, M. González-Burgos, and L. de Teresa. Minimal time for the null controllability of parabolic systems: the effect of the condensation index of complex sequences. *J. Funct. Anal.*, 267(7):2077–2151, 2014.
- [AKBGBdT15] F. Ammar Khodja, A. Benabdallah, M. González-Burgos, and L. de Teresa. New phenomena for the null controllability of parabolic systems: Minimal time and geometrical dependence. *Submitted*, 2015.

- [ALM15] N. Anantharaman, M. Léautaud, and F. Macià. Wigner measures and observability for the schrödinger equation on the disk. *submitted*, 2015.
- [BBGBO14] A. Benabdallah, F. Boyer, M. González-Burgos, and G. Olive. Sharp estimates of the one-dimensional boundary control cost for parabolic systems and application to the N -dimensional boundary null controllability in cylindrical domains. *SIAM J. Control Optim.*, 52(5):2970–3001, 2014.
- [BLR92] C. Bardos, G. Lebeau, and J. Rauch. Sharp sufficient conditions for the observation, control, and stabilization of waves from the boundary. *SIAM J. Control Optim.*, 30(5):1024–1065, 1992.
- [BO14] F. Boyer and G. Olive. Approximate controllability conditions for some linear 1D parabolic systems with space-dependent coefficients. *Math. Control Relat. Fields*, 4(3):263–287, 2014.
- [CGR10] J.-M. Coron, S. Guerrero, and L. Rosier. Null controllability of a parabolic system with a cubic coupling term. *SIAM Journal on Control and Optimization*, 48(8):5629–5653, 2010.
- [CL14] J.-M. Coron and P. Lissy. Local null controllability of the three-dimensional Navier-Stokes system with a distributed control having two vanishing components. *Invent. Math.*, 198(3):833–880, 2014.
- [Cor07] J.-M. Coron. *Control and nonlinearity*, volume 136 of *Mathematical Surveys and Monographs*. American Mathematical Society, Providence, RI, 2007.
- [CT10] N. Cîndea and M. Tucsnak. Internal exact observability of a perturbed Euler-Bernoulli equation. *Ann. Acad. Rom. Sci. Ser. Math. Appl.*, 2(2):205–221, 2010.
- [DL09] B. Dehman and G. Lebeau. Analysis of the HUM control operator and exact controllability for semilinear waves in uniform time. *SIAM J. Control Optim.*, 48(2):521–550, 2009.
- [DL16] M. Duprez and P. Lissy. Indirect controllability of some linear parabolic systems of m equations with $m - 1$ controls involving coupling terms of zero or first order. *Journal de Mathématiques Pures et Appliquées*, To appear, 2016.
- [DLRL14] B. Dehman, J. Le Rousseau, and M. Léautaud. Controllability of two coupled wave equations on a compact manifold. *Arch. Ration. Mech. Anal.*, 211(1):113–187, 2014.
- [EZ10] Sylvain E. and Enrique Z. A systematic method for building smooth controls for smooth data. *Discrete and Continuous Dynamical Systems - Series B*, 14(4):1375–1401, 2010.
- [EZ11] S. Ervedoza and E. Zuazua. Sharp observability estimates for heat equations. *Arch. Ration. Mech. Anal.*, 202(3):975–1017, 2011.
- [FAKD16] F. Chouly F. Ammar-Khodja and M. Duprez. Partial null controllability of parabolic linear systems. *Math. Control Relat. Fields*, To appear, 2016.
- [GBdT10] M. González-Burgos and L. de Teresa. Controllability results for cascade systems of m coupled parabolic PDEs by one control force. *Port. Math.*, 67(1):91–113, 2010.
- [GBPG06] M. González-Burgos and R. Pérez-García. Controllability results for some nonlinear coupled parabolic systems by one control force. *Asymptot. Anal.*, 46(2):123–162, 2006.
- [Gro86] M. Gromov. *Partial differential relations*, volume 9 of *Ergebnisse der Mathematik und ihrer Grenzgebiete (3) [Results in Mathematics and Related Areas (3)]*. Springer-Verlag, Berlin, 1986.
- [KL05] V. Komornik and P. Loreti. *Fourier series in control theory*. Springer Monographs in Mathematics. Springer-Verlag, New York, 2005.
- [Leb92] G. Lebeau. Contrôle de l'équation de Schrödinger. *J. Math. Pures Appl. (9)*, 71(3):267–291, 1992.
- [LGMdT15] M. Lopez-Garcia, A. Mercado, and L. de Teresa. Null controllability of a cascade system of Schrödinger equations. *Submitted*, 2015.
- [Lio88] J.-L. Lions. *Contrôlabilité exacte, perturbations et stabilisation de systèmes distribués. Tome 1*, volume 8 of *Recherches en Mathématiques Appliquées [Research in Applied Mathematics]*. Masson, Paris, 1988. Contrôlabilité exacte. [Exact controllability], With appendices by E. Zuazua, C. Bardos, G. Lebeau and J. Rauch.
- [Lis13] P. Lissy. *Sur la contrôlabilité et son coût pour quelques équations aux dérivées partielles*. PhD thesis, Université Pierre et Marie Curie, 2013.
- [Mil06] L. Miller. The control transmutation method and the cost of fast controls. *SIAM J. Control Optim.*, 45(2):762–772 (electronic), 2006.
- [Phu01] K. Phung. Observability and control of Schrödinger equations. *SIAM J. Control Optim.*, 40(1):211–230 (electronic), 2001.
- [RdT11] L. Rosier and L. de Teresa. Exact controllability of a cascade system of conservative equations. *C. R. Math. Acad. Sci. Paris*, 349(5-6):291–296, 2011.
- [SM65] L. M. Silverman and H. E. Meadows. Controllability and time-variable unilateral networks. *IEEE Trans. Circuit Theory*, CT-12:308–314, 1965.