

Monte Carlo modeling of phonon transport in nanostructures

David LACROIX



Outline



- Heat transport in nano & microstructures, basics, models and challenges
- Using Monte Carlo technique to solve the Boltzmann transport equation for phonons
- Application of MC-BTE tool to appraise thermal properties in nanostructures
- Improvement of MC-BTE by coupling with ab-initio calculations
- Summary and perspectives

Heat transport in nano & microstructures, basics, models and challenges


Tailoring heat transport in nano & microstructures

Challenges

- **Control of overheating**
 - minimize failure,
 - hotspots occurrence
 - improve performance of materials
 - etc
- **Tailoring heat transport properties**
 - thermoelectric material improvement
 - thermal cloaking, thermal rectification
 - etc
- **Thermal management applications**
 - electronic, optical, optoelectronic and thermoelectric devices,
 - thermal diode
 - etc




Nature 489, 414–418 (2012)




<http://telab.vuse.vanderbilt.edu/research.html>

Heat transport modeling, a multiscale issue




<http://www.dierk-raabe.com/>



Heat transport in nano & microstructures

Basics

- Heat transfer at the nanoscale differs from what occur in bulk material:
 - Fourier's law needs to be considered with caution
 - Heat transport equation is no longer valid
 - Thermal properties of materials depend on **length scales** and temperature
- Heat transport varies between diffusive and ballistic regimes



$$\Phi = -k \nabla T$$


$$\rho C \frac{dT}{dt} = \nabla \cdot (k \nabla T) + q_{vol}$$

$$k_{nano} ???$$

$$dT/dt ???$$



Approach based on heat carriers transport: "phonons"





$$T_{ballistic} = \left(\frac{T_h^4 + T_c^4}{2} \right)^{1/4}$$


Phonon and heat propagation

In semiconductors “phonons” are quasiparticles that characterize the vibrational motions of a lattice. They propagate heat and can be either considered as wave or particles.

Vibration ↔ Dispersion relations




$\Lambda \equiv \ell$: phonon mean free path



Kinetic model for thermal conductivity:

$$k = \frac{1}{3} \rho C v_g \Lambda \quad ; \quad \Lambda = \frac{v_g}{\tau}$$

Scattering mechanisms



Boltzmann transport equation for phonons

Phonons obey to the **Boltzmann Transport Equation (BTE)**. When considered as particles their motion and interactions (scattering) in nanostructures depends on: temperature, dispersion properties and scattering lifetimes of the considered material.

The BTE is solved in the frame of the relaxation time approximation by a Monte Carlo method.

BTE

$$\frac{\partial f}{\partial t} + \nabla_{\mathbf{k}} \omega \cdot \nabla_{\mathbf{r}} f + \mathbf{F} \cdot \nabla_{\mathbf{p}} f = \left. \frac{\partial f}{\partial t} \right|_{scat}$$

f is the distribution function
↔ number of phonons

$$N(t, r) = \frac{1}{V} \sum_{\mathbf{K}} f(t, r, \mathbf{K})$$

Relaxation time approximation

$$\left. \frac{\partial f}{\partial t} \right|_{scat} = \frac{f_{\omega} - f_{\omega}^0}{\tau(\omega)}$$

Problem: $\tau(\omega)$ appraisal is not explicit. Analytic expressions can be found for some bulk materials (Si, Ge, GaN, C, etc) but littérature is poor for complex compounds




Solution? Ab-initio calculation of τ

Using Monte Carlo technique to solve the Boltzmann transport equation for phonons

Monte Carlo solution of the BTE


The MC solution of the BTE for phonon lies on several steps:

- Design of the nanostructure geometry and discretization
- Prescription of boundary conditions
- Initialization of the phonon state in the discretized cells
- Motion of phonon during a time step
- Scattering of phonon to restore thermodynamic equilibrium
- Calculation of local temperature and heat flux
- Derivation of thermal conductivity
- Assessment of other quantities (phonon spectrum vs mfp, phonon phase function, etc)




Monte Carlo solution of the BTE - initialization

Nanostructures



Structures are discretized taking into account periodicities
 Temperature are prescribed in first and last cells (blackbodies)




Energy within a cell

$$E = \int_{\omega} \sum_p \frac{1}{\exp(\hbar\omega/k_B T) - 1} D_p(\omega) g_p \hbar\omega d\omega$$

Cumulative distribution function

$$F(X) = \frac{\int_0^X \sum_p f^0(\omega, T) D_p(\omega) g_p \hbar\omega d\omega}{\int_0^{\omega^{\max}} \sum_p f^0(\omega, T) D_p(\omega) g_p \hbar\omega d\omega}$$




1. Sampling of a phonon population (energy bundles) at a given temperature T , according to dispersion relations (isotropic). Random location of phonons.

Monte Carlo solution of the BTE – transport and scattering

2. Follow phonon displacement according to their group velocity and boundary conditions

$$\frac{\partial f}{\partial t} + \nabla_{\mathbf{k}} \omega \cdot \nabla_{\mathbf{r}} f + \mathbf{F} \cdot \nabla_{\mathbf{p}} f = \left. \frac{\partial f}{\partial t} \right|_{scat}$$


$$\mathcal{C} \quad r(t + \delta t) = r(t) + v_g(\omega, p) \delta t$$



3. Proceed to phonon scattering with respect to the Matthiessen rule, calculation of E and T

$$P_{scat} = 1 - \exp\left[\frac{-\delta t}{\tau(\omega, p, T)}\right]$$

$$\tau(\omega, p, T)^{-1} = \sum_{process} \tau_{process}(\omega, p, T)^{-1}$$



Lifetimes of scattering processes (Normal, Umklapp, Impurity) are derived from M.G. Holland for Si and Ge

Monte Carlo solution of the BTE – post processing

4. Extract T and Φ according to the local phonon distribution in the nanostructure



$$\Phi_z = \sum_{i=1}^N \frac{\hbar \omega_i V_{gz}}{V}$$

Silicon nanofilm

Lz = 2 μ m

$\delta t = 1$ ps





Nz = 20 cells

40000 time steps

8 cores / 6 hours

Cross plane TC



k = 128.7 W/m K





Application of MC-BTE tool to appraise thermal properties in nanostructures

Monte Carlo simulations – Nanofilms I


Diffuse regime



Ballistic regime



Monte Carlo simulations – Nanofilms II




Rx, Ry: reflections

D: diffuse

S: Specular



Wire: Rx = D, Ry = D




Film In-plane: Rx = D, Ry = S




Bulk /film Cross-plane: Rx = S, Ry = S

Thermal conductivity in Si vs T; Lz = 2μm




In-plane Thermal conductivity in Si film vs Lx




Monte Carlo simulations – Nanowires I


Smooth nanowires



Si nanowire TC vs T




Si nanowire TC vs cross-section




Simulations match experiments, except for very thin diameters (bulk limit)

Monte Carlo simulations – Nanowires II

Corrugated and modulated nanowires




Si Nanowires
with shape
modulation



C. Blanc, APL 103, 043109


E. Buitrago, Microelectronic Engineering 97, 345–348

MC design of modulated nanowires





Monte Carlo simulations – Nanowires III



Smooth and step constrictions



$$d(z) = d_{\max} \left[1 - \frac{(1 - R_d)}{1 + C(z - z_0)^2} \right] ; \quad R_d = \frac{d_{\min}}{d_{\max}}$$



Spatial discretization impact




$$k_{\text{smooth}} < k_{\text{step}}$$



importance of Λ_b

Monte Carlo simulations – Nanowires IV

Long constriction 'canal shape'




TC in canal NW smaller than in single NW with the minimal diameter

No significant effect of 'canal' length,






Constriction resistance

V. Jean, IJHMT 86, 648-645




Monte Carlo simulations – Nanowires V

Modulated nanowire







4 periods nanowire



Increase of period number leads to a decrease of the thermal conductivity



Monte Carlo simulations – Porous membranes

Porous membranes/membranes with inclusions




Monodisperse inclusions

Polydisperse inclusions




Monte Carlo simulations – PnC membranes I

Phononic (PnC) Si membranes





'Staggered'

'Aligned'



R. Anufriev, PRB 93, 045411




Good agreement between experiments & simulations

The TC is always lower when pores are in staggered configuration for a same S/V ratio

Monte Carlo simulations – PnC membranes II

Accumulated TC in PnC Si membranes


Extract from MC the contribution discrete phonon frequencies to the TC



Bulk : 50% of TC due to phonon with $mfp < 500nm$
PnC : 65% of TC due to phonon with $mfp < 500nm$

Ballistic transport in PnC membranes

Distribution of the exit angle of phonons just before the cold thermostat for $a=160nm$ and $d=126nm$



Some phonons experiment ballistic transport in aligned PnC


Improvement of MC-BTE by coupling with ab-initio calculations

Monte Carlo simulations, ab-initio coupling I

The MC solution of the BTE for phonon has a main weakness, the necessity to have an explicit formulation of phonon lifetimes of the studied material.

- **Idea:** replace analytic lifetime expressions of basic material (Si, Ge, etc) by the one provided by DFT calculation
- Use the real dispersions properties of the material (frequency, polarization branches including optical mode, group velocities)


Monte Carlo simulations, ab-initio coupling II



DFT calculations: Dispersion properties
& phonon lifetimes



Discretization of the
first Brillouin zone on
a 31x31x31 K grid




Monte Carlo simulations, ab-initio coupling III

The MC-ab initio solution of the BTE for phonon lies on the same principle as above: discretization, BC, initialization, phonon drift and phonon scattering. Changes are related to:

- Use of a K space discretization instead of frequency one
- Calculation of scattering term of the BTE

For each K point, a phonon is sampled in a cell and carries a given number of modes N.



$$N_{aScatt} = N_{aD} + \frac{\delta t}{\tau(K_1, K_2, K_3, p)} (N_{BE}(T^*) - N_{aD})$$

Monte Carlo simulations, ab-initio coupling IV

Calculation of T and Φ according to the local phonon distribution in the nanostructure



$$\Phi_z = \sum_{i=1}^N \frac{\hbar \omega_i V_{gz}}{V}$$

Silicon nanofilm

$L_z = 2\mu\text{m}$

$\delta t = 1\text{ps}$





$N_z = 20$ cells

10000 time steps

1 core / 12 hours

Cross plane TC

$k = 153.2 \text{ W/m K}$







Holland relaxation time : $k = 128.7 \text{ W/m K} !!!$ Overestimation of the TC with MC-ab-initio !?!



Calculation without $\tau_i(\omega)$: $k_{\text{MC-NU}} = 155.2 \text{ W/m K}$


Monte Carlo simulations, ab-initio coupling IV

Monte Carlo post-processing, modes contribution to Thermal Conductivity




Monte Carlo simulations, ab-initio coupling V

Thermal conductivity in Si vs T; $L_z = 2\mu\text{m}$



Cross-plane Thermal conductivity in Si film vs L_z



- ✓ Temperature and thickness well recovered
- ✓ Impurity scattering explain the light overestimation; need to be implemented in MC-ab-initio

Summary and perspectives

Summary

- MC solution of BTE offers a good flexibility to model heat transport in different kind of nanostructures close to the real ones
- Computational cost is reasonable (max 1 week)
- Possibility to include real material dispersion properties
- Gives transient information on heat transport
- Gives spectral information on phonon contribution to thermal properties
- Actually coherent effect are not considered

Colleagues et collaborations



L. Chaput, A. Pr., LEMTA



H. Chaynes, IE, LEMTA



M. Isaev, Post-doc, LEMTA




V. Jean, PhD, LEMTA



Y. Han, Post-doc LEMTA



D. Lacroix, Pr, LEMTA




S. Li, Post-doc, LEMTA




G. Pernot, A. Pr, LEMTA




N. Stein, A. Pr., IJL




K. Termentzidis, CR 1, LEMTA



M. Verdier, PhD, LEMTA



X. Zianni, invited Pr, DEMOKRITOS



Master students!




Aristotle University of Thessaloniki



DEMOKRITOS NATIONAL CENTER FOR SCIENTIFIC RESEARCH

Monte Carlo simulations, ab-initio coupling VI

Calculation of T and Φ using Cold-Hot-Cold boundaries



Silicon nanofilm

$L_z = 2 \times 2 \mu\text{m}$

$\delta t = 1 \text{ ps}$

$N_z = 25$ cells

10000 time steps

1 core / 18 hours

Cross plane TC

$k = 146.3 \text{ W/m K}$

