



Towards real time computation of 3D magnetic field in parametrized Polyhelix magnets using a reduced basis Biot-Savart model

Cécile Daversin, Romain Hild, Christophe Prud'Homme, Christophe Trophime

► To cite this version:

Cécile Daversin, Romain Hild, Christophe Prud'Homme, Christophe Trophime. Towards real time computation of 3D magnetic field in parametrized Polyhelix magnets using a reduced basis Biot-Savart model. MoRePas, Apr 2018, Nantes, France. hal-01801696

HAL Id: hal-01801696

<https://hal.science/hal-01801696>

Submitted on 28 May 2018

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

TOWARDS REAL TIME COMPUTATION OF 3D MAGNETIC FIELD IN PARAMETRIZED POLYHELIX MAGNETS USING A REDUCED BASIS BIOT-SAVART MODEL

C. Daversin³, R. Hild¹, C. Prud'homme¹, C. Trophime²

¹ IRMA (Université de Strasbourg, CNRS), ² LNCMI (CNRS, UGA, UPS, Insa, EMFL), France, ³ formerly at IRMA, currently at Simula

Laboratoire National des Champs Magnétiques Intenses (LNCMI)

Magnetic Field (T:Tesla)


Human brain: 10^{-12} T
Earth: 5.10^{-5} T
MRI: 1T
Superconductor: 24T

Static Magnetic Field

Grenoble: 37T, soon 43T

Pulsed Magnetic Field

Toulouse: 99T



Objectives

- Design a Reduced Basis method for Biot & Savart law, allowing to change experimental (conductivity, heat transfer coefficient,...) or geometric (helices shape, radius,...) parameters.
- Compare Finite Element and Reduced Basis (RB) results, and illustrate the use of the method with different applications.

Non-linear Electro-Thermo-Magnetic

Electric

$$\begin{cases} -\nabla \cdot \sigma(T) \nabla V = 0 & \text{in } \Omega_C \\ -\sigma(T) V \cdot \mathbf{n} = 0 & \text{on } \Gamma_N \\ V = V_D & \text{on } \Gamma_I \\ V = 0 & \text{on } \Gamma_O \end{cases}$$

Thermic

$$\begin{cases} -\nabla \cdot \kappa(T) \nabla T = \sigma(T) \nabla V \cdot \nabla V & \text{in } \Omega_T \\ -\kappa(T) T \cdot \mathbf{n} = h(T - T_w) & \text{on } \Gamma_C \\ -\kappa(T) T \cdot \mathbf{n} = 0 & \text{on } \Gamma_E \end{cases}$$

Magnetostatic

Biot & Savart law:
 $\mathbf{B}(\mathbf{x}) = \frac{\mu_0}{4\pi} \int_{\Omega_C} \frac{-\sigma(T) \nabla V(\mathbf{r}) \times (\mathbf{x} - \mathbf{r})}{|\mathbf{x} - \mathbf{r}|^3} d\mathbf{r}$
 $\forall \mathbf{x} \in \Omega_M$

V electric potential

T temperature

$\sigma(T)/\kappa(T)$ electric/thermal conductivity

h exchange coefficient

T_w water's temperature

Reduced Basis Method


Reduced Basis Method (RBM)

- Use a more appropriate basis, made of solutions
- Use **affine decomposition** to have an efficient computation

$$a(u, v, \boldsymbol{\mu}) = \sum_{q=0}^{Q^a} \Theta_q^a(\boldsymbol{\mu}) a_q(u, v)$$

Offline phase:

- Using POD or greedy algorithm, find the best parameters to approach the problem
- Build the basis, and pre-compute matrices and vectors
- **Online phase:** solve a reduced problem for a parameter, real-time



Empirical Interpolation Method (EIM)

In case of non-affine or non-linear problem, need to solve a large number of problem

Simultaneous EIM RBM (SER)

Reduce the number of solution to compute during the offline phase

Biot & Savart Reduced Basis (BSRB)

Reduced Basis for V and EIM for $\sigma(T)$:

$$V(\mathbf{r}; \boldsymbol{\mu}) = \sum_{n=1}^N V_n(\boldsymbol{\mu}) \xi_n^V(\mathbf{r}) \quad \sigma(\mathbf{r}; \boldsymbol{\mu}, T) = \sum_{m=1}^{M_\sigma} \beta_m^\sigma(\boldsymbol{\mu}, T) q_m^\sigma(\mathbf{r})$$

Reduced Basis for \mathbf{B} :

$$\mathbf{B}(\mathbf{x}; \boldsymbol{\mu}) = \sum_{n=1}^N \sum_{m=1}^{M_\sigma} V_n(\boldsymbol{\mu}) \beta_m^\sigma(\boldsymbol{\mu}, T) \frac{\mu_0}{4\pi} \int_{\Omega_C} \frac{-q_m^\sigma(\mathbf{r}) \nabla \xi_n^V(\mathbf{r}) \times (\mathbf{x} - \mathbf{r})}{|\mathbf{x} - \mathbf{r}|^3} d\mathbf{r}$$


Geometric parameters:

Ω_C and the distance $|\mathbf{x} - \mathbf{r}|$ depends on the parameters.

⇒ Need to use the discrete version of EIM to interpolate the magnetic field:


$$\mathbf{B}(\mathbf{x}; \boldsymbol{\mu}) \approx \sum_{m=1}^{M_B} \beta_m^B(\boldsymbol{\mu}) \mathbf{q}_m^B(\mathbf{x})$$

Comparison between Finite Element and Reduced Basis




Parameters: $\sigma_0, k_0, L, \alpha, h, T_w, V_D$			
Computing time:			
dofs	FE	RB	
V	1 350 000	45s	0.05s
B	3000	110s	0.0005s

Optimization of the homogeneity by controlling the shape of the helices



Shape of the cuts of the helices
before/after



initial and optimized homogeneity
in a ball at the center of the helices

Ingredients:

- ϕ : geometric transformation on the helices (Ω_C)

$$\phi = \begin{pmatrix} x \cos(\alpha) + y \sin(\alpha) \\ -x \sin(\alpha) + y \cos(\alpha) \\ z \end{pmatrix}$$

- α : Bezier curve which control points p_k are the parameters of the optimization.

$$\alpha(t) = \sum_{k=0}^n C_n^k t^k (1-t)^{n-k} p_k \quad (1)$$

	init	optimal	gain
$\max(B_z)$	0.41337	0.4051	-2%
$\min(B_z)$	0.41076	0.4034	-1.79%
$\frac{\max(B_z)}{\min(B_z)} - 1$	5381.9	3544.9	34%

Conclusions

- A Finite Element, full 3D, parallel, multi-physics model, coupling thermoelectric, magneto static (Maxwell and Biot & Savart) and mechanic.
- A Reduced Basis method for Biot & Savart allowing a real time computation for the magnetic field in the region of interest.
- Use of the Discrete Empirical Interpolation Method (DEIM) to deal with geometric parameters, giving the opportunity to do geometrical optimization.
- Use of the Simultaneous EIM and RB (SER) to deal with non linearities and to accelerate the DEIM offline phase.
- In the future, accelerate the Biot & Savart reduced basis construction.
- Integrate the RB models into a tool for magnet designers without numerical simulation knowledge to visualize the 3D magnetic field maps in real time while changing parameters.