

**THALES**



# Thermoacoustic sound generation model in porous nanomaterials

**Guiraud Pierre**

**Giordano Stefano** (IEMN)

**Bou-Matar Olivier** (IEMN)

**Lardat Raphael** (Thales)

**Pernod Philippe** (IEMN)

**2019 INTERNATIONAL CONGRESS ON ULTRASONICS**

BRUGES, BELGIUM, 3-6 SEPT 2019

[www.thalesgroup.com](http://www.thalesgroup.com)

OPEN



# Table of contents

## ➤ I. Introduction

- Context
- Thermoacoustic Principle
  - Sound Generation process
  - Thermophones examples

## ➤ II. Theory

- One Temperature Model (1T)
  - Conservation Equations
  - Solutions and Boundary Conditions
  - Performances & Limitations
- Two Temperature Model (2T)
  - Motivation
  - Conservation Equations
  - Solutions
  - Boundary conditions
- Acoustic Diffraction


## ➤ III. Analysis

- Near Field Sound Generation
- Frequency and Power Spectrum
  - Thin Thermophone
  - Thick Thermophone


# I. Introduction: Context

## Conventional Sound Generating devices

### > Electroacoustic transducer



### > Piezoelectric devices



### > Pros

- Low power driven devices
- Sound quality optimized for more than one century

### > Cons

- Shape dependent devices
- Mechanically resonant devices

[https://www.researchgate.net/publication/277928278\\_A\\_Model\\_Updating\\_Technique\\_Based\\_on\\_the\\_Constitutive\\_Relation\\_Error\\_for\\_In\\_Situ\\_Identification\\_of\\_Admittance\\_Coefficient\\_of\\_Sound\\_Absorbing\\_Materials](https://www.researchgate.net/publication/277928278_A_Model_Updating_Technique_Based_on_the_Constitutive_Relation_Error_for_In_Situ_Identification_of_Admittance_Coefficient_of_Sound_Absorbing_Materials)


<https://fr.wikipedia.org/wiki/Piez%C3%A9o%C3%A9lectricit%C3%A9>

# I. Introduction: Thermoacoustic Principle

## Sound Generation process

An alternative current is applied to a material with a **high thermal conductivity** and a **low thermal capacity**.

The heat profile of the material follows the current profile and the compression dilatation of the air on the surface of the material due to **the fluctuating temperature generates an acoustic wave** whose frequency is proportional to the input frequency of the current.



### ➤ Pros

- Generation process independent of the shape
- Wideband sound generation
- Flexible design


### ➤ Cons

- Not efficient generation compared to conventional speakers
- New, not yet optimized, not well understood technology



# I. Introduction: Thermoacoustic Principle

## Thermophones Examples

- Thinfilm Thermophones (suspended nanowires, paper based, laser scribing...etc)



- Thick Thermophones (foam, sponge... etc)



[1] Xiao et al., *Flexible, stretchable, Transparent Carbon Nanotube Thin Film Loudspeakers*, *Nano Letters*, 2008

[2] Loeblein et al., *Configurable 3D Boron Nitride-Carbon Architecture...*, *Small*, 2014

[3] Aliev et al., *Alternative Nanostructures for Thermophones*, *ACS Nano* 9, 2015

Réf: Thèse CIFRE Défense - le 19 août 2019

Thales / Modèle : 87211168-DOC-DMF-FR-001

OPEN

## II. Theory: One Temperature Model (1T)


### Conservation Equations

➤ In a liquid

- $\frac{\rho}{B} \frac{\partial p}{\partial t} - \rho \alpha_T \frac{\partial T}{\partial t} + \rho \vec{V} \cdot \vec{v} = 0$
- $\rho \frac{\partial \vec{v}}{\partial t} = -\vec{V} p + \mu \nabla^2 \vec{v} + (\lambda + \mu) \vec{V} (\vec{V} \cdot \vec{v})$
- $\rho C_p \frac{\partial T}{\partial t} = \kappa \nabla^2 T + \alpha_T T_0 \frac{\partial p}{\partial t}$

➤ In a solid

$$- \rho_s \frac{\partial^2 \vec{u}}{\partial t^2} = (\lambda_{0,s} + \mu_{0,s}) \vec{V} (\vec{V} \cdot \vec{u}) + \mu_{0,s} \nabla^2 \vec{u} + (\lambda_s$$



[4] Guiraud et al., *Multilayer modeling of thermoacoustic sound generation for thermophone analysis and design*, Journal of Sound and Vibration 2019


## II. Theory: One Temperature Model (1T)

### Solutions

- $T = Ae^{-ik_{ac}x} + Be^{+ik_{ac}x} + Ce^{-\theta_{th}x} + De^{+\theta_{th}x}$
- $\tilde{p}(T), v(T), q(T)$

### Boundary Conditions

- Continuity of :  $T, \tilde{p}(T), v(T), q(T)$
- Semi infinite back and front mediums




[4] Guiraud et al., *Multilayer modeling of thermoacoustic sound generation for thermophone analysis and design*, Journal of Sound and Vibration 2019

## II. Theory: One Temperature Model (1T)

### Performances & Limitations


- Uniform distribution of the power, not realistic in a complex foam like geometry
- The thickness of the thermophone only influence the HCPUA but the sound generation process remains solely at the surface



[4] Guiraud et al., *Multilayer modeling of thermoacoustic sound generation for thermophone analysis and design*, Journal of Sound and Vibration 2019

## II. Theory: Two Temperature Model (2T)

### Motivation



## II. Theory: Two Temperature Model (2T)


### Conservation Equations

#### > In a fluid

- $\frac{\rho \partial p}{B \partial t} - \rho \alpha_T \frac{\partial T}{\partial t} + \rho \vec{V} \cdot \vec{v} = 0$
- $\rho \frac{\partial \vec{v}}{\partial t} = -\vec{V} p + \mu \nabla^2 \vec{v} + (\lambda + \mu) \vec{V} (\vec{V} \cdot \vec{v})$
- $\rho C_p \frac{\partial T}{\partial t} = \kappa \nabla^2 T + \alpha_T T_0 \frac{\partial p}{\partial t}$

#### > In a solid

$$- \rho_s C_{V,s} \frac{\partial T_s}{\partial t} = \kappa_s \nabla^2 T_s + S_0$$



6 Parameters in each layers:


- $p$
- $v$
- $q$
- $T$
- $q_s$
- $T_s$

## II. Theory: Two Temperature Model (2T)

### Solutions

- $T = Ae^{-ik_{ac}x} + Be^{+ik_{ac}x} + Ce^{-\theta_{th}x} + De^{+\theta_{th}x}$
- $\tilde{p}(T), v(T), q(T)$
- $T_s = Ee^{-\theta_{solid}x} + Fe^{+\theta_{solid}x} + T_{s,0}$
- $q_s(T_s)$

6 constants (A,B,C,D,E,F) are necessary in each layers to fully define all the parameters



## II. Theory: Two Temperature Model (2T)

### Boundary conditions

➤ In the fluid (0 to N+1)


- $T^+ = T^-$
- $\tilde{p}^+ = \tilde{p}^-$
- $v^+ = v^-$       coupling term
- $q^+ = q^- + g(T_s - T)$

➤ In the solid(1 to N)

- $T_s^+ = T_s^-$
- $q_s^+ = q_s^- - g(T_s - T)$       coupling term

➤ At the Edges (0 and N+1)


- Semi Infinite Back Medium
- Semi Infinite Front Medium



## II. Theory: Acoustic Diffraction


### I Use of Rayleigh's integral to Compare Simulations and Experiments

Simulation



Add the Diffraction using the calculated generated velocity


$$\triangleright p_{FF}(X_r) = \frac{i\omega\rho_g}{4\pi} \int_S v(x_e) \frac{e^{-ikr}}{r} dS$$



Generate the Frequency and Power Spectrum of the Thermophone



### III. Analysis: Near Field Sound Generation

#### I Comparison of the 1T and 2T model





### III. Analysis: Near Field Sound Generation

#### Thick and Thin Thermophone at 3kHz: Temperature





### III. Analysis: Near Field Sound Generation

#### Thick and Thin Thermophone at 3kHz: Heat flux



### III. Analysis: Near Field Sound Generation


#### Thick and Thin Thermophone at 3kHz: Particle Velocity




### III. Analysis: Frequency and Power Spectrum

#### Comparison with experimental results from Aliev and al [3]


[5]



[3]



[3]



[3] Aliev et al., *Alternative nanostructures for thermophones*, ACS Nano 9, 2015

[5] Tian an al, *Graphene-on-Paper Sound Source Devices*, ACS Nano 2011



Réf: Thèse CIFRE Défense - le 19 août 2019

Thales / Modèle : 87211168-DOC-DMF-FR-001

OPEN

### III. Analysis: Frequency and Power Spectrum

#### Thinfilm Thermophone Spectrum



[3] Aliev et al., *Alternative nanostructures for thermophones*, ACS Nano 9, 2015




Réf: Thèse CIFRE Défense - le 19 août 2019

Thales / Modèle : 87211168-DOC-DMF-FR-001

OPEN

### III. Analysis: Frequency and Power Spectrum

#### Thick Thermophone Spectrum



[3] Aliev et al., *Alternative nanostructures for thermophones*, ACS Nano 9, 2015

Réf: Thèse CIFRE Défense - le 19 août 2019

Thales / Modèle : 87211168-DOC-DMF-FR-001

OPEN

# I. Theoretical models: Conclusions

## | One Temperature model

### ➤ Strengths

- Consider the propagation of the wave in the solid
- Flexible design of thermophone with any number of different layers
- Working for planar, cylindrical and spherical waves

### ➤ Weaknesses

- Not adapted for thick, complex thermophone geometry
- None of them take the static raise of temperature in the pores into account for high input power

## | Two Temperatures model

### ➤ Strengths

- Novel thermophone theoretical model
- More adapted for complex, thick, foam like thermophone geometry
- Simpler model performing almost as well as the one temperature one for thin thermophones

### ➤ Weaknesses

- For now only for free field configuration with planar waves
- Only the energy conservation equation is considered in the solid

**THALES**



**Thank you for your attention**

### **Guiraud Pierre**

Bou-Matar Olivier (IEMN)

Giordano Stefano (IEMN)

Pernod Philippe (IEMN)

Hourlier Djamilia (IEMN)

Coquet Philippe (CINTRA)

Lardat Raphael

Doisy Martine

Pouliguen Philippe

Bazzali Emmanuelle

Teo Edwin

(Thales)

(Thales)

(DGA)

(DGA)

(CINTRA)

Réf: Thèse CIFRE Défense - le 19 août 2019

© THALES DMS FRANCE SAS – Tous Droits Réservés


[www.thalesgroup.com](http://www.thalesgroup.com)

OPEN




# Bonus: One Temperature Model (1T)

## I Model extension





Multilayer for planar waves



Multilayer for cylindrical or spherical waves

# Bonus: Thermal Layer (1T)

## Free Field radiation



# Bonus: Added Losses at the Boundaries

## Equations

### In a liquid

- $\frac{\rho \partial p}{B \partial t} - \rho \alpha_T \frac{\partial T}{\partial t} + \rho \vec{V} \cdot \vec{v} = 0$
- $\rho \frac{\partial \vec{v}}{\partial t} = -\vec{V} p + \mu \nabla^2 \vec{v} + (\lambda + \mu) \vec{V} (\vec{V} \cdot \vec{v})$
- $\rho C_p \frac{\partial T}{\partial t} = \kappa \nabla^2 T + \alpha_T T_0 \frac{\partial p}{\partial t}$



### In a solid

- $\rho_s C_{V,s} \frac{\partial T_s}{\partial t} = \kappa_s \nabla^2 T_s + S_0$

### Heat flux continuity

- $q^+ = q^- + g(T_s - T) - \beta_s T$

Added coefficient for conduction, convection and radiation losses



# Bonus: Coupling Coefficient Determination

## Equations

- Real total contact area between solid and air:

$$NSg = a\rho_s Vh$$

Then  $g = \frac{a\rho_s Vh}{NS} \cong 10^5 \text{ W/m}^2\text{K}$

## New Parameters

- $a$ : Specific area of the foam (about  $2000 \text{ m}^2/\text{g}$ ) [6,7,8]
- $h$ : Real heat film transfer coefficient (about  $200 \text{ W/m}^2\text{K}$ ) [9]

[6] Peigney et al., *Specific Surface Area of Carbon Nanotubes and bundles of Carbon Nanotubes*, Carbon 39, 2001

[7] Drieschner et al., *High surface area graphene foams by chemical vapor deposition*, 2D Materials, 2016

[8] Zhang et al., *Porous 3D graphene-based bulk materials with exceptional high surface area and excellent conductivity for supercapacitors*, Scientific Reports, 2013

[9] Silvestri et al., *Thermal characterization of carbon nanotube foam using MEMS microhotplates and thermographic analysis*, Nanoscale, 2016

# Bonus: Theoretical Parameters used

	$\rho$ [kg·m <sup>-3</sup> ]	$C_p$ [J·kg <sup>-1</sup> ·K <sup>-1</sup> ]	$C_V$ [J·kg <sup>-1</sup> ·K <sup>-1</sup> ]	$B$ [Pa]	$\alpha_T$ [K <sup>-1</sup> ]	$\kappa$ [W·K <sup>-1</sup> ·m <sup>-1</sup> ]	$\lambda$ [N·s·m <sup>-2</sup> ]	$\mu$ [N·s·m <sup>-2</sup> ]
Gas, air	1.20	$9.96 \times 10^2$	$7.17 \times 10^2$	$1.01 \times 10^5$	$3.33 \times 10^{-3}$	$26.2 \times 10^{-3}$	$16.82 \times 10^{-6}$	$5.61 \times 10^{-6}$

TABLE I. Parameters of the propagating medium (air).

	$\rho_s$ [kg·m <sup>-3</sup> ]	$C_{V,s}$ [J·kg <sup>-1</sup> ·K <sup>-1</sup> ]	$B_s$ [Pa]	$\kappa_s$ [W·K <sup>-1</sup> ·m <sup>-1</sup> ]	$L_l$ [m]	$L_s$ [m]	$A$ [cm <sup>2</sup> ]
CNT Sheet	1	716	$1.11 \times 10^{11}$	50	$18 \times 10^{-6}$	$10 \times 10^{-9}$	Square $1.5 \times 1.5$
ITO PAN	220	606	$1.65 \times 10^{11}$	310	$5 \times 10^{-6}$	$450 \times 10^{-9}$	Square $1.2 \times 1.5$
MWNT Sponge	30	716	$1.11 \times 10^{11}$	100	$100 \times 10^{-6}$	$10 \times 10^{-9}$	Square $1 \times 1$
Graphene Sponge	2.75	660	$1.44 \times 10^8$	6.3	$800 \times 10^{-6}$	$5 \times 10^{-9}$	Circle $d = 1.8$

TABLE II. Parameters of the thermophone materials used in the experiments and theoretical models. <sup>3</sup>

[3] Aliev et al., *Alternative nanostructures for thermophones*, ACS Nano 9, 2015

Réf: Thèse CIFRE Défense - le 19 août 2019

Thales / Modèle : 87211168-DOC-DMF-FR-001