



## Technical Note: Mathematical Development of the Interplexing 6 Signals for the Galileo E1 Band

Lorenzo Ortega Espluga, Charly Poulliat, Marie-Laure Boucheret, Marion Aubault, Hanaa Al Bitar-El Natour

### ► To cite this version:

Lorenzo Ortega Espluga, Charly Poulliat, Marie-Laure Boucheret, Marion Aubault, Hanaa Al Bitar-El Natour. Technical Note: Mathematical Development of the Interplexing 6 Signals for the Galileo E1 Band. 2020. hal-02944923

HAL Id: hal-02944923

<https://hal.science/hal-02944923>

Preprint submitted on 21 Sep 2020

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Mathematical Development of the Interplexing 6 Signals for the Galileo E1 Band

Lorenzo Ortega, Charly Poulliat, Marie Laure Boucheret,  
Marion Aubault-Roudier, Hanaa Al-Bitar

June 1, 2020

The general expression of the Interplexing 6 signals is:

$$\begin{aligned} s(t) &= \sqrt{2P} \cos \left( 2\pi f_c t - \frac{\pi}{2} s_1(t) + \beta_2 s_1(t) s_2(t) + \beta_3 s_1(t) s_3(t) + \beta_4 s_1(t) s_4(t) + \beta_5 s_1(t) s_5(t) + \beta_6 s_1(t) s_6(t) + \phi \right) \\ &= \sqrt{2P} \cos (2\pi f_c t + A + B + C + D + E + \phi) \end{aligned} \quad (1)$$

where:

- $A = \beta_2 s_1(t) s_2(t)$
- $B = \beta_3 s_1(t) s_3(t)$
- $C = \beta_4 s_1(t) s_4(t)$
- $D = \beta_5 s_1(t) s_5(t)$
- $E = \beta_6 s_1(t) s_6(t)$

then:

$$s(t) = \sqrt{2P} \left[ \begin{array}{l} \cos(2\pi f_c t + \phi) \left[ \begin{array}{l} \cos(-\frac{\pi}{2} s_1(t)) \cos(A + B + C + D + E) - \\ \sin(-\frac{\pi}{2} s_1(t)) \sin(A + B + C + D + E) \end{array} \right] \\ + \sin(2\pi f_c t + \phi) \left[ \begin{array}{l} \sin(-\frac{\pi}{2} s_1(t)) \cos(A + B + C + D + E) + \\ \cos(-\frac{\pi}{2} s_1(t)) \sin(A + B + C + D + E) \end{array} \right] \end{array} \right] \quad (2)$$

where  $\cos(-\frac{\pi}{2} s_1(t)) = 0$ , yielding  $s(t)$  to:

$$s(t) = \sqrt{2P} \left[ \begin{array}{l} \cos(2\pi f_c t + \phi) [s_1(t) \sin(A + B + C + D + E)] \\ + \sin(2\pi f_c t + \phi) [s_1(t) \cos(A + B + C + D + E)] \end{array} \right] \quad (3)$$

where  $\sin(A + B + C + D + E)$  is:

$$\sin(A + B + C + D + E) = \left[ \begin{array}{l} \sin(A) \cos(B) \cos(C) \cos(D) \cos(E) - \sin(A) \cos(B) \cos(C) \sin(D) \sin(E) - \\ \sin(A) \cos(B) \sin(C) \sin(D) \cos(E) - \sin(A) \cos(B) \sin(C) \cos(D) \sin(E) - \\ \sin(A) \sin(B) \sin(C) \cos(D) \cos(E) + \sin(A) \sin(B) \sin(C) \sin(D) \sin(E) - \\ \sin(A) \sin(B) \cos(C) \sin(D) \cos(E) - \sin(A) \sin(B) \cos(C) \cos(D) \sin(E) + \\ \cos(A) \sin(B) \cos(C) \cos(D) \cos(E) - \cos(A) \sin(B) \cos(C) \sin(D) \sin(E) - \\ \cos(A) \sin(B) \sin(C) \sin(D) \cos(E) - \cos(A) \sin(B) \sin(C) \cos(D) \sin(E) + \\ \cos(A) \cos(B) \sin(C) \cos(D) \cos(E) - \cos(A) \cos(B) \sin(C) \sin(D) \sin(E) + \\ \cos(A) \cos(B) \cos(C) \sin(D) \cos(E) + \cos(A) \cos(B) \cos(C) \cos(D) \sin(E) \end{array} \right] \quad (4)$$

and

$\cos(A + B + C + D + E)$  is:

$$\cos(A + B + C + D + E) = \left[ \begin{array}{l} \cos(A)\cos(B)\cos(C)\cos(D)\cos(E) - \cos(A)\cos(B)\cos(C)\sin(D)\sin(E) - \\ \cos(A)\cos(B)\sin(C)\sin(D)\cos(E) - \cos(A)\cos(B)\sin(C)\cos(D)\sin(E) - \\ \cos(A)\sin(B)\sin(C)\cos(D)\cos(E) + \cos(A)\sin(B)\sin(C)\sin(D)\sin(E) - \\ \cos(A)\sin(B)\cos(C)\sin(D)\cos(E) - \cos(A)\sin(B)\cos(C)\cos(D)\sin(E) - \\ \sin(A)\sin(B)\cos(C)\cos(D)\cos(E) + \sin(A)\sin(B)\cos(C)\sin(D)\sin(E) + \\ \sin(A)\sin(B)\sin(C)\sin(D)\cos(E) + \sin(A)\sin(B)\sin(C)\cos(D)\sin(E) - \\ \sin(A)\cos(B)\sin(C)\cos(D)\cos(E) + \sin(A)\cos(B)\sin(C)\sin(D)\sin(E) - \\ \sin(A)\cos(B)\cos(C)\sin(D)\cos(E) - \sin(A)\cos(B)\cos(C)\cos(D)\sin(E) \end{array} \right] \quad (5)$$

Then, from equation (3) and considering the definition of  $A, B, C, D, E$ , we derive:

$$s_1(t) \sin(A + B + C + D + E) = \left[ \begin{array}{l} s_2(t)\sin(\beta_2)\cos(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \\ s_2(t)s_5(t)s_6(t)\sin(\beta_2)\cos(\beta_3)\cos(\beta_4)\sin(\beta_5)\sin(\beta_6) - \\ s_2(t)s_4(t)s_5(t)\sin(\beta_2)\cos(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6) - \\ s_2(t)s_4(t)s_6(t)\sin(\beta_2)\cos(\beta_3)\sin(\beta_4)\cos(\beta_5)\sin(\beta_6) - \\ s_2(t)s_3(t)s_4(t)\sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6) + \\ s_2(t)s_3(t)s_4(t)s_5(t)s_6(t)\sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\sin(\beta_6) - \\ s_2(t)s_3(t)s_5(t)\sin(\beta_2)\sin(\beta_3)\cos(\beta_4)\sin(\beta_5)\cos(\beta_6) - \\ s_2(t)s_3(t)s_6(t)\sin(\beta_2)\sin(\beta_3)\cos(\beta_4)\cos(\beta_5)\sin(\beta_6) + \\ s_3(t)\cos(\beta_2)\sin(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \\ s_3(t)s_5(t)s_6(t)\cos(\beta_2)\sin(\beta_3)\cos(\beta_4)\sin(\beta_5)\sin(\beta_6) - \\ s_3(t)s_4(t)s_5(t)\cos(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6) - \\ s_3(t)s_4(t)s_6(t)\cos(\beta_2)\sin(\beta_3)\sin(\beta_4)\cos(\beta_5)\sin(\beta_6) + \\ s_4(t)\cos(\beta_2)\cos(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6) - \\ s_4(t)s_5(t)s_6(t)\cos(\beta_2)\cos(\beta_3)\sin(\beta_4)\sin(\beta_5)\sin(\beta_6) + \\ s_5(t)\cos(\beta_2)\cos(\beta_3)\cos(\beta_4)\sin(\beta_5)\cos(\beta_6) + \\ s_6(t)\cos(\beta_2)\cos(\beta_3)\cos(\beta_4)\cos(\beta_5)\sin(\beta_6) \end{array} \right] \quad (6)$$

Let us now redefine the Galileo E1 OS equations in [1] as a function of  $s_2(t)$ ,  $s_3(t)$ ,  $s_4(t)$  and  $s_5(t)$ :

$$\begin{aligned} s_{E1-OS_{data}}(t) &= d_{E1-B}(t)c_{E1-B}(t)(\alpha BOC(1,1) + \beta BOC(6,1)) = \alpha s_2(t) + \beta s_4(t). \\ s_{E1-OS_{pilot}}(t) &= c_{E1-C}(t)(\alpha BOC(1,1) - \beta BOC(6,1)) = \alpha s_3(t) - \beta s_5(t). \end{aligned} \quad (7)$$

considering equation (7), equation (4) can be simplified to :

$$\left[ \begin{array}{l} s_2(t)[\sin(\beta_2)\cos(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \cos(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6)] \\ + s_2(t)s_5(t)s_6(t)[- \sin(\beta_2)\cos(\beta_3)\cos(\beta_4)\sin(\beta_5)\sin(\beta_6) - \cos(\beta_2)\sin(\beta_3)\sin(\beta_4)\cos(\beta_5)\sin(\beta_6)] \\ + s_3(t)[\cos(\beta_2)\sin(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \sin(\beta_2)\cos(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6)] \\ + s_2(t)s_4(t)s_6(t)[- \sin(\beta_2)\cos(\beta_3)\sin(\beta_4)\cos(\beta_5)\sin(\beta_6) - \cos(\beta_2)\sin(\beta_3)\cos(\beta_4)\sin(\beta_5)\sin(\beta_6)] \\ + s_5(t)[\cos(\beta_2)\cos(\beta_3)\cos(\beta_4)\sin(\beta_5)\cos(\beta_6) - \sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6)] \\ + s_6(t)[\cos(\beta_2)\cos(\beta_3)\cos(\beta_4)\cos(\beta_5)\sin(\beta_6) + \sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\sin(\beta_6)] \\ + s_4(t)[\cos(\beta_2)\cos(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6) - \sin(\beta_2)\sin(\beta_3)\cos(\beta_4)\sin(\beta_5)\cos(\beta_6)] \\ + s_2(t)s_3(t)s_6(t)[- \sin(\beta_2)\sin(\beta_3)\cos(\beta_4)\cos(\beta_5)\sin(\beta_6) - \cos(\beta_2)\cos(\beta_3)\sin(\beta_4)\sin(\beta_5)\sin(\beta_6)] \end{array} \right] \quad (8)$$

Consequently:

$$\begin{aligned} (\sin(\beta_2)\cos(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \cos(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6)) &= \alpha \\ (\cos(\beta_2)\sin(\beta_3)\cos(\beta_4)\cos(\beta_5)\cos(\beta_6) - \sin(\beta_2)\cos(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6)) &= \alpha \\ (\cos(\beta_2)\cos(\beta_3)\cos(\beta_4)\sin(\beta_5)\cos(\beta_6) - \sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6)) &= -\beta \\ (\cos(\beta_2)\cos(\beta_3)\sin(\beta_4)\cos(\beta_5)\cos(\beta_6) - \sin(\beta_2)\sin(\beta_3)\sin(\beta_4)\sin(\beta_5)\cos(\beta_6)) &= \beta \end{aligned} \quad (9)$$

This linear system lead to  $\beta_2 = \beta_3$  and  $\beta_4 = -\beta_5$ , leaving equation (6) to:

$$s_1(t) \sin(A + B + C + D + E) = \left[ \begin{array}{l} (s_2(t) + s_3(t)) \cos(\beta_6) \frac{\sin(2\beta_2)}{2} + \\ (s_4(t) - s_5(t)) \cos(\beta_6) \frac{\sin(2\beta_4)}{2} + \\ s_6(t) \sin(\beta_6) \frac{[\cos(2\beta_2) + \cos(2\beta_4)]}{2} + \\ s_2(t)s_3(t)s_6(t) \sin(\beta_6) [\cos^2(\beta_2) \sin^2(\beta_4) - \sin^2(\beta_2) \cos^2(\beta_4)] \end{array} \right] \quad (10)$$

Now, from equation (3) and considering the definition of  $A, B, C, D, E$ , we derive:

$$s_1(t) \cos(A + B + C + D + E) = \left[ \begin{array}{l} s_1(t) \cos(\beta_2) \cos(\beta_3) \cos(\beta_4) \cos(\beta_5) \cos(\beta_6) - \\ s_1(t)s_5(t)s_6(t) \cos(\beta_2) \cos(\beta_3) \cos(\beta_4) \sin(\beta_5) \sin(\beta_6) - \\ s_1(t)s_4(t)s_5(t) \cos(\beta_2) \cos(\beta_3) \sin(\beta_4) \sin(\beta_5) \cos(\beta_6) - \\ s_1(t)s_4(t)s_6(t) \cos(\beta_2) \cos(\beta_3) \sin(\beta_4) \cos(\beta_5) \sin(\beta_6) - \\ s_1(t)s_3(t)s_4(t) \cos(\beta_2) \sin(\beta_3) \sin(\beta_4) \cos(\beta_5) \cos(\beta_6) + \\ s_1(t)s_3(t)s_4(t)s_5(t)s_6(t) \cos(\beta_2) \sin(\beta_3) \sin(\beta_4) \sin(\beta_5) \sin(\beta_6) - \\ s_1(t)s_3(t)s_5(t) \cos(\beta_2) \sin(\beta_3) \cos(\beta_4) \sin(\beta_5) \cos(\beta_6) - \\ s_1(t)s_3(t)s_6(t) \cos(\beta_2) \sin(\beta_3) \cos(\beta_4) \cos(\beta_5) \sin(\beta_6) - \\ s_1(t)s_2(t)s_3(t) \sin(\beta_2) \sin(\beta_3) \cos(\beta_4) \cos(\beta_5) \cos(\beta_6) + \\ s_1(t)s_2(t)s_3(t)s_5(t)s_6(t) \sin(\beta_2) \sin(\beta_3) \cos(\beta_4) \sin(\beta_5) \sin(\beta_6) + \\ s_1(t)s_2(t)s_3(t)s_4(t)s_5(t) \sin(\beta_2) \sin(\beta_3) \sin(\beta_4) \sin(\beta_5) \cos(\beta_6) + \\ s_1(t)s_2(t)s_3(t)s_4(t)s_6(t) \sin(\beta_2) \sin(\beta_3) \sin(\beta_4) \cos(\beta_5) \sin(\beta_6) - \\ s_1(t)s_2(t)s_4(t) \sin(\beta_2) \cos(\beta_3) \sin(\beta_4) \cos(\beta_5) \cos(\beta_6) + \\ s_1(t)s_2(t)s_4(t)s_5(t)s_6(t) \sin(\beta_2) \cos(\beta_3) \sin(\beta_4) \sin(\beta_5) \sin(\beta_6) - \\ s_1(t)s_2(t)s_5(t) \sin(\beta_2) \cos(\beta_3) \cos(\beta_4) \sin(\beta_5) \cos(\beta_6) - \\ s_1(t)s_2(t)s_6(t) \sin(\beta_2) \cos(\beta_3) \cos(\beta_4) \cos(\beta_5) \sin(\beta_6) \end{array} \right] \quad (11)$$

Considering equation (7), equation (11) can be simplified to :

$$\left[ \begin{array}{l} s_1(t) [\cos(\beta_2) \cos(\beta_3) \cos(\beta_4) \cos(\beta_5) \cos(\beta_6) - \sin(\beta_2) \sin(\beta_3) \sin(\beta_4) \sin(\beta_5) \cos(\beta_6)] \\ + s_1(t)s_5(t)s_6(t) [-\cos(\beta_2) \cos(\beta_3) \cos(\beta_4) \sin(\beta_5) \sin(\beta_6) + \sin(\beta_2) \sin(\beta_3) \sin(\beta_4) \cos(\beta_5) \sin(\beta_6)] \\ + s_1(t)s_2(t)s_3(t) [-\sin(\beta_2) \sin(\beta_3) \cos(\beta_4) \cos(\beta_5) \cos(\beta_6) - \cos(\beta_2) \cos(\beta_3) \sin(\beta_4) \sin(\beta_5) \cos(\beta_6)] \\ + s_1(t)s_4(t)s_6(t) [-\cos(\beta_2) \cos(\beta_3) \sin(\beta_4) \cos(\beta_5) \sin(\beta_6) + \sin(\beta_2) \sin(\beta_3) \cos(\beta_4) \sin(\beta_5) \sin(\beta_6)] \\ + s_1(t)s_3(t)s_4(t) [\sin(\beta_2) \cos(\beta_3) \cos(\beta_4) \sin(\beta_5) \cos(\beta_6) - \cos(\beta_2) \sin(\beta_3) \sin(\beta_4) \cos(\beta_5) \cos(\beta_6)] \\ + s_1(t)s_2(t)s_6(t) [-\sin(\beta_2) \cos(\beta_3) \cos(\beta_4) \cos(\beta_5) \sin(\beta_6) + \cos(\beta_2) \sin(\beta_3) \sin(\beta_4) \sin(\beta_5) \sin(\beta_6)] \\ + s_1(t)s_2(t)s_4(t) [-\sin(\beta_2) \cos(\beta_3) \sin(\beta_4) \cos(\beta_5) \cos(\beta_6) - \cos(\beta_2) \sin(\beta_3) \cos(\beta_4) \sin(\beta_5) \cos(\beta_6)] \\ + s_1(t)s_3(t)s_6(t) [-\cos(\beta_2) \sin(\beta_3) \cos(\beta_4) \cos(\beta_5) \sin(\beta_6) + \sin(\beta_2) \cos(\beta_3) \sin(\beta_4) \sin(\beta_5) \sin(\beta_6)] \end{array} \right] \quad (12)$$

with  $\beta_2 = \beta_3$  and  $\beta_4 = -\beta_5$ , equation (12) yields to:

$$s_1(t) \cos(A + B + C + D + E) = \left[ \begin{array}{l} s_1(t) \cos(\beta_6) \frac{[\cos(2\beta_2) + \cos(2\beta_4)]}{2} + \\ s_1(t)s_2(t)s_3(t) \cos(\beta_6) [\cos^2(\beta_2) \sin^2(\beta_4) - \sin^2(\beta_2) \cos^2(\beta_4)] - \\ (s_4(t) - s_5(t))s_1(t)s_6(t) \sin(\beta_6) \frac{\sin(2\beta_4)}{2} - \\ (s_2(t) + s_3(t))s_1(t)s_6(t) \sin(\beta_6) \frac{\sin(2\beta_2)}{2} \end{array} \right] \quad (13)$$

Considering equations (10) and (13), equation (3) yields to

$$s(t) = \sqrt{2P} \left[ \begin{array}{l} \cos(2\pi f_c t + \phi) \left[ \begin{array}{l} (s_2(t) + s_3(t)) \cos(\beta_6) \frac{\sin(2\beta_2)}{2} + \\ (s_4(t) - s_5(t)) \cos(\beta_6) \frac{\sin(2\beta_4)}{2} + \\ s_6(t) \sin(\beta_6) \frac{[\cos(2\beta_2) + \cos(2\beta_4)]}{2} + \\ s_2(t)s_3(t)s_6(t) \sin(\beta_6) [\cos^2(\beta_2) \sin^2(\beta_4) - \sin^2(\beta_2) \cos^2(\beta_4)] \end{array} \right] \\ + \sin(2\pi f_c t + \phi) \left[ \begin{array}{l} s_1(t) \cos(\beta_6) \frac{[\cos(2\beta_2) + \cos(2\beta_4)]}{2} + \\ s_1(t)s_2(t)s_3(t) \cos(\beta_6) [\cos^2(\beta_2) \sin^2(\beta_4) - \sin^2(\beta_2) \cos^2(\beta_4)] - \\ (s_4(t) - s_5(t))s_1(t)s_6(t) \sin(\beta_6) \frac{\sin(2\beta_4)}{2} - \\ (s_2(t) + s_3(t))s_1(t)s_6(t) \sin(\beta_6) \frac{\sin(2\beta_2)}{2} \end{array} \right] \end{array} \right] \quad (14)$$

## References

- [1] E. Rebeyrol. *Galileo Signals and Payload Optimization*. PhD thesis, 2007.