



FullSubNet: A Full-Band and Sub-Band Fusion Model for Real-Time Single-Channel Speech Enhancement

Xiang Hao, Xiangdong Su, Radu Horaud, Xiaofei Li

► To cite this version:

Xiang Hao, Xiangdong Su, Radu Horaud, Xiaofei Li. FullSubNet: A Full-Band and Sub-Band Fusion Model for Real-Time Single-Channel Speech Enhancement. ICASSP 2021 - IEEE International Conference on Acoustics, Speech, and Signal Processing, Jun 2021, Toronto, Canada. pp.1-5. hal-03135727

HAL Id: hal-03135727

<https://hal.science/hal-03135727>

Submitted on 9 Feb 2021

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

FULLSUBNET: A FULL-BAND AND SUB-BAND FUSION MODEL FOR REAL-TIME SINGLE-CHANNEL SPEECH ENHANCEMENT

Xiang Hao^{1,2}, Xiangdong Su^{2*}, Radu Horaud³, and Xiaofei Li^{1†}

¹Westlake University & Westlake Institute for Advanced Study, Hangzhou, China

²College of Computer Science, Inner Mongolia University, Hohhot, China

³Inria Grenoble Rhône-Alpes, Montbonnot Saint-Martin, France

ABSTRACT

This paper proposes a full-band and sub-band fusion model, named as FullSubNet, for single-channel real-time speech enhancement. Full-band and sub-band refer to the models that input full-band and sub-band noisy spectral feature, output full-band and sub-band speech target, respectively. The sub-band model processes each frequency independently. Its input consists of one frequency and several context frequencies. The output is the prediction of the clean speech target for the corresponding frequency. These two types of models have distinct characteristics. The full-band model can capture the global spectral context and the long-distance cross-band dependencies. However, it lacks the ability to modeling signal stationarity and attending the local spectral pattern. The sub-band model is just the opposite. In our proposed FullSubNet, we connect a pure full-band model and a pure sub-band model sequentially and use practical joint training to integrate these two types of models' advantages. We conducted experiments on the DNS challenge (INTERSPEECH 2020) dataset to evaluate the proposed method. Experimental results show that full-band and sub-band information are complementary, and the FullSubNet can effectively integrate them. Besides, the performance of the FullSubNet also exceeds that of the top-ranked methods in the DNS Challenge (INTERSPEECH 2020).

Index Terms— FullSubNet, Full-band and Sub-band Fusion, Sub-band, Speech Enhancement

1. INTRODUCTION

In recent years, deep learning-based single-channel speech enhancement methods have greatly improved speech enhancement systems, speech quality and intelligibility. These methods are often trained in a supervised setting and can be divided into time-domain and frequency-domain methods. The time-domain methods [1–3] use the neural network to map noisy speech waveform to clean speech waveform directly. The frequency-domain methods [4–7] typically use the noisy spectral feature (e.g., complex spectrum, magnitude spectrum) as the input of a neural model. Learning target is the spectral feature of clean speech or a certain mask (e.g., Ideal Binary Mask [8], Ideal Ratio Mask [9], complex Ideal Ratio Mask (cIRM) [10]). In general, due to the high dimension and the lack of apparent geometric structure for the time domain signal, the frequency domain methods still dominate the vast majority of speech enhancement methods. In this paper, we focus on real-time single-channel speech enhancement in the frequency domain.

In our previous work [11], a sub-band-based method was proposed for single-channel speech enhancement. Unlike the traditional full-band-based methods, the method performed in a sub-band style: The input of the model consists of one frequency, together with several context frequencies. The output is a prediction of the clean speech target for the corresponding frequency. All the frequencies are processed independently. This method is designed on the following grounds. (1) It learns the frequency-wise signal stationarity to discriminate between speech and stationary noise. It is known that speech is non-stationary, while many types of noise are relatively stationary. The temporal evolution of frequency-wise STFT magnitude reflects the stationarity, which is the foundation for the conventional noise power estimators [12, 13] and speech enhancement methods [14, 15]. (2) It focuses on the local spectral pattern presented in the current and context frequencies. The local spectral pattern has been proved to be informative for discriminating between speech and other signals. This method was submitted to the DNS challenge [16] in INTERSPEECH 2020 and ranked the fourth place out of the 16 real-time track submissions.

The sub-band model meets the DNS challenge's real-time requirement, and the performance is also very competitive. However, since it cannot model the global spectral pattern and exploit the long-distance cross-band dependencies. Especially for the sub-band with an extremely low signal-to-noise ratio (SNR), the sub-band model can hardly recover the clean speech, while it will be possible with the help of full-band dependency. On the other hand, the full-band models [4, 5] are trained to learn the regression between the high-dimensional input and output, lacking a mechanism dedicated to the sub-band information, such as the signal stationarity.

This paper proposes a full-band and sub-band fusion model named FullSubNet to address the above problems. Based on plenty of preliminary experiments, the FullSubNet is designed as a series connection of the full-band model and sub-band model. In short, the full-band model's output is input to the sub-band model. Through effective joint training, these two models are jointly optimized. The FullSubNet can capture the global (full-band) context while retaining the ability to model signal stationarity and attend the local spectral pattern. Like the sub-band model, the FullSubNet still meets the real-time requirement and can exploit future information within a reasonable latency. We evaluate the FullSubNet on the DNS challenge (INTERSPEECH 2020) dataset. Experimental results show that the FullSubNet prominently outperforms both the sub-band model [17] and a pure full-band model with a larger amount of parameters with the FullSubNet, which indicates that the sub-band information and the full-band information are complementary. The proposed fusion model is effective for integrating them. Besides, we also compare the performance with the top-ranked methods in the

*Equal contribution

†Corresponding author




Fig. 1. Diagram of the proposed FullSubNet. The second line in the rectangle describes the dimensions of the data at the current stage, e.g., “1 (F)” represents one F -dimensional vector. “ $F (2N + 1)$ ” represents F independent $(2N + 1)$ -dimensional vectors.

DNS challenge, and the results show that our objective performance measures are better than them.

2. METHOD

We use the representation of speech signal in the short-time fourier transform (STFT) domain:

$$X(t, f) = S(t, f) + N(t, f). \quad (1)$$

where $X(t, f)$, $S(t, f)$ and $N(t, f)$ respectively represent the complex-valued time-frequency (T-F) bin of noisy speech, noise-free speech (the reverberant image signal received at the microphone) and interference noise at time frame t and frequency bin f with $t = 1, \dots, T$ and $f = 0, \dots, F - 1$. T and F denote the total number of frames and frequency bins, respectively.

This paper focuses only on the denoising task, and the target is to suppress noise $N(t, f)$ and recover the reverberant speech signal $S(t, f)$. We propose a full-band and sub-band fusion model to accomplish this task, including a pure full-band model G_{full} and a pure sub-band model G_{sub} . The basic workflow is shown in Fig. 1. Next, we will introduce each part in detail.

2.1. Input

Previous works [4, 5, 11, 17] have proved that magnitude spectral feature can provide crucial clues about the global spectral pattern at full-band, while the local spectral pattern and signal stationarity at

sub-band. Therefore, we use the noisy full-band magnitude spectral features

$$\mathbf{X}(t) = [|X(t, 0)|, \dots, |X(t, f)|, \dots, |X(t, F - 1)|]^T \in \mathbb{R}^F. \quad (2)$$

We use its sequence

$$\tilde{\mathbf{X}} = (\mathbf{X}(1), \dots, \mathbf{X}(t), \dots, \mathbf{X}(T)) \quad (3)$$

as the input of the full-band model G_{full} . Then, G_{full} can capture the global contextual information and outputs a spectral embedding with the size being the same as $\tilde{\mathbf{X}}$, which is expected to provide complementary information to the following sub-band model G_{sub} .

The sub-band model G_{sub} predicts the frequency-wise clean-speech target according to the signal stationarity and local spectral mode encoded in the noisy sub-band signal, as well as the full-band model’s output. In detail, we take a time-frequency point $|X(t, f)|$ and its adjacent $2 \times N$ time-frequency points as a sub-band unit. N is the number of neighbor frequencies considered on each side. For boundary frequencies, with $f - N < 0$ or $f + N > F - 1$, circular Fourier frequencies are used. We concatenate the sub-band unit and the output of the full-band model, denoted as $G_{\text{full}}(|X(t, f)|)$, as the input of the sub-band model G_{sub} ,

$$\begin{aligned} \mathbf{x}(t, f) = & [|X(t, f - N)|, \dots, |X(t, f - 1)|, |X(t, f)| \\ & |X(t, f + 1)|, \dots, |X(t, f + N)|, \\ & G_{\text{full}}(|X(t, f)|)]^T \in \mathbb{R}^{2N+2}. \end{aligned} \quad (4)$$

For the frequency f , the input sequence of G_{sub} is

$$\tilde{\mathbf{x}}(f) = (\mathbf{x}(1, f), \dots, \mathbf{x}(t, f), \dots, \mathbf{x}(T, f)). \quad (5)$$

In this sequence, the temporal evolution along with time axis reflect the signal stationarity, which is an efficient cues to discriminate between speech and relatively stationary noise. The noisy sub-band spectra (composed of $2N + 1$ frequencies) and its temporal dynamics provides the local spectral pattern, which can be learned by the dedicated sub-band model. While the signal stationarity cues and the local pattern are actually present in the input of the full-band model G_{full} as well, however, they are not especially learned by the full-band model G_{full} . Consequently, the sub-band model G_{sub} still learns some extra/different information relative to the full-band model G_{full} . Meanwhile, the output of the full-band model G_{full} provide some complementary information not seen by the sub-band model G_{sub} .

Since the full-band spectral feature $\mathbf{X}(t)$ contains F frequencies, we eventually generate F independent input sequences for G_{sub} with a dimension of $2N + 2$ for each.

2.2. Learning target

There is no doubt that the precise estimation of phase can provide more hearing perception quality improvement, especially in low signal-to-noise ratio (SNR) conditions. However, the phase is wrapped in $-\pi \sim \pi$ and has chaotic data distribution, which makes it not easy to estimate. Instead of estimating the phase directly, like the previous works [11, 17], we adopt the complex Ideal Ratio Mask (cIRM) as our model’s learning target. Follow [10], we use hyperbolic tangent to compress cIRM in training and use inverse function to uncompressed mask in inference ($K = 10$, $C = 0.1$). We denote cIRM as $\mathbf{y}(t, f) \in \mathbb{R}^2$ for one T-F bin. The sub-band model takes as input sequence $\tilde{\mathbf{x}}(f)$ for the frequency f and then predicts the cIRM sequence

$$\tilde{\mathbf{y}}(f) = (\mathbf{y}(1, f), \dots, \mathbf{y}(t, f), \dots, \mathbf{y}(T, f)). \quad (6)$$

2.3. Model architecture

Fig. 1 shows the architecture of the FullSubNet. The full-band and sub-band models in the FullSuNet have the same model structure, including two stacked unidirectional LSTM layers and one linear (fully connected) layer. The LSTM of the full-band model contains 512 hidden units in each layer and uses ReLU as the output layer’s activation function. The full-band model outputs a F -dimensional vector at each time step, with one element for each frequency. The sub-band units are then concatenated with this vector frequency by frequency to form F independent input samples for the sub-band model following Equation 4. According to our previous experiments, the sub-band model is not necessary to be as large as the full-band model, and thus 384 hidden units are used in each layer of LSTM. According to the settings in [10], the output layer of the sub-band model does not use activation functions. It is important to note that all the frequencies share one unique sub-band network (and its parameters). During training, considering the limited LSTM memory capacity, the input-target sequence pairs are generated with a constant-length sequence.

To make the model easier to optimize, the input sequence must be normalized to equalize the input levels. For the full-band model, we empirically calculate the mean value μ_{full} of the magnitude spectral features on the full-band sequence $\tilde{\mathbf{X}}$ and normalize the input sequence as $\frac{\tilde{\mathbf{x}}}{\mu_{\text{full}}}$. The sub-band model process the frequencies independently. For frequency f , we caculate the mean value $\mu_{\text{sub}}(f)$ on the input sequence $\tilde{\mathbf{x}}(f)$ and normalize the input sequence as $\frac{\tilde{\mathbf{x}}(f)}{\mu_{\text{sub}}(f)}$.

In the real-time inference stage, we usually use the cumulative normalization method [18, 19], i.e., at each time, the mean value used for normalization is computed using all the available frames. However, in the practical real-time speech enhancement system, the speech signal is usually silent initially, which means that the speech signal’s beginning part is mostly invalid. In this work, to better show the FullSubNet’s performance regardless of the normalization problem, we directly use μ_{full} and $\mu_{\text{sub}}(f)$ computed on the entire test clip to perform normalization during inference.

Same as the method mentioned in [17], our proposed method supports output delay, which enables the model to explore future information within a reasonably small delay. As shown in the Fig. 1, to infer $\mathbf{y}(t - \tau)$, the future time steps, i.e. $\mathbf{x}(t - \tau + 1), \dots, \mathbf{x}(t)$, are provided in the input sequence.

3. EXPERIMENTAL SETUP

3.1. Datasets

We evaluated the FullSubNet on the DNS Challenge (INTERSPEECH 2020) dataset [16]. The clean speech set includes over 500 hours of clips from 2150 speakers. The noise dataset includes over 180 hours of clips from 150 classes. To make full use of the dataset, we simulate the speech-noise mixture with dynamic mixing during model training. In detail, before the start of each training epoch, 75% of the clean speeches are mixed with randomly selected room impulse responses (RIR) from (1) the Multichannel Impulse Response Database [20] with three reverberation times (T60) 0.16 s, 0.36 s, and 0.61 s. (2) the Reverb Challenge dataset [21] with three reverberation times 0.3 s, 0.6 s and 0.7 s. After that, the speech-noise mixtures are dynamically generated by mixing the clean speech (75% of them are reverberant) and noise with a random SNR in between -5 and 20 dB. The total data “seen” by the model is over 5000 hours after ten epochs of training. The DNS Challenge provides a publicly available test dataset, including two categories of

synthetic clips, i.e., without and with reverberations. Each category has 150 noisy clips with SNR levels distributed in between 0 dB to 20 dB. We use this test dataset for evaluation.

3.2. Implementation

The signals are transformed to the STFT domain using a 512-sample (32 ms) Hanning window with a frame step of 256 samples. We use PyTorch to implement the FullSubNet. Adam optimizer is used with a learning rate of 0.001. The sequence length for training is set to $T = 192$ frames (about 3 s). According to the real-time requirement of the DNS Challenge (INTERSPEECH 2020), we set $\tau = 2$, which exploits two future frames to enhance the current frame, and uses a $16 \times 2 = 32ms$ look ahead. As in [17], we set 15 neighbor frequencies for each side of the input frequency of the sub-band model in the FullSubNet.

3.3. Baselines

To testify the full-band and sub-band fusion method’s effectiveness, we compare with the following two models, which use the same experimental settings and learning target (cIRM) as the FullSubNet.

- **Sub-band model** [17]: The sub-band model has achieved very competitive performance in the DNS-Challenge (the fourth place of the real-time track). To compare performance fairly, like to train the FullSubNet, we use dynamic mixing during training.

- **Full-band model**: We construct a pure full-band model, which contains three LSTM layers with 512 hidden units for each layer. The full-band model’s architecture, i.e., a stack of LSTM layers, is actually widely used for speech enhancement, such as in [6, 26]. This model is slightly larger than the proposed fusion model, and thence the comparison would be fair enough.

In addition to these two models, we also compared with the top-ranked methods in the DNS challenge (INTERSPEECH 2020), including NSNet [22], DTLN [23], Conv-TasNet [24], DCCRN [19] and PoCoNet [25].

4. RESULTS

4.1. Comparison with the baselines

In the last three rows of Table 1, we compare the performance of the sub-band model, the full-band model, and the FullSubNet. “# Para” and “Look Ahead” in the table respectively represent the parameter amount of the model and the length of used future information. “With Reverb” means that the noisy speeches in the test dataset have not only noise but also a certain degree of reverberation, which significantly increases the difficulty for speech enhancement. “Without Reverb” means that the noisy speeches in the test dataset have only noise. For a fair comparison, these three models use the same training target (cIRM), experimental settings, and look ahead.

From the table, we can find that most of the full-band model’s evaluation scores are better than the ones of the sub-band model, as the full-band model exploits the wide-band information using a larger network. It is interesting to find that, relative to the full-band model, the sub-band model seems more effective for the “With Reverb” data, as the superiority of the full-band model for “With Reverb” is smaller than the one for “Without Reverb.” This indicates that the sub-band model effectively models the reverberation effect by focusing on the temporal evolution of the narrow-band spectrum. The possible reason is that the cross-band dependency of the reverberation effect is actually much lower than the one of signal spectra.

Table 1. The performance in terms of WB-PESQ [MOS], NB-PESQ [MOS], STOI [%], and SI-SDR [dB] on the DNS challenge test dataset.

Method	# Para (M)	Look Ahead (ms)	Rank	With Reverb				Without Reverb			
				WB-PESQ	NB-PESQ	STOI	SI-SDR	WB-PESQ	NB-PESQ	STOI	SI-SDR
Noisy	-	-	-	1.822	2.753	86.62	9.033	1.582	2.454	91.52	9.071
NSNet [22]	5.1	0	-	2.365	3.076	90.43	14.721	2.145	2.873	94.47	15.613
DTLN [23]	1.0		RT-8		2.70	84.68	10.53		3.04	94.76	16.34
Conv-TasNet [24]	5.08	33	NRT-5	2.750				2.73			
DCCRN-E [19]	3.7	37.5	RT-1		3.077				3.266		
PoCoNet [25]	50		NRT-1	2.832				2.748			
Sub-band Model [17]	1.3	32	RT-4	2.650	3.274	90.53	14.673	2.369	3.052	94.24	16.153
Full-band Model	6.0	32	-	2.681	3.344	90.64	13.580	2.731	3.256	95.71	16.190
FullSubNet	5.6	32	-	2.969	3.473	92.62	15.750	2.777	3.305	96.11	17.290

Regarding the FullSubNet: (1) Although the sub-band model’s performance is already very competitive, after integrating the full-band model (stacked by two LSTM layers and one linear layer), the model performance has been dramatically improved. This improvement shows that the global spectral pattern and the long-distance cross-band dependencies are essential for speech enhancement. (2) The performance of the FullSubNet also significantly exceeds the full-band model. We must first point out that this improvement does not come from using more parameters. In fact, the FullSubNet (two layers of full-band LSTM plus two layers of sub-band LSTM) has even fewer parameters than the full-band model (three layers of full-band LSTM). After integrating the sub-band model, the FullSubNet inherits the sub-band model’s unique ability, namely exploiting signal stationarity and local spectral patterns, and the capability of modeling the reverberation effect. The apparent superiority of the FullSubNet over the full-band model demonstrates that the information exploited by the sub-band model is indeed not learned by the full-band model, which is complementary to the full-band model. Overall, these results testify that the proposed fusion model successfully integrates the virtues of full-band and sub-band techniques.

4.2. Comparison with the state-of-the-art methods

In Table 1, in addition to showing that the FullSubNet can effectively integrate two complementary models, we also compare its performance with the top-ranked methods in DNS Challenge (INTERSPEECH 2020). The “Rank” column in the table indicates whether to support real-time processing and the challenge’s ranking. e.g., “RT-8” means the eighth place of the real-time (RT) track. “NRT-1” means the first place of the non-real-time (NRT) track.

In Table 1, NSNet is the official baseline method of the DNS challenge, which uses a compact RNN to enhance the noisy short-time speech spectra in a single-frame-in, single-frame-out manner. We use the DNS challenge recipe provided in the asteroid toolkit¹ to implement and train NSNet. The training data are generated using the method mentioned in [17]. In the table, no matter which metric, our proposed method greatly surpasses NSNet with all metrics.

DTLN, Conv-TasNet, DCCRN, and PoCoNet are the top-ranked methods in the DNS challenge’s subjective listening test. To ensure the fairness of comparison, we directly quote performance scores from their original papers. The vacant place in the table means that the corresponding score was not reported in the original paper. DTLN [23] is capable of real-time processing. It combines the STFT operation and a learned analysis and synthesis basis into

a stacked-network with less than one million parameters. [24] proposed a low-latency Conv-TasNet. Conv-TasNet [18] is a widely-used time-domain audio separation network, which has a large computational complexity. Consequently, the low-latency Conv-TasNet does not satisfy the real-time requirement. DCCRN [19] simulates the complex-valued operation inside the convolution recurrent network. It won the first place of the real-time track. PoCoNet [25] is a convolutional neural network with frequency-positional embeddings employed. Besides, a semi-supervised method is adopted to increase conversational training data by pre-enhancing the noisy datasets. It won the first place of the non-real-time track. These methods cover a large range of advanced deep learning-based speech enhancement techniques and represent the state-of-the-arts to an extent. The original paper of these methods provided the evaluation results on the same test set used in this work but with not all the metrics used in this work. It can be seen that the proposed fusion model achieves considerably better objective scores than all of them on this limited dataset. The performance of PoCoNet is close to ours, but it is a non-real-time model with a much larger network (about 50 M parameters). The proposed FullSubNet provides a new model dedicated to the full-band/sub-band fusion, which is likely not conflicting with the advanced techniques employed in these state-of-the-art models. Therefore, it worth expecting that speech enhancement capability can be further improved by properly combining them.

Regarding the computational complexity, the one STFT frame (32 ms) processing time of the proposed model (PyTorch implementation) is 10.32 ms tested on a virtual quad-core CPU (2.4 GHz) based on Intel Xeon E5-2680 v4, which obviously meets the real-time requirement. Later, we will open-source the code and pre-trained models, and show some enhanced audio clips at <https://github.com/haoxiangsnr/FullSubNet>.

5. CONCLUSION

In this paper, we propose a full-band and sub-band fusion model, named as FullSubNet, for real-time single-channel speech enhancement. This model is designed to integrate the advantages of the full-band and the sub-band models, that is, it can capture the global (full-band) spectral information and the long-distance cross-band dependencies, meanwhile retaining the ability to modeling signal stationarity and attending the local spectral pattern. On the DNS challenge (INTERSPEECH 2020) test dataset, we demonstrated that the sub-band information and the full-band information are complementary, and the FullSubNet can effectively integrate them. We also compared the performance with some top-ranked methods for the DNS challenge, and the results show that the FullSubNet outperforms these methods.

¹https://github.com/mpariente/asteroid/tree/master/egs/dns_challenge

6. REFERENCES

- [1] Dario Rethage, Jordi Pons, and Xavier Serra, “A wavenet for speech denoising,” in *2018 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*. IEEE, 2018, pp. 5069–5073.
- [2] A. Pandey and D. Wang, “Tcnn: Temporal convolutional neural network for real-time speech enhancement in the time domain,” in *ICASSP 2019 - 2019 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, 2019, pp. 6875–6879.
- [3] Xiang Hao, Xiangdong Su, Zhiyu Wang, Hui Zhang, and Battushiren, “UNetGAN: A Robust Speech Enhancement Approach in Time Domain for Extremely Low Signal-to-Noise Ratio Condition,” in *Proc. Interspeech 2019*, 2019, pp. 1786–1790.
- [4] Y. Xu, J. Du, L. Dai, and C. Lee, “A regression approach to speech enhancement based on deep neural networks,” *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, vol. 23, no. 1, pp. 7–19, 2015.
- [5] D. Wang and J. Chen, “Supervised speech separation based on deep learning: An overview,” *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, vol. 26, no. 10, pp. 1702–1726, 2018.
- [6] Jitong Chen and DeLiang Wang, “Long short-term memory for speaker generalization in supervised speech separation,” *The Journal of the Acoustical Society of America*, vol. 141, no. 6, pp. 4705–4714, 2017.
- [7] H. Erdogan, J. R. Hershey, S. Watanabe, and J. Le Roux, “Phase-sensitive and recognition-boosted speech separation using deep recurrent neural networks,” in *2015 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, pp. 708–712.
- [8] DeLiang Wang, “On Ideal Binary Mask As the Computational Goal of Auditory Scene Analysis,” in *Speech Separation by Humans and Machines*, Pierre Divenyi, Ed., pp. 181–197. Kluwer Academic Publishers, Boston, 2005.
- [9] Lei Sun, Jun Du, Li-Rong Dai, and Chin-Hui Lee, “Multiple-target deep learning for lstm-rnn based speech enhancement,” in *2017 Hands-free Speech Communications and Microphone Arrays (HSCMA)*. IEEE, 2017, pp. 136–140.
- [10] D. S. Williamson, Y. Wang, and D. Wang, “Complex ratio masking for monaural speech separation,” *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, vol. 24, no. 3, pp. 483–492, 2016.
- [11] Xiaofei Li and Radu Horaud, “Narrow-band Deep Filtering for Multichannel Speech Enhancement,” *arXiv preprint arXiv:1911.10791*, 2019.
- [12] Timo Gerkmann and Richard C Hendriks, “Unbiased mmse-based noise power estimation with low complexity and low tracking delay,” *IEEE Transactions on Audio, Speech, and Language Processing*, vol. 20, no. 4, pp. 1383–1393, 2011.
- [13] Xiaofei Li, Laurent Girin, Sharon Gannot, and Radu Horaud, “Non-stationary noise power spectral density estimation based on regional statistics,” in *2016 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*. IEEE, 2016, pp. 181–185.
- [14] Yariv Ephraim and David Malah, “Speech enhancement using a minimum-mean square error short-time spectral amplitude estimator,” *IEEE Transactions on acoustics, speech, and signal processing*, vol. 32, no. 6, pp. 1109–1121, 1984.
- [15] Israel Cohen and Baruch Berdugo, “Speech enhancement for non-stationary noise environments,” *Signal processing*, vol. 81, no. 11, pp. 2403–2418, 2001.
- [16] Chandan KA Reddy, Ebrahim Beyrami, Harishchandra Dubey, Vishak Gopal, Roger Cheng, Ross Cutler, Sergiy Matusevych, Robert Aichner, Ashkan Aazami, Sebastian Braun, et al., “The interspeech 2020 deep noise suppression challenge: Datasets, subjective speech quality and testing framework,” *arXiv preprint arXiv:2001.08662*, 2020.
- [17] Xiaofei Li and Radu Horaud, “Online monaural speech enhancement using delayed subband lstm,” *arXiv preprint arXiv:2005.05037*, 2020.
- [18] Y. Luo and N. Mesgarani, “Conv-tasnet: Surpassing ideal time-frequency magnitude masking for speech separation,” *IEEE/ACM Transactions on Audio, Speech, and Language Processing*, vol. 27, no. 8, pp. 1256–1266, 2019.
- [19] Yanxin Hu, Yun Liu, Shubo Lv, Mengtao Xing, Shimin Zhang, Yihui Fu, Jian Wu, Bihong Zhang, and Lei Xie, “Dccrn: Deep complex convolution recurrent network for phase-aware speech enhancement,” *arXiv preprint arXiv:2008.00264*, 2020.
- [20] Elior Hadad, Florian Heese, Peter Vary, and Sharon Gannot, “Multichannel audio database in various acoustic environments,” in *2014 14th International Workshop on Acoustic Signal Enhancement (IWAENC)*. IEEE, 2014, pp. 313–317.
- [21] Keisuke Kinoshita, Marc Delcroix, Sharon Gannot, Emanuël AP Habets, Reinhold Haeb-Umbach, Walter Kellermann, Volker Leutnant, Roland Maas, Tomohiro Nakatani, Bhiksha Raj, et al., “A summary of the reverb challenge: state-of-the-art and remaining challenges in reverberant speech processing research,” *EURASIP Journal on Advances in Signal Processing*, vol. 2016, no. 1, pp. 7, 2016.
- [22] Y. Xia, S. Braun, C. K. A. Reddy, H. Dubey, R. Cutler, and I. Tashev, “Weighted speech distortion losses for neural-network-based real-time speech enhancement,” in *ICASSP 2020 - 2020 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, 2020, pp. 871–875.
- [23] Nils L Westhausen and Bernd T Meyer, “Dual-signal transformation lstm network for real-time noise suppression,” *arXiv preprint arXiv:2005.07551*, 2020.
- [24] Yuichiro Koyama, Tyler Vuong, Stefan Uhlich, and Bhiksha Raj, “Exploring the Best Loss Function for DNN-Based Low-latency Speech Enhancement with Temporal Convolutional Networks,” *arXiv:2005.11611 [cs, eess]*, Aug. 2020, arXiv: 2005.11611.
- [25] Umut Isik, Ritwik Giri, Neerad Phansalkar, Jean-Marc Valin, Karim Helwani, and Arvindh Krishnaswamy, “Poconet: Better speech enhancement with frequency-positional embeddings, semi-supervised conversational data, and biased loss,” *arXiv preprint arXiv:2008.04470*, 2020.
- [26] Felix Weninger, Hakan Erdogan, Shinji Watanabe, Emmanuel Vincent, Jonathan Le Roux, John R Hershey, and Björn Schuller, “Speech enhancement with lstm recurrent neural networks and its application to noise-robust asr,” in *International Conference on Latent Variable Analysis and Signal Separation*. Springer, 2015, pp. 91–99.