



**HAL**  
open science

## Temporal integration of short-duration pulse trains in cochlear implant listeners: Psychophysical and electrophysiological measurements

Olivier Macherey, Pierre Stahl, Bastien Intartaglia, Sabine Meunier, Stéphane Roman, Daniele Schön

### ► To cite this version:

Olivier Macherey, Pierre Stahl, Bastien Intartaglia, Sabine Meunier, Stéphane Roman, et al.. Temporal integration of short-duration pulse trains in cochlear implant listeners: Psychophysical and electrophysiological measurements. *Hearing Research*, 2021, 403, pp.108176. 10.1016/j.heares.2021.108176 . hal-03438693

**HAL Id: hal-03438693**

**<https://hal.science/hal-03438693>**

Submitted on 21 Nov 2021

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution - NonCommercial - NoDerivatives 4.0 International License

1 TEMPORAL INTEGRATION OF SHORT-DURATION PULSE TRAINS IN  
2 COCHLEAR IMPLANT LISTENERS:  
3 PSYCHOPHYSICAL AND ELECTROPHYSIOLOGICAL MEASUREMENTS  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35

7 Olivier MACHEREY<sup>1</sup>, Pierre STAHL<sup>1</sup>, Bastien INTARTAGLIA<sup>2</sup>, Sabine MEUNIER<sup>1</sup>, Stéphane  
8 ROMAN<sup>2,3</sup>, and Daniele SCHÖN<sup>2</sup>

11 <sup>1</sup>Aix Marseille Univ, CNRS, Centrale Marseille, LMA, Marseille, France

12 <sup>2</sup>Aix Marseille Univ, Inserm, INS, Inst Neurosci Syst, Marseille, France

13 <sup>3</sup>Dept. Pediatric Otolaryngology and Neck Surgery, Aix Marseille Univ, Marseille, France

17 **Keywords** : temporal integration, electrically-evoked auditory brainstem response, objective  
18 measures, cochlear implant fitting, neural facilitation  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33

24 **Correspondence to Olivier Macherey**

25  
26 LMA-CNRS  
27 4 Impasse Nikola Tesla  
28 CS 40006  
29 13453 Marseille Cedex 13  
30 FRANCE  
31 Tel: +33 (0) 484 524 197  
32 Email: macherey@lma.cnrs-mrs.fr  
33

34 **ABSTRACT**

1  
2 35 While electrically-evoked auditory brainstem response (eABR) thresholds for low-rate pulse  
3  
4 36 trains correlate well with behavioral thresholds measured at the same rate, the correlation is  
5  
6 37 much weaker with behavioral thresholds measured at high rates, such as used clinically. This  
7  
8 38 implies that eABRs to low-rate stimuli cannot be reliably used for objective programming of  
9  
10 39 threshold levels in cochlear implant (CI) users. Here, we investigate whether the use of  
11  
12 40 bunched-up pulses (BUPS), consisting of groups of closely-spaced pulses may be used as an  
13  
14 41 alternative stimulus.

15  
16  
17 42 Experiment 1 measured psychophysical detection thresholds for several stimuli having  
18  
19 43 a period of 32 ms in nine CI subjects implanted with a Med-EL device. The stimuli differed in  
20  
21 44 the number of pulses present in each period (from 1 to 32), the pulse rate within period (1000  
22  
23 45 pps and as high as possible for BUPS) and the electrode location (apical or basal). The  
24  
25 46 correlation between psychophysical thresholds obtained for a high-rate (1000 pps) clinical  
26  
27 47 stimulus and for the BUPS stimuli increased as the number of pulses per period of BUPS  
28  
29 48 increased from 1 to 32. This first psychophysical experiment suggests that the temporal  
30  
31 49 processes affecting the threshold of clinical stimuli are also present for BUPS.

32  
33  
34  
35 50 Experiment 2 measured eABRs on the apical electrode of eight CI subjects for BUPS  
36  
37 51 having 1, 2, 4, 8, 16 or 32 pulses per period. For all subjects, wave V was visible for BUPS  
38  
39 52 having up to 16 pulses per period. The latency of wave V at threshold increased as a function  
40  
41 53 of the number of pulses per period, suggesting that the eABR reflects the integration of multiple  
42  
43 54 pulses at such low levels or that the neural response to each individual pulse increases along  
44  
45 55 the sequence due to facilitation processes. There was also a strong within-subject correlation  
46  
47 56 between electrophysiological and behavioral thresholds for the different BUPS stimuli. This  
48  
49 57 demonstrates that the drop in behavioral threshold obtained when increasing the number of  
50  
51 58 pulses per period of the BUPS can be measured electrophysiologically using eABRs. In  
52  
53 59 contrast, the across-subject correlation between eABR thresholds for BUPS and clinical  
54  
55 60 thresholds remained relatively weak and did not increase with the number of pulses per period.  
56  
57  
58  
59 61 Implications of the use of BUPS for objective programming of CIs are discussed.

## 62 1. INTRODUCTION

63  
64 In cochlear implants (CIs), the current level needed to produce an auditory sensation in a given  
65 subject may depend on many factors such as the position of the electrode(s) relative to the  
66 auditory nerve fibers and the amount of neural survival (Bierer, 2010; Long et al., 2014;  
67 Mesnildrey et al., 2020). Usually, fitting a CI requires clinicians to measure thresholds and  
68 comfortable listening levels for each individual electrode. As these levels may change over  
69 time, particularly during the first months after activation, this fitting process needs to be  
70 repeated on multiple sessions. The time devoted to cochlear programming in clinics has,  
71 therefore, increased tremendously over the past decades, especially since the number of CI  
72 implantation is constantly increasing. In addition, fitting young children remains a complicated  
73 process because there is currently no reliable method that allows the clinician to determine  
74 thresholds and most comfortable levels objectively.

75 A lot of effort has been devoted into finding electrophysiological measures able to  
76 predict the current levels needed for each electrode to produce a given sensation. Electrically-  
77 evoked compound action potentials (eCAPs) and auditory brainstem responses (eABRs) are  
78 two examples of such *objective* measures which are usually recorded using a relatively low  
79 stimulation pulse rate (a few tens of Hz). At these low rates, eCAP and eABR thresholds  
80 correlate well with psychophysical thresholds measured at the same rate (see Miller et al.,  
81 2008 for a review). However, contemporary CIs use much higher pulse rates than that, usually  
82 higher than 900 pps. Psychophysical thresholds measured at such high rates do not correlate  
83 well with eCAP or eABR thresholds measured at low rates (Brown et al., 1999). The reason  
84 for this is the across-electrode and across-subject variability in temporal integration. When  
85 pulse rate increases, the psychophysical threshold drops but the magnitude of this drop is  
86 variable both across subjects and across electrodes within a given subject (McKay et al.,  
87 2013a).

88 At the level of the auditory nerve, there may be several temporal processes affecting  
89 the neural response to individual pulses, as reviewed by Boulet et al. (2016). These processes

90 may partly or fully be responsible for the observed variability in temporal integration. When  
91 pulse rate is increased, the relative effects of neural refractoriness, accommodation, facilitation  
92 and spike-rate adaptation may change and consequently modify the neural response to each  
93 pulse. Although the relative contributions of these processes have not been unravelled in CI  
94 users, it is expected that refractoriness, adaptation and accommodation reduce the response  
95 to subsequent pulses in a pulse train whereas facilitation should have the opposite effect. In  
96 addition, at a more central level, neural activity is believed to be temporally integrated across  
97 different time scales. Even though the exact site(s) at which this temporal integration occurs  
98 remain unclear, phenomenological threshold and loudness models usually implement this  
99 process using a sliding temporal integration window with a short duration ranging from about  
100 7 to 20 ms (McKay and McDermott, 1998; Carlyon et al., 2005; Macherey et al., 2007; McKay  
101 et al., 2013b). These models predict that an increase in pulse rate will increase the number of  
102 spikes falling into the window which will consequently lower the threshold or increase the  
103 loudness.

104         The aim of the present study is to modify the signal used to measure eABRs (i.e. low-  
105 rate pulse train) to make it perceptually closer to the stimuli used clinically (i.e., high-rate pulse  
106 trains). Our modification is based on a study by McKay et al. (2013a) who measured behavioral  
107 threshold as a function of pulse rate for several electrodes and subjects. They reported highly  
108 variable slopes of temporal integration functions between 40 and 500 pps. Above 500 pps,  
109 however, the slopes were more consistent both across electrodes and across subjects. This  
110 suggests that if we were able to predict the threshold for an arbitrarily high rate of stimulation,  
111 we could potentially infer the approximate threshold for any stimulus with a rate above 500 pps  
112 which would be relevant clinically. Here, therefore, we choose to focus on very high rates of  
113 stimulation and to insert gaps within the stimulus to be able to record the eABR response in  
114 the absence of stimulus artefacts. In the following, we refer to this class of stimuli as “bunched-  
115 up pulses stimuli” (BUPS, c.f. Figure 1) which consist of sequences of closely-spaced pulses  
116 repeated at a relatively low sequence rate. As the amount of temporal integration at the level

117 of the brainstem remains poorly known, the following experiments are performed for  
118 sequences containing different numbers of pulses ranging from 1 to 32.

119 In Experiment 1, we measure psychophysical thresholds for different BUPS stimuli. In  
120 particular, we investigate whether the correlation between psychophysical thresholds for a  
121 clinical stimulus and for BUPS increases when increasing the number of pulses within the  
122 stimulus sequence. In Experiment 2, we test the feasibility of measuring eABRs in response  
123 to different BUPS stimuli.

## 124 2. EXPERIMENT 1: PSYCHOPHYSICAL THRESHOLDS

### 125 2.1. METHODS

#### 126 2.1.1. *Subjects and Experimental Platform*

127 Nine Med-EL CI users took part (c.f. Table 1 for biographical details). The psychophysical  
128 procedures were programmed in Matlab and used the Research Interface Box (RIB2,  
129 University of Innsbruck) and a National Instruments card (PCI-6533, National Instruments,  
130 Austin, TX) connected to a PC to stimulate the implant. Subjects provided informed consent  
131 and were paid for their participation. All experiments were approved by the Local Ethics  
132 committee (Eudract 2012-A00438-35).

#### 133 2.1.2. *Stimuli*

134 All stimuli were electrical pulse trains having a period of 32 ms (31 Hz) as shown in Figure 1.  
135 Within each period, the stimuli consisted of sequences of 1, 2, 4, 8, 16 or 32 electrical anodic-  
136 first symmetric biphasic pulses with a 2.1-  $\mu$ s inter-phase gap presented either at a rate of 1000  
137 pps or at the maximum rate possible (corresponding to a gap between the offset of one pulse  
138 and the onset of the next pulse of 2.1  $\mu$ s). The stimuli presented at a “clinical” rate of 1000 pps  
139 are referred to as CLIN (clinical stimulus) while those presented at the maximum rate are  
140 referred to as BUPS (bunched-up pulses stimulus). The number  $n$  following each of these

145 acronyms refers to the number of pulses present within a period. Note that when only 1 pulse  
1 per period is present, BUPS1 and CLIN1 are identical. Therefore, in total, 11 stimulus  
2 146  
3 conditions were tested.  
4 147  
5

6 148 The experiment was repeated on two electrodes which were the most apical and the  
7  
8 most basal active electrode in each subject's processor map. In case the most basal electrode  
9 149  
10 produced uncomfortable percepts, the next most basal electrode was chosen instead. These  
11 150  
12 electrodes are indicated in Table 2 for each subject. The phase duration differed across  
13 151  
14 subjects and was chosen to match the longer phase duration of the two electrodes tested as  
15 152  
16 specified in the clinical maps of the subjects. Consequently, both the within-period pulse rate  
17 153  
18 and the duration of the BUPS sequences also varied across subjects (c.f. Table 2). The total  
19 154  
20 stimulus duration (difference between the onset of the first pulse of the first sequence and the  
21 155  
22 offset of the last pulse of the last sequence) was fixed at a value as close as possible to 420  
23 156  
24 ms. Because some of our stimuli had large gaps between periods, this duration could slightly  
25 157  
26 vary across conditions (between 419.3 and 451.3 ms). An inspection of Donaldson et al.'s  
27 158  
28 (1997) data suggest that such small differences in stimulus duration should not affect detection  
29 159  
30 thresholds.  
31  
32  
33 160  
34  
35 161  
36

### 37 162 *2.1.3. Procedure*

38  
39  
40 163 Thresholds and Most Comfortable Loudness (MCL) levels were first approximately determined  
41  
42 164 using a loudness chart labeled from '0' (no sound) to '10' (too loud), label '1' corresponding to  
43  
44 165 detection threshold and label '6' to MCL. Detection thresholds were then measured adaptively  
45  
46 166 in a two-interval, two-alternative, three-down, 1-up forced choice task (Levitt, 1971). In each  
47  
48 167 trial, two intervals were presented separated by a 500-ms gap. The intervals were cued visually  
49  
50 168 on a computer screen. One interval contained the stimulus while the other contained no sound.  
51  
52 169 Subjects had to identify in which interval (1 or 2) a sound was present by clicking on one of  
53  
54 170 two virtual buttons displayed on the screen. The starting level was set to 25% of the dynamic  
55  
56 171 range (expressed in  $\mu\text{A}$ ) as initially measured using the loudness chart. This ensured that the  
57  
58 172 stimulus was clearly audible at the beginning of the procedure. After three consecutive correct  
59  
60  
61  
62  
63  
64  
65

173 responses, the stimulus level was decreased while it was increased after each incorrect  
174 response. The amount of increase and decrease varied during the procedure: it was equal to  
175 0.6 dB before the first reversal, 0.3 dB before the third reversal and 0.15 dB subsequently.  
176 Each procedure was resumed after 10 reversals and the threshold was defined as the mean  
177 of the last 6 reversals. Feedback was provided after each trial.

#### 2.1.4. Sessions

178  
179 For each electrode, data were collected in blocks of 11 adaptive runs corresponding to each  
180 stimulus condition presented in random order. Six data blocks (2 electrodes x 3 repeats) were  
181 collected across three sessions lasting 2 to 3 hours each.

#### 2.1.5. Modeling

182 The loudness model of McKay et al. (2013b), incorporating refractoriness and temporal  
183 integration, was implemented and fitted to the threshold data averaged across electrodes and  
184 subjects. For each stimulus, the model first determines the magnitude of the neural response  
185 to each pulse relative to the very first pulse. Then, this activity is integrated by a sliding temporal  
186 integration window whose shape derives from normal-hearing psychoacoustic data (Oxenham,  
187 2001). Such temporal integration window models have previously been shown to account for  
188 normal hearing behavior on a variety of tasks such as level increment detection or forward  
189 masking (Oxenham & Moore, 1994; Moore et al., 1996; Oxenham, 2001). The shape of the  
190 temporal window is given by:

$$W(t) = (1 - w) \exp\left(\frac{t}{T_{b1}}\right) + w \exp\left(\frac{t}{T_{b2}}\right), t < 0, \quad (\text{eq. 1})$$

$$W(t) = \exp(-t/T_a), t \geq 0$$

191 where  $t$  is the time relative to the peak of the window,  $T_{b1}$  and  $T_{b2}$  are two time constants  
192 modeling the decay of forward masking,  $w$  weights the relative importance of these two time  
193 constants and  $T_a$  is the time constant modeling the decay of backward masking. Similar to



199 McKay et al. (2013b), we used the parameter values obtained by Oxenham (2001):  $T_{b1}=4.6$   
1 ms,  $T_{b2}=16.6$  ms,  $w=0.17$ , and  $T_a=3.5$  ms.

201 Finally, the overall excitation is assumed to correspond to the maximum output of the  
202 integrator across the stimulus. The model makes the assumption that the threshold difference  
203 between two stimuli corresponds to the difference in current level needed to obtain the same  
204 maximum output of the integrator.

205 In the present case, the model predicts a threshold difference between each stimulus  
206 and our reference pulse train CLIN1/BUPS1. For CLIN1/BUPS1, there is only one pulse  
207 presented every 32 ms and complete recovery from refractoriness is assumed between  
208 periods, meaning that the neural responses produced by all pulses are identical. For a higher  
209 number of pulses per period, the neural response produced by the first pulse is assumed to be  
210 the same as for CLIN1/BUPS1. The response produced by subsequent pulses *within* each  
211 period, however, is assumed to be reduced by a factor  $\alpha$  for CLIN and  $\beta$  for BUPS compared  
212 to that to the first pulse. Refractory effects are assumed to fully recover between periods for  
213 all stimuli except for CLIN32. For CLIN32, which is a continuous 1000-pps pulse train, the  
214 responses to all pulses (except the very first one) of the whole stimulus are reduced by the  
215 same factor  $\alpha$ . This can be viewed as a constant effect of refractoriness across the period.  
216 Finally, the threshold difference between a given stimulus and the reference is assumed to be  
217 equal to the difference in dB between the excitation produced by this stimulus and that  
218 produced by the reference, divided by a parameter  $S$  representing the slope of the current  
219 versus neural excitation function in log/log units (c.f. McKay et al., 2013b for details). The three  
220 model parameters  $\alpha$ ,  $\beta$ , and  $S$  were fitted by minimizing the sum of the squared differences  
221 between model predictions and threshold data averaged across electrodes and subjects.

222

## 223 2.2. RESULTS

224

225 Figure 2A shows for each subject, the mean threshold as a function of number of pulses per  
226 period for both CLIN and BUPS stimuli for the two electrodes tested. Before computing the

227 correlations between BUPS and CLIN thresholds which was the main aim of this experiment,  
1  
2 228 all data except the CLIN1/BUPS1 thresholds were analyzed in a 3-way repeated measures  
3  
4 229 ANOVA with factors STIMULUS TYPE (CLIN and BUPS), ELECTRODE (apical and basal)  
5  
6 230 and NUMBER OF PULSES per period (2, 4, 8, 16 and 32). In case Mauchly's test of sphericity  
7  
8 231 was significant, the Greenhouse-Geissler correction was applied and corrected degrees of  
9  
10 232 freedom are indicated below. The analysis revealed no effect of ELECTRODE ( $F(1,8)=0.28$ ,  
11  
12 233  $p=0.6$ ) but significant effects of the main factors STIMULUS TYPE ( $F(1,8)=41.08$ ,  $p<0.001$ )  
13  
14 234 and NUMBER OF PULSES ( $F(1.11,8.92)=86.05$ ,  $p<0.001$ ). Not surprisingly, thresholds  
15  
16 235 decreased when the number of pulses within each period increased. This decrease, averaged  
17  
18 236 across electrodes, amounted to 1.2 dB and 1.9 dB per doubling of the number of pulses for  
19  
20 237 CLIN and BUPS, respectively (c.f. Figure 2B). The mean threshold difference between CLIN  
21  
22 238 and BUPS increased from 0.48 dB for 2 pulses to 3.43 dB for 32 pulses (significant NUMBER  
23  
24 239 OF PULSES by STIMULUS TYPE interaction:  $F(1.62,12.95)=27.87$ ,  $p<0.001$ ; c.f. Figure 2C).  
25  
26 240 Post-hoc t-tests with Bonferroni correction showed that the difference between CLIN and  
27  
28 241 BUPS was significantly larger for 32 pulses than for all other numbers of pulses and also larger  
29  
30 242 for 16 pulses than for 2 and 4 pulses. This specific result will be discussed in section 4.1. The  
31  
32 243 other interaction terms of the ANOVA were not significant.

33 244 The model predictions for BUPS and CLIN are shown by the dotted lines in Figure 2B  
34  
35 245 together with the mean thresholds across subjects. The model provides a good fit, showing  
36  
37 246 lower thresholds for BUPS than for CLIN for all conditions except for CLIN2/BUPS2.  
38  
39 247 Furthermore, the values of the fitted parameters  $\alpha$  (0.3) and  $S$  (1.9) were in the same range as  
40  
41 248 the parameters fitted on the threshold vs. pulse rate functions of McKay et al. (2013b) for whom  
42  
43 249  $\alpha$  was roughly equal to 0.55 and the optimal  $S$  was 1.7. Similar to the subjects' data, the  
44  
45 250 predicted threshold difference between BUPS and CLIN (dotted line in Figure 2C) increases  
46  
47 251 as a function of the number of pulses per period. This is specifically due to the shape of the  
48  
49 252 temporal integration window which attenuates the response to additional pulses more when  
50  
51 253 they are separated by large inter-pulse intervals. This makes the added pulses of CLIN  
52  
53 254 contribute less and less to the response relatively compared to the added BUPS pulses.  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65

255 As our final aim was to investigate whether BUPS may be used to predict the threshold  
1 of clinical stimuli, we calculated the correlation coefficients between the threshold for CLIN32  
2 256 of clinical stimuli, we calculated the correlation coefficients between the threshold for CLIN32  
3  
4 257 (which is a regular 1000-pps stimulus, similar to pulse trains used clinically) and the threshold  
5  
6 258 for the different BUPS stimuli, i.e. for the different numbers of pulses per period. Figures 3A  
7  
8 259 and 3B show these correlations for the apical and basal electrodes, respectively. The  
9  
10 correlation coefficients ranged from 0.65 for BUPS1 to 0.80 for BUPS32 for the apical electrode  
11 260  
12 and from 0.88 to 0.97 for the basal electrode (c.f. Table 3). After applying Bonferroni-Holm  
13 261  
14 correction for multiple comparisons, none of the coefficients obtained for the apical electrode  
15 262  
16 remained significant ( $p>0.05$ ) unlike the coefficients for the basal electrode which were all  
17 263  
18 significant ( $p<0.05$ ). Importantly, Mann-Kendall tests showed for both electrodes a trend for  
19 264  
20 increased correlation with increases in the number of pulses ( $S=13$ ,  $p=0.008$  for both  
21 265  
22 electrodes).  
23  
24 266

267 We also investigated whether the across-electrode CLIN32 threshold difference could  
28  
29 268 be accounted for by BUPS thresholds by correlating the differences in threshold between the  
30  
31 apical and basal electrodes for the CLIN32 and the different BUPS stimuli, again as a function  
32 269  
33 of the number of pulses per period of the BUPS (c.f. Table 3). The correlation coefficients  
34 270  
35 ranged from 0.78 to 0.84 and were all significant after Bonferroni-Holm correction ( $p<0.05$ ).  
36 271  
37 Here again, Mann-Kendall test revealed a significant trend for increased correlation with  
38 272  
39 increases in the number of pulses ( $S=11$ ,  $p=0.028$ ).  
40 273  
41

42 274 To summarize, these results demonstrate that an increasing part of the across-subject  
43  
44 275 threshold variance in clinical stimuli is captured by BUPS when increasing the number of  
45  
46 276 pulses per period. Therefore, BUPS appear to be a promising tool to use for eABR recordings.  
47  
48 More specifically, if we were able to predict the psychophysical threshold of BUPS stimuli using  
49 277  
50 eABR, we may be able to further infer the psychophysical threshold of a regular clinical high-  
51 278  
52 rate pulse train (called CLIN32 here) from this measure.  
53 279  
54

55 280

58 281

60 282

### 283 3. EXPERIMENT 2: ELECTROPHYSIOLOGICAL THRESHOLDS

1  
2 284  
3  
4 285 The aim of Experiment 2 was to investigate the possibility of recording eABRs to BUPS with a  
5  
6 286 large number of pulses and to test if the behavioral and electrophysiological thresholds for  
7  
8 287 BUPS correlate.

#### 10 288 11 12 13 289 3.1. METHODS

##### 14 290 15 16 17 291 *3.1.1. Subjects*

18  
19  
20 292 Ten subjects took part in this experiment, including eight who already participated in  
21  
22 293 Experiment 1 (i.e., all subjects except M005) and two who did not (M016 and M017) . The  
23  
24 294 stimuli were delivered to the implant using the same hardware and a similar Matlab interface  
25  
26 295 as in Experiment 1. All measures were performed within a single session lasting 3 to 4 hours.

##### 27 296 28 29 30 31 297 *3.1.2. Stimuli*

32  
33 298 eABRs were recorded in response to six BUPS stimuli (N=1, 2, 4, 8, 16 and 32) presented on  
34  
35 299 the most apical electrode only (electrode 1). In order to reduce the influence of the stimulus  
36  
37 300 artefacts in the recordings, the BUPS were presented in alternating polarity. This means the  
38  
39 301 electrical pulses were all anodic-first in the odd-numbered periods of the stimulus and cathodic-  
40  
41 302 first in the even-numbered periods. The phase duration was the same as in Experiment 1 for  
42  
43 303 subjects who participated in both experiments or was equal to the phase duration used in the  
44  
45 304 clinical map for the other participants (c.f. Table 1).

##### 46 305 47 48 49 50 51 306 *3.1.3. Threshold and MCL determination*

52  
53 307 At the beginning of the session, comfortably-loud levels (labelled as '7' on the loudness chart)  
54  
55 308 were first measured for the six BUPS stimuli using the same loudness chart as in Experiment  
56  
57 309 1. Because eABR measures require long stimulus presentations (several thousands of  
58  
59 310 repetitions), we checked that the comfortably loud levels obtained with 420-ms stimuli were

311 still comfortable when increasing the duration to 5 seconds. The subjects were informed that  
312 they would later have to listen to this sound for several minutes. In case a stimulus was  
313 perceived as too loud or uncomfortable, the level was decreased in steps of 0.1 dB until the  
314 subject judged it to be acceptable. Due to time limitations, detection thresholds were measured  
315 using a 1-up, 1-down procedure which aimed to be faster than the forced-choice procedure of  
316 Experiment 1. For each stimulus, the subjects were asked to raise their hands any time they  
317 heard a sound. The presentation level started at comfort and was manually decreased in steps  
318 of 0.5 dB until the subject could not hear it. Then it was increased in steps of 0.1 dB until it was  
319 detected again. Five reversals were obtained and the threshold was assumed to correspond  
320 to the average of the last 4 reversals. In addition to the threshold measures of the six BUPS  
321 stimuli to be used in the eABR measurements, we also measured detection thresholds for 420-  
322 ms anodic-first and cathodic-first 1000-pps pulse trains presented on electrode 1 (i.e. stimuli  
323 corresponding to CLIN32 of Expt. 1). All thresholds were measured twice in pseudo-random  
324 order and the average of the two values was kept for further analysis.

325

#### 326 *3.1.4. Electrically-evoked Auditory Brainstem Responses (eABR)*

327 For the eABR measurements, the participants seated in a comfortable reclining chair in an  
328 electrically-shielded, sound-attenuated room and were asked to rest or sleep with their eyes  
329 closed. The PC-based system controlled the timing of the stimulus presentations and delivered  
330 an external trigger to the evoked potential recording system (Microvitae,  $\mu\text{V}$ -ABR). Auditory  
331 brainstem responses were collected at a 30-kHz sampling rate with three Ag-AgCl scalp  
332 electrodes placed on the forehead (Fz - active), the nape of the neck (reference) and the  
333 earlobe contralateral to the implanted ear (ground). Electrode impedances were kept below 5  
334 k $\Omega$ .

335 To ensure that the neural responses were not contaminated by CI and muscular  
336 artifacts, online averaging was enabled using artefact rejection for visualizing purposes. All  
337 recording traces exceeding  $\pm 30 \mu\text{V}$  between 2-ms and 10-ms post-stimulus time were rejected  
338 from online averaging but were saved on the PC. Recording lasted until approximately three

339 thousand non-artefacted sweeps were reached for each stimulus and participant even though,  
1  
2 340 due to time restrictions or especially noisy recordings, this number was not always reached.  
3  
4 341 On average, 3417 sweeps (s.d. = 436) were obtained for each stimulus.  
5

6 342 eABR functions were collected for BUPS stimuli in the following order N=1, 4, 16, 2, 8,  
7  
8 343 and 32. For each stimulus, the recording usually started at a subthreshold level of 9  $\mu$ A to be  
9  
10 344 able to compare the suprathreshold recordings to it and then at levels corresponding to 100,  
11  
12 345 75 and 50% of the perceptual dynamic range. If there still was a detectable response at 50%,  
13  
14 346 the level was further decreased to 25%, otherwise, it was increased to 62.5% (i.e., the level  
15  
16 347 between 50 and 75%). The dynamic range was subsequently bisected depending on whether  
17  
18 348 or not a visually-detectable response was present in the recording. Except for a few exceptions  
19  
20 349 detailed below where eABRs were difficult or impossible to observe, between 4 and 7  
21  
22 350 recordings (4.8 on average) containing a detectable response were obtained for each stimulus  
23  
24 351 and subject.  
25  
26  
27  
28  
29  
30

### 31 353 3.1.5. *Data analysis*

32  
33 354 All analyses were performed using custom MATLAB scripts (MathWorks). First,  
34  
35 355 electrophysiological recordings were bandpass filtered between 70 and 2500 Hz using a 2<sup>nd</sup>  
36  
37 356 order Butterworth filter. Then, sweeps with activity exceeding  $\pm 30 \mu$ V between 2-ms and 10-  
38  
39 357 ms post-stimulus time were rejected as artefact. eABR traces were further averaged over a 0  
40  
41 358 to 15-ms window. Wave V peaks and troughs were identified visually based on the latency and  
42  
43 359 decrease in amplitude with decreasing stimulus level. Amplitudes were calculated as the  
44  
45 360 difference (in  $\mu$ V) between the positive peak and the following trough for wave V. Similar to  
46  
47 361 Bierer et al. (2011), the eABR threshold was arbitrarily defined as the current level for which  
48  
49 362 the amplitude of Wave V was 0.1  $\mu$ V. This threshold level was either interpolated from the  
50  
51 363 input-output growth function or, in case the smallest response obtained had an amplitude larger  
52  
53 364 than 0.1  $\mu$ V, it was *extrapolated* assuming a linear decrease of the amplitude growth function  
54  
55 365 from the two lower-level responses collected. The latency of wave V was defined as the time  
56  
57 366 difference between the positive peak and the stimulus onset.  
58  
59  
60  
61  
62  
63  
64  
65

367 3.2. RESULTS

368  
369 Two out of the ten subjects either showed no measurable eABR responses (M001) or only a  
370 response at the highest level for BUPS1 (M014). The following analyses are therefore  
371 restricted to the remaining eight subjects. An example of eABR responses for the different  
372 BUPS stimuli is shown in Figure 4 for subject M002. It was possible to record eABRs in all  
373 eight subjects up to 16 pulses. For 32 pulses, the artefact prevented us from observing wave  
374 V in 4 subjects. Long-lasting artefacts were also sometimes present for high numbers of  
375 pulses, as shown for BUPS16 in Figure 4. Because we were only able to measure responses  
376 to BUPS32 in 4 subjects, the analyses below encompass, except otherwise stated, the data  
377 obtained with all stimuli except BUPS32.

378  
379 *3.2.1. Analysis of wave V amplitudes at the minimum and maximum stimulation levels*

380 Figures 5A and 5B show the amplitude of wave V at the maximum stimulation level  
381 (corresponding to a comfortably loud percept) and at the minimum level at which a response  
382 could be detected, respectively. The minimum and maximum amplitude values were analyzed  
383 in a two-way repeated measures ANOVA with within-subject factors NUMBER OF PULSES  
384 (five levels: 1, 2, 4, 8 and 16 pulses) and STIMULATION LEVEL (two levels: min and max  
385 amplitudes). Not surprisingly, the analysis showed significantly larger amplitudes at high  
386 stimulation level (main effect of STIMULATION LEVEL:  $F(1,7)=74.7$ ,  $p<0.001$ ). The NUMBER  
387 OF PULSES did not significantly affect wave V amplitudes ( $F(4,28)=2.11$ ,  $p=0.11$ ). Moreover,  
388 the sensitivity of eABRs to changes in stimulation level did not significantly change when  
389 increasing the number of pulses (STIMULATION LEVEL by NUMBER OF PULSES interaction:  
390  $F(4,28)=1.83$ ,  $p=0.15$ ). Note that the above analysis on wave V amplitudes was performed for  
391 stimuli eliciting the same loudness percept (either near-threshold or at MCL). However, given  
392 both threshold and MCL decrease when increasing the number of pulses, this implies that for  
393 a fixed current level, the amplitude of wave V tended to be larger when the number of pulses  
394 in the stimulus increased.

### 3.2.2. Analysis of wave V latencies at the minimum and maximum stimulation levels

Figures 5C and 5D show the latency of wave V also at the maximum and minimum levels, respectively. The latency values were analyzed in a two-way repeated measures ANOVA which showed highly significant effects of STIMULATION LEVEL ( $F(1,7)=243.09$ ,  $p<0.001$ ), NUMBER OF PULSES ( $F(4,28)=11.27$ ,  $p<0.001$ ) and of their interaction ( $F(4,28)=11.99$ ,  $p<0.001$ ). This interaction was further examined in two additional one-way repeated measures ANOVA performed separately at the two levels. These analyses showed a significant effect of NUMBER OF PULSES at the minimum ( $F(4,28)=14.49$ ,  $p<0.001$ ) but not at the maximum level ( $F(4,28)=1.70$ ,  $p=0.18$ ). At the minimum level (Fig. 5D), the latency increased on average from 4.12 ms for BUPS1 to 4.60 ms for BUPS16. Post-Hoc Pairwise comparisons with Bonferroni correction showed significantly longer latencies for BUPS16 than for BUPS1 ( $p=0.011$ ), BUPS2 ( $p=0.008$ ) and BUPS4 ( $p=0.011$ ). This increased latency for a large number of pulses per period cannot be explained by differences in amplitude because, as previously shown, the amplitudes were similar across BUPS conditions at this minimum level (Fig. 5B). This result, therefore, suggests that at low levels, wave V of the eABR reflects some sort of short-term integration of neural activity or, alternatively, that the response to pulses presented later in the pulse sequence is larger than the response to the early pulses. This aspect of the data will be discussed in section 4.3.

### 3.2.3. Analysis of eABR thresholds

As the main aim of this experiment was to evaluate if eABR and behavioral thresholds for BUPS correlate, we arbitrarily defined the eABR threshold as the stimulation current level producing a wave V amplitude of 0.1  $\mu\text{V}$  (c.f. Bierer et al., 2011). These eABR thresholds were inferred from wave-V amplitude growth functions for the different BUPS conditions as shown in Figure 6 for subjects M016 and M017.

Similar to the psychophysical thresholds measured in Experiment 1 (c.f. Fig. 2), eABR thresholds decreased when increasing the number of pulses as shown in Figure 7A. This observation was confirmed by a one-way repeated measures ANOVA showing a highly



423 significant effect of the factor NUMBER OF PULSES ( $F(4,28)=21.16$ ,  $p<0.001$ ). Post-hoc  
424 pairwise comparisons using the Bonferroni correction showed the threshold to be significantly  
425 lower for BUPS16 than for BUPS1 ( $p=0.002$ ) and BUPS2 ( $p=0.003$ ), lower for BUPS8 than for  
426 BUPS1 ( $p=0.006$ ) and lower for BUPS4 than for BUPS1 ( $p=0.001$ ). The decrease in eABR  
427 threshold when doubling the number of pulses within the stimulus amounted to 1.1 dB  
428 (averaged across conditions and subjects). This value is smaller than the value found  
429 psychophysically in Experiment 1 (1.9 dB).

430 To test whether the *within-subject differences* in eABR thresholds obtained for different  
431 BUPS were related to the change in behavioral thresholds, we normalized the threshold of  
432 each subject relative to its mean threshold across conditions separately for behavioral  
433 thresholds and for eABR thresholds. The data points from all subjects were then pooled  
434 together, as shown in Figure 7B and further subjected to a correlation analysis. This  
435 normalization caused an additional loss of 1 degree of freedom per subject. The result showed  
436 a strong correlation between the normalized behavioral and eABR thresholds ( $r=0.89$ ,  $d.f.=34$ ,  
437  $p<0.001$ ). This means that about 80% of the within-subject variance in behavioral thresholds  
438 for the different BUPS conditions is captured by the eABR measurements.

439 Across-subject correlations between eABR thresholds for different number of pulses  
440 and clinical (behavioral) thresholds were also analyzed and are shown in Figure 8. The  
441 correlation coefficients ranged from 0.49 to 0.72 but none were significant after Bonferroni-  
442 Holm correction. In addition, contrary to the correlations reported in Experiment 1, there was  
443 no trend for increased correlation with increases in the number of pulses per period.

#### 4. DISCUSSION

444  
445  
446  
447 In sections 4.1 to 4.3, we discuss the main observations of Experiments 1 and 2, compare the  
448 results with data available in the literature and propose possible underlying mechanisms that  
449 may account for them. Section 4.4 focuses on the use of BUPS for objective fitting of CIs,  
450 which was the main aim of this study.

451 4.1. FACTORS AFFECTING PSYCHOPHYSICAL THRESHOLD DIFFERENCES  
1  
2 452 BETWEEN CLIN AND BUPS  
3

4 453  
5

6 454 Experiment 1 showed that psychophysical thresholds for both BUPS and CLIN  
7  
8  
9 455 decreased when increasing the number of pulses per period from 1 to 32. This result is  
10  
11 456 consistent with previous studies showing that increasing the number of pulses within a stimulus  
12  
13 457 (via an increase in stimulus duration and/or pulse rate) yields lower threshold (Donaldson et  
14  
15 458 al., 1997; Kreft et al., 2004; McKay et al., 2013a; Zhou et al., 2015). Below we discuss two  
16  
17 459 outcomes of Experiment 1: the fact that thresholds for BUPS were consistently lower than for  
18  
19  
20 460 CLIN for all numbers of pulses per period (c.f. Figure 2A, B) and that this threshold difference  
21  
22 461 increased when increasing the number of pulses (c.f. Figure 2C).  
23

24 462 We showed that both outcomes could be accounted for by the temporal integration  
25  
26 463 model of McKay et al. (2013b) which incorporates refractoriness and temporal integration. On  
27  
28 464 the one hand, the smaller inter-pulse intervals of BUPS increase the effect of refractoriness  
29  
30  
31 465 within each stimulus period compared to CLIN. This tends to *decrease* the overall amount of  
32  
33 466 activity for BUPS pulses. On the other hand, the smaller inter-pulse intervals of BUPS imply  
34  
35 467 that the overall neural activity produced within a period is more compressed in time than for  
36  
37  
38 468 CLIN and, therefore, more efficiently integrated by the temporal window. With the set of model  
39  
40 469 parameters derived from the data, this more efficient integration overcomes the effect of  
41  
42 470 refractoriness and predicts lower thresholds for BUPS than for CLIN. Furthermore, as the  
43  
44 471 number of pulses increases, more and more CLIN pulses start to fall outside the integration  
45  
46  
47 472 window, making the threshold difference between BUPS and CLIN even larger.  
48

49 473 In addition to the effects of refractoriness and central integration, several additional  
50  
51 474 processes that were not modeled may also influence the response of auditory nerve fibers  
52  
53 475 differently for CLIN and BUPS. Boulet et al. (2016) classified these processes depending on  
54  
55 476 their timescale range of operation. Let us first consider the processes occurring shortly after  
56  
57  
58 477 each pulse (facilitation and accommodation). First, there is evidence from computational  
59  
60 478 modeling (Boulet et al., 2016), single-unit recordings in cats (Zhang et al., 2007; Heffer et al.,  
61  
62  
63  
64  
65

1 479 2010) and eCAP measurements in humans (Hey et al., 2017) that the neural response to a  
2 480 pulse can be enhanced when it is shortly preceded by a subthreshold pulse. The time constant  
3  
4 481 of this *facilitation* phenomenon as measured in humans using eCAPs was found to be in the  
5  
6 482 100-150  $\mu$ s range (Tabibi et al., 2019). It should, therefore, be especially strong for BUPS but  
7  
8 483 less for CLIN, and should consequently produce the opposite effect as refractoriness, i.e.,  
9  
10  
11 484 lowering BUPS thresholds compared to CLIN. The potential effects of accommodation (also  
12  
13 485 sometimes referred to as *subthreshold adaptation*) are more difficult to predict. Accomodation  
14  
15 486 corresponds to the decreased response probability of a nerve fiber following a subthreshold  
16  
17 487 stimulus and should therefore have an opposite effect to facilitation. However, modeling work  
18  
19 488 suggests that the operating timescale of accomodation ranges from 0.5 to 5 ms, which is  
20  
21 489 slightly longer than the operating timescale of facilitation (Boulet et al., 2016). Given the  
22  
23 490 interpulse intervals within each BUPS sequence are much shorter than that (c.f. Table 2), it is  
24  
25 491 possible that the responses to each pulse were not affected much by this process for BUPS.  
26  
27 492 In contrast, the interpulse interval within each CLIN stimulus sequence is 1 ms suggesting  
28  
29 493 accommodation may have played a larger role in this case. This mechanism could therefore  
30  
31 494 be a contributor to the increased threshold difference between CLIN and BUPS observed when  
32  
33 495 increasing the number of pulses per period.  
34  
35  
36

37  
38 496 Finally, we have so far mostly reasoned on what may occur *within* each period of a  
39  
40 497 stimulus. It is worth noting that all stimuli except CLIN32 show large gaps (> 16 ms) between  
41  
42 498 the offset of a pulse sequence and the onset of the next pulse sequence (i.e. the next period).  
43  
44 499 These large gaps may have the effect of partially resetting spike-rate adaptation between  
45  
46 500 periods. This could, therefore, provide the opportunity to detect the stimulus across multiple  
47  
48 501 periods (via “multiple looks”, Viemeister and Wakefield, 1991; Donaldson et al., 1997). This  
49  
50 502 ability should be reduced for CLIN compared to BUPS because the gaps between periods are  
51  
52 503 longer for BUPS. For example, CLIN32 is a constant-rate pulse train and has been shown in  
53  
54 504 single-unit recordings to produce spike-rate adaptation across the whole stimulus duration  
55  
56 505 (Zhang et al., 2007). It is, therefore, possible that a stronger across-period adaptation for CLIN  
57  
58  
59  
60  
61  
62  
63  
64  
65

1  
2 506 than for BUPS also contributed to the increased threshold difference between BUPS and CLIN  
3 507 when increasing the number of pulses per period.

4 508 In conclusion, although our threshold data can simply be accounted for by only considering  
5 509 refractoriness and central integration, it is possible that they result from a more complex  
6 510 interplay between these different processes, especially since the effects of facilitation,  
7 511 accomodation and spike-rate adaptation may be partially counteracting each other and are  
8 512 expected to depend on the interpulse interval.

9 513

#### 10 514 4.2. CAVEAT OF USING DIFFERENT PHASE DURATIONS ACROSS SUBJECTS

11 515

12 516 As one aim of the present study was to use the same stimuli in the psychophysical and  
13 517 electrophysiological experiments, we anticipated that it would be easier to measure eABRs for  
14 518 pulse sequences having a short duration. This is why we chose to use the shortest phase  
15 519 duration possible for each subject in both experiments. One caveat arising from this  
16 520 experimental design is that the phase duration varied across subjects and may have provided  
17 521 an additional source of across-subject variance in the threshold data. During the analysis, we  
18 522 noticed that the subjects with relatively long phase durations were those showing the largest  
19 523 threshold drop when increasing the number of pulses per period. Phase duration was shown  
20 524 to correlate with the threshold difference between BUPS1 and BUPS32 ( $r=0.71$ ,  $d.f.=7$ ,  $p=0.03$ )  
21 525 and also with the threshold difference between CLIN1 and CLIN32 ( $r=0.69$ ,  $d.f.=7$ ,  $p=0.04$ ).  
22 526 This means that the longer the phase duration the larger the threshold drop when increasing  
23 527 the number of pulses per period. Thus it cannot be excluded that the stronger correlation  
24 528 between BUPS thresholds and CLIN32 found when increasing the number of pulses per period  
25 529 was also partly driven by this difference in phase duration.

26 530

27 531

28 532

29 533

534 4.3. MEASURING eABR TO PULSE TRAINS

1  
2 535  
3  
4 536 Below, we list three main results of Experiment 2 and discuss them in relation with previously  
5  
6 537 published data.

7  
8 538  
9  
10  
11 539 (i) *The wave-V amplitude vs. current level growth functions collected in Experiment 2*  
12  
13 540 *shifted towards lower level when increasing the number of pulses per period (c.f. Figure 6).*  
14  
15 541 *This suggests that for a fixed current level, increasing the number of pulses per period tends*  
16  
17 542 *to yield larger wave-V amplitudes.*

18  
19 543  
20  
21  
22 544 Davids et al. (2008a) measured eABRs following 500-pps pulse trains with durations  
23  
24 545 ranging from 2 ms (containing 2 pulses) to 10 ms. Their experiment was performed at a single  
25  
26 546 “comfortably loud” current level held constant for all stimulus durations. Contrary to our results,  
27  
28 547 they did not find larger wave-V amplitudes when keeping the current level fixed and increasing  
29  
30 548 the duration. One possible explanation for this discrepancy could be the large rate difference  
31  
32 549 between their stimuli and ours. In our case, the within-period pulse rate of BUPS varied from  
33  
34 550 14.3 to 29.4 kpps whereas their pulse rate was only 500 pps. It is possible that increasing the  
35  
36 551 number of pulses per period has a larger effect on the neural response amplitude at high rate,  
37  
38 552 i.e. that it produces larger perceptual and electrophysiological changes. This explanation would  
39  
40 553 be consistent with behavioral data showing that the slope of the threshold vs. stimulus duration  
41  
42 554 functions are steeper at high (1000 pps) than at low pulse rate (100 pps; Pfingst et al., 1991).  
43  
44 555 Moreover, our observation that wave-V amplitude increases when increasing the number of  
45  
46 556 pulses per period is consistent with the results of Kodera et al. (1983) showing that the ABR  
47  
48 557 of *normal-hearing* cats increases with stimulus duration up to 2-4 ms at 2000 Hz and up to 4-  
49  
50 558 8 ms at 500 Hz.

51 559  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65

560 (ii) The wave-V latency (relative to stimulus onset) of the eABR responses of Experiment  
1  
2 561 2 was similar across the different stimuli at most comfortable loudness levels but increased as  
3  
4 562 a function of the number of pulses per period at low level.  
5

6 563  
7  
8  
9 564 In another study, Davids et al. (2008b) fixed the stimulus duration of their stimuli at 2  
10  
11 565 ms and measured eABR responses for pulse trains having different rates (varying from 500 to  
12  
13 566 3600 pps) and also for a single pulse. They found no effect of stimulus condition on the mean  
14  
15 567 wave-V latency measured relative to the *offset* of the stimulus. Expressing their latencies in a  
16  
17 568 similar way as we did (i.e., relative to the onset), this may imply that the response latencies of  
18  
19 569 their 2-ms pulse trains were actually longer than that of their single pulse. This would be  
20  
21  
22 570 consistent with our observation that at low level, latency increases with the number of pulses  
23  
24 571 per period. Similarly, Kodera et al. (1983) found that the ABR latency of their acoustically-  
25  
26 572 stimulated cats increased as a function of duration and that this increase was larger at low  
27  
28  
29 573 levels.  
30

31 574 This leads us to discuss the cause of these eABR amplitude (i) and latency (ii)  
32  
33 575 increases as a function of the number of pulses per period. We think it may be the result of two  
34  
35 576 mechanisms. First, it is possible that wave V reflects the output of an *integration* of neural  
36  
37 577 activity across a few milliseconds, which would be consistent with the normal hearing cats'  
38  
39 578 data previously mentioned (Kodera et al., 1983) and would explain why the eABR response  
40  
41  
42 579 amplitude tends to grow when increasing the number of pulses (keeping the current level  
43  
44 580 fixed). Concerning the response latencies, at low levels, the probability of auditory nerve fiber  
45  
46 581 discharge may be similar for the different pulses within the BUPS sequence, thereby inducing  
47  
48  
49 582 an increase in latency when increasing the number of pulses. At high levels, however, most  
50  
51 583 fibers may discharge in response to the first pulse and be refractory to the subsequent pulses,  
52  
53 584 yielding similar response latencies for the different BUPS stimuli. This *integration* explanation  
54  
55 585 seems, however, difficult to reconcile with the observation by Davids et al. (2008b) that the  
56  
57  
58 586 eABR response amplitude was not larger for a 2-ms, 3600-pps pulse train than for a single  
59  
60 587 pulse presented at the same current level. Or it would mean that the very first pulse of their 2-

588 ms stimulus contributed almost exclusively to the neural response, e.g. due to nerve fibers  
1  
2 589 being in their refractory state or strongly adapted for the subsequent pulses. Another  
3  
4 590 explanation could be that the increased amplitude and latency do not arise from the integration  
5  
6 591 of neural activity but are the result of neural facilitation processes and that wave V represents  
7  
8 592 the aggregate (compound) of the responses to several individual pulses. Facilitation is  
9  
10  
11 593 expected to be stronger at our very high rates (BUPS) than at 3600 pps and is also more  
12  
13 594 effective at low than at high levels (Tabibi et al., 2019). It is therefore possible that at low  
14  
15 595 current levels, the response to individual pulses becomes larger and larger across the BUPS  
16  
17 596 period. Such a response build-up could in principle yield an increased amplitude of the  
18  
19 597 compound response (larger wave-V amplitude) and may also shift the *peak* of the compound  
20  
21 598 response in time, thereby producing an increase in wave-V latency. At high levels, however,  
22  
23  
24 599 as previously mentioned, the response may be dominated by the first pulse(s) in the train with  
25  
26 600 the later pulses contributing less because of refractoriness.

28 601  
29  
30  
31 602 (iii) *eABR thresholds (defined as the current level needed to reach a wave-V amplitude*  
32  
33 603 *of 0.1  $\mu$ V) decreased when increasing the number of pulses per period.*

35 604  
36  
37  
38 605 In contrast, Davids et al. (2008b) did not find an effect of pulse rate on eABR thresholds.  
39  
40 606 More specifically, threshold was not different between their single-pulse stimulus and their 2-  
41  
42 607 ms pulse trains (which contained 8 pulses at most). The cause of this discrepancy with our  
43  
44 608 data also remains unclear but may be due to different definitions of thresholds between studies  
45  
46 609 (lowest current at which wave V could be identified for Davids et al. vs. arbitrary fixed-amplitude  
47  
48 610 response here) or, once more, to differences in pulse rate. As discussed previously, the higher  
49  
50  
51 611 rate used in the present study is expected to yield a stronger effect of neural facilitation and a  
52  
53 612 more efficient integration within the hypothetical temporal integration window.

54 613  
55  
56  
57 614  
58  
59  
60 615

#### 616 4.4. IMPLICATIONS FOR CI FITTING

1  
2 617  
3  
4 618 Independently of the mechanisms underlying our observations, Experiment 2 showed a strong  
5  
6 619 within-subject correlation between behavioral and eABR thresholds for the different BUPS  
7  
8 620 stimuli. This suggests that part of the temporal integration observed behaviorally can be  
9  
10 621 captured by the eABR measurements. Note, however, that the final aim would be to use these  
11  
12 622 stimuli to predict clinical thresholds in patients. For it to be possible, it would be necessary that  
13  
14 623 the eABR thresholds for BUPS also correlate with clinical thresholds *across-subjects*. In  
15  
16 624 Experiment 2, there was no increased correlation between BUPS eABR thresholds and  
17  
18 625 behavioral clinical thresholds when increasing the number of pulses within the BUPS  
19  
20 626 sequence. This contrasts with the increased correlation observed in Experiment 1 when  
21  
22 627 comparing clinical and *behavioral* BUPS thresholds. While this result does not appear  
23  
24 628 encouraging, we think it is premature to draw conclusions on the potential usefulness of BUPS  
25  
26 629 for clinical threshold predictions for two reasons. First, as already stated in section 4.2, the  
27  
28 630 across-subject correlations reported in the present study may all be affected by across-subject  
29  
30 631 differences in phase duration and should, therefore, be taken with caution. Second, the size of  
31  
32 632 our subject sample remains small and Experiment 2 should only be considered as a first  
33  
34 633 attempt to evaluate the possibility to record eABRs to BUPS. Experiments involving a larger  
35  
36 634 number of subjects tested with the same phase duration are currently running in our labs to  
37  
38 635 identify if BUPS can provide a method to reliably predict clinical thresholds using eABR  
39  
40 636 measurements.  
41  
42  
43  
44  
45  
46  
47 637

#### 48 638 **ACKNOWLEDGEMENTS**

49 639 We thank the subjects for their participation and two anonymous reviewers for their  
50  
51 640 suggestions and constructive comments on a previous version of this manuscript. This work  
52  
53 641 was supported by a grant from the Agence Nationale de la Recherche (Grant No. ANR-11-  
54  
55 642 PDOC-0022).  
56  
57  
58  
59  
60 643



## 644 REFERENCES

- 1 645  
2 646 Bierer J. A. (2010). Probing the electrode-neuron interface with focused cochlear implant stimulation.  
3 647 *Trends in amplification*, 14(2), 84–95.  
4 648  
5 649 Bierer, J. A., Faulkner, K. F., & Tremblay, K. L. (2011). Identifying cochlear implant channels with poor  
6 650 electrode-neuron interfaces: electrically evoked auditory brain stem responses measured with the  
7 651 partial tripolar configuration. *Ear and hearing*, 32(4), 436–444.  
8  
9  
10 652  
11 653 Boulet, J., White, M., & Bruce, I. C. (2016). Temporal Considerations for Stimulating Spiral Ganglion  
12 654 Neurons with Cochlear Implants. *Journal of the Association for Research in Otolaryngology : JARO*,  
13 655 17(1), 1–17.  
14  
15 656  
16 657 Brown, C. J., Hughes, M. L., Lopez, S. M., & Abbas, P. J. (1999). Relationship between EABR thresholds  
17 658 and levels used to program the CLARION speech processor. *The Annals of otology, rhinology &*  
18 659 *laryngology. Supplement*, 177, 50–57.  
19  
20 660  
21 661 Carlyon, R. P., van Wieringen, A., Deeks, J. M., Long, C. J., Lyzenga, J., & Wouters, J. (2005). Effect of  
22 662 inter-phase gap on the sensitivity of cochlear implant users to electrical stimulation. *Hearing*  
23 663 *research*, 205(1-2), 210–224.  
24  
25 664  
26 665 Davids, T., Valero, J., Papsin, B. C., Harrison, R. V., & Gordon, K. A. (2008a). Effects of stimulus  
27 666 manipulation on electrophysiological responses in pediatric cochlear implant users. Part I: duration  
28 667 effects. *Hearing research*, 244(1-2), 7–14.  
29  
30 668  
31 669 Davids, T., Valero, J., Papsin, B. C., Harrison, R. V., & Gordon, K. A. (2008b). Effects of stimulus  
32 670 manipulation on electrophysiological responses of pediatric cochlear implant users. Part II: rate  
33 671 effects. *Hearing research*, 244(1-2), 15–24.  
34  
35 672  
36 673 Donaldson, G. S., Viemeister, N. F., & Nelson, D. A. (1997). Psychometric functions and temporal  
37 674 integration in electric hearing. *The Journal of the Acoustical Society of America*, 101(6), 3706–3721.  
38  
39 675  
40 676 Heffer, L. F., Sly, D. J., Fallon, J. B., White, M. W., Shepherd, R. K., & O'Leary, S. J. (2010). Examining  
41 677 the auditory nerve fiber response to high rate cochlear implant stimulation: chronic sensorineural  
42 678 hearing loss and facilitation. *Journal of neurophysiology*, 104(6), 3124–3135.  
43  
44 679  
45 680 Hey, M., Müller-Deile, J., Hessel, H., & Killian, M. (2017). Facilitation and refractoriness of the  
46 681 electrically evoked compound action potential. *Hearing research*, 355, 14–22.  
47  
48 682  
49 683 Kodera, K., Marsh, R. R., Suzuki, M., & Suzuki, J. (1983). Portions of tone pips contributing to  
50 684 frequency-selective auditory brain stem responses. *Audiology : official organ of the International*  
51 685 *Society of Audiology*, 22(3), 209–218.  
52  
53 686  
54 687 Kreft, H. A., Donaldson, G. S., & Nelson, D. A. (2004). Effects of pulse rate on threshold and dynamic  
55 688 range in Clarion cochlear-implant users. *The Journal of the Acoustical Society of America*, 115(5 Pt 1),  
56 689 1885–1888.  
57  
58 690  
59  
60  
61  
62  
63  
64  
65

691 Levitt H. (1971). Transformed up-down methods in psychoacoustics. *The Journal of the Acoustical*  
1 692 *Society of America*, 49(2), 467+.

2 693

3 694 Long, C. J., Holden, T. A., McClelland, G. H., Parkinson, W. S., Shelton, C., Kelsall, D. C., & Smith, Z. M.  
4 695 (2014). Examining the electro-neural interface of cochlear implant users using psychophysics, CT  
5 696 scans, and speech understanding. *Journal of the Association for Research in Otolaryngology : JARO*,  
6 697 15(2), 293–304.

7 698

8 699 Macherey, O., Carlyon, R. P., van Wieringen, A., & Wouters, J. (2007). A dual-process integrator-  
9 700 resonator model of the electrically stimulated human auditory nerve. *Journal of the Association for*  
10 701 *Research in Otolaryngology : JARO*, 8(1), 84–104.

11 702

12 703 McKay, C. M., & McDermott, H. J. (1998). Loudness perception with pulsatile electrical stimulation:  
13 704 the effect of interpulse intervals. *The Journal of the Acoustical Society of America*, 104(2 Pt 1), 1061–  
14 705 1074.

15 706

16 707 McKay, C. M., Chandan, K., Akhoun, I., Siciliano, C., & Kluk, K. (2013a). Can ECAP measures be used  
17 708 for totally objective programming of cochlear implants?. *Journal of the Association for Research in*  
18 709 *Otolaryngology : JARO*, 14(6), 879–890.

19 710

20 711 McKay, C. M., Lim, H. H., & Lenarz, T. (2013b). Temporal processing in the auditory system: insights  
21 712 from cochlear and auditory midbrain implantees. *Journal of the Association for Research in*  
22 713 *Otolaryngology : JARO*, 14(1), 103–124.

23 714

24 715 Mesnildrey, Q., Venail, F., Carlyon, R. P., & Macherey, O. (2020). Polarity Sensitivity as a Potential  
25 716 Correlate of Neural Degeneration in Cochlear Implant Users. *Journal of the Association for Research*  
26 717 *in Otolaryngology : JARO*, 21(1), 89–104.

27 718

28 719 Miller, C. A., Brown, C. J., Abbas, P. J., & Chi, S. L. (2008). The clinical application of potentials evoked  
29 720 from the peripheral auditory system. *Hearing research*, 242(1-2), 184–197.

30 721

31 722 Moore, B. C., Peters, R. W., & Glasberg, B. R. (1996). Detection of decrements and increments in  
32 723 sinusoids at high overall levels. *The Journal of the Acoustical Society of America*, 99(6), 3669-77.

33 724

34 725 Oxenham, A. J. (2001). Forward masking: adaptation or integration?. *The Journal of the Acoustical*  
35 726 *Society of America*, 109(2), 732–741.

36 727

37 728 Oxenham, A. J., & Moore, B. C. (1994). Modeling the additivity of nonsimultaneous masking. *Hearing*  
38 729 *Research*, 80(1), 105-18.

39 730

40 731 Pfingst, B. E., DeHaan, D. R., & Holloway, L. A. (1991). Stimulus features affecting psychophysical  
41 732 detection thresholds for electrical stimulation of the cochlea. I: Phase duration and stimulus  
42 733 duration. *The Journal of the Acoustical Society of America*, 90(4 Pt 1), 1857–1866.

43 734

44 735 Tabibi, S., Kegel, A., Lai, W. K., Bruce, I. C., & Dillier, N. (2019). Measuring temporal response  
45 736 properties of auditory nerve fibers in cochlear implant recipients. *Hearing research*, 380, 187–196.

46 737

47

48

49

50

51

52

53

54

55

56

57

58

59

60

61

62

63

64

65

738 Trune, D. R., Mitchell, C., & Phillips, D. S. (1988). The relative importance of head size, gender and age  
1 739 on the auditory brainstem response. *Hearing research*, 32(2-3), 165–174.  
2 740  
3 741 Viemeister, N. F., & Wakefield, G. H. (1991). Temporal integration and multiple looks. *The Journal of*  
4 742 *the Acoustical Society of America*, 90(2 Pt 1), 858–865.  
5 743 Zhang, F., Miller, C. A., Robinson, B. K., Abbas, P. J., & Hu, N. (2007). Changes across time in spike rate  
6 744 and spike amplitude of auditory nerve fibers stimulated by electric pulse trains. *Journal of the*  
7 745 *Association for Research in Otolaryngology : JARO*, 8(3), 356–372.  
8 746  
9 747 Zhou, N., Kraft, C. T., Colesa, D. J., & Pfingst, B. E. (2015). Integration of Pulse Trains in Humans and  
10 748 Guinea Pigs with Cochlear Implants. *Journal of the Association for Research in Otolaryngology : JARO*,  
11 749 16(4), 523–534.  
12 750  
13 751  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65

752 **TABLES**

753

Subject	Age (y)	CI use (y)	Etiology	Duration of deafness (y)	Electrode array
M001	52	4	post-chemotherapy	14	flex soft 31
M002	68	3	unknown	3	standard long
M004	74	6	unknown	10	standard long
M005	36	2	congenital hereditary	20	standard long
M010	36	6	congenital	16	standard long
M012	66	5	unknown	2	standard long
M013	72	1	unknown	1	standard long
M014	58	1	autoimmune disease	1	flex 28
M015	48	2	unknown	15	flex 28
M016	43	2	congenital hereditary	20	flex 28
M017	68	1	unknown	3	flex 28

754

755

**Table 1** : Subject details showing age (years), duration of cochlear implant use (years), etiology, duration of profound deafness (years), type of electrode array, electrodes tested (M016 abd M017 only took part in Expt. 2 and were therefore only tested on their most apical electrode) and phase duration in  $\mu$ s.

759

Subject	Electrodes tested	Phase dur. ( $\mu$ s)	Within-period rate (kpps)	BUPS1 dur. ( $\mu$ s)	BUPS2 dur. ( $\mu$ s)	BUPS4 dur. ( $\mu$ s)	BUPS8 dur. ( $\mu$ s)	BUPS16 dur. ( $\mu$ s)	BUPS32 dur. ( $\mu$ s)
M001	1 & 10	38	12.47	78	158	319	640	1281	2564
M002	1 & 11	25	18.45	52	106	215	432	865	1732
M004	1 & 12	25	18.45	52	106	215	432	865	1732
M005	1 & 10	25	18.45	52	106	215	432	865	1732
M010	1 & 8	15	29.24	32	66	135	272	545	1092
M012	1 & 10	33	14.25	68	138	279	560	1121	2244
M013	1 & 8	20	22.62	42	86	175	352	705	1412
M014	1 & 11	41	11.60	84	170	343	688	1377	2756
M015	1 & 11	21	21.65	44	90	183	368	737	1476
M016	1	24	19.16	50	102	207	416	833	1668
M017	1	21	21.65	44	90	183	368	737	1476

760

761

762

**Table 2**: Electrodes tested and stimulus parameters used in the two experiments including phase duration, pulse rate within a BUPS sequence and durations of the BUPS sequences.

763

764

765

766

767

768

769

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11 770  
12 771  
13 772  
14 773  
15 774  
16 775  
17 776  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65

#pulses	Apex	Base	Difference Apex-Base
1	0.651	<b>0.884</b>	<b>0.779</b>
2	0.619	<b>0.907</b>	<b>0.781</b>
4	0.666	<b>0.918</b>	<b>0.799</b>
8	0.745	<b>0.941</b>	<b>0.829</b>
16	0.789	<b>0.924</b>	<b>0.796</b>
32	0.805	<b>0.967</b>	<b>0.842</b>

**Table 3:** Results of the correlation analyses between behavioral thresholds for BUPS and behavioral thresholds for CLIN32. The first two columns show the correlation coefficients for analyses performed on the apical and basal electrode data. The third column shows the correlation coefficients for the between-electrode threshold differences. Bolded values indicate statistically significant correlations after Bonferroni-Holm correction ( $p < 0.05$ ).

777 **FIGURE CAPTIONS**

1 778  
2 779  
3 780 **Figure 1:** Schematic representation of the CLIN and BUPS stimuli used in Experiments 1 and  
4  
5 781 2. The pulse rate within period was 1000 pps for CLIN and was as fast as possible for BUPS.  
6  
7

8 782  
9  
10 783 **Figure 2:** (A) Results of Experiment 1 showing, for each subject, the psychophysical thresholds  
11  
12 784 as a function of the number of pulses per period for CLIN and BUPS and for the two electrodes.  
13  
14 785 (B) Symbols: Mean threshold drop (averaged across electrodes and subjects) as a function of  
15  
16 786 number of pulses expressed relative to the threshold for the CLIN1/BUPS1, Dotted line: model  
17  
18  
19 787 fit using McKay et al.'s temporal integration model. (C) Mean threshold difference between  
20  
21 788 CLIN and BUPS (averaged across electrodes and subjects) as a function of number of pulses  
22  
23 789 and model predictions (dotted line).  
24  
25

26 790  
27  
28 791 **Figure 3:** Evolution of the correlation coefficient between CLIN32 threshold and BUPS  
29  
30 792 threshold as a function of the number of pulses within a BUPS period. Panels (A) and (B) show  
31  
32 793 the across-subject correlations for the apical and basal electrodes, respectively. The values of  
33  
34 794 the correlation coefficients are given in Table 3.  
35  
36

37 795  
38  
39 796 **Figure 4:** Example of eABR waveforms collected in subject M002 for the different BUPS  
40  
41 797 conditions. The waveforms were shifted vertically for better visualization and ordered based  
42  
43 798 on the current level. The tick spacing on the y-axis corresponds to an amplitude difference of  
44  
45 799 2  $\mu$ V. The red crosses show the peak of wave V; this time point was taken to compute the  
46  
47  
48 800 latencies. The amplitudes were assumed to be equal to the difference in amplitude between  
49  
50 801 this peak and the next trough. The traces do not all start at time 0 because the trigger was sent  
51  
52 802 to the recording system when the last pulse of each period was presented.  
53  
54

55 803  
56  
57 804 **Figure 5:** (A) and (B) Wave V amplitudes measured at the maximum and minimum levels,  
58  
59 805 respectively, for the different subjects and across-subject mean. (C) and (D) Wave-V latencies  
60  
61  
62  
63  
64  
65

806 measured at the maximum and minimum levels, respectively, for the different subjects and  
1  
2 807 across-subject mean. For all panels, the thin lines represent individual subjects while the thick  
3  
4 808 line shows the mean and standard error across subjects.

5  
6 809  
7  
8  
9 810 **Figure 6:** Examples of input-output growth functions of wave V amplitudes obtained in two  
10  
11 811 subjects M016 and M017. The open symbols represent real data points of the functions while  
12  
13 812 the filled symbols are the thresholds (either interpolated or extrapolated from the actual  
14  
15 813 measurements). Threshold was assumed to correspond to the current level for which the  
16  
17 814 amplitude is equal to 0.1  $\mu\text{V}$ . These values were obtained by interpolation or extrapolation of  
18  
19 815 the growth functions.

20  
21  
22 816  
23  
24 817 **Figure 7:** (A) eABR thresholds as a function of number of pulses per period for individual  
25  
26 818 subjects and mean across subjects; (B) within-subject correlation between eABR and  
27  
28 819 behavioral thresholds for BUPS stimuli. Each color represent one BUPS condition, using the  
29  
30 820 same color code as in Figure 6.

31  
32  
33 821  
34  
35 822 **Figure 8:** Across-subject correlations between BUPS eABR thresholds and clinical thresholds  
36  
37 823 measured behaviorally for different number of pulses per BUPS period.

38  
39  
40 824  
41 825







Figure 2

[Click here to access/download/Modeling/Modeling\\_Figure2\\_BUPS1Paper\\_Rev1.eps](#)







Figure 4








Figure 6


### Subject M016






### Subject M017



Current level (dB re 1  $\mu$ A)







**COVER LETTER**

Dear Editor,

Please find our manuscript entitled “TEMPORAL INTEGRATION OF SHORT-DURATION PULSE TRAINS IN COCHLEAR IMPLANT LISTENERS: PSYCHOPHYSICAL AND ELECTROPHYSIOLOGICAL MEASUREMENTS” for submission to Hearing research. This is an original work that has not been published nor submitted to another journal.

Sincerely,

Olivier Macherey