



Orthogonal modes of a fully anisotropic and heterogeneous elastic medium

Laurent Seppecher

► To cite this version:

Laurent Seppecher. Orthogonal modes of a fully anisotropic and heterogeneous elastic medium. 2023. hal-04045491v1

HAL Id: hal-04045491

<https://hal.science/hal-04045491v1>

Preprint submitted on 24 Mar 2023 (v1), last revised 29 Jun 2023 (v4)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Orthogonal modes of a fully anisotropic and heterogeneous elastic medium

Laurent Seppecher*

March 24, 2023

Abstract

The aim of this short note is to give a synthetic presentation of the mathematical elements that are used to solve the elastic wave system of equations in a bounded anisotropic elastic body, in a general framework. In particular, the proof of existence of a basis of orthogonal modes is given. We explain how these modes can be used to efficiently approach dynamic problems in time or harmonic regimes.

The mathematical content of this note is an application of classical results from elliptic equation theory and from spectral theory of self-adjoint operators. Such elements can be found for instance in the well known books [3, 2] or in French [1] for scalar elliptic equations. Even if the mathematics described in this note are classical, their presentation in a synthetic way, directly applicable to anisotropic and heterogeneous elastic bodies, may be useful for shortening the study of the dynamics of such media.

We consider a bounded elastic body $\Omega \in \mathbb{R}^3$ attached to fixed referential on a part of its boundary. We investigate the existence of an orthogonal basis of modes and recall how these modes can be used to efficiently approach the solutions of the static, harmonic and dynamic elastic problems.

1 Notations

The elastic body Ω is characterized by a fully anisotropic 4th-order elastic tensor $C_{ijkl}(x)$ and a density $\rho(x)$. Its boundary is denoted $\partial\Omega$. The space of the 3×3 hermitian matrices is denoted $\mathcal{S}_3(\mathbb{C})$. The double dot product denotes the twice-contracted tensorial product. Depending on the situation we write

$$(C : S)_{ij} = \sum_{k\ell} C_{ijkl} S_{k\ell}, \quad (S : C)_{k\ell} = \sum_{ij} S_{ij} C_{ijkl} S_{k\ell}, \quad S : T = \sum_{ij} S_{ij} T_{ij}.$$

for any $S, T \in \mathcal{S}_3(\mathbb{R})$.

The space $H^1(\Omega)$ is the Sobolev space of complex valued square integrable functions whose the gradient is also square integrable. The space $H^1(\Omega)^3$ is three dimensional vectorial valued version of $H^1(\Omega)$.

*Institut Camille Jordan, Ecole Centrale de Lyon & UCBL, Lyon, F-69003, France

2 General hypotheses

The following hypotheses on the elastic medium are general and match both the classical framework of continuum mechanics and the mathematical theory of variational formulations that provides the well-posedness of the problem.

We assume that the elastic body Ω is Lipschitz smooth (the boundary is locally a graph of a Lipschitz function). We also assume that this body is rigidly attached on a open part Γ_{Dir} of its boundary $\partial\Omega$ to a fixed referential. We then make the three following assumptions on the elastic tensor \mathbf{C} .

It has bounded coefficients:

$$\mathbf{C} \in L^\infty(\Omega, \mathbb{R}^{3^4}), \quad (1)$$

it is symmetric on $\mathcal{S}_3(\mathbb{R})$:

$$\forall x \in \Omega, \quad \forall S, T \in \mathcal{S}_3(\mathbb{R}), \quad S : \mathbf{C}(x) : T = T : \mathbf{C}(x) : S, \quad (2)$$

and it is positive definite on $\mathcal{S}_3(\mathbb{R})$:

$$\exists \alpha > 0, \quad \forall x \in \Omega, \quad \forall S \in \mathcal{S}_3(\mathbb{R}), \quad S : \mathbf{C}(x) : S \geq \alpha \|S\|_2^2. \quad (3)$$

Remark that such tensor is characterized by 21 independent coefficients in dimension 3. We also assume that the density is bounded by above and by below by a positive value.

$$\rho \in L^\infty(\Omega) \quad \text{and} \quad \exists \beta > 0, \quad \forall x \in \Omega, \quad \rho(x) \geq \beta. \quad (4)$$

3 The elasto-static problem

The body is fixed on Γ_{Dir} and some boundary stress \mathbf{g} is applied on $\Gamma_{\text{Neu}} := \partial\Omega \setminus \overline{\Gamma_{\text{Dir}}}$. A internal stress \mathbf{f} is also applied inside Ω . Hence the displacement \mathbf{u} satisfies the following system of equations/boundary conditions:

$$\begin{cases} -\operatorname{div}(\mathbf{C} : \mathcal{E}(\mathbf{u})) = \mathbf{f} & \text{in } \Omega \\ \mathbf{u} = \mathbf{0} & \text{on } \Gamma_{\text{Dir}} \\ (\mathbf{C} : \mathcal{E}(\mathbf{u})) \cdot \mathbf{n} = \mathbf{g} & \text{on } \Gamma_{\text{Neu}}. \end{cases} \quad (5)$$

Theorem 1. *Define the space $\mathcal{H} := \{\mathbf{u} \in H^1(\Omega)^3 \mid \mathbf{u} = \mathbf{0} \text{ on } \Gamma_{\text{Dir}}\}$. If $\mathbf{f} \in L^2(\Omega)^3$ and $\mathbf{g} \in L^2(\Gamma_{\text{Neu}})^3$, then the problem (5) admits a unique solution \mathbf{u} in \mathcal{H} . Moreover, this solution satisfies the energy estimate*

$$\|\mathcal{E}(\mathbf{u})\|_{L^2(\Omega)} \leq c_1 \|\mathbf{f}\|_{L^2(\Omega)} + c_2 \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})}$$

where c_1 and c_2 are constants depending only on $\Omega, \Gamma_{\text{Neu}}$ and α from (3). In the case $\mathbf{g} = \mathbf{0}$, this problem defines a bounded linear operator $A : \mathbf{f} \in L^2(\Omega) \mapsto \mathbf{u} \in \mathcal{H}$.

Proof. The space \mathcal{H} is endowed with the inner product

$$\langle \mathbf{u}, \mathbf{v} \rangle_{\mathcal{H}} := \int_{\Omega} \mathcal{E}(\mathbf{u}) : \mathcal{E}(\mathbf{v})$$

and the associated norm $\|\mathbf{u}\|_{\mathcal{H}} := \langle \mathbf{u}, \mathbf{u} \rangle_{\mathcal{H}}^{1/2} = \|\mathcal{E}(\mathbf{u})\|_{L^2(\Omega)}$. This is indeed a norm (equivalent to the H^1 -norm) thanks to Poincaré (constant c_P) and Korn (constant c_K) inequalities:

$$\|\mathbf{u}\|_{H^1(\Omega)} \leq c_P \|\nabla \mathbf{u}\|_{L^2(\Omega)} \leq c_P c_K \|\mathcal{E}(\mathbf{u})\|_{L^2(\Omega)} = c_P c_K \|\mathbf{u}\|_{\mathcal{H}}.$$

The variational formulation of (5) reads

$$\int_{\Omega} (\mathbf{C} : \mathcal{E}(\mathbf{u})) : \mathcal{E}(\bar{\mathbf{v}}) = \int_{\Omega} \mathbf{f} \cdot \bar{\mathbf{v}} + \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \bar{\mathbf{v}}, \quad \forall \mathbf{v} \in \mathcal{H}. \quad (6)$$

The left-hand side bilinear form $a(\mathbf{u}, \mathbf{v})$ is continuous in \mathcal{H} :

$$|a(\mathbf{u}, \mathbf{v})| \leq \|\mathbf{C}\|_{L^\infty(\Omega)} \|\mathbf{u}\|_{\mathcal{H}} \|\mathbf{v}\|_{\mathcal{H}}.$$

The right-hand side linear form $L\mathbf{v}$ is continuous in \mathcal{H} :

$$\begin{aligned} |L\mathbf{v}| &\leq \|\mathbf{f}\|_{L^2(\Omega)} \|\mathbf{v}\|_{L^2(\Omega)} + \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})} \|\mathbf{v}\|_{L^2(\Gamma_{\text{Neu}})} \\ &\leq \|\mathbf{f}\|_{L^2(\Omega)} \|\mathbf{v}\|_{H^1(\Omega)} + c_T \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})} \|\mathbf{v}\|_{H^1(\Omega)} \\ &\leq c_{\text{PK}} \left(\|\mathbf{f}\|_{L^2(\Omega)} + c_T \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})} \right) \|\mathbf{v}\|_{\mathcal{H}}. \end{aligned}$$

Where c_T is the norm of the trace operator $T : \mathcal{H} \rightarrow L^2(\Gamma_{\text{Neu}})$. Moreover a is coercive in \mathcal{H} :

$$|a(\mathbf{u}, \mathbf{u})| = \int_{\Omega} \mathcal{E}(\mathbf{u}) : \mathbf{C} : \mathcal{E}(\bar{\mathbf{u}}) \geq \alpha \int_{\Omega} |\mathcal{E}(\mathbf{u})|^2 \geq \alpha \|\mathbf{u}\|_{\mathcal{H}}^2.$$

Thanks to Lax-Milgram theorem, the variational formulation (6) admits a unique solution $\mathbf{u} \in \mathcal{H}$. Moreover, it satisfies

$$\begin{aligned} \alpha \|\mathbf{u}\|_{\mathcal{H}}^2 &\leq a(\mathbf{u}, \mathbf{u}) \leq |L\mathbf{u}| \leq c_{\text{PK}} \left(\|\mathbf{f}\|_{L^2(\Omega)} + c_T \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})} \right) \|\mathbf{u}\|_{\mathcal{H}}. \\ \|\mathbf{u}\|_{\mathcal{H}} &\leq \frac{c_{\text{PK}}}{\alpha} \left(\|\mathbf{f}\|_{L^2(\Omega)} + c_T \|\mathbf{g}\|_{L^2(\Gamma_{\text{Neu}})} \right). \end{aligned}$$

□

4 The elasto-dynamic problem

In the same setting, we look for elasto-dynamic solutions $\mathbf{U}(x, t)$ that satisfies the elastic wave system of equations/boundary conditions

$$\begin{cases} \rho \partial_{tt} \mathbf{U} - \text{div}(\mathbf{C} : \mathcal{E}(\mathbf{U})) = \mathbf{F} & \text{in } \Omega \times \mathbb{R} \\ \mathbf{U} = \mathbf{0} & \text{on } \Gamma_{\text{Dir}} \times \mathbb{R} \\ (\mathbf{C} : \mathcal{E}(\mathbf{U})) \cdot \mathbf{n} = \mathbf{G} & \text{on } \Gamma_{\text{Neu}} \times \mathbb{R}. \end{cases} \quad (7)$$

where the sources $\mathbf{F}(x, t)$ and $\mathbf{G}(x, t)$ can vary in space and time. We may look for time solutions under the frequency decomposition (Fourier) form

$$\mathbf{U}(x, t) = \int_{\mathbb{R}} \mathbf{u}(x, \omega) e^{i\omega t} d\omega.$$

We then write the sources as

$$\mathbf{F}(x, t) = \int_{\mathbb{R}} \mathbf{f}(x, \omega) e^{i\omega t} d\omega \quad \text{and} \quad \mathbf{G}(x, t) = \int_{\mathbb{R}} \mathbf{g}(x, \omega) e^{i\omega t} d\omega.$$

Then for each fixed frequency $\omega \in \mathbb{R}$, $\mathbf{u}(\cdot, \omega)$ satisfies the harmonic wave system of equations

$$\begin{cases} \text{div}(\mathbf{C} : \mathcal{E}(\mathbf{u})) + \rho \omega^2 \mathbf{u} = -\mathbf{f} & \text{in } \Omega \\ \mathbf{u} = \mathbf{0} & \text{on } \Gamma_{\text{Dir}} \\ (\mathbf{C} : \mathcal{E}(\mathbf{u})) \cdot \mathbf{n} = \mathbf{g} & \text{on } \Gamma_{\text{Neu}}. \end{cases} \quad (8)$$

The specific case $\mathbf{f} = \mathbf{0}$ and $\mathbf{g} = \mathbf{0}$ is called the homogenous harmonic problem and, as we will see, it is an eigenvalue problem. The following theorem states the existence of an orthogonal modal basis in a weighed space that depends on the density.

Theorem 2. *There exists a unique non decreasing sequence of eigenvalues $(\lambda_k)_{k \in \mathbb{N}}$ satisfying $\lambda_0 > 0$ and $\lim_{n \rightarrow +\infty} \lambda_k = +\infty$ and there exists a sequence of eigenmodes $(\mathbf{u}_k)_{k \in \mathbb{N}}$ in \mathcal{H} such that*

$$\forall k \in \mathbb{N}, \quad \begin{cases} \operatorname{div}(\mathbf{C} : \mathcal{E}(\mathbf{u}_k)) + \rho \lambda_k \mathbf{u}_k = \mathbf{0} & \text{in } \Omega \\ \mathbf{u}_k = \mathbf{0} & \text{on } \Gamma \\ (\mathbf{C} : \mathcal{E}(\mathbf{u}_k)) \cdot \mathbf{n} = \mathbf{0} & \text{on } \partial\Omega \setminus \Gamma. \end{cases}$$

The sequence $(\mathbf{u}_k)_{k \in \mathbb{N}}$ is complete in $L^2(\Omega)^3$ and orthonormal in the sense

$$\int_{\Omega} \rho \mathbf{u}_k \cdot \bar{\mathbf{u}}_{\ell} = \delta_{k\ell}, \quad \forall k, \ell \in \mathbb{N}.$$

Moreover, the eigenmodes \mathbf{u}_k are in $C^\infty(\Omega)^3$ and even in $C^\infty(\bar{\Omega})^3$ if Ω is smooth.

Proof. We first define a new Hilbert space

$$L_\rho^2(\Omega)^3 := \left\{ \mathbf{u} : \Omega \rightarrow \mathbb{R}^3 \mid \int_{\Omega} \rho |\mathbf{u}|^2 < +\infty \right\}$$

endowed with the inner product

$$\langle \mathbf{u}, \mathbf{v} \rangle_\rho := \int_{\Omega} \rho \mathbf{u} \cdot \bar{\mathbf{v}}.$$

This Hilbert space is isomorphic to the classic Hilbert space $L^2(\Omega)^3$ as $0 < \beta \leq \rho \leq \|\rho\|_{L^\infty(\Omega)} < +\infty$. We define now a linear operator A_ρ by

$$A_\rho \mathbf{f} := A(\rho \mathbf{f}) \tag{9}$$

where $A : L^2(\Omega) \rightarrow \mathcal{H}$ is the bounded linear operator given by Theorem 1. This new operator satisfies the following properties:

1. $A_\rho : L_\rho^2(\Omega)^3 \rightarrow L_\rho^2(\Omega)^3$ is bounded. Indeed,

$$\begin{aligned} \|A_\rho(\mathbf{f})\|_{L_\rho^2(\Omega)} &= \|\sqrt{\rho} A(\rho \mathbf{f})\|_{L^2(\Omega)} \leq \|\rho\|_{L^\infty(\Omega)}^{\frac{1}{2}} \|A(\rho \mathbf{f})\|_{L^2(\Omega)} \leq c_1 \|\rho\|_{L^\infty(\Omega)}^{\frac{1}{2}} \|\rho \mathbf{f}\|_{L^2(\Omega)} \\ &\leq c_1 \|\rho\|_{L^\infty(\Omega)} \|\sqrt{\rho} \mathbf{f}\|_{L^2(\Omega)} \leq c_1 \|\rho\|_{L^\infty(\Omega)} \|\mathbf{f}\|_{L_\rho^2(\Omega)}. \end{aligned}$$

2. The operator A_ρ is self-adjoint in $L_\rho^2(\Omega)^3$. Indeed, consider $\mathbf{f} \in L_\rho^2(\Omega)^3$ and call $\mathbf{u} := A_\rho \mathbf{f}$. It satisfies

$$a(\mathbf{u}, \mathbf{v}) = \int_{\Omega} \rho \mathbf{f} \cdot \bar{\mathbf{v}}, \quad \forall \mathbf{v} \in \mathcal{H}.$$

Then for any $\varphi \in L_\rho^2(\Omega)^3$,

$$\begin{aligned} \langle A_\rho \mathbf{f}, \varphi \rangle_\rho &= \langle \mathbf{u}, \varphi \rangle_\rho = \int_{\Omega} \rho \mathbf{u} \cdot \bar{\varphi} = \overline{a(A(\rho \varphi), \mathbf{u})} = \overline{a(A_\rho \varphi, \mathbf{u})} = a(\mathbf{u}, A_\rho \varphi) = \int_{\Omega} \rho \mathbf{f} \cdot \overline{A_\rho \varphi} \\ &= \langle \mathbf{f}, A_\rho \varphi \rangle_\rho. \end{aligned}$$

3. The operator $A_\rho : L_\rho^2(\Omega)^3 \rightarrow L_\rho^2(\Omega)^3$ is compact. Indeed, from the Rellich theorem, the canonical injection $I : H^1(\Omega) \hookrightarrow L^2(\Omega)$ is compact. By equivalence of topologies $I : \mathcal{H} \hookrightarrow L_\rho^2(\Omega)^3$ is also compact. Hence the operator $A_\rho : L_\rho^2(\Omega)^3 \rightarrow L_\rho^2(\Omega)^3$ is compact as the composition of $A_\rho : L_\rho^2(\Omega)^3 \rightarrow \mathcal{H}$ continuous and $I : \mathcal{H} \hookrightarrow L_\rho^2(\Omega)^3$ compact.

From the spectral theory of self-adjoint compact operators (see [2] chapter 6), A_ρ admits an orthogonal spectral decomposition: there exists a unique positive decreasing sequence of eigenvalues $(\mu_n)_{n \in \mathbb{N}}$ of \mathbb{R}^+ such that $\mu_n \rightarrow 0$ when $n \rightarrow +\infty$, and there exists an orthogonal Hilbert basis of eigenvectors $(\mathbf{f}_n)_{n \in \mathbb{N}}$ of $L_\rho^2(\Omega)^3$ such that

$$A_\rho \mathbf{f}_n = \mu_n \mathbf{f}_n, \quad \forall n \in \mathbb{N}.$$

Call now $\lambda_n := 1/\mu_n$ and $\mathbf{u}_n := A_\rho \mathbf{f}_n / \|A_\rho \mathbf{f}_n\|_{L_\rho^2(\Omega)} \in \mathcal{H}$. For all $n \in \mathbb{N}$, \mathbf{u}_n satisfies

$$-\operatorname{div}(\mathbf{C} : \mathcal{E}(\mathbf{u}_n)) = \rho \frac{\mathbf{f}_n}{\|A_\rho \mathbf{f}_n\|_{L_\rho^2(\Omega)}} = \rho \lambda_n \frac{A_\rho \mathbf{f}_n}{\|A_\rho \mathbf{f}_n\|_{L_\rho^2(\Omega)}} = \rho \lambda_n \mathbf{u}_n.$$

Moreover, $\|\mathbf{u}_n\|_{L_\rho^2(\Omega)} = 1$ and for any $n \neq m$, $\int_\Omega \rho \mathbf{u}_n \cdot \overline{\mathbf{u}_m} = 0$ because

$$\int_\Omega \rho A_\rho \mathbf{f}_n \cdot \overline{A_\rho \mathbf{f}_m} = \mu_n \mu_m \int_\Omega \rho \mathbf{f}_n \cdot \overline{\mathbf{f}_m} = \langle \mathbf{f}_n, \mathbf{f}_m \rangle_\rho = 0.$$

The smoothness of the eigenmodes \mathbf{u}_n is showed by recurrence and with the use of the Sobolev injection theorem. \square

5 Approximation of the solution using the modes

If the modes are computed in advance, they can be used to efficiently approach any solution of the elastic system by computing only few first coefficients of the modal decomposition of the solution.

5.1 Elasto-static solution

Let $\mathbf{u} \in \mathcal{H}$ be a solution of the elastostatic system with sources \mathbf{f} and \mathbf{g} . We can decompose \mathbf{u} on the eigenmodes:

$$\mathbf{u} = \sum_{n \in \mathbb{N}} \alpha_n \mathbf{u}_n \tag{10}$$

where $(\alpha_n) \in \ell^2(\mathbb{N})$. Hence

$$\begin{aligned} \sum_{n \in \mathbb{N}} \alpha_n \int_\Omega (\mathbf{C} : \mathcal{E}(\mathbf{u}_n)) : \mathcal{E}(\mathbf{v}) &= \int_\Omega \mathbf{f} \cdot \mathbf{v} + \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \mathbf{v}, \quad \forall \mathbf{v} \in \mathcal{H} \\ \sum_{n \in \mathbb{N}} \alpha_n \lambda_n \int_\Omega \rho \mathbf{u}_n \cdot \mathbf{v} &= \int_\Omega \mathbf{f} \cdot \mathbf{v} + \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \mathbf{v}, \quad \forall \mathbf{v} \in \mathcal{H}. \end{aligned}$$

Choosing $\mathbf{v} = \overline{\mathbf{u}_n}$ we get from the orthogonality of the modes in $L_\rho^2(\Omega)^3$,

$$\alpha_n \lambda_n = \int_\Omega \mathbf{f} \cdot \overline{\mathbf{u}_n} + \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \overline{\mathbf{u}_n}, \quad \forall n \in \mathbb{N}.$$

If we call $f_n := \int_\Omega \mathbf{f} \cdot \overline{\mathbf{u}_n}$ and $g_n := \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \overline{\mathbf{u}_n}$, we get the formula

$$\alpha_n = \frac{f_n + g_n}{\lambda_n}. \tag{11}$$

In a practical point of view, if one has knowledge of the modes $(\lambda_n, \mathbf{u}_n)$, given \mathbf{f} and \mathbf{g} , we fix a maximum mode number $N \in \mathbb{N}$ and compute the inner products $f_0, \dots, f_N, g_0, \dots, g_N$

and the corresponding coefficients $\alpha_0, \dots, \alpha_N$. The approximated solution is computed as the truncation of the series

$$\mathbf{u}^{\text{app}}(x) := \sum_{n=0}^N \alpha_n \mathbf{u}_n(x).$$

An L^2 -error bound can be computed. It depends both on the smoothness of \mathbf{f} and \mathbf{g} and the increase speed of the eigenvalues sequence.

5.2 Harmonic solutions

Let $\mathbf{u}(\cdot, \omega) \in \mathcal{H}$ be a solution of the of the harmonic system with sources \mathbf{f} and \mathbf{g} . We can decompose \mathbf{u} in space using the eigenmodes:

$$\mathbf{u}(x, \omega) = \sum_{n \in \mathbb{N}} \alpha_n(\omega) \mathbf{u}_n(x). \quad (12)$$

We then write

$$\begin{aligned} \sum_{n \in \mathbb{N}} \alpha_n(\omega) \int_{\Omega} (\mathbf{C} : \mathcal{E}(\mathbf{u}_n)) : \mathcal{E}(\mathbf{v}) - \omega^2 \alpha_n(\omega) \int_{\Omega} \rho \mathbf{u}_n \cdot \mathbf{v} &= \int_{\Omega} \mathbf{f}(\cdot, \omega) \cdot \mathbf{v} + \int_{\Gamma_{\text{Neu}}} \mathbf{g}(\cdot, \omega) \cdot \mathbf{v}, \quad \forall \mathbf{v} \in \mathcal{H} \\ \sum_{n \in \mathbb{N}} \alpha_n(\omega) (\lambda_n - \omega^2) \int_{\Omega} \rho \mathbf{u}_n \cdot \mathbf{v} &= \int_{\Omega} \mathbf{f} \cdot \mathbf{v} + \int_{\Gamma_{\text{Neu}}} \mathbf{g} \cdot \mathbf{v}, \quad \forall \mathbf{v} \in \mathcal{H}. \end{aligned}$$

Choosing $\mathbf{v} = \overline{\mathbf{u}_n}$ we get from the orthogonality of the modes:

$$\alpha_n(\omega) (\lambda_n - \omega^2) = \int_{\Omega} \mathbf{f}(\cdot, \omega) \cdot \overline{\mathbf{u}_n} + \int_{\Gamma_{\text{Neu}}} \mathbf{g}(\cdot, \omega) \cdot \overline{\mathbf{u}_n}, \quad \forall n \in \mathbb{N}.$$

If we call $f_n(\omega) := \int_{\Omega} \mathbf{f}(\cdot, \omega) \cdot \overline{\mathbf{u}_n}$ and $g_n(\omega) := \int_{\Gamma_{\text{Neu}}} \mathbf{g}(\cdot, \omega) \cdot \overline{\mathbf{u}_n}$, we get the formula

$$\alpha_n(\omega) = \frac{f_n(\omega) + g_n(\omega)}{\lambda_n - \omega^2}. \quad (13)$$

We clearly see the problem when ω^2 is equal to one eigenvalue λ_n . If $\omega^2 \notin \{\lambda_n \mid n \in \mathbb{N}\}$ it can be shown that the problem (8) admits a unique solution in \mathcal{H} and this solution is given by formulas (12) and (13).

5.3 Dynamic solutions

Let $\mathbf{U}(\cdot, t) \in \mathcal{H}$ be a solution of the of the time wave system of equations with sources \mathbf{f} and \mathbf{g} . This solution can be approached by Fourier recomposition mode-by-mode through the formula

$$\mathbf{U}(x, t) = \sum_{n \in \mathbb{N}} \int_{\mathbb{R}} \alpha_n(\omega) e^{i\omega t} d\omega \mathbf{u}_n(x), \quad \forall x \in \Omega, t \in \mathbb{R}, \quad (14)$$

where $\alpha_n(\omega)$ is given by (13).

References

- [1] G. Allaire. *Analyse numérique et optimisation: une introduction à la modélisation mathématique et à la simulation numérique*. Editions Ecole Polytechnique, 2005.

- [2] H. Brezis. *Functional analysis, Sobolev spaces and partial differential equations*, volume 2. Springer, 2011.
- [3] L. C. Evans. *Partial differential equations*, volume 19. American Mathematical Society, 2022.