

## Large-core hollow fibers for speckle-based displacement sensing

Jonas H Osório, Thiago D Cabral, Eric Fujiwara, Marcos a R Franco, Foued Amrani, Frédéric Delahaye, Frédéric Gérôme, Fetah Benabid, Cristiano M B Cordeiro

### ▶ To cite this version:

Jonas H Osório, Thiago D Cabral, Eric Fujiwara, Marcos a R<br/> Franco, Foued Amrani, et al.. Large-core hollow fibers for speckle-based displacement sensing.<br/> SBFoton (International Optics and Photonics Conference ), Jul 2023, Campinas, Brazil. pp.TS-MON-05-02.<br/> hal-04161095

## HAL Id: hal-04161095 https://hal.science/hal-04161095

Submitted on 13 Jul 2023

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Large-core hollow fibers for speckle-based displacement sensing

Jonas H. Osório Institute of Physics Gleb Wataghin University of Campinas Campinas, Brazil jhosorio@ifi.unicamp.br

Marcos A. R. Franco Institute for Advanced Studies Department of Aerospace Science and Technology São José dos Campos, Brazil marcos@ieav.cta.br

Frédéric Gérôme XLIM Institute, CNRS UMR 7252 University of Limoges Limoges, France gerome@xlim.fr Thiago D. Cabral School of Mechanical Engineering University of Campinas Campinas, Brazil tdcabral@ifi.unicamp.br

Foued Amrani Glophotonics Limoges, France fouedamrani@glophotonics.fr

Fetah Benabid XLIM Institute, CNRS UMR 7252 University of Limoges Limoges, France f.benabid@xlim.fr Eric Fujiwara School of Mechanical Engineering University of Campinas Campinas, Brazil fujiwara@fem.unicamp.br

Frédéric Delahaye Glophotonics Limoges, France fredericdelahaye@glophotonics.fr

Cristiano M. B. Cordeiro Insitute of Physics Gleb Wataghin University of Campinas Campinas, Brazil embc@ifi.unicamp.br

Abstract—We study the application of a large-core hollow fiber as a platform for displacement sensing. The sensor is assembled by inserting and appropriately moving a single-mode fiber in the empty core of the hollow fiber. Such a construction allows attaining a speckled intensity profile at the hollow fiber output, which is evaluated while one controllably displaces the single-mode fiber in its interior. Our results allow identifying this scheme as a promising means for exploring the multimode characteristics of hollow fibers in sensing contexts.

#### Keywords—fiber optics, photonic crystal fibers, hollow-core fibers, fiber sensors, speckle

#### I. INTRODUCTION

The striking recent advancements in the hollow-core photonic crystal fibers (HCPCFs) field place this family of waveguides in a prominent position among the currently available enabling technologies in photonics. Indeed, roughly after 30 years after their proposition, HCPCFs now stand out as the lowest-loss optical fibers working all along from the ultraviolet to the infrared [1, 2], and establish themselves as building blocks for several applications such as the development of optical sources and sensors [3, 4].

While high-order modes (HOMs) are omnipresent in the modal content of HCPCFs, in typical applications, the fiber design and the corresponding experimental setups are tailored so that, in practice, the fiber exhibits an effective single-mode operation. In this regard, HCPCF architectures can be designed to efficiently filter families of HOMs that might contaminate the fiber modal content, hence reaching a very high extinction ratio between HOMs and the core fundamental mode [5]. Similarly, the light launching setups can be set to afford appropriate alignment and mode-matching conditions to circumvent the multimode behavior of these fibers. This is particularly acute in high-power beam delivery applications using, for example, large-core HCPCFs (here referring to those exhibiting core diameters larger than 100  $\mu$ m) [6].

Alternatively, we here explore the multimodal behavior of a large-core HCPCF and investigate its application for detecting micrometric displacements. The sensor is built up by inserting and controllably moving a single-mode fiber (SMF) inside the HCPCF and has its operation assessed by evaluating the speckled output beam emerging from the system. We consider that our results widen the framework of HCPCF applications and offer a promising path for the exploration of their multimode behavior in the realm of fiber sensors.

#### II. SPECKLE-BASED DISPLACEMENT SENSING WITH A LARGE-CORE HCPCF

Fig. 1a exhibits the cross-section of the HCPCF we use in this investigation. It consists of a silica tubular-lattice HCPCF whose microstructure is formed by a set of 12 tubes (with a thickness of 680 nm), which delineates a 140  $\mu$ m-diameter hollow core. Fig. 1b shows the fiber's transmission spectrum between 480 nm and 1300 nm – measured for a fiber with a length of 4 m –, where one can discern two transmission bands, namely between 510 nm and 630 nm, and between 740 nm and 1230 nm. In the measurements to be described in the following, we used a laser source emitting at 543 nm. The vertical dashed line in Fig. 1b readily informs that this wavelength lies within one of the fiber's transmission bands.

Fig. 2a shows the experimental setup we employed for characterizing our sensing platform. By appropriately adjusting two alignment mirrors (M1 and M2) and an objective lens L1, light from a 543 nm laser source has been launched into a commercial SMF with operation in the visible



Fig. 1 (a) HCPCF cross-section and (b) its transmission spectrum between 480 nm and 1380 nm. The vertical dashed line indicates the wavelength of 543 nm.

J.H.O. and E.F. thank FAPESP (grants 2021/13097-9 and 2017/25666-2), and C.M. B. C, E. F., and M. A. R. F. thank CNPq for financial support (grants 403418/2021-6, 310650/2020-8, and 309989/2021-3).

range (Newport FSA, 125 µm external diameter), which had been in turn previously and cautiously introduced in the core of the HCPCF. We sequentially affixed the SMF to a motorized translation stage so it could be controllably moved inside the HCPCF during the displacement sensing measurements.

To collimate the beam emerging from the HCPCF and project it onto a camera, one placed an objective lens (L2 in Fig. 2a) at the HCPCF output. Fig. 2b shows the HCPCF output beam intensity distribution measured by the camera when the SMF end was 3 mm apart from the HCPCF extremity (an illustration of the fiber microstructure has been superposed to the image for eye guidance). We can observe that, due to the very dissimilar HCPCF and SMF core sizes, a highly multimode beam is attained at the HCPCF output, which makes it adequate for the realization of the specklebased sensing tests we will describe in the following. We inform that we run in-depth numerical and experimental studies on the evolution of the multimode propagation inside our large-core HCPCF and that the corresponding analyses will be reported in a forthcoming publication [7].

While the intensity distribution of a speckle pattern I(x, y) results from the interference of M modes, it can be algebraically described by Eq. 1, where a(x, y) and  $\phi(x, y)$  represent, respectively, the amplitude and phase distributions of the optical modes contributing to I(x, y). The subscripts m and n represent the m-th and n-th fiber modes.

$$I(x, y) = \sum_{m=1}^{M} \sum_{n=1}^{M} a_m a_n \exp[i(\phi_m - \phi_n)]$$
(1)

If the system from which the speckle pattern arises is disturbed by an external stimulus, the specklegram is expected to change from  $I_0(x, y)$ , namely the specklegram related to the initial state, to a different state I(x, y). This variation between the specklegrams is typically quantified by the zeromean normalized cross-correlation (ZNCC) metric, which is given by Eq. (2), where  $0 \le Z \le 1$  is the ZNCC coefficient and the overlines specify the average values of I and  $I_0$  [8]. Eq. (2) readily informs that Z decreases as I differs from  $I_0$ .

$$Z = \frac{\iint (I - \bar{I})(I_0 - \bar{I_0}) dx dy}{[\iint (I - \bar{I})^2 dx dy \iint (I_0 - \bar{I_0})^2 dx dy]^{1/2}}$$
(2)

Although the ZNCC metric is intrinsically robust and able to provide the framework for the realization of sensing measurements, one may calculate the extended ZNCC (EZNCC), which is able to enlarge the system measurement range [9]. It is computed by Eq. (3), where *EZ* is the EZNCC coefficient, EZ<sub>0</sub> is a reference level, *Z* is the ZNCC between *I* and  $I_0$ , and  $\tau = 0.7$  is an empiric threshold parameter [8].

$$EZ = EZ_0 - [Z(I, I_0, \tau) - 1]$$
(3)

Here, we employ the EZNCC metric to characterize our displacement sensing platform. This is done by computing the EZNCC coefficient as we controllably move the SMF inside the HCPCF towards the z-axis positive direction (as shown in Fig. 2a). The SMF departing point has been chosen to be that when its extremity was 3 mm apart from the HCPCF end-face. We mention that the specklegram images have been recorded using a low-cost webcam ( $800 \times 600$  pixels) and that the EZNCC has been calculated through MATLAB routines. It allows identifying our setup as a cost-effective platform.

Fig. 2c shows the graph of the EZNCC coefficient as a function of the SMF displacement inside the HCPCF.



Fig. 2 (a) Diagram of the experimental setup. (b) Measured HCPCF output profile for the case in which the SMF extremity is 3 mm apart from the HCPCF tip (a representation of the HCPCF cladding has been superposed to the image for eye guidance). (c) EZNCC versus the SMF displacement inside the HCPCF. The dashed blue line indicates a linear curve fitted to the experimental data ( $R^2 = 0.9996$ ).

Observation of the data allows recognizing a linear trend between the EZNCC and the SMF displacement. By linear fitting the experimental data, one can estimate a value of  $14.27 \pm 0.07 \text{ mm}^{-1}$  for our device's sensitivity ( $R^2 = 0.9996$ ). Additionally, if one considers the maximum random uncertainty as 0.01 (EZNCC units), one can reckon our system resolution at 0.7 µm. We can hence identify our platform as a valid path for the development of new displacement sensors and evaluate that this study has the potential of disclosing a set of other speckle-based sensing applications based on the multimode characteristics of large-core HCPCFs.

#### III. CONCLUSIONS

We studied the use of a large-core HCPCF as a platform for speckle-based displacement sensing. We understand that our investigation identifies a promising avenue for exploring the multimode behavior of HCPCFs in the sensing field.

#### REFERENCES

- J. H. Osório *et al.* "Hollow-core fibers with reduced surface roughness and ultralow loss in the short-wavelength range," Nat. Commun. 14, 1146 (2023).
- [2] G. T. Jasion *et al.* "0.174 dB/km hollow core double nested antiresonant nodeless fiber (DNANF)," 2022 Optical Fiber Communications Conference and Exhibition (OFC), 1-3 (2022).
- [3] M. Chafer *et al.* "Near- and middle-ultraviolet reconfigurable Raman source using a record-low UV/visible transmission loss inhibitedcoupling hollow-core fiber," Opt. Laser Technol. 147, 107678 (2022).
- [4] W. M. Guimarães *et al.* "Angle-resolved hollow-core fiber curvature sensing approach," Fibers 9, 11, 72 (2021).
- [5] F. Amrani *et al.* "Low-loss single-mode hybrid-lattice hollow-core photonic-crystal fibre," Light Sci. Appl. 10, 7 (2021).
- [6] B. Debord *et al.* "Ultra-large core size hypocycloid-shape inhibited coupling kagome fibers for high-energy laser beam handling," J. Light. Technol. 10, 7 (2021).
- [7] J. H. Osório *et al.* "Hollow-core fiber-based speckle displacement sensor," arXiv:2211.10217 (2022).
- [8] E. Fujiwara *et al.* "Polymer optical fiber specklegram strain sensor with extended dynamic range," Opt. Eng. 57, 116107 (2018).