



HAL
open science

Quantization-based simulation of spiking neurons: theoretical properties and performance analysis

Mariana Bergonzi, Joaquín Fernández, Rodrigo Castro, Alexandre Muzy,
Ernesto Kofman

► To cite this version:

Mariana Bergonzi, Joaquín Fernández, Rodrigo Castro, Alexandre Muzy, Ernesto Kofman.
Quantization-based simulation of spiking neurons: theoretical properties and performance analysis.
Journal of Simulation, In press, pp.1-24. 10.1080/17477778.2023.2284143 . hal-04301560

HAL Id: hal-04301560

<https://hal.science/hal-04301560>

Submitted on 23 Nov 2023

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Quantization-Based Simulation of Spiking Neurons: Theoretical Properties and Performance Analysis

Mariana Bergonzi^{ab}, Joaquín Fernández^a, Rodrigo Castro^{cd}, Alexandre Muzy^e,
Ernesto Kofman^{ab}

^aCIFASIS-CONICET, Rosario, Argentina; ^bFCEIA-UNR, Rosario, Argentina;
^cICC-CONICET, Buenos Aires, Argentina; ^dFCEyN-UBA, Buenos Aires, Argentina;
^eUniversité Côte d’Azur, CNRS, I3S, Nice, France

ARTICLE HISTORY

Compiled November 23, 2023

ABSTRACT

In this work we present an exhaustive analysis of the use of Quantized State Systems (QSS) algorithms for the discrete event simulation of Leaky Integrate and Fire models of spiking neurons. Making use of some properties of these algorithms, we first derive theoretical error bounds for the sub-threshold dynamics as well as estimates of the computational costs as a function of the accuracy settings. Then, we corroborate those results on different simulation experiments, where we also study how these algorithms scale with the size of the network and its connectivity.

The results obtained show that the QSS algorithms, without any type of optimization or specialization, obtain accurate results with low computational costs even in large networks with a high level of connectivity.

KEYWORDS

Hybrid Systems; Discontinuity Handling; Quantized State Systems; Spiking Neural Networks; Event-Driven Simulation

1. Introduction

The presence of discontinuities in systems of Ordinary Differential Equations (ODE) has been always a challenge for the numerical integration algorithms used for their simulation. Steps that integrate through discontinuities usually introduce unacceptable large errors and for this reason they must be avoided. For this purpose, it is necessary to detect the precise instant of time at which each discontinuity occurs in order to advance the simulation up to that time. Then, the integration can be restarted from the situation after the event occurrence (Cellier & Kofman, 2006). This process, known as *zero crossing detection and handling*, effectively avoids integrating through discontinuities at the price of large computational costs: the detection of the discontinuity times usually requires iterations (Park & Barton, 1996) and then restarting the simulation implies using a small step size.

Models of spiking Integrate and Fire neurons are a particular case of discontinuous ODEs. There, when some variable (usually the membrane potential) reaches a thresh-

old, the neuron fires producing a spike that not only resets some internal variables but that is also propagated through synaptic connections to other neurons in the network. When the size of a spiking neural network (SNN) grows, the time between successive spikes on the whole network becomes smaller, and consequently the maximum step size that can be used by the numerical algorithms is reduced. In addition, the computational cost of each step grows with the number of neurons.

Thus, simulating large SNN with standard zero crossing detection and handling algorithms becomes impractical and different solutions have been proposed to overcome that problem (Brette et al., 2007; Hansel, Mato, Meunier, & Neltner, 1998; Morrison & Diesmann, 2007; Shelley & Tao, 2001). Most of these solutions involve using a fixed small step size and whenever one or more spikes are detected within an integration step, instead of reducing the step size to the time instant of the first spike, some correction procedure is executed.

In the last two decades, a family of numerical ODE algorithms that replaces the classic time discretization by the quantization of the state variables was developed. These algorithms, called Quantized State Systems (QSS) methods (Cellier & Kofman, 2006; Kofman, 2002; Kofman & Junco, 2001; Migoni, Bortolotto, Kofman, & Cellier, 2013), approximate the ODEs in an event driven fashion where each step only involves local computations around a state variable that experiences a significant change. QSS methods, besides having strong theoretical properties regarding stability and error bounds, are particularly efficient to integrate discontinuous models (Kofman, 2004a) since zero crossing detection is straightforward and the occurrence of a discontinuity only provokes local computations similar to those of a normal step.

In this work, we first analyze different theoretical properties of QSS methods applied to the simulation of Leaky Integrate and Fire (LIF) spiking neurons that establish upper bounds for different errors (synaptic current, membrane potential, and firing times) and also estimate the expected computational costs. We also perform an exhaustive comparison of computational costs and errors for the different QSS algorithms in the simulation of a single neuron model. This analysis is then scaled up to a neural network level, studying the way the computational costs increase with the growth of the network and its connectivity.

We shall see that *out-of-the-box* QSS methods, without any optimization or specialization, offer a promising alternative for the simulation of SNNs, providing accurate results with low computational costs.

The article is organized as follows. Section 2 provides the background in which the rest of the work is based, including the description of LIF models and QSS algorithms. Then, Section 3 contains the main theoretical results and Section 4 reports and analyzes the simulation results. Finally, Section 5 presents the conclusions and the future work.

2. Background

In this section we introduce different ODE models of spiking neurons and the numerical methods used to simulate them. We then present the QSS family of methods and we continue by recalling the core concept of *activity* that allows analyzing the computational costs of QSS simulations. Finally, we introduce the software tool we have used to run the different experiments throughout this work and we discuss previous results where these methods were used to simulate spiking neurons.

2.1. Modeling and Simulation of Spiking Neurons

Spiking neurons are usually described by systems of ODEs with discontinuities associated to the firing times. Among the different models that have been proposed, we can mention the following ones:

- Hodgkin–Huxley (HH) model ([Hodgkin & Huxley, 1952](#)): this detailed model, developed in the 1950s, describes the electrical action potentials of neurons accounting for ion channel potentials. The main drawback of this model is that its simulation is computationally expensive, since each neuron is represented by four differential equations governed by 10 parameters. Thus, its usage is usually limited to networks formed by few neurons ([Izhikevich, 2003b](#)).
- Leaky Integrate and Fire (LIF) model ([Lapicque, 1907](#); [Stein, 1967](#)): this simplified model, introduced by Lapicque in 1907, is also based on an electrical representation. The circuit consists of a resistor and a capacitor in parallel, representing the leakage and capacitance of the membrane ([Burkitt, 2006](#)), respectively. The membrane capacitor is charged until it reaches a certain threshold, after which it discharges producing an action potential (spike). This behaviour is modeled by the differential equation

$$\dot{v}(t) = I(t) + a - bv(t), \quad \text{if } v(t) \geq v_u \text{ then } v \leftarrow c,$$

where $v(t)$ is the membrane potential, $I(t)$ is the input current and a , b , c , and v_u (the threshold) are the model parameters.

Several modifications have been proposed to improve the LIF model, such as the inclusion of a quadratic term on $v(t)$ (quadratic integrate and fire ([Ermentrout, 1996](#))), or the addition of a second state variable in order to represent more complex behaviors (integrate and fire or burst ([Izhikevich, 2003b](#))). Other variants are the exponential integrate-and-fire neuron ([Fourcaud-Trocmé & Brunel, 2005](#); [Fourcaud-Trocmé, Hansel, Van Vreeswijk, & Brunel, 2003](#)), the generalized integrate-and-fire neuron ([Brunel, Hakim, & Richardson, 2003](#); [Richardson, Brunel, & Hakim, 2003](#)) and the noisy LIF ([Gerstner, Kistler, Naud, & Paninski, 2014](#)). Izhikevich’s model ([Izhikevich, 2003a, 2007](#)), that consists of a second order nonlinear system (with states representing the membrane potential and the membrane recovery), can also be regarded as an extension of the LIF model.

The above presented models can be simulated with classic numerical methods ([Brette et al., 2007](#)), although some problems often appear since every time a neuron emits or receives a spike a discontinuity occurs. This constitutes a difficulty for conventional (time discretization-based) numerical methods because they cannot integrate across discontinuities since the polynomial approximations on which these numerical schemes are based are not valid on discontinuous functions. To overcome this problem, the methods must detect each discontinuity, then advance the simulation time to that instant, and finally restart the simulation from the new situation ([Cellier & Kofman, 2006](#)).

This whole process, which usually involves iterations to find the precise instant of the discontinuity occurrence, is computationally expensive. Moreover, in a model like that of a spiking neural network, the rate of occurrence of discontinuities (*i.e.*, spikes) grows with the number of neurons and then the maximum step size is limited to a smaller value as the size of the system grows.

To overcome these problems, different strategies have been implemented. A

simple solution is to use a small fixed step size that introduces a small error in the spiking times. A more precise and sophisticated approach is that of (Hanuschkin, Kunkel, Helias, Morrison, & Diesmann, 2010a) in which synapses communicate between neurons at discrete time instants (usually larger than the integration step size) making use of a correction mechanism to take into account the late arrival of incoming spikes.

A different approach is followed in (Zheng, Tonnelier, & Martinez, 2009), where the authors propose a numerical integration method for generic simulations of nonlinear spiking neuron models called *voltage-stepping*. This approach is based on the discretization of the voltage values in order to simulate with a local event-driven method and to take advantage of its properties. Then, in (Kaabi, Tonnelier, & Martinez, 2011) this approach is scaled up to a neural network level using the Discrete Event System Specification (DEVS) (Zeigler, Kim, & Praehofer, 2000).

Another approach also related to event-driven techniques is the one presented in (Mascart, Scarella, Reynaud-Bouret, & Muzy, 2022), where the authors modeled only the time of the spikes by a point processes and they developed a specific algorithm called Activity Tracking with Time Asynchrony (ATiTA).

2.2. Quantized State System Methods

QSS methods are a family of numerical integration algorithms that replace the time discretization of classic numerical integration algorithms by the quantization of the state variables.

Given a time invariant ODE in its State Equation System (SES) representation:

$$\dot{\mathbf{x}} = \mathbf{f}(\mathbf{x}(t), t) \quad (1)$$

where $\mathbf{x}(t) \in \mathbb{R}^n$ is the state vector, the first order Quantized State System (QSS1) method (Kofman & Junco, 2001) solves an approximate ODE called Quantized State System:

$$\dot{\mathbf{x}} = \mathbf{f}(\mathbf{q}(t), t). \quad (2)$$

Here, $\mathbf{q}(t)$ is the *quantized state* vector. Each component of the quantized state $q_i(t)$ follows a piecewise constant trajectory that only changes when its difference with the corresponding state $x_i(t)$ reaches the quantum ΔQ_i .

The quantized state trajectory is related to the corresponding state trajectory $x_i(t)$ as follows:

$$q_i(t) = \begin{cases} q_i(t_k) & \text{if } |x_i(t) - q_i(t_k)| < \Delta Q_i \\ x_i(t) & \text{otherwise} \end{cases}$$

for $t_k < t \leq t_{k+1}$, where t_{k+1} is the first time after t_k at which $|x_i(t) - q_i(t_k)| = \Delta Q_i$. In addition, we consider that initially $\mathbf{q}(t_0) = \mathbf{x}(t_0)$. This defines a *hysteretic quantization function* generating trajectories like those depicted in Figure 1.

Since the quantized state trajectories $q_i(t)$ are piecewise constant, then, provided that the system is autonomous (or that $\mathbf{f}(\cdot, t)$ is piecewise constant with t), the state derivatives $\dot{x}_i(t)$ also follow piecewise constant trajectories and, consequently, the states $x_i(t)$ follow piecewise linear trajectories. In non autonomous systems Eq. (2)

Figure 1. Typical QSS1 state and quantized state trajectories.

can be rewritten as

$$\dot{\mathbf{x}}(t) = \mathbf{f}(\mathbf{q}(t), t) = \tilde{\mathbf{f}}(\mathbf{q}(t), \mathbf{u}(t))$$

for some *input trajectories* $\mathbf{u}(t)$ that are approximated by piecewise constant trajectories $\mathbf{v}(t)$ such that the difference $v_i(t) - u_i(t)$ remains bounded by a certain quantity (given by the input quantization). That way, the QSS1 approximation actually integrates the system

$$\dot{\mathbf{x}}(t) = \tilde{\mathbf{f}}(\mathbf{q}(t), \mathbf{v}(t))$$

Due to the particular form of the trajectories, the numerical solution of Eq. (2) is straightforward and can be easily translated into a simulation algorithm.

Since QSS1 is only first order accurate and a good accuracy cannot be obtained without significantly increasing the number of steps, a second order accurate method called QSS2 was proposed (Kofman, 2002).

QSS2 has the same conceptual definition as QSS1, except that the components of $\mathbf{q}(t)$ are calculated to follow piecewise linear trajectories (rather than piecewise constant, as in QSS1), as shown in Figure 2. Then, the state derivatives $\dot{\mathbf{x}}(t)$ are computed as piecewise linear trajectories so that the states $\mathbf{x}(t)$ follow piecewise parabolic trajectories.

Figure 2. Typical QSS2 state and quantized state trajectories.

The idea was also extended in a similar way to obtain a third order accurate QSS method called QSS3, in which the quantized states $q_i(t)$ follow piecewise parabolic trajectories while the states follow piecewise cubic trajectories.

An important advantage of the QSS methods is that they handle discontinuities in a straightforward and very efficient manner (Kofman, 2004b). According to the order of the method, the quantized state variables follow piecewise constant, linear or parabolic trajectories. Then, detecting zero crossings is straightforward, as it involves solving a quadratic equation in the worst case (QSS3). Once a discontinuity is detected, the algorithm handles it as an ordinary step, in which only the state derivatives that are affected by that discontinuity are recomputed.

The efficiency in the discontinuity handling and the fact that the computations at each step are confined to the states that experience changes imply that these algorithms are very efficient to simulate large systems with heterogeneous activity involving discontinuities. The family of QSS methods also includes a set of algorithms called Linearly Implicit QSS (LIQSS), which are appropriate to simulate some stiff

systems (Migoni et al., 2013). LIQSS methods combine the principles of QSS methods with those of classic linearly implicit solvers. There are LIQSS algorithms that perform first, second, and third order accurate approximations: LIQSS1, LIQSS2, and LIQSS3, respectively. The main idea behind LIQSS methods is inspired by classic implicit methods that evaluate the state derivatives at future instants of time.

2.3. Theoretical Properties of QSS Methods

The fact that the difference between the states x_i and the corresponding quantized states q_i is bounded by the quantum ΔQ_i allows to rewrite Eq. (2) as

$$\dot{\mathbf{x}} = \mathbf{f}(\mathbf{x}(t) + \Delta\mathbf{x}(t), t) \quad (3)$$

where $\Delta\mathbf{x}(t) \triangleq \mathbf{q}(t) - \mathbf{x}(t)$ is a perturbation term bounded by the quantum.

In consequence, the use of a QSS algorithm is equivalent to the addition of a bounded perturbation to the original system and several properties regarding convergence, stability, and global error bounds can be easily derived (Cellier & Kofman, 2006; Kofman & Junco, 2001) for linear and non-linear systems. One of those properties establishes that the use of QSS in stable linear time invariant systems of the form $\dot{\mathbf{x}}(t) = \mathbf{A}\mathbf{x}(t) + \mathbf{B}\mathbf{u}(t)$ produces a global error that can be bounded by the formula¹

$$|\mathbf{x}(t) - \mathbf{x}_a(t)| \leq |\mathbf{V}| \cdot |\Re\{\Lambda\}^{-1} \cdot \Lambda| \cdot |\mathbf{V}^{-1}| \cdot \Delta\mathbf{Q} \quad (4)$$

where \mathbf{x} and \mathbf{x}_a are the QSS and the analytical solutions, and $\Lambda = \mathbf{V}^{-1}\mathbf{A}\mathbf{V}$ is the Jordan decomposition of matrix \mathbf{A} . That way, there is a linear dependence between the quantum and the global error bound.

For these reasons, the quantum plays an equivalent role to that of the tolerance in variable step size algorithms.

2.4. Activity and QSS Methods

The concept of activity associated to continuous signals was introduced in (Jammalamadaka, 2003; Muzy, Jammalamadaka, Zeigler, & Nutaro, 2011) in order to measure the rate of change of the signal. The formal definition of the activity metrics for a continuous signal $x_i(t)$ between an initial time t_0 and a final time t_f is given by:

$$A_{x_i(t_0, t_f)} \triangleq \int_{t_0}^{t_f} \left| \frac{dx_i(\tau)}{d\tau} \right| \cdot d\tau \quad (5)$$

This definition measures the distance between successive maxima and minima of a signal and results proportional to the number of segments used by a piecewise constant approximation like that of Figure 1.

With the goal of considering higher order approximations like that of Figure 2, this notion was extended in (Castro & Kofman, 2015), defining the concept of n -th order activity that takes into account not only the values but also the derivatives of the

¹The expression $|\mathbf{x}|$ denotes the component-wise absolute value of $\mathbf{x} \in \mathbb{R}^n$. Also, $\mathbf{a} \preceq \mathbf{b}$ expresses a set of component-wise inequalities $a_i \leq b_i$ on all the components of $\mathbf{a} \in \mathbb{R}^n$ and $\mathbf{b} \in \mathbb{R}^n$.

trajectory. Formally, given a signal $x_i(t)$, its n -th order activity in the interval $[t_0, t_f]$ is defined as

$$A_{x_i(t_0, t_f)}^{(n)} \triangleq \int_{t_0}^{t_f} \left| \frac{d^n x_i(\tau)}{d\tau^n} \right|^{1/n} \cdot d\tau \quad (6)$$

Using this definition, it is possible to estimate the number of segments of polynomials up to order $n - 1$ that are needed to approximate the signal $x_i(t)$ with an error less than ΔQ_i in the interval $[t_0, t_f]$ as

$$k_{x_i(t_0, t_f)}^{(n)}(\Delta Q_i) \approx \left(\frac{1}{\Delta Q_i} \right)^{1/n} \int_{t_0}^{t_f} \left| \frac{d^n x_i(\tau)}{d\tau^n} \right|^{1/n} \cdot d\tau = \frac{A_{x_i(t_0, t_f)}^{(n)}}{(\Delta Q_i)^{1/n}} \quad (7)$$

In QSS methods, using n equal to the order of the method (that uses polynomials of order up to $n - 1$ in the quantized states) this formula allows estimating the number of steps performed in the i -th state variable when a quantum size ΔQ_i is selected.

A simple consequence of Eq. (7) is that the number of steps grows linearly with the accuracy (i.e., with the inverse of the quantum size) in the first order accurate QSS1 and LIQSS1 methods. It also grows with the square root of the accuracy in QSS2 and LIQSS2 and with the cubic root of the accuracy in the third order schemes.

2.5. The Stand Alone QSS Solver

While some DEVS-based simulation tools have implementations of different QSS algorithms (D’Abreu & Wainer, 2005; Quesnel, Duboz, Ramat, & Traoré, 2007; Zeigler, Muzy, & Kofman, 2018), the most efficient and complete tool for the family of QSS solvers is the Stand-Alone QSS solver (Fernández & Kofman, 2014).

The models in this solver are described using a subset of the Modelica language (Mattsson, Elmqvist, & Otter, 1998) called μ -Modelica. The tool automatically translates the models into a C language piece of code, containing the set of ODEs with the corresponding zero crossing functions and event handlers for discontinuous cases. The tool also extracts structure information (incidence matrices) and produces the code for the symbolic evaluation of the Jacobian matrix. The C code produced is then linked to the different QSS algorithms (QSS and LIQSS of order one to three) or to classic ODE solvers like DOPRI (Dormand & Prince, 1980), DASSL (Petzold, 1982), CVODE (Cohen, Hindmarsh, & Dubois, 1996) and IDA (Hindmarsh et al., 2005).

The fact that the tool provides all the information about the structure of the model and the code for the symbolic evaluation of the sparse Jacobian matrices implies that the results obtained by this tool using classic ODE solvers are noticeably faster than the results obtained by other interfaces (Kofman, Fernández, & Marzorati, 2021). In addition, the fact that the solver uses the same piece of code for computing the ODE right hand side functions in the different algorithms (QSS and classic ODE integrators), allows fair performance comparisons among them.

2.6. QSS and SNN Simulation

There exist some previous related works applying state discretization to simulate spiking neural network models. Among them, the already mentioned voltage-stepping methods of (Kaabi et al., 2011; Zheng et al., 2009) are not formally QSS methods, but use the same ideas and lead to event-driven simulations.

Also, in (Grinblat, Ahumada, & Kofman, 2012) the authors explored the use of QSS algorithms in the simulation of spiking neuron networks based on Izhikevich’s model (Izhikevich, 2003a, 2007) while in (Castro, Kofman, & Cellier, 2011) the Delay QSS (DQSS) method was applied to simulate delayed cellular neural networks with impulsive effects. However, those results were obtained using a less efficient implementation of QSS provided by the PowerDEVS toolkit.

In (Fernandez, Kofman, & Bergero, 2017) QSS simulations of a SNN model adapted from (Vogels & Abbott, 2005) are presented showing that QSS algorithms are not only efficient but they can be also efficiently parallelized.

3. Main Theoretical Results

In this section we describe first the Leaky Integrate and Fire (LIF) model used along this work, taken from (Schmidt et al., 2018). We use two equivalent descriptions of that model, with one and two state variables. Then we derive theoretical properties of their QSS approximations including error bounds and computational complexity.

As expected, we will see that all the error bounds depend linearly on the quantum size and that the computational costs estimations depend on the $1/n$ -th power of the quantum where n is the order of the algorithm.

3.1. Model Description

The LIF model used in this work corresponds to that of (Schmidt et al., 2018) representing the synapses with instantaneous jumps and exponential decay. In this case the state variable is the membrane potential $V(t)$ and the corresponding sub-threshold dynamics is described by the following differential equation:

$$\frac{dV}{dt} = -\frac{V(t) - E_L}{\tau_m} + \frac{I_s(t)}{C_m} \quad (8)$$

where E_L is the leak potential, τ_m is the membrane time constant, and C_m is the membrane capacity and

$$I_s(t) = I_s(t_l) \cdot e^{-(t-t_l)/\tau_s} \quad (9)$$

is the synaptic current which is represented as an exponentially decaying signal that was restarted after receiving a spike. Here, t_l is the instant of time in which the neuron received the last incoming spike and τ_s is the postsynaptic current time constant.

When the neuron receives a spike, the synaptic current is updated according to the following law

$$I_s(t^+) \leftarrow I_s(t) + \Delta I \triangleq I_s(t) + J \quad (10)$$

where J is the excitatory synaptic strength.

Whenever the membrane potential reaches the firing threshold θ , a spike is emitted by the neuron and the potential is reset to the resting potential V_r .

In addition, the neuron enters a refractory period of duration τ_r in which the membrane potential keeps the value $V(t) = V_r$. After that period, the neuron comes back to the sub-threshold dynamics described by Eq. (8).

We shall consider two equivalent representations for the synaptic current. In the first one we directly use Eq. (9) to compute its evolution so that the entire neuron has a single state variable $V(t)$. We shall refer to this model as the *single-state* model.

In the second representation we shall compute $I_s(t)$ from an additional differential equation given by

$$\frac{dI_s}{dt} = -\frac{I_s(t)}{\tau_s} \quad (11)$$

such that the neuron model has now two states ($V(t)$ and $I_s(t)$).

Although both representations are equivalent, their numerical solutions will differ. The single-state model is a time-varying ODE and the accuracy of the approximation given by the QSS methods will depend not only on the quantum, but also on the order of the method and on the rate at which incoming spikes are received. The subthreshold dynamics of the two-state model is linear time-invariant and we shall see that stronger properties and simpler error bounds can be established. For this reason, more accurate results can be expected.

We analyze next the different theoretical properties of the QSS approximation of each representation.

3.2. QSS Sub-Threshold Error Bounds

QSS algorithms have a global error bound formula for linear time invariant systems depending on the quantum size ΔQ_i used in each variable, given by Eq. (4). Here, we shall specialize that formula for a particular case where the evolution matrix has a triangular structure, as it is the case of the two-state LIF model used in this work. We shall also extend the existing results to take into account the presence of impulsive input dynamics.

Theorem 1. *Error Bound.*

Consider an LTI system of the form

$$\begin{aligned} \frac{dz_1}{dt}(t) &= -az_1(t) + bz_2(t) + u_1(t) \\ \frac{dz_2}{dt}(t) &= -cz_2 + u_2(t) \end{aligned} \quad (12)$$

with $a > 0$, $b > 0$, $c > 0$, and consider its QSS approximation

$$\begin{aligned} \frac{dx_1}{dt}(t) &= -aq_1(t) + bq_2(t) + u_1(t) \\ \frac{dx_2}{dt}(t) &= -cq_2(t) + u_2(t) \end{aligned} \quad (13)$$

If a quantum ΔQ_i is used for variable x_i , then the maximum difference between the

solutions of both systems is given by

$$|x_1(t) - z_1(t)| \leq \Delta_1 \triangleq \Delta Q_1 + \frac{2b}{a} \Delta Q_2 \quad (14)$$

$$|x_2(t) - z_2(t)| \leq \Delta Q_2 \quad (15)$$

provided that the initial state verifies Eqs.(14)-(15).

This theorem, whose proof can be found in A.1, provides a bound for the error in both states of the model of Eq. (8) and Eq. (11) taking $z_1(t) = V(t)$ and $z_2(t) = I_s(t)$. However, it does not take into account the eventual presence of impulsive inputs like those that occur when an input spike is received. In order to overcome this difficulty, we extend next the results to that case.

Theorem 2. *Error bounds under impulsive input sequences.*

Consider an LTI system of the form

$$\frac{d\mathbf{z}}{dt}(t) = A\mathbf{z}(t) + B\mathbf{u}(t) + E \sum_{j=1}^N \delta(t - t_j) \quad (16)$$

where $\sum_{j=1}^N \delta(t - t_j)$ represents a sequence of input impulses with t_j being independent of the solution of Eq. (16). Consider also the QSS approximation given by

$$\frac{d\mathbf{x}}{dt}(t) = A\mathbf{q}(t) + B\mathbf{u}(t) + E \sum_{i=1}^N \delta(t - t_i) \quad (17)$$

Suppose that in absence of input impulses the condition $|\mathbf{x}(t_0) - \mathbf{z}(t_0)| \preceq \mathbf{e}_{\max}$ implies that $|\mathbf{x}(t) - \mathbf{z}(t)| \preceq \mathbf{e}_{\max}$ for all $t \geq t_0$. Then, in presence of an arbitrary impulse input sequence the condition $|\mathbf{x}(t_0) - \mathbf{z}(t_0)| \preceq \mathbf{e}_{\max}$ implies that $|\mathbf{x}(t) - \mathbf{z}(t)| \preceq \mathbf{e}_{\max}$ for all $t \geq t_0$.

With the result of this theorem, whose proof can be found in A.2, we can ensure that the error in the QSS approximation of the synaptic current $I_s(t) = z_2(t)$ computed from Eq. (11) is bounded according to Eq. (15) even in presence of an input sequence of impulses. Taking into account that the firing of a neuron does not have any effect on its synaptic current I_s , this error bound is also valid beyond the sub-threshold dynamics provided that the sequence of input spikes received does not change.

Taking also into account the single-state model, we also derive the next result that establishes an upper bound for the error in a time-varying system.

Theorem 3. *Error bound in a linear time-varying system Consider a first order ODE*

$$\frac{dz_1}{dt}(t) = -az_1(t) + u(t) \quad (18)$$

with $a > 0$ and $u(t)$ being a piecewise continuous trajectory. Let

$$\frac{dx_1}{dt}(t) = -aq_1(t) + v(t) \quad (19)$$

be a QSS approximation of order N where $v(t)$ and $u(t)$ verify

$$|v(t) - u(t)| \leq c(t - t_k)^N \quad (20)$$

where t_k is the time of the last QSS step. Then, assuming that $x_1(t_0) = z_1(t_0)$, it results that

$$|z_1(t) - x_1(t)| \leq \Delta Q_1 + \frac{c}{a} \Delta t_{\max}^N \quad (21)$$

where ΔQ_1 is the quantum and Δt_{\max} is the maximum interval between successive steps.

This result, whose proof can be found in A.3, establishes that the error bound depends not only on the quantum but also in the order n of the approximation and in the maximum time Δt_{\max} between successive steps.

In the context of the single-state model of the neuron given by Eqs.(8) and (9), the condition of Eq. (20) is verified since a QSS method of order N will approximate the synaptic current $I_s(t)$ using polynomial segments of order $n - 1$ and the error term will result proportional to Δt^n where Δt is the time elapsed since the last update of the approximated signal.

In this case, we can expect the error to decrease not only with the quantum size and method order, but also as the input spike rate grows. Anyway, as the quantum becomes smaller, the time between successive changes in $V(t)$ results smaller than the time between input spikes. In that case, Δt_{\max} is inversely proportional to the total number of changes in the quantized state. From the activity formula of Eq. (7) the number of steps is inversely proportional to $\Delta Q^{1/n}$. Then, Δt_{\max} is proportional to $\Delta Q^{1/n}$ and $(\Delta t_{\max})^n$ is proportional to ΔQ . This implies that the error in Eq. (21) becomes proportional to the quantum size.

3.3. QSS Firing Time and Firing Rate Error Bounds

The most important feature of a spiking neuron is the time at which the output spikes are produced. Thus, it is crucial to analyze the error that the QSS approximations introduce in the firing times. The following theorem provides an upper bound for this error

Theorem 4. *Firing Time Error Bound.*

Consider the LTI system of Eq. (12) and its QSS approximation of Eq. (13).

Let t_θ be the instant of time at which the analytical solution $z_1(t)$ crosses the threshold θ . Let \tilde{t}_θ be the instant of time at which $x_1(t)$ crosses θ .

Suppose also that $x_1(0) = z_1(0) = V_r$, $u_1(t) = \bar{u}_1$, and assume that $z_2(t)$ is constant and it verifies

$$z_2(t) = \bar{z}_2 > \frac{a(\theta + \Delta_1) - u_1}{b} \quad (22)$$

for all $t \in [0, t_\theta]$ with Δ_1 defined in Eq. (14). Then, the maximum difference between

the firing times of both systems is given by

$$|t_\theta - \tilde{t}_\theta| < \left| \frac{1}{a} \log \left(1 + \frac{\Delta Q_1 + \frac{2b}{a} \Delta Q_2}{\theta - \frac{b\bar{z}_2 + u_1}{a}} \right) \right| \quad (23)$$

A straightforward consequence of this theorem, whose proof can be found in A.4, is that the difference between the analytical firing period of a two-state neuron with constant synaptic current and that of its QSS approximation is equal to the bound in the firing time.

Corollary 1. *Firing Period Error Bound*

Consider an LTI system of Eq. (12) and its QSS approximation of Eq. (13) with $u_1(t) = \bar{u}_1$, and assume that $z_2(t)$ is constant and it verifies Eq. (22). Suppose also that $z_1(t)$ and $x_1(t)$ are reset to the value V_r whenever they reach θ .

Let T be the time period between two consecutive resets of $z_1(t)$, and let \tilde{T} be the time period between two consecutive resets of $x_1(t)$.

Then, the difference between both periods is bounded by

$$|\Delta T| = |T - \tilde{T}| \leq \Delta T_{\max} \triangleq \left| \frac{1}{a} \log \left(1 + \frac{\Delta Q_1 + \frac{2b}{a} \Delta Q_2}{\theta - \frac{b\bar{z}_2 + u_1}{a}} \right) \right| \quad (24)$$

The bound given by Eq. (24) can be simplified if we compute the relative error in the period assuming that the synaptic current $z_2(t)$ is large. The following proposition states this result:

Proposition 1. *Relative Error of the Firing Period*

Consider an LTI system of Eq. (12) and its QSS approximation of Eq. (13) under the same assumptions of Corollary 1. Assume also that $z_2(t)$ verifies

$$|b\bar{z}_2 + u_1| \gg a(\theta - V_r) \quad (25)$$

Then, the relative error between the firing periods of both systems is bounded by

$$\left| \frac{\Delta T}{T} \right| \leq \frac{\Delta T_{\max}}{T} \simeq \left| \frac{\Delta_1}{\theta - V_r} \right| \quad (26)$$

The proof of this proposition can be found in A.5.

This last result implies that when the synaptic current of the two-state neuron is sufficiently large, the relative error in the period is bounded by a magnitude that becomes independent on that current. Moreover, that error depends linearly on the quantum used in both variables.

Regarding the single-state neuron, very similar results can be easily derived based on the fact that the error in the membrane potential results proportional to the quantum size as analyzed after Theorem 3.

3.4. Activity and Computational Complexity

As introduced in Section 2.4, the activity of order n of a signal allows estimating the number of steps performed by a QSS algorithm in order to approximate that signal. In the context of the QSS approximation of a two-state neuron model, we shall exploit this idea to have a theoretical estimation of the computational costs associated to the simulation with QSS algorithms of different orders and different quantum sizes. For that goal, we shall compute the n -order activity of the synaptic current on a synapse s , $I_s(t)$, since this is the state that experiences more sudden changes. The reason is that a neuron usually receives many more spikes than it produces.

We consider then a neuron receiving a train of input spikes with a constant rate $1/T_s$. In order to compute the activity of the signal I_s between two consecutive input spikes, we can express the analytical solution of $z_2(t)$ in Eq. (12) as

$$z_2(t) = (I_0 + \Delta I)e^{-ct} = I_m e^{-ct}$$

where

$$I_m = I_0 + \Delta I \quad (27)$$

is the synaptic current $z_2(t = 0)$ at the beginning of each period, $\Delta I = J$ is the increment in the synaptic current after receiving a spike, and I_0 is the synaptic current at the end of the period, *i.e.*,

$$z_2(T_s) = (I_0 + \Delta I)e^{-cT_s} = I_0 \quad (28)$$

Thus, we can express I_0 depending on ΔI and T_s as

$$I_0 = \frac{\Delta I \cdot e^{-cT_s}}{1 - e^{-cT_s}} \quad (29)$$

The activity of order n of $z_2(t)$ in a period can be then expressed as

$$\begin{aligned} A_{0,T_s}^{(n)} &= \int_0^{T_s} \left| \frac{d^n(I_m \cdot e^{-ct})}{dt^n} \right| \frac{1}{n!} dt = \int_0^{T_s} \left| \frac{I_m \cdot (-c)^n \cdot e^{-ct}}{n!} \right| \frac{1}{n!} dt \\ &= \int_0^{T_s} \left(\frac{I_m \cdot c^n \cdot e^{-ct}}{n!} \right) \frac{1}{n!} dt = \left(\frac{I_m}{n!} \right) \frac{1}{n!} c \cdot \int_0^{T_s} e^{-\frac{c}{n}t} dt \\ &= \left(\frac{I_m}{n!} \right) \frac{1}{n!} c \left(\left. e^{-\frac{c}{n}t} \right|_0^{T_s} \right) = \left(\frac{I_m}{n!} \right) \frac{1}{n!} n \left(1 - e^{-\frac{c}{n}T_s} \right) \end{aligned}$$

From Eq. (28) we have

$$e^{-cT} = \frac{I_0}{I_0 + \Delta I} = \frac{I_0}{I_m} \quad (30)$$

and then

$$A_{0,T_s}^{(n)} = \left(\frac{I_m}{n!}\right)^{\frac{1}{n}} n \left(1 - \left(\frac{I_0}{I_m}\right)^{\frac{1}{n}}\right) = n \cdot \frac{I_m^{1/n} - I_0^{1/n}}{n!^{1/n}} \quad (31)$$

where I_m and I_0 can be computed from the system parameters using Eqs.(27) and (29).

Then, from Eq. (31) and using the estimate of the number of steps of Eq. (7), we can estimate the number of steps required by a QSS method of order n to approximate one period of the synaptic current as:

$$k_{x_i(t_0,t_f)}^{(n)}(\Delta Q_i) \approx \frac{A_{0,T_s}^{(n)}}{(\Delta Q_i)^{1/n}} = n \frac{I_m^{1/n} - I_0^{1/n}}{(n! \Delta Q_i)^{1/n}} \quad (32)$$

Equation (32) shows that the number of steps per period in I_s is inversely proportional to the $1/n$ -th power of the quantum in the current ΔQ_i .

Regarding the number of steps in the membrane potential $V(t)$, we can take into account that its variation is mainly driven by the synaptic current. During a QSS simulation, each step in the synaptic current will change the derivative of the membrane potential, which will possibly shorten the time of its next change. Thus, unless a very large or a very small quantum is used in V , we can expect that the number of steps in the membrane potential is similar to that on the synaptic current.

Regarding the single-state model of Eq. (8) and Eq. (9) it results more involved to compute the n -th order activity since the analytical solution for $V(t)$ has a more complex expression. Anyway, it is still valid that the number of steps will be inversely proportional to the $1/n$ -th power of the quantum size as established by Eq. (7).

4. Simulation Results and Performance Analysis

In this section we compare the performance of different numerical algorithms under different accuracy settings in the simulation of a single neuron. Then, we extend the analysis to populations of neurons with and without synaptic connections between them.

In all the simulations we used the *Stand Alone QSS Solver* tool (Fernández & Kofman, 2014) running on an Intel Core i5-9400 CPU @ 2.90GHz Intel i5 desktop computer under Ubuntu 20.04 OS. We considered both, the single and the two-state representations of the neuron model as presented in Section 3.1 with the set of parameters described in Table 1.

The models used in this section can be downloaded from <https://fceia.unr.edu.ar/~kofman/files/SNNmodels.zip> and the results reported can be reproduced using the Stand Alone QSS Solver, available at <https://github.com/CIFASIS/qss-solver>.

Model parameters	
Value	Description
$\tau_m = 10$ ms	membrane time constant
$\tau_r = 2$ ms	absolute refractory period
$\tau_s = 0.5$ ms	postsynaptic current time constant
$C_m = 250$ pF	membrane capacity
$V_r = -65$ mV	reset potential
$\theta = -50$ mV	fixed firing threshold
$EL = -65$ mV	leak potential
$J = 87.8$ pA	excitatory synaptic strength
$\nu_{bg} = 8$ spikes/s	average external spike rate
$k_{ext} = 940$	external inputs per population

Table 1. Model parameters taken from (Potjans & Diesmann, 2014).

4.1. Single Neuron Model

We simulated the models presented in Section 3.1 with different QSS methods (QSS, QSS2, QSS3)² changing the quantum value for the state variables ($V(t)$, and $I_s(t)$ in the two-state model). The quantum values were chosen from around one order of magnitude below the variation of the corresponding signals up to four orders of magnitude below, that is, we changed ΔQ_{I_s} from 10^{-1} nA to 10^{-4} nA and ΔQ_V from 10^{-1} mV to 10^{-4} mV.

In order to measure the errors, we also computed a reference solution using the classic DASSL solver with a very low tolerance (five orders of magnitude below the minimum tolerance settings used for the QSS algorithms). In addition, we simulated the models using DOPRI5 algorithm under different accuracy settings in order to compare the performance of QSS methods with that of a classic ODE solver. Among the different classic solvers that can be selected in the Stand Alone QSS Solver (DOPRI5, DASSL, CVODE, and IDA), DOPRI5 was the one exhibiting the best performance.

Besides using the parameters of Table 1, we adopted the following initial conditions: $V(0) = -65$ mV and $I_s(0) = 0.4$ nA in all the experiments. The input spike train of the neuron is a Poisson process with stationary rate $\nu_{ext} = k_{ext}\nu_{bg}$ generated from a pseudo-random number generator³ with fixed seed such that the different simulation runs can be compared under identical conditions.

The final simulation time was set to 1 second, after which the neuron received a total of 7,513 input spikes and emitted 10 output spikes.

Based on the results obtained, we analyze next the different errors and computational costs associated to each simulation.

4.1.1. Error Analysis

We computed errors in two different ways associated to each simulation:

- Maximum absolute error e_{\max} : is the largest absolute value of the difference between the reference and the approximate solution.
- Mean absolute error e_{mean} : is the mean value of the absolute difference between the reference and the approximate solution.

²We did not include Linearly Implicit QSS Methods because the models are not stiff.

³The QSS Solvers uses the standard stdlib C library for generating pseudo-random sequences.

For the membrane potential V we measured these errors up to the first emitted spike (sub-threshold dynamics) and only the mean absolute error for the whole simulation. We did not report the maximum membrane potential error because it will be always equal to the voltage jump between the threshold and the reset potential (even if the difference in the firing times is infinitely small).

For the current I_s we measured the maximum and the mean absolute errors during the whole simulation, only in the model with two state variables. In the single-state model, we also report the number of emitted spikes in each simulation (we do not report it in the two-state model because it was always correct).

Regarding the firing times, we measured the error between the time of the i -th firing in the reference solution and the time of the i -th firing of each numerical solution, reporting the mean firing time error (only for the simulations that give the correct number of emitted spikes). For the two-state model, we also reported the theoretical error bound given by Eq. (23).

All these errors are reported in Table 2 (two-state model) and Table 3 (single-state model). In all the tables, the column labeled as *Tol.* represents the quantum ΔQ used in QSS methods and the Relative and the Absolute Tolerance used in DOPRI5 algorithm.

The errors reported correspond to those obtained using a particular pseudo-random sequence for the Poisson input spike train. In Appendix B we also report the mean and the standard deviation of these errors after using 30 different pseudo-random sequences. Those results show that the errors obtained using different sequences are very similar, a fact that can be explained from the high rate at which input spikes are received. Thus, in the rest of the work we shall analyze the results obtained using single pseudo-random sequence.

Method	Tol [nA,mV]	I_s [nA]		V_{sub} [mV]		V [mV]	t_θ [s]	
		e_{mean}	e_{max}	e_{mean}	e_{max}	e_{mean}	e_{mean}	e_{theor}
QSS	1E-1	2.38E-2	7.25E-2	3.95E-2	1.41E-1	5.15E-2	7.17E-5	6.38E-4
	1E-2	2.51E-3	5.26E-3	4.36E-3	1.45E-2	5.12E-3	8.10E-6	6.20E-5
	1E-3	2.49E-4	6.01E-4	4.90E-4	1.68E-3	5.44E-4	9.65E-7	6.18E-6
	1E-4	2.51E-5	8.14E-5	4.58E-5	1.57E-4	4.85E-5	5.62E-8	6.18E-7
QSS2	1E-1	9.32E-3	8.53E-2	3.44E-2	1.18E-1	5.93E-2	9.41E-5	6.38E-4
	1E-2	3.52E-3	1.34E-2	4.33E-3	1.49E-2	5.99E-3	6.32E-6	6.20E-5
	1E-3	2.68E-4	1.27E-3	2.74E-4	1.46E-3	2.76E-4	3.24E-7	6.18E-6
	1E-4	2.53E-5	1.30E-4	2.58E-5	7.15E-5	3.04E-5	5.99E-8	6.18E-7
QSS3	1E-1	1.28E-2	8.65E-2	2.82E-2	8.79E-2	4.01E-2	6.21E-5	6.38E-4
	1E-2	3.67E-3	1.16E-2	3.73E-3	1.34E-2	5.57E-3	5.17E-6	6.20E-5
	1E-3	2.78E-4	1.14E-3	2.84E-4	1.19E-3	2.98E-4	4.58E-7	6.18E-6
	1E-4	2.47E-5	1.14E-4	2.24E-5	1.10E-4	2.68E-5	4.09E-8	6.18E-7
DOPRI5	1E-1	5.92E-2	4.56E-1	5.91E-2	8.67E-2	7.82E-2	1.17E-4	-
	1E-2	5.86E-2	4.42E-1	6.95E-3	1.03E-2	3.55E-2	1.02E-4	-
	1E-3	5.89E-2	4.39E-1	6.96E-4	1.16E-3	1.24E-2	4.60E-5	-
	1E-4	5.89E-2	4.39E-1	6.68E-5	1.35E-4	3.29E-3	1.21E-5	-

Table 2. Errors in the two-state model.

A noticeable feature is that the errors in all the simulations with the two-state model, irrespective of the quantum size, are small enough to preserve the qualitative features of the reference solution (for instance the number of emitted spikes, the length of the period between spikes, the signal shape). This fact was expected from the

Method	Tol [nA,mV]	V_{sub} [mV]		V [mV]	Output spikes	t_θ [s]
		e_{mean}	e_{max}	e_{mean}		e_{mean}
QSS	1E-1	2.02E+0	1.34E+1	4.06E+0	27	-
	1E-2	4.32E-1	7.72E-1	2.23E+0	17	-
	1E-3	9.76E-2	2.59E-1	7.24E-1	12	-
	1E-4	6.85E-2	1.95E-1	7.80E-2	10	7.99E-5
QSS2	1E-1	3.17E-1	5.05E-1	1.22E+0	7	-
	1E-2	6.20E-2	9.49E-2	1.25E-1	10	1.90E-4
	1E-3	4.59E-3	7.22E-3	1.05E-2	10	1.39E-5
	1E-4	4.80E-4	6.74E-4	7.49E-4	10	1.19E-6
QSS3	1E-1	5.50E-2	1.85E-1	7.96E-2	10	7.38E-5
	1E-2	1.89E-2	3.17E-2	3.76E-2	10	3.68E-5
	1E-3	3.92E-3	5.53E-3	7.32E-3	10	7.78E-6
	1E-4	4.39E-4	6.10E-4	6.49E-4	10	9.40E-7
DOPRI5	1E-3	3.19E-1	4.46E-1	1.56E+0	13	-
	1E-4	3.98E-2	5.78E-2	7.42E-2	10	1.20E-4
	1E-5	2.71E-3	3.65E-3	2.59E-2	10	8.58E-5
	1E-6	2.26E-4	2.97E-4	9.34E-3	10	3.07E-5

Table 3. Errors in QSS Simulation of the single-state model. Note that the number of output spikes in the reference solution is 10.

distinctive theoretical properties of QSS methods which are not shared by classic numerical integration schemes. In discrete time algorithms, for instance, increasing the step size may result in unstable solutions and/or unacceptable errors due to the missing of zero crossings (Cellier & Kofman, 2006).

In the single-state model the errors are significantly larger (particularly for lower order algorithms, which is consistent with Theorem 3). As a consequence, some features of the qualitative behavior are not properly preserved, resulting, for instance, in a different number of emitted spikes.

An example of this is illustrated in Figure 3 where the evolution of the membrane potential is shown for QSS2 varying the accuracy ($\Delta Q = 1E-1$ and $\Delta Q = 1E-2$) along with the reference solution (DASSL). Here we can observe an almost perfect trajectory for the smallest quantum, where the trajectories cannot be distinguished with the naked eye. However, for the largest quantum, a small sub-threshold error in the membrane potential causes a spike in an instant where the reference solution does not actually reach the threshold.

Figure 3. Membrane potential trajectories with QSS2 and the reference high accuracy solution (DASSL). Full simulation (left) and partial details (right).

4.1.1.1. Synaptic Current. The maximum error in I_s (in the two-state model) resulted very similar to the quantum size. According to Theorem 2, that error should be bounded by the quantum itself. However, due to numerical inaccuracies caused by round off errors these maximum errors result slightly larger. Measured mean absolute errors were about one order of magnitude less than the quantum size.

The classic algorithm DOPRI5, in turn, produces results in the current that are very similar irrespective of the tolerance, and the errors result larger than those obtained with QSS in all cases.

4.1.1.2. Sub-Threshold Membrane Potential. In the two-state model, the maximum sub-threshold error was in all cases very similar to the quantum size. According to Eq. (14) in Theorem 1, the maximum sub-threshold error is $|e_V| \leq \Delta Q_V + \frac{2b}{a} \Delta Q_{I_s} = \Delta Q_V + 8 \cdot 10^7 \Delta Q_{I_s} = 81 \Delta Q_V$ since we are using in all cases⁴ $\Delta Q_V = 10^6 \Delta Q_{I_s}$. This shows that the theoretical estimate was conservative for this state. Like in the previous case, the mean absolute errors were always below the quantum size. DOPRI5 produces similar errors to those of QSS methods in the membrane potential.

In the single-state model simulations, in all cases the errors were larger than those obtained in the other model with the same accuracy. As expected from Eq. (21) the lower order algorithms present larger errors. In the first order method (QSS) these errors can even affect some qualitative features (like the number of emitted spikes), except for the highest accuracy settings. The second and third order schemes obtain errors that are in the order of the quantum size. The best results in terms of accuracy, as expected, are obtained with the third order schemes since they approximate better the time varying input signal $I_s(t)$. QSS3, in particular, preserves the number of emitted spikes for all the considered quantum sizes.

Here, DOPRI5 produces significantly larger errors than QSS2 and QSS3 algorithms so the tolerances were reduced by two orders of magnitude to obtain similar results in terms of accuracy.

⁴The quantum was expressed in mV and nA in the different tables, but the model considers that the membrane potential and the synaptic current are measured in SI units (V and A, respectively).

4.1.1.3. Complete Membrane Potential Trajectory. In the two-state model, since the spikes are emitted with a very small time error, the resulting mean error of the membrane potential is in the order of the quantum size.

In the single-state model, there are several situations in which the spikes are not correctly emitted producing a large mean absolute error in the membrane potential (notice the situation shown in Figure 3). As expected, third order schemes are the most accurate.

Regarding DOPRI5, the errors in the membrane potential resulted larger than those of QSS methods in all cases.

4.1.1.4. Firing times. The firing time errors observed in the two-state model were almost negligible. Taking into account that the firing period of the neuron is on the order of $\frac{1}{10} = 0.1$ sec., the observed errors varied from 0.1% to 0.0001% of this period according to the quantum size.

The observed firing time errors were about one order of magnitude smaller than the theoretical error bound obtained from Eq. (23) that does not take into account the accumulation among different periods and considers a constant input. Thus, the behavior of the QSS algorithms regarding the firing times, which is a crucial feature of a spiking neuron simulation, was even better than what could be expected.

In the single-state model the errors were larger, and in some cases they could not be measured because the number of emitted spikes did not coincide with that of the reference solution. Anyway, the higher order schemes still obtained small errors at least for high accuracy settings.

DOPRI5 firing time errors resulted larger than those produced by QSS algorithms, even when using smaller tolerance settings.

4.1.2. Computational Costs

The results regarding computational costs are summarized in Table 4. A simple observation of these results shows that the number of steps performed by each algorithm grows with the accuracy settings. This is, the number of steps grows with the inverse of the quantum. This growth, as expected, is inversely proportional to the quantum in QSS, inversely proportional to the square root of the quantum in QSS2 and inversely proportional to the cubic root of the quantum in QSS3. Execution times change accordingly.

In all cases the CPU times using the single-state model are less than the ones using the two-state model for the same accuracy settings. However, under identical accuracy settings, the errors obtained using the single-state model are larger. This fact can be observed in Figure 4, that plots the CPU time against the mean error in the sub-threshold membrane potential for both models and for all QSS methods. The plot also shows that QSS2 offers the best trade-off in the two-state model (unless a very small error is requested) while QSS3 obtains the best performance in the single-state model (unless a large errors are accepted).

Method	Tol [nA,mV]	Two-state model			Single-state model	
		Simulation Steps		CPU Time	Simulation Steps	CPU Time
		I_s	V	[ms]	V	[ms]
QSS	1E-1	11,308	3,753	2.5	5,118	1.8
	1E-2	70,536	42,140	12.6	44,874	6.8
	1E-3	670,681	434,965	116.7	435,617	48.7
	1E-4	6,672,923	4,373,657	1,115.3	4,328,986	463.7
QSS2	1E-1	8,150	1,982	2.0	2,036	1.6
	1E-2	11,167	9,361	3.6	9,299	2.6
	1E-3	35,176	37,937	10.7	37,224	6.4
	1E-4	90,798	114,655	28.9	11,3969	17.3
QSS3	1E-1	7,841	2,970	4.4	3,164	3.3
	1E-2	11,352	7,151	7.4	7,597	4.5
	1E-3	18,683	14,403	12.0	12,555	6.2
	1E-4	31,047	28,452	20.9	22,356	9.7
DOPRI5	1E-1	7,609	7,609	2.9	7,683	3.0
	1E-2	7,651	7,651	2.9	7,648	3.3
	1E-3	7,880	7,880	2.9	7,747	3.0
	1E-4	8,554	8,554	3.1	8,241	3.1

Table 4. Computational costs in the simulation of the two-state and the single-state models

Figure 4. CPU Times vs. Mean Error in the sub-threshold membrane potential (V_{sub}) using different QSS algorithms.

In order to check that the mean number of steps performed by each method between consecutive spikes is in agreement with the analysis of Section 3.4, we compute next the activity of orders one to three and the expected number of steps per period of the synaptic current for the different accuracy settings in the two-state model.

The synaptic current variation is $\Delta I = J = 8.78 \cdot 10^{-2}$ nA. Then, from Eq. (29) with $c = \frac{1}{\tau_s}$ and $T = \frac{1}{\nu_{\text{ext}}}$ it results $I_0 \approx 0.519$ nA and $I_m = I_0 + \Delta I \approx 0.607$ nA. Thus, according to Eq. (31) and Eq. (32), the activity of orders 1 to 3 and the expected number of steps⁵ in each period of the synaptic current for the different quantum values are those reported in Table 5.

Order	$A^{(n)}$ [nA]	ΔQ_i [nA]	$k^{(n)}(\Delta Q_i) + 1$	QSS _n
1	$I_m - I_0 = 0.0878$	1E-1	1.878	1.51
		1E-2	9.78	9.39
		1E-3	88.8	89.28
		1E-4	879	888.3
2	$\frac{2(\sqrt{I_m} - \sqrt{I_0})}{\sqrt{2!}} = 0.083$	1E-1	1.26	1.08
		1E-2	1.83	1.49
		1E-3	3.62	4.68
		1E-4	9.28	12.09
3	$\frac{3(\sqrt[3]{I_m} - \sqrt[3]{I_0})}{\sqrt[3]{3!}} = 0.071$	1E-1	1.15	1.04
		1E-2	1.33	1.51
		1E-3	1.71	2.49
		1E-4	2.53	4.13

Table 5. Act. of order n , estimated and measured number of steps per period in I_s .

A very close agreement can be noticed for all methods. A final remark is that it is impossible to simulate with less than one step per period without missing input spikes. Table 5 shows that the number of steps per period in second order methods (up to $\Delta Q_i = 1\text{E-}2$) and third order methods (up to $\Delta Q_i = 1\text{E-}3$) are close to that minimum.

4.2. Model of Multiple Neurons

We consider now a model formed by N unconnected instances of the neuron model in order to analyze the growth of the computational costs with the number of neurons when using QSS and classic numerical algorithms.

In these configurations (using the single-state and the two-state model), each neuron has an independent input spike train following, as before, a Poisson distribution with a constant rate ν_{ext} generated from a pseudo-random sequence with a fixed seed.

For all neurons, the parameters were those of Table 1. The initial states were randomly chosen with uniform distribution $V(t = 0) \sim U[-65, -64]\text{mV}$, $I_s(t = 0) \sim U[0.4, 0.5]\text{nA}$.

We simulated both, the single-state and the two-state models varying the number of neurons from 10 to 10,000 until a final simulation time of $t_f = 0.1$ sec. We used QSS2 for the two-state model and QSS3 for the single-state model, as these methods offered the best performance in terms of CPU-time vs. accuracy in Figure 4. We selected different quantum values in order to measure the growth of the computational costs

⁵The expected number of steps is the result obtained from Eq. (32) plus one step corresponding to the arrival of the input spike.

with the accuracy settings and to check for convergence in the number of emitted spikes. We also simulated the models using DOPRI5.

The results are reported in Table 6 and the growth of the simulation time (CPU time) with respect to the number of neurons (N) is plotted in Figure 5.

Tol	N	Steps	CPU Time [ms]	Out Spikes	Steps	CPU Time [ms]	Out Spikes
Two-state model - QSS2				Single-state model - QSS3			
1E-1	10	9,589	2.0	10	10,738	3.6	10
	100	95,622	23.8	59	106,990	36.6	61
	1,000	955,748	329.4	660	1,069,560	460.1	666
	10,000	9,532,780	5,538.3	6,280	10,676,992	6,649.7	6,389
1E-2	10	21,798	3.7	9	15,225	5.1	9
	100	218,267	44.1	53	151,505	51.8	54
	1,000	2,179,150	631.4	628	1,514,438	643.6	637
	10,000	21,776,481	10,622.2	5,901	15,122,208	9,324.5	6,015
1E-3	10	73,694	10.0	9	20,216	6.4	9
	100	736,682	116.6	52	201,980	67.8	52
	1,000	7,360,380	1,778.2	623	2,016,058	860.7	625
	10,000	73,541,327	29,225.3	5,839	20,136,964	12,423.9	5,874
1E-4	10	206,240	25.9	9	30,033	9.2	9
	100	2,062,500	305.7	52	300,646	99.7	52
	1,000	20,601,643	4,649.8	623	3,001,045	1,234.7	623
	10,000	205,876,468	77,555.3	5,837	29,987,701	18,209.9	5,840
Two-state model - DOPRI				Single-state model - DOPRI			
1E-4	10	7,607	12.7	9	7,599	14.3	9
	100	75,450	1,081.4	52	75,410	1,211.1	52
	1,000	754,199	108,660.0	624	753,749	120,215.0	624
	10,000	7,523,758	1.104E+7	5852	7,520,462	1.20E+7	5,852

Table 6. Computational costs of the both models with N disconnected neurons

We can observe that:

- The number of steps grows linearly with the number of neurons N in QSS methods for all accuracy settings. This is an almost obvious result since each step is local to a state variable.
- In DOPRI5, the number of steps also grows linearly with N . This is due to the fact that the rate of occurrence of discontinuities grows with N and thus the maximum step size becomes proportional to $1/N$.
- The CPU time grows with $N \log(N)$ in QSS methods. This is due to the fact that the number of steps grows linearly with N and the simulation engine uses a binary-tree scheduler to find the time of the next change, which adds a $\log N$ extra cost per step.
- The CPU time in DOPRI5 grows quadratically. The reason is that the number of steps grows with N and the cost of each step is also proportional to N since DOPRI5 steps are computed on the whole system.
- When the number of neurons is large, the number of emitted spikes in QSS methods differs depending on the quantum, but it eventually converges as the quantum becomes smaller. The reason is that a situation like that of Figure 3, where a very small error in the membrane potential can cause a spurious or a

Figure 5. CPU Time vs Number of Neurons using different tolerance settings.

- missing spike, becomes more likely as the number of neurons grows.
- DOPRI5 errors become negligible as the number of neurons grows. The reason is that the step size becomes smaller (limited by the time elapsed between discontinuities) and the numerical errors fall far below the accuracy settings.

4.3. Model of a Network of Neurons

We consider now a model of $N = 10,000$ interconnected neurons, with 8,000 of excitatory type and 2,000 of inhibitory type.

The structure of the network was formed such that each neuron has m randomly chosen input synaptic connections, where 80% of these incoming connections are of excitatory type following the parameters found in (Schmidt et al., 2018). That way, each neuron has both, its own input spike train with the same Poisson distribution as before, and the spike received from their incoming synaptic connections.

The synaptic strength of the excitatory connections were randomly chosen with values uniformly distributed in the interval $J \pm 0.1J$. Inhibitory synaptic strengths were chosen with values $gJ \pm 0.1gJ$ with the scaling parameter $g = 5$. This scaling parameter was selected such that the rate of the emitted spikes does not change significantly with the number m of incoming connections. A synaptic delay $\tau_d = 1\text{E-}3$ sec. was used.

We simulated the system varying the number of connections of each neuron m from 10 to 1,000 in order to measure the growth in the computational costs as the network increases its connectivity. We used QSS2 method for the two-state model and QSS3 for the single-state model. In both cases, we also changed the quantum size until observing convergence in the number of emitted spikes. Like in the previous case, the final simulation time was $t_f = 0.1$ sec.

The simulation results for both models are reported in Table 7. Analyzing the results, we can make the following remarks:

- The number of steps performed by each method (and the CPU-time) is similar to that of the disconnected network of $N = 10,000$ neurons in Section 4.2. It

		Two-state model - QSS2			Single-state model - QSS3		
Tol	m	Steps	CPU Time [ms]	Out Spikes	Steps	CPU Time [ms]	Out Spikes
1E-1	10	10,038,883	6,265.6	6,367	10,700,559	7,307.3	6,472
	100	10,203,316	6,934.8	7,599	10,798,311	7,290.1	7,342
	1,000	11,081,929	10,263.8	7,163	11,365,275	9,106.4	7,449
1E-2	10	20,579,013	11,262.5	5,950	15,164,106	9,678.8	6,096
	100	20,892,009	12,528.5	6,967	15,483,527	10,317.5	7,234
	1,000	24,148,242	17,226.2	6,481	18,869,024	14,067.2	8,087
1E-3	10	73,279,806	40,832.9	5,923	20,181,053	13,537.3	5,952
	100	73,318,426	39,057.1	6,963	20,523,676	13,167.6	6,733
	1,000	80,969,462	43,008.3	8,520	23,996,908	16,744.9	5,642
1E-4	10	205,737,401	88,732.6	5,923	30,017,686	21,058.2	5,923
	100	204,734,130	93,031.9	6,956	30,245,928	23,277.5	6,917
	1,000	214,334,158	100,814.0	7,112	34,979,710	23,924.3	7,610
1E-5	10	620,024,618	272,732.0	5,923	51,816,833	32,689.3	5,923
	100	615,513,913	274,602.0	6,956	51,796,598	34,278.3	6,956
	1,000	632,190,653	283,982.0	7,071	56,367,979	39,815.5	7,023

Table 7. Computational Costs in a network of interconnected neurons (two-state and single-state models)

only grows by a small percentage for $m = 1,000$. This can be explained by the fact that the number of spikes that a neuron receives from the network (except for $m = 1,000$) is significantly smaller than the number of spikes it receives from its Poisson-distributed input train.

- The number of emitted spikes converges only for a small quantum, particularly when m is large. The reason is that now the error introduced by a missing or a spurious spike is propagated through the network, and this propagation becomes faster and wider as the connectivity growths.

In this case, the chaotic nature of the system makes impossible that two simulations under different accuracy settings provide identical results in the long term. Thus, the *best* quantum size selection would depend on the goals according to the application. A network with $N = 10,000$ neurons and $m = 1,000$ incoming connections per neuron can be simulated in about 9-10 seconds using a quantum size $\Delta Q = 0.1$ and QSS2 or QSS3 method or in about 40 seconds using QSS3 and a quantum size that produces much less spurious or missed spikes.

5. Conclusions

We presented an exhaustive analysis of the performance of QSS algorithms in the simulation of Leaky Integrate and Fire spiking neurons. We first derived theoretical properties that established error bounds and computational cost estimates for the QSS simulation of a single neuron. Such properties cannot be in general obtained for classic numerical algorithms in these type of models.

Then, we performed comprehensive simulation experiments using different QSS methods under different accuracy settings. The results of these experiments corroborated the theoretical analysis, exhibiting promising advantages of the QSS algorithms with respect to classic numerical integration schemes. It is remarkable that the second

and third order QSS methods integrate the model with very small errors performing about one step per input spike period. It is also remarkable that the errors in the firing times were almost negligible.

We then simulated networks with a growing number of neurons and with a growing level of connectivity. As the number of neurons N grows, the computational costs grow with $N \log(N)$ due to the logarithmic cost associated to the binary tree scheduler while classic discrete-time algorithms grow with N^2 due to the reduction of the time between discontinuities.

When the level of connectivity grows, CPU times are not significantly affected but the model becomes more chaotic and the effect of a missing or a spurious spike (caused by a small error in the membrane potential) is rapidly and widely propagated throughout the network.

A general conclusion of the analysis is that QSS methods (particularly QSS2 for the two-state model and QSS3 for the single-state model) allow to simulate large spiking neural networks with high accuracy and very low computational costs. This is achieved without any modification or specialization of the algorithms, as it is a natural consequence of the way the QSS methods work in the Stand-Alone QSS Solver.

We are currently working on specializing the simulation algorithm for the features of this model. In particular, the presence of the synaptic delay implies that there is no direct interaction between the different neuron during this period. This fact can be exploited, as it was done in (Hanuschkin, Kunkel, Helias, Morrison, & Diesmann, 2010b), to perform a sequential simulation of the N neurons for that period of time without taking care about the ordering in which the steps are performed. With this, we can avoid the factor $\log(N)$ and reduce the computational cost to scale linearly with the number of neurons N . We are also working on exploiting this idea in the context of parallel simulation.

Future work can also be done to further specialize the QSS methods themselves. For instance, in the two-state model we could enforce a step in the membrane potential V whenever a step in the synaptic current I_s is performed. That will synchronize the steps in both states improving in this case the computational costs and the accuracy.

It is also worth exploring the possibility of using a smaller quantum size as the membrane potential approaches the firing threshold to prevent spurious or missing spikes. This can be easily done by using a membrane potential relative to the threshold such that it is close to zero near the firing condition. That way, using logarithmic quantization will reduce the quantum near the threshold.

Acknowledgments

This work was supported by ANPCYT under Grant PICT-2017 2436, CONICET under Grant PIP 2022-2024 11220210100093CO and CNRS PRIME eXpIAIn research team.

References

Brette, R., Rudolph, M., Carnevale, T., Hines, M., Beeman, D., Bower, J. M., ... others (2007). Simulation of networks of spiking neurons: a review of tools and strategies. *Journal of computational neuroscience*, 23(3), 349–398.

- Brunel, N., Hakim, V., & Richardson, M. J. (2003). Firing-rate resonance in a generalized integrate-and-fire neuron with subthreshold resonance. *Physical Review E*, *67*(5), 051916.
- Burkitt, A. N. (2006). A review of the integrate-and-fire neuron model: I. homogeneous synaptic input. *Biological cybernetics*, *95*(1), 1–19.
- Castro, R., & Kofman, E. (2015). Activity of order n in continuous systems. *Simulation*, *91*(4), 337–348.
- Castro, R., Kofman, E., & Cellier, F. E. (2011). Quantization-based integration methods for delay-differential equations. *Simulation Modelling Practice and Theory*, *19*(1), 314–336.
- Cellier, F., & Kofman, E. (2006). *Continuous System Simulation*. New York: Springer.
- Cohen, S. D., Hindmarsh, A. C., & Dubois, P. F. (1996). Cvode, a stiff/nonstiff ode solver in c. *Computers in physics*, *10*(2), 138–143.
- D’Abreu, M. C., & Wainer, G. A. (2005). M/cd++: modeling continuous systems using modelica and devc. In *Modeling, analysis, and simulation of computer and telecommunication systems, 2005. 13th ieee international symposium on* (pp. 229–236).
- Dormand, J. R., & Prince, P. J. (1980). A family of embedded runge-kutta formulae. *Journal of computational and applied mathematics*, *6*(1), 19–26.
- Ermentrout, B. (1996). Type i membranes, phase resetting curves, and synchrony. *Neural computation*, *8*(5), 979–1001.
- Fernandez, J., Kofman, E., & Bergero, F. (2017). A parallel quantized state system solver for odes. *Journal of Parallel and Distributed Computing*, *106*, 14–30.
- Fernández, J., & Kofman, E. (2014). A Stand-Alone Quantized State System Solver for Continuous System Simulation. *Simulation: Transactions of the Society for Modeling and Simulation International*, *90*(7), 782–799.
- Fourcaud-Trocmé, N., & Brunel, N. (2005). Dynamics of the instantaneous firing rate in response to changes in input statistics. *Journal of computational neuroscience*, *18*(3), 311–321.
- Fourcaud-Trocmé, N., Hansel, D., Van Vreeswijk, C., & Brunel, N. (2003). How spike generation mechanisms determine the neuronal response to fluctuating inputs. *Journal of neuroscience*, *23*(37), 11628–11640.
- Gerstner, W., Kistler, W. M., Naud, R., & Paninski, L. (2014). *Neuronal dynamics: From single neurons to networks and models of cognition*. Cambridge University Press.
- Grinblat, G. L., Ahumada, H., & Kofman, E. (2012). Quantized state simulation of spiking neural networks. *Simulation*, *88*(3), 299–313.
- Hansel, D., Mato, G., Meunier, C., & Neltner, L. (1998). On numerical simulations of integrate-and-fire neural networks. *Neural Computation*, *10*(2), 467–483.
- Hanuschkin, A., Kunkel, S., Helias, M., Morrison, A., & Diesmann, M. (2010a). A general and efficient method for incorporating precise spike times in globally time-driven simulations. *Frontiers in neuroinformatics*, *4*, 113.
- Hanuschkin, A., Kunkel, S., Helias, M., Morrison, A., & Diesmann, M. (2010b). A general and efficient method for incorporating precise spike times in globally time-driven simulations. *Frontiers in neuroinformatics*, *4*, 113.
- Hindmarsh, A. C., Brown, P. N., Grant, K. E., Lee, S. L., Serban, R., Shumaker, D. E., & Woodward, C. S. (2005). Sundials: Suite of nonlinear and differential/algebraic equation solvers. *ACM Transactions on Mathematical Software (TOMS)*, *31*(3), 363–396.
- Hodgkin, A. L., & Huxley, A. F. (1952). A quantitative description of membrane current and its application to conduction and excitation in nerve. *The Journal of physiology*, *117*(4), 500.
- Izhikevich, E. M. (2003a). Simple model of spiking neurons. *IEEE Transactions on neural networks*, *14*(6), 1569–1572.
- Izhikevich, E. M. (2003b). Which model to use for cortical spiking neurons. *IEEE Transactions on Neural Networks*, *14*, 1569–1572.
- Izhikevich, E. M. (2007). *Dynamical systems in neuroscience*. MIT press.
- Jammalamadaka, R. (2003). Activity characterization of spatial models: Application to the discrete event solution of partial differential equations. *Master’s thesis, University of Ari-*

- zona, Tucson, Arizona, USA.
- Kaabi, M. G., Tonnelier, A., & Martinez, D. (2011). On the performance of voltage stepping for the simulation of adaptive, nonlinear integrate-and-fire neuronal networks. *Neural computation*, 23(5), 1187–1204.
- Kofman, E. (2002). A Second Order Approximation for DEVS Simulation of Continuous Systems. *Simulation: Transactions of the Society for Modeling and Simulation International*, 78(2), 76–89.
- Kofman, E. (2004a). Discrete Event Simulation of Hybrid Systems. *SIAM Journal on Scientific Computing*, 25(5), 1771–1797.
- Kofman, E. (2004b). Discrete event simulation of hybrid systems. *SIAM Journal on Scientific Computing*, 25(5), 1771–1797.
- Kofman, E., Fernández, J., & Marzorati, D. (2021). Compact sparse symbolic jacobian computation in large systems of odes. *Applied Mathematics and Computation*, 403, 126181.
- Kofman, E., & Junco, S. (2001). Quantized State Systems. A DEVS Approach for Continuous System Simulation. *Transactions of SCS*, 18(3), 123–132.
- Lapicque, L. (1907). Recherches quantitatives sur l’excitation électrique des nerfs. *J. Physiol. Paris.*, 9, 620–635.
- Mascart, C., Scarella, G., Reynaud-Bouret, P., & Muzy, A. (2022). Scalability of large neural network simulations via activity tracking with time asynchrony and procedural connectivity. *Neural Computation*, 34(9), 1915–1943.
- Mattsson, S. E., Elmqvist, H., & Otter, M. (1998). Physical system modeling with modelica. *Control Engineering Practice*, 6(4), 501–510.
- Migoni, G., Bortolotto, M., Kofman, E., & Cellier, F. (2013). Linearly Implicit Quantization-Based Integration Methods for Stiff Ordinary Differential Equations. *Simulation Modelling Practice and Theory*, 35, 118–136.
- Morrison, A., & Diesmann, M. (2007). Maintaining causality in discrete time neuronal network simulations. In *Lectures in supercomputational neurosciences* (pp. 267–278). Springer.
- Muzy, A., Jammalamadaka, R., Zeigler, B. P., & Nutaro, J. J. (2011). The activity-tracking paradigm in discrete-event modeling and simulation: The case of spatially continuous distributed systems. *Simulation*, 87(5), 449–464.
- Park, T., & Barton, P. I. (1996). State event location in differential-algebraic models. *ACM Transactions on Modeling and Computer Simulation (TOMACS)*, 6(2), 137–165.
- Petzold, L. R. (1982). *Description of dassl: a differential/algebraic system solver* (Tech. Rep.). Sandia National Labs., Livermore, CA (USA).
- Potjans, T. C., & Diesmann, M. (2014). The cell-type specific cortical microcircuit: relating structure and activity in a full-scale spiking network model. *Cerebral cortex*, 24(3), 785–806.
- Quesnel, G., Duboz, R., Ramat, É., & Traoré, M. K. (2007). Vle: a multimodeling and simulation environment. In *Proceedings of the 2007 summer computer simulation conference* (pp. 367–374).
- Richardson, M. J., Brunel, N., & Hakim, V. (2003). From subthreshold to firing-rate resonance. *Journal of neurophysiology*, 89(5), 2538–2554.
- Schmidt, M., Bakker, R., Shen, K., Bezgin, G., Diesmann, M., & van Albada, S. J. (2018). A multi-scale layer-resolved spiking network model of resting-state dynamics in macaque visual cortical areas. *PLOS computational biology*, 14(10), e1006359.
- Shelley, M. J., & Tao, L. (2001). Efficient and accurate time-stepping schemes for integrate-and-fire neuronal networks. *Journal of Computational Neuroscience*, 11(2), 111–119.
- Stein, R. B. (1967). Some models of neuronal variability. *Biophysical journal*, 7(1), 37–68.
- Vogels, T. P., & Abbott, L. F. (2005). Signal propagation and logic gating in networks of integrate-and-fire neurons. *Journal of neuroscience*, 25(46), 10786–10795.
- Zeigler, B. P., Kim, T. G., & Praehofer, H. (2000). *Theory of modeling and simulation*. Academic press.
- Zeigler, B. P., Muzy, A., & Kofman, E. (2018). *Theory of modeling and simulation: Discrete event & iterative system computational foundations*. Academic Press.

Zheng, G., Tonnelier, A., & Martinez, D. (2009). Voltage-stepping schemes for the simulation of spiking neural networks. *Journal of computational neuroscience*, 26(3), 409–423.

Appendix A. Proof of Theorems and Propositions

A.1. Theorem 1

Proof. Defining $\Delta x_i \triangleq q_i - x_i$, Eq. (13) can be rewritten as a perturbed equation

$$\begin{aligned}\frac{dx_1}{dt}(t) &= -a(x_1(t) + \Delta x_1(t)) + b(x_2(t) + \Delta x_2(t)) + u_1(t) \\ \frac{dx_2}{dt}(t) &= -c(x_2(t) + \Delta x_2(t)) + u_2(t)\end{aligned}\tag{A1}$$

Defining also the error as $e_i \triangleq x_i - z_i$, and subtracting Eq. (12) from Eq. (A1), the error dynamics results

$$\begin{aligned}\frac{de_1}{dt}(t) &= -a(e_1(t) + \Delta x_1(t)) + b(e_2(t) + \Delta x_2(t)) \\ \frac{de_2}{dt}(t) &= -c(e_2(t) + \Delta x_2(t))\end{aligned}\tag{A2}$$

Noticing that $|\Delta x_i| = |q_i - x_i| \leq \Delta Q_i$ (from the definition of the quantum). Then, it results that the condition $e_2 = \Delta Q_2$ implies that $|e_2| \geq \Delta x_2$ and then $e_2(t) + \Delta x_2(t) \geq 0$, which means that $\frac{de_2}{dt}(t) \leq 0$ and thus $e_2(t)$ cannot become greater than ΔQ_2 . Similarly, the condition $e_2 = -\Delta Q_2$ implies that $\frac{de_2}{dt}(t) \geq 0$ and $e_2(t)$ cannot become smaller than $-\Delta Q_2$. Thus, Eq. (15) holds.

This also implies that

$$b|e_2(t) + \Delta x_2(t)| \leq 2b\Delta Q_2.\tag{A3}$$

On the other side, the condition

$$e_1 \geq \Delta Q_1 + \frac{2b}{a}\Delta Q_2 \implies e_1 + \Delta x_1 \geq \frac{2b}{a}\Delta Q_2$$

and then

$$-a(e_1(t) + \Delta x_1(t)) \leq -2b\Delta Q_2$$

Thus, from Eq. (A3) and this last equation, we conclude that $e_1 \geq \Delta Q_1 + \frac{2b}{a}\Delta Q_2$ implies that

$$-a(e_1(t) + \Delta x_1(t)) + b(e_2(t) + \Delta x_2(t)) \leq -2b\Delta Q_2 + |b(e_2(t) + \Delta x_2(t))| \leq 0\tag{A4}$$

saying that the error e_1 cannot grow beyond $\Delta Q_1 + \frac{2b}{a}\Delta Q_2$. An identical analysis concludes that e_1 cannot become less than $-\Delta Q_1 - \frac{2b}{a}\Delta Q_2$ showing that Eq. (14) holds and completing the proof. \square

A.2. Theorem 2

Proof. Let t_1 be the time of the first input impulse. Then, from t_0 to t_1 we know that $|\mathbf{x}(t) - \mathbf{z}(t)| \leq \mathbf{e}_{\max}$. When the input event arrives, both the analytical solution $\mathbf{z}(t)$ and the numerical solution $\mathbf{x}(t)$ are increased or decreased by the same quantity. Thus $|\mathbf{x}(t_1^+) - \mathbf{z}(t_1^+)| \leq \mathbf{e}_{\max}$, which implies that the error bounds holds until the time of the second impulse t_2 . Then, using induction, we conclude that the error bound holds for all $t \geq t_0$ completing the proof. \square

A.3. Theorem 3

Proof. Defining $\Delta x_1 \triangleq q_1 - x_1$, Eq. (19) can be rewritten as a perturbed equation

$$\frac{dx_1}{dt}(t) = -a(x_1(t) + \Delta x_1(t)) + v(t) \quad (\text{A5})$$

Defining also the error as $e \triangleq x_1 - z_1$, and subtracting Eq. (18) from Eq. (A5), the error dynamics results

$$\frac{de}{dt}(t) = -a(e(t) + \Delta x_1(t)) + v(t) - u(t) \quad (\text{A6})$$

Then, considering $e = e_1 + e_2$, we can split the derivative of the error as:

$$\frac{de_1}{dt}(t) = -a(e_1(t) + \Delta x_1(t)) \quad (\text{A7})$$

$$\frac{de_2}{dt}(t) = -ae_2(t) + v(t) - u(t) \quad (\text{A8})$$

Noticing that $|\Delta x_1| = |q_1 - x_1| \leq \Delta Q_1$ (from the definition of the quantum). Then, it results that the condition $e_1 = \Delta Q_1$ implies that $|e_1| \geq \Delta x_1$ and then $e_1(t) + \Delta x_1(t) \geq 0$, which means that $\frac{de_1}{dt}(t) \leq 0$ and thus $e_1(t)$ cannot become greater than ΔQ_1 . Similarly, the condition $e_1 = -\Delta Q_1$ implies that $\frac{de_1}{dt}(t) \geq 0$ and $e_1(t)$ cannot become smaller than $-\Delta Q_1$. Thus, $|e_1| \leq \Delta Q_1$.

Then, defining $\Delta t = (t - t_k)$ and Δt_{max} the largest Δt , we can assure from the hypothesis that $|v(t) - u(t)| < c\Delta t^n$. This imply that if $e_2 = \frac{c}{a} \cdot \Delta t_{max}^n$, then $|ae_2| \geq v(t) - u(t)$, so $\frac{de_2}{dt} \leq 0$ and $e_2(t)$ cannot become greater than $\frac{c}{a} \cdot \Delta t_{max}^n$. Similarly, if $e_2 = -\frac{c}{a} \cdot \Delta t_{max}^n$, then $\frac{de_2}{dt}(t) \leq 0$ and $e_2(t)$ cannot become smaller than $-\frac{c}{a} \Delta t_{max}^n$. Thus, $|e_2| \leq \frac{c}{a} \cdot \Delta t_{max}^n$.

Then, $|e| \leq |e_1| + |e_2| \leq \Delta Q_1 + \frac{c}{a} \cdot \Delta t_{max}^n$ completing the proof. \square

A.4. Theorem 4

Proof. The analytical solution of z_1 is given by $z_1(t) = e^{-at}v_1 + v_2$ with

$$v_1 = V_r - \frac{b\bar{z}_2 + u_1}{a}$$

and

$$v_2 = \frac{b\bar{z}_2 + u_1}{a} \quad (\text{A9})$$

Since at time t_θ the state z_1 reaches the threshold, we have $z_1(t_\theta) = e^{-at_\theta}v_1 + v_2 = \theta$, and then

$$t_\theta = \frac{1}{a} \log\left(\frac{v_1}{\theta - v_2}\right)$$

In order to verify that the argument of the logarithm is positive, notice that, from Eqs.(22) and (A9) it results

$$v_2 = \frac{b\bar{z}_2 + u_1}{a} > \frac{b\frac{a\theta - u_1}{b} + u_1}{a} = \theta$$

and $v_1 = V_r - v_2 < V_r - \theta < 0$.

Then, recalling that error bound between $z_1(t)$ and $x_1(t)$ according to Eq. (14) in Theorem 1 is given by Δ_1 , we can assure that the numerical solution $x_1(t)$ will be able to reach the threshold only after the analytical solution satisfies $z_1(t) \geq \theta - \Delta_1$, so the minimum time at which $x_1(t)$ can reach the threshold is given by:

$$\tilde{t}_\theta^{\min} = \frac{1}{a} \log\left(\frac{v_1}{(\theta - \Delta_1) - v_2}\right)$$

So, the difference between the firing time of the analytical solution and the minimum possible firing time of the numerical solution can be computed as

$$\begin{aligned} t_\theta - \tilde{t}_\theta^{\min} &= \frac{1}{a} \left(\log\left(\frac{v_1}{\theta - v_2}\right) - \log\left(\frac{v_1}{(\theta - \Delta_1) - v_2}\right) \right) \\ &= \frac{1}{a} \log\left(\frac{v_1}{\theta - v_2} \cdot \frac{(\theta - \Delta_1) - v_2}{v_1}\right) \\ &= \frac{1}{a} \log\left(1 - \frac{\Delta_1}{\theta - v_2}\right) \\ &= \frac{1}{a} \log\left(1 - \frac{\Delta Q_1 + \frac{2b}{a}\Delta Q_2}{\theta - \frac{b\bar{x}_2 + u_1}{a}}\right) \end{aligned}$$

An identical analysis shows that the numerical solution $x_1(t)$ will not be able to reach the threshold after the analytical solution satisfies $z_1(t) \geq \theta + \Delta_1$. Thus, the

maximum time in which $x_1(t)$ could reach the threshold is given by

$$\tilde{t}_\theta^{\max} = \frac{1}{a} \log\left(\frac{v_1}{(\theta + \Delta_1) - v_2}\right).$$

Then, the difference between the firing time of the analytical solution and the maximum firing time of the numerical solution is

$$|\tilde{t}_\theta^{\max} - t_\theta| = \left| \frac{1}{a} \log\left(1 + \frac{\Delta_1}{\theta - v_2}\right) \right|. \quad (\text{A10})$$

Notice that, since $\frac{\Delta_1}{\theta - v_2} < 0$ it results

$$|t_\theta - \tilde{t}_\theta^{\min}| = \left| \frac{1}{a} \log\left(1 - \frac{\Delta_1}{\theta - v_2}\right) \right| < \left| \frac{1}{a} \log\left(1 + \frac{\Delta_1}{\theta - v_2}\right) \right| = |t_\theta - \tilde{t}_\theta^{\max}|$$

Then, $|t_\theta - \tilde{t}_\theta| < |\tilde{t}_\theta^{\max} - t_\theta|$, completing the proof after replacing in Eq. (A10) with the corresponding expressions for Δ_1 and v_2 . □

A.5. Proposition 1

Proof. Since $V_r \leq z_1(t) \leq \theta$, then, from Eq. (12)

$$-aV_r + b\bar{z}_2 + u_1 \leq \dot{z}_1(t) \leq -a\theta + b\bar{z}_2 + u_1 = -aV_r + b\bar{z}_2 + u_1 + aV_r - a\theta$$

Notice that $|b\bar{z}_2 + u_1| \gg a(\theta - V_r)$ implies $b\bar{z}_2 + u_1 + a(V_r - \theta) \approx b\bar{z}_2 + u_1$, and,

$$-aV_r + b\bar{z}_2 + u_1 \leq \dot{z}_1(t) \leq -aV_r + b\bar{z}_2 + u_1 + a(V_r - \theta) \approx -aV_r + b\bar{z}_2 + u_1$$

implying that $\dot{z}_1(t)$ is almost constant, *i.e.*, $\dot{z}_1 \approx d_1 \triangleq -aV_r + b\bar{z}_2 + u_1$.

That way, the firing period of z_1 is approximately

$$T \approx \frac{\theta - V_r}{d_1} \quad (\text{A11})$$

and taking into account that the error between x_1 and z_1 is bounded by Δ_1 , the maximum error in the period is given by

$$|\Delta T| \leq \Delta T_{\max} \approx \frac{\Delta_1}{d_1} \quad (\text{A12})$$

and dividing Eq. (A12) with Eq. (A11) we obtain the bound of Eq. (26) completing the proof. □

Appendix B. Statistical Error Analysis

In order to verify that the errors reported in Tables 2-3 do not change significantly with the pseudo-random sequence that generates the input spike train, we repeated all the simulations using 30 different seeds and we measured the different errors in each case. Then, we computed the mean value and the standard deviation of each reported error.

Table B1 shows the results corresponding to the synaptic current I_s in the two-state model, corroborating that the errors on that state are very similar for all the simulations (the standard deviation is from one to two orders of magnitude below the mean error value).

Method	Tol [nA,mV]	I_s [nA]			
		μe_{mean}	σe_{mean}	μe_{max}	σe_{max}
QSS	1E-1	2.15E-2	1.10E-4	5.00E-2	2.24E-5
	1E-2	2.50E-3	1.37E-5	5.90E-3	6.27E-4
	1E-3	2.50E-4	1.33E-6	6.00E-4	7.28E-5
	1E-4	2.51E-5	1.55E-7	6.77E-5	6.42E-6
QSS2	1E-1	7.63E-3	1.34E-4	4.99E-2	7.14E-5
	1E-2	3.54E-3	2.87E-5	1.38E-2	3.66E-4
	1E-3	2.66E-4	2.54E-6	1.27E-3	8.45E-6
	1E-4	2.53E-5	1.68E-7	1.27E-4	3.25E-6
QSS3	1E-1	1.18E-2	1.55E-4	4.99E-2	7.81E-5
	1E-2	3.68E-3	1.92E-5	1.21E-2	5.02E-4
	1E-3	2.79E-4	3.04E-6	1.11E-3	2.51E-5
	1E-4	2.47E-5	1.89E-7	1.14E-4	1.18E-6

Table B1. Mean value and standard deviation of the measured errors in the synaptic current I_s (two-state model) over 30 simulations using different pseudo-random sequences.

Table B2 reports the results regarding the membrane potential, also for the two-state model. There, all the sub-threshold errors have also a very small deviation. In the case of the full trajectory of the membrane potential, the mean errors are still similar to the quantum, but there is more variation due to some errors in the number of emitted spikes for the largest quantum.

Table B3 repeats the results of Table B2 for the single-state model. The conclusions are also very similar, except that this time the errors in the number of emitted spikes are more frequent.

Method	Tol [nA,mV]	V_{sub} [nA]				V [nA]		Out Spikes μe_{mean}
		μe_{mean}	σe_{mean}	μe_{max}	σe_{max}	μe_{mean}	σe_{mean}	
QSS	1E-1	3.44E-2	3.54E-3	1.41E-1	1.86E-2	1.49E-1	1.46E-1	0.26667
	1E-2	4.00E-3	2.96E-4	1.54E-2	1.14E-3	4.02E-2	9.99E-2	0.066667
	1E-3	4.16E-4	3.84E-5	1.57E-3	9.84E-5	6.30E-3	3.10E-2	0.033333
	1E-4	4.24E-5	2.55E-6	1.59E-4	1.17E-5	5.05E-5	6.05E-6	0
QSS2	1E-1	3.54E-2	2.36E-3	1.11E-1	9.68E-3	2.51E-1	2.46E-1	0.53333
	1E-2	4.65E-3	3.22E-4	1.54E-2	1.15E-3	2.07E-2	5.81E-2	0
	1E-3	2.89E-4	1.23E-5	1.19E-3	2.02E-4	3.49E-4	3.49E-4	0
	1E-4	2.91E-5	1.12E-6	6.86E-5	1.90E-5	2.80E-5	2.38E-6	0
QSS3	1E-1	2.85E-2	1.63E-3	1.10E-1	2.07E-2	6.86E-2	9.21E-2	0.033333
	1E-2	3.67E-3	2.07E-4	1.29E-2	1.44E-3	8.24E-3	1.44E-2	0
	1E-3	2.81E-4	2.03E-5	1.10E-3	7.81E-5	3.59E-4	2.90E-4	0
	1E-4	2.52E-5	1.57E-6	1.13E-4	5.89E-6	2.69E-5	2.32E-6	0

Table B2. Mean value and standard deviation of the measured errors in the membrane potential V (two-state model) over 30 simulations using different pseudo-random sequences.

Method	Tol [nA,mV]	V_{sub} [nA]				V [nA]		Out Spikes μe_{mean}
		μe_{mean}	σe_{mean}	μe_{max}	σe_{max}	μe_{mean}	σe_{mean}	
QSS	1E-1	8.18E-1	1.47E-1	2.07E+0	2.38E+0	4.19E+0	2.52E-1	20.7333
	1E-2	1.89E-1	3.71E-2	9.61E-1	2.59E+0	2.53E+0	2.59E-1	7.5333
	1E-3	4.01E-2	1.59E-2	1.25E-1	6.15E-2	8.15E-1	2.97E-1	2.1
	1E-4	1.01E-2	1.20E-2	3.58E-2	3.67E-2	2.40E-1	2.40E-1	0.4
QSS2	1E-1	2.38E-1	3.66E-2	4.51E-1	5.67E-2	1.09E+0	3.09E-1	2.5
	1E-2	4.51E-2	4.83E-3	7.90E-2	8.24E-3	2.72E-1	2.10E-1	0.5
	1E-3	3.40E-3	3.54E-5	5.89E-3	2.89E-4	2.66E-2	5.23E-2	0.1
	1E-4	3.52E-4	2.40E-6	5.88E-4	1.42E-5	8.96E-4	5.73E-4	0
QSS3	1E-1	4.38E-2	2.05E-2	1.23E-1	4.53E-2	3.51E-1	2.89E-1	0.7
	1E-2	1.48E-2	2.16E-3	2.95E-2	5.48E-3	1.03E-1	1.27E-1	0.1
	1E-3	2.94E-3	2.13E-4	4.94E-3	3.92E-4	1.16E-2	2.20E-2	0
	1E-4	3.31E-4	7.61E-6	5.23E-4	1.35E-5	6.96E-4	3.66E-4	0

Table B3. Mean value and standard deviation of the measured errors in the membrane potential V (single-state model) over 30 simulations using different pseudo-random sequences.