



HAL
open science

Annealed Gallium-Doped Zinc Oxide (ZnO:Ga) Thin Films for Sub-ppm NO₂ Sensing

Benjamin Paret, Philippe Menini, Thierry Camps, Yohann Thimont, Antoine Barnabé, Laurent Mazonq, Lionel Presmanes

► **To cite this version:**

Benjamin Paret, Philippe Menini, Thierry Camps, Yohann Thimont, Antoine Barnabé, et al.. Annealed Gallium-Doped Zinc Oxide (ZnO:Ga) Thin Films for Sub-ppm NO₂ Sensing. PROCEEDINGS, 2024, 97, pp.61. 10.3390/proceedings2024097061 . hal-04796318

HAL Id: hal-04796318

<https://hal.science/hal-04796318v1>



Submitted on 21 Nov 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Abstract

Annealed Gallium-Doped Zinc Oxide (ZnO:Ga) Thin Films for Sub-ppm NO₂ Sensing [†]

Benjamin Paret ^{1,2}, Philippe Menini ² , Thierry Camps ², Yohann Thimont ¹, Antoine Barnabé ¹, Laurent Mazenq ² and Lionel Presmanes ^{1,*} 

¹ CIRIMAT, Université Toulouse 3 Paul Sabatier, Toulouse INP, CNRS, Université de Toulouse, 118 Route de Narbonne, CEDEX 9, 31062 Toulouse, France; benjamin.paret@univ-tlse3.fr (B.P.); yohann.thimont@univ-tlse3.fr (Y.T.); antoine.barnabe@univ-tlse3.fr (A.B.)

² Laboratoire d'Analyse et d'Architecture des Systèmes (LAAS), Université de Toulouse, CNRS, UPS, 7 Av Colonel Roche, CEDEX 4, 31031 Toulouse, France; philippe.menini@laas.fr (P.M.); thierry.camps@laas.fr (T.C.); lmazenq@laas.fr (L.M.)

* Correspondence: lionel.presmanes@univ-tlse3.fr

[†] Presented at the XXXV EUROSENSORS Conference, Lecce, Italy, 10–13 September 2023.

Abstract: In this work, gallium-doped zinc oxide was deposited with a Radio Frequency Magnetron sputtering method on test platforms. The NO₂ sensing properties of the resulting devices were studied. The sensing properties of ZnO:Ga thin films were successfully stabilized through annealing in dry air, and then improved by either a thinning of the layer or an increase in the roughness of the substrate. The sensing response with an R_{gas}/R_{air} of 15 for 100 ppb of NO₂ under 50% humidity was obtained, with a response time below 10 min.

Keywords: NO₂ sensing; thin films; RF sputtering; GZO; annealing



Citation: Paret, B.; Menini, P.; Camps, T.; Thimont, Y.; Barnabé, A.; Mazenq, L.; Presmanes, L. Annealed Gallium-Doped Zinc Oxide (ZnO:Ga) Thin Films for Sub-ppm NO₂ Sensing. *Proceedings* **2024**, *97*, 61.

<https://doi.org/10.3390/proceedings2024097061>

Academic Editors: Pietro Siciliano and Luca Francioso

Published: 20 March 2024



Copyright: © 2024 by the authors. Licensee MDPI, Basel, Switzerland. This article is an open access article distributed under the terms and conditions of the Creative Commons Attribution (CC BY) license (<https://creativecommons.org/licenses/by/4.0/>).

1. Introduction

Resistive gas sensors based on Metal Oxide Semiconductors (MOSs) are a promising solution for cheap, reliable, and highly sensitive gas sensors. Among them, ZnO has interesting characteristics for such application thanks to its large band gap and its high chemical stability. RF magnetron sputtering is a widely used process in the Incorporated Circuit industry, well fit for mass production, and allows for control over the microstructure of the thin films deposited. The present work shows high NO₂ sensing properties of ZnO:Ga thin films integrated on test platforms, as well as an improvement of the sensitive layers through structure modifications.

2. Materials and Methods

Ga-doped ZnO thin films (4% in cation sites) with thicknesses of 12, 25, 50, and 100 nm were deposited at room temperature on simplified test platforms by RF magnetron sputtering with an Ar plasma. The as-deposited ZnO:Ga thin films were first characterized in terms of structure, grain size, and total thickness by Grazing Incidence X-ray (GIXRD), AFM, SEM, TEM, and profilometry. The resulting devices were annealed in synthetic air for 4 h at 500 °C, 600 °C, and 700 °C, respectively. The influence of layer thickness and annealing temperature on the gas sensing properties was studied.

The test platforms used for these experiments were produced through classic lithography in a clean room. A 600 nm layer of SiO₂ was thermally grown on a silicon wafer for electric isolation. Pt electrodes for electric contact were deposited on top. The thermal SiO₂ was very smooth. To increase the roughness of the platform, an alternative platform was designed with the addition of a layer of 300 nm of SiO₂ obtained with PECVD, providing a much rougher surface.

The sensing properties of the produced devices were examined with a dilution gas test bench in synthetic air at 250 °C with a humidity level of 50%. This temperature was previously found to be the optimum temperature for NO₂ sensing for the studied ZnO:Ga material [1,2]. The devices were first electrically stabilized for 10 h in these conditions before the injection of a set of 6 pulses of NO₂ at 100 ppb (2 h in NO₂, 2 h in synthetic air). The electric resistance was measured at the beginning and at the end of each injection, providing a measurement of the electrical response to gas as R_{gas}/R_{air} . In the meantime, the response time was calculated as the time needed for a device to reach 90% of its final response value.

3. Discussion

The structural and microstructural analysis of the thin films show columnar growth, as shown in Figure 1, and has a preferential orientation along the (002) plane. A recrystallization phenomenon was observed for the samples annealed above 600 °C, which might explain the increase in the sensing properties but not why the devices annealed at 700 °C did not show as-good results.




Figure 1. STEM capture of a 50 nm thick ZnO:Ga thin film deposited by RF sputtering on a Si substrate covered by smooth thermal SiO₂.

The experiments on the gas dilution test bench showed that the annealing stabilized the sensing properties of the devices. The devices annealed at 600 °C showed a sensitivity improvement, with an R_{gas}/R_{air} response of nine, whereas devices annealed at other temperatures or not annealed at all were measured with a response between 2.5 and 3. The response time, however, was never impacted and was recorded as roughly 80 min for all devices.

The NO₂ sensing properties of four test substrates coated with ZnO:Ga with a thickness of 12, 25, 50, and 100 nm, each annealed at 600 °C for 4 h, were compared. Both the response and the response time were greatly improved for thinner films. Films of 12 nm and 25 nm showed a response value of R_{gas}/R_{air} equal to 15, and their response time was measured at around 10 min.

The NO₂ sensing properties of a 50 nm thin film of ZnO:Ga deposited on a rough test platform were studied after annealing at 600 °C. Compared to a similar device obtained on a smooth test platform, its electric resistivity and gas response were identical, but its response time was five times shorter.

Author Contributions: Investigation and writing by B.P.; validation and supervision by L.P. and P.M.; material and electrical characterization support by A.B., Y.T. and T.C.; and clean room supervision by L.M. All authors have read and agreed to the published version of the manuscript.

Funding: This work received funding from the French ANR agency under grant agreement ANR-20-CE04-012. This work was supported by the LAAS-CNRS micro and nanotechnologies platform, a member of the French Renatech network.

Institutional Review Board Statement: Not applicable.

Informed Consent Statement: Not applicable.

Data Availability Statement: The datasets presented in this article are not readily available because the data are part of an ongoing study.

Conflicts of Interest: The authors declare no conflicts of interest.

References

1. Gunasekaran, V. Intégration et Caractérisation de Couches Sensibles de ZnO:Ga et de Cobaltites Spinelles ($\text{Co}_x\text{Fe}_{3-x}\text{O}_4$; $1 \leq x \leq 3$) sur Véhicules de Test Pour la Détection de Dioxyde D'azote Sub-ppm et D'éthanol. Ph.D Thesis, University Paul Sabatier–Toulouse III, Toulouse, France, 2020.
2. Presmanes, L.; Gunasekaran, V.; Thimont, Y.; Sinnarasa, I.; Barnabe, A.; Menini, P.; Tailhades, P. Ga doped ZnO thin films deposited by RF sputtering for NO_2 sensing. In Proceedings of the 2019 5th Experiment International Conference (exp.at'19), Funchal, Portugal, 12–14 June 2019; pp. 454–457. [[CrossRef](#)]

Disclaimer/Publisher's Note: The statements, opinions and data contained in all publications are solely those of the individual author(s) and contributor(s) and not of MDPI and/or the editor(s). MDPI and/or the editor(s) disclaim responsibility for any injury to people or property resulting from any ideas, methods, instructions or products referred to in the content.