



HAL
open science

About S-Variables and Descriptor Systems

Dimitri Peaucelle

► **To cite this version:**

Dimitri Peaucelle. About S-Variables and Descriptor Systems. Workshop on Automatic Control Theory Japan-France Research Networking, Nov 2024, Kyoto (Japan), Japan. hal-04926040

HAL Id: hal-04926040

<https://hal.science/hal-04926040v1>

Submitted on 3 Feb 2025

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

About S-Variables and Descriptor Systems

ディミトリ・ポーセル Dimitri Peaucelle - LAAS-CNRS - Université de Toulouse

*Workshop on Automatic Control Theory
Japan-France Research Networking
Kyoto - 8 November 2024*

The S-Variable approach has been central in my collaborative work with Japanese colleagues in the past 20 years. The terminology took some time to be settled. We have used terms such as "Dilated-LMIs" (Yoshio Ebihara), "Slack Variable" (Masayuki Sato) and some others, to finally stop iterating with the publication of the book "S-Variable Approach to LMI-Based Robust Control". An other existing terminology in the litterature (mainly by Emilia Fridman) for that same technique is the "Descriptor system approach" and indeed there are interesting extensions to descriptor systems using this technique. In this talk we will recall some previous work on that topic and present some open questions for further collaborative work.

- [Aizerman and Gantmakher, 1964], Lossless [Yakubovitch, 1971]

$$\eta^* Q \eta < 0 \quad \forall \eta^* Q_1 \eta \leq 0 \quad \Leftrightarrow \quad \exists s > 0 : Q \prec s Q_1$$

- ▲ Extensions: bounded real lemma, passivity, dissipation, KYP

- Lossy

$$\eta^* Q \eta < 0 \quad \forall \begin{cases} \eta^* Q_1 \eta \leq 0 \\ \eta^* Q_2 \eta \leq 0 \end{cases} \quad \Leftrightarrow \quad \exists s_1 > 0, s_2 > 0 : Q \prec s_1 Q_1 + s_2 Q_2$$

- ▼ Extensions such as μ -analysis, IQCs, quadratic separation, are (in most cases) conservative

- S-procedure

$$\eta^* Q \eta < 0 \quad \forall \eta^* Q_1 \eta \leq 0 \quad \Leftrightarrow \quad \exists s > 0 : Q \prec s Q_1$$

- S-Variable approach

$$\eta^* Q \eta < 0 \quad \forall M \eta = 0 \quad \Leftrightarrow \quad M^{\perp T} Q M^{\perp} \prec 0 \quad \Leftrightarrow \quad \exists S : Q \prec S M + M^* S^* = \{S M\}^{\mathcal{H}}$$

- S-procedure based proof [Ebihara et al., 2015]: $Q_1 = M^* M$ and $S = s \frac{1}{2} M^*$

- ▲ Many new degrees of freedom

- ▼ Increased size of LMIs & many more decision variables

- Lossless

$$\eta^* Q \eta < 0 \quad \forall M \eta = 0 \quad \Leftrightarrow \quad \exists S : Q \prec \{SM\}^{\mathcal{H}}$$

- Lossy but Robust [Peaucelle et al., 2000]

$$\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \forall \zeta \in [0, 1] \quad \Leftarrow \quad \exists S : \begin{cases} Q^{[0]} \prec \{SM^{[0]}\}^{\mathcal{H}} \\ Q^{[1]} \prec \{SM^{[1]}\}^{\mathcal{H}} \end{cases}$$

$$Q(\zeta) = (1 - \zeta)Q^{[0]} + \zeta Q^{[1]} \quad , \quad M(\zeta) = (1 - \zeta)M^{[0]} + \zeta M^{[1]}$$

- Lossy but good for design (see WUDS 2023 Kyoto [Peaucelle, 2023])

$$\begin{cases} \eta^* Q \eta < 0 & \forall M_1 \eta = 0 \\ \eta^* Q \eta < 0 & \forall M_2 \eta = 0 \end{cases} \quad \Leftarrow \quad \exists S = M_2^* V : Q \prec \{SM_1\}^{\mathcal{H}}$$

- ▲ Heuristics for Control (and Robust Control) Design
- ▼ Convex only for chosen M_2

- Lossless

$$\eta^* Q \eta < 0 \quad \forall M \eta = 0 \quad \Leftrightarrow \quad \exists S : Q \prec \{SM\}^{\mathcal{H}}$$

- Lossy but Robust [Peaucelle et al., 2000]

$$\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \forall \zeta \in [0 \ 1] \quad \Leftrightarrow \quad \exists S : \begin{cases} Q^{[0]} \prec \{SM^{[0]}\}^{\mathcal{H}} \\ Q^{[1]} \prec \{SM^{[1]}\}^{\mathcal{H}} \end{cases}$$

$$\begin{bmatrix} Q(\zeta) \\ M(\zeta) \end{bmatrix} = (1 - \zeta) \begin{bmatrix} Q^{[0]} \\ M^{[0]} \end{bmatrix} + \zeta \begin{bmatrix} Q^{[1]} \\ M^{[1]} \end{bmatrix} \in \text{CO} \left\{ \begin{bmatrix} Q^{[0]} \\ M^{[0]} \end{bmatrix}, \begin{bmatrix} Q^{[1]} \\ M^{[1]} \end{bmatrix} \right\}$$

- ▲ Efficient for analysis of parametric uncertain systems, including polynomial and rational

$$V(x, \zeta) = x^* P(\zeta) x > 0 \quad \dot{V}(x, \zeta) < 0 \quad \forall \ddot{y} + \alpha_1(\zeta) \dot{y} + \frac{1}{\alpha_2(\zeta)} y = 0 \quad \alpha_i(\zeta) \text{ affine of } \zeta \in [0 \ 1]$$

■ Affine descriptor version (alternative to building LFTs ▲ smaller size)

$$\dot{V}(x, \zeta) < 0 \quad \forall \begin{cases} \ddot{y} + \alpha_1(\zeta) \dot{y} + \pi = 0 \\ \alpha_2(\zeta) \pi = y \end{cases}$$

■ State-space descriptor version with $x = (y \ \dot{y})^T$

$$\eta^* \underbrace{\begin{bmatrix} 0 & 0 & P(\zeta) \\ 0 & 0 & 0 \\ P(\zeta) & 0 & 0 \end{bmatrix}}_{Q(P(\zeta))} \eta < 0 \quad \forall \underbrace{\left[\begin{array}{cc|c|cc} 1 & 0 & 0 & 0 & -1 \\ 0 & 1 & 1 & 0 & \alpha_1(\zeta) \\ 0 & 0 & \alpha_2(\zeta) & -1 & 0 \end{array} \right]}_{M(\zeta)} \underbrace{\begin{pmatrix} \dot{x} \\ \pi \\ x \end{pmatrix}}_{\eta} = 0$$

▲ (Lossy) S-variable result: Robust stability holds true if $\exists P^{[0]} \succ 0, P^{[1]} \succ 0$ and S :

$$Q(P^{[0]}) \prec \{SM^{[0]}\}^{\mathcal{H}} \quad , \quad Q(P^{[1]}) \prec \{SM^{[1]}\}^{\mathcal{H}}$$

- Lifting by taking higher order derivatives:

$$\left[\begin{array}{c} 1 \\ \frac{d}{dt} \end{array} \right] (y^{(2)} + \alpha_1(\zeta)y^{(1)} + \frac{1}{\alpha_2(\zeta)}y) = \left[\begin{array}{c} y^{(2)} + \alpha_1(\zeta)y^{(1)} + \frac{1}{\alpha_2(\zeta)}y \\ y^{(3)} + \alpha_1(\zeta)y^{(2)} + \frac{1}{\alpha_2(\zeta)}y^{(1)} \end{array} \right] = 0$$

- State-space descriptor version with $\hat{x}_1 = (y \quad y^{(1)} \quad y^{(2)})^T$

$$\left[\begin{array}{ccc|cc} 1 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 1 & 0 \\ 0 & 0 & 1 & 0 & 1 \\ 0 & 0 & 0 & \alpha_2(\zeta) & 0 \\ 0 & 0 & 0 & 0 & \alpha_2(\zeta) \end{array} \middle| \begin{array}{ccc} 0 & -1 & 0 \\ 0 & 0 & -1 \\ 0 & \alpha_1(\zeta) & 0 \\ 0 & 0 & \alpha_1(\zeta) \\ -1 & 0 & 0 \\ 0 & -1 & 0 \end{array} \right] \begin{pmatrix} \dot{\hat{x}}_1 \\ \hat{\pi}_1 \\ \hat{x}_1 \end{pmatrix} = 0$$

- ▲ (Lossy) S-variable result applies and gives a less conservative, larger size, LMI
- ▲ Proof involves a higher order parameter-dependent Lyapunov function ▼ Initial conditions ?

- Lifting by causal / non causal, rationally parameter-dependent, filters :

$$\begin{bmatrix} 1 \\ H(s, \zeta) \end{bmatrix} (y^{(2)} + \alpha_1(\zeta)y^{(1)} + \frac{1}{\alpha_2(\zeta)}y) = 0$$

- ▲ (Lossy) S-variable result applies and gives a less conservative, larger size, LMI
- ▲ Stable causal filters can be chosen with zero initial conditions. Link with recent work by Scherer?
- ▲ Connexion to dynamic IQC multipliers?
- ▼ Choice of filters?
- ▼ Parameter-dependent lifting and SOS type hierarchies?
- ▼ Hierarchies of LMI? Convergence to exactness?

- The S-variable Robustness conditions for $\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \forall \zeta \in [0, 1]$ involve LMI constraints on vertices

$$Q(P^{[0]}) \prec \{SM^{[0]}\}^{\mathcal{H}}, \quad Q(P^{[1]}) \prec \{SM^{[1]}\}^{\mathcal{H}}$$

- For each constraint exist a dual variable $H^{[0]} \succeq 0$ and $H^{[1]} \succeq 0$ respectively.

- ▲ [Ebihara et al., 2015] If the primal LMIs are unfeasible (or marginally feasible) and dual variables satisfy

$$\exists \zeta \in [0, 1] \quad : \quad (1 - \zeta)H^{[0]} + \zeta H^{[1]} = 0$$

then ζ is a worst-case such that $\exists M(\zeta) \eta \quad : \quad \eta^* Q(\zeta) \eta \geq 0$.

- ▲ In practice, solve convex 2nd order cone problem $\zeta^* = \min_{\zeta} \|(1 - \zeta)H^{[0]} + \zeta H^{[1]}\|_2$. Gives rather good close to "worst case" values.

- One polytopic uncertainty

$$\eta^* Q(P(\zeta)) \eta < 0 \quad \forall M(\zeta) \eta = 0 \quad M(\zeta) = \sum_{v=1}^{\bar{v}} \zeta_v M^{[v]} \quad \zeta_v \geq 0 \quad \sum_{v=1}^{\bar{v}} \zeta_v = 1$$

- ▲ Holds true if $\exists P^{[v=1 \dots \bar{v}]} \succ 0$ and S :

$$Q(P^{[v]}) \prec \{SM^{[v]}\}^{\mathcal{H}} \quad \forall v = 1 \dots \bar{v}.$$

- Proof: By convexity, the LMIs imply

$$Q(P(\zeta)) \prec \{SM(\zeta)\}^{\mathcal{H}} \quad \forall \zeta_v \geq 0 \quad \sum_{v=1}^{\bar{v}} \zeta_v = 1$$

where $P(\zeta) = \sum_{v=1}^{\bar{v}} \zeta_v P^{[v]}$, and concludes the proof using the S-variable result.

- Two (or more) polytopic uncertainties [Is this new?]

$$\eta^* Q(P(\zeta_1, \zeta_2)) \eta < 0 \quad \forall \begin{bmatrix} M_1(\zeta_1) \\ M_2(\zeta_2) \end{bmatrix} \eta = 0 \quad M_i(\zeta_i) = \sum_1^{\bar{v}_i} \zeta_{i,v_i} M_i^{[v_i]} \quad \zeta_{i,v_i} \geq 0 \quad \sum_{v_i=1}^{\bar{v}_i} \zeta_{i,v_i} = 1$$

- ▲ Holds true if $\exists P^{[v_1=1\dots\bar{v}_1, v_2=1\dots\bar{v}_2]} \succ 0$, $S_1^{v_2=1\dots\bar{v}_2}$ and $S_2^{v_1=1\dots\bar{v}_1}$:

$$Q(P^{[v_1, v_2]}) \prec \left\{ S_1^{[v_2]} M_1^{[v_1]} + S_2^{[v_1]} M_2^{[v_2]} \right\}^{\mathcal{H}} \quad \forall v_i = 1 \dots \bar{v}_i$$

- Proof: By convexity, the LMIs imply

$$Q(P(\zeta_1, \zeta_2)) \prec \left\{ S_1(\zeta_2) M_1(\zeta_1) + S_2(\zeta_1) M_2(\zeta_2) \right\}^{\mathcal{H}} = \left\{ \begin{bmatrix} S_1(\zeta_2) & S_2(\zeta_1) \end{bmatrix} \begin{bmatrix} M_1(\zeta_1) \\ M_2(\zeta_2) \end{bmatrix} \right\}^{\mathcal{H}}$$

where $P(\zeta_1, \zeta_2) = \sum_{v_1=1}^{\bar{v}_1} \sum_{v_2=1}^{\bar{v}_2} \zeta_{1,v_1} \zeta_{2,v_2} P^{[v_1, v_2]}$, $S_i(\zeta_k) = \sum_{v_k=1}^{\bar{v}_k} \zeta_{k,v_k} S_i^{[v_k]}$
and concludes the proof using the S-variable result.

$$\ddot{y} + \alpha_1(\zeta_1)\dot{y} + \frac{1}{\alpha_2(\zeta_2)}y = 0 \quad \alpha_i(\zeta_i) \text{ affine of } \zeta_i \in [0 \ 1]$$

$$\eta^* \underbrace{\begin{bmatrix} 0 & 0 & P(\zeta) \\ 0 & 0 & 0 \\ P(\zeta) & 0 & 0 \end{bmatrix}}_{Q(P(\zeta))} \eta < 0 \quad \forall \underbrace{\left[\begin{array}{cc|c|cc} 1 & 0 & 0 & 0 & -1 \\ 0 & 1 & 1 & 0 & \alpha_1(\zeta_1) \\ 0 & 0 & \alpha_2(\zeta_2) & -1 & 0 \end{array} \right]}_{M(\zeta)} \underbrace{\begin{pmatrix} \dot{x} \\ \pi \\ x \end{pmatrix}}_{\eta} = 0$$

▲ Multi-polytopic result applies : $Q(P^{[v_1, v_2]}) \prec \left\{ \left[\begin{array}{cc} S_1^{[v_2]} & S_2^{[v_1]} \end{array} \right] \left[\begin{array}{c} M_1^{[v_1]} \\ M_2^{[v_2]} \end{array} \right] \right\}^{\mathcal{H}}$ at the 4 vertices.

▲ Less conservative than having $\left[\begin{array}{cc} S_1^{[v_2]} & S_2^{[v_1]} \end{array} \right] = S$ over all vertices.

▲ At the expense of increasing the size of π , and reordering of rows,

the $M(\zeta) = \begin{bmatrix} M_1(\zeta_1) \\ M_2(\zeta_2) \end{bmatrix}$ is always achievable.

$$T(\zeta) = N^*(\zeta)RN(\zeta) < 0 \quad N(\zeta) \text{ is polynomial (or rational) of } \{\zeta_1, \dots, \zeta_{\bar{k}}\}$$

- Equivalently written as

$$w^*Rw < 0 \quad \forall w = N(\zeta)z$$

- Descriptor version

$$\begin{pmatrix} w \\ z \end{pmatrix}^* \begin{bmatrix} R & 0 \\ 0 & 0 \end{bmatrix} \begin{pmatrix} w \\ z \end{pmatrix} < 0 \quad \forall \begin{bmatrix} -I & N(\zeta) \end{bmatrix} \begin{pmatrix} w \\ z \end{pmatrix} = 0$$

- At the expense of including additional algebraically constrained vectors π

$$\eta^* \begin{bmatrix} R & 0 \\ 0 & 0 \end{bmatrix} \eta = \eta^* Q \eta < 0 \quad \forall \begin{bmatrix} M_1(\zeta_1) \\ \vdots \\ M_{\bar{k}}(\zeta_{\bar{k}}) \end{bmatrix} \eta = 0 \quad M_k(\zeta_k) \text{ affine of } \zeta_k$$

$$N(\zeta) = \begin{bmatrix} (1 + 2\zeta_1)(4 + \zeta_2) & (1 + 2\zeta_1)\zeta_2 \\ (4 + \zeta_2) & \zeta_1 + \zeta_2 \end{bmatrix}$$

■ Decomposed in canonic monomial basis [Peaucelle and Sato, 2009]

$$N(\zeta)z = \begin{bmatrix} 4 + 8\zeta_1 & 0 \\ 4 & \zeta_1 \end{bmatrix} z + \begin{bmatrix} 1 + 2\zeta_1 & 1 + 2\zeta_1 \\ 1 & 1 \end{bmatrix} \zeta_2 z$$

gives a systematic way of building affine descriptor form for $w = N(\zeta)z$

$$\left[\begin{array}{cc|cc|cc} -1 & 0 & 1 + 2\zeta_1 & 1 + 2\zeta_1 & 4 + 8\zeta_1 & 0 \\ 0 & -1 & 1 & 1 & 4 & \zeta_1 \\ 0 & 0 & -1 & 0 & \zeta_2 & 0 \\ 0 & 0 & 0 & -1 & 0 & \zeta_2 \end{array} \right] \begin{pmatrix} w \\ \pi \\ z \end{pmatrix} = 0$$

$$N(\zeta) = \begin{bmatrix} (1 + 2\zeta_1)(4 + \zeta_2) & (1 + 2\zeta_1)\zeta_2 \\ (4 + \zeta_2) & \zeta_1 + \zeta_2 \end{bmatrix}$$

- Use Linear-Fractional Transformation (eg. in Robust Control Toolbox or LFR toolbox)

$$N(\zeta) = N_{11} + N_{12}\Delta(I - N_{22}\Delta)^{-1}N_{21} \quad \Delta \text{ diagonal matrix of } \zeta_1, \zeta_2$$

gives an easy (but usually large) descriptor form for $w = N(\zeta)z$

$$\begin{bmatrix} -I & N_{11} & N_{12}\Delta \\ 0 & N_{12} & I - N_{22}\Delta \end{bmatrix} \eta = 0$$

at the expense of reordering the rows the uncertainties appear as needed.

$$N(\zeta) = \begin{bmatrix} (1 + 2\zeta_1)(4 + \zeta_2) & (1 + 2\zeta_1)\zeta_2 \\ (4 + \zeta_2) & \zeta_1 + \zeta_2 \end{bmatrix}$$

▲ No need to decompose in canonic monomial basis, by exploiting the structure:

$$\left[\begin{array}{cc|cc} -1 & 0 & 1 + 2\zeta_1 & 0 \\ 0 & -1 & 1 & 0 \\ 0 & 0 & -1 & 4 + \zeta_2 \end{array} \right] \begin{pmatrix} w \\ \hat{\pi} \\ z \end{pmatrix} = 0$$

$$\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \forall \zeta \in [0, 1] \quad \Leftrightarrow \quad \exists S : Q(P^{[v]}) \prec \{ S M^{[v]} \}^{\mathcal{H}}$$

- ▼ S is of the size of M^* . May become very large.
- ▼ Need for efficient software to build limited size $M(\zeta)$, project to do so in Julia with Ch. Louembet
- ▼ Need to find systematic reduction (exact / approximate) tools for affine descriptor models
- ▲ Non conservative size reduction of LMIs if $M(\zeta) = T \begin{bmatrix} \hat{M}(\zeta) \\ \check{M} \end{bmatrix}$, T invertible

$$\exists \hat{S} : \begin{cases} \check{M}^{\perp T} Q_0 \check{M}^{\perp} \prec \{ \hat{S} \hat{M}_0 \check{M}^{\perp} \}^{\mathcal{H}} \\ \check{M}^{\perp T} Q_1 \check{M}^{\perp} \prec \{ \hat{S} \hat{M}_1 \check{M}^{\perp} \} \end{cases}$$

- ▲ Exists also a (conservative but efficient) size reduction of LMIs

$$\text{if } M(\zeta) = \begin{bmatrix} \hat{M}(\zeta) & \check{M} \end{bmatrix} T \text{ and } \begin{bmatrix} 0 \\ I \end{bmatrix}^* T^{-*} Q(\zeta) T^{-1} \begin{bmatrix} 0 \\ I \end{bmatrix} = \hat{Q}_{22} \succeq 0.$$

■ Bounded uncertainties, where $Q(\zeta) = (1 - \zeta)Q^{[0]} + \zeta Q^{[1]}$, $M(\zeta) = (1 - \zeta)M^{[0]} + \zeta M^{[1]}$

$$\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \zeta \in [0 \ 1]} \quad \Leftrightarrow \quad \exists S : \begin{cases} Q^{[0]} \prec \{SM^{[0]}\}^{\mathcal{H}} \\ Q^{[1]} \prec \{SM^{[1]}\}^{\mathcal{H}} \end{cases}$$

■ Unbounded uncertainties [Peaucelle and Sato, 2009] where $M(\zeta) = M^{[0]} + \zeta M^{[\infty]}$

$$\{ \eta^* Q \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \zeta} \quad \Leftrightarrow \quad \exists G = -G^* : Q \prec \{M^{[\infty]*} G M^{[0]}\}^{\mathcal{H}}$$

▲ Surprisingly simple proof

$$Q \prec \{M^{[\infty]*} G M^{[0]}\}^{\mathcal{H}} = \{M^{[\infty]*} G M(\zeta)\}^{\mathcal{H}} - \zeta \{M^{[\infty]*} G M^{[\infty]}\}^{\mathcal{H}}$$

last term is zero $M^{[\infty]*} G M^{[\infty]}\}^{\mathcal{H}} = M^{[\infty]*} (G + G^*) M^{[\infty]} = 0$. Hence

$$Q \prec \{SM(\zeta)\}^{\mathcal{H}} \quad , \quad \text{with } S = M^{[\infty]*} G$$

■ Bounded uncertainties, where $Q(\zeta) = (1 - \zeta)Q^{[0]} + \zeta Q^{[1]}$, $M(\zeta) = (1 - \zeta)M^{[0]} + \zeta M^{[1]}$

$$\{ \eta^* Q(\zeta) \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \zeta \in [0 \ 1]} \quad \Leftrightarrow \quad \exists S : \begin{cases} Q^{[0]} \prec \{ S M^{[0]} \}^{\mathcal{H}} \\ Q^{[1]} \prec \{ S M^{[1]} \}^{\mathcal{H}} \end{cases}$$

■ Unbounded uncertainties [Peaucelle and Sato, 2009] where $M(\zeta) = M^{[0]} + \zeta M^{[\infty]}$

$$\{ \eta^* Q \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \zeta} \quad \Leftrightarrow \quad \exists G = -G^* : Q \prec \{ M^{[\infty]*} G M^{[0]} \}^{\mathcal{H}}$$

■ Positive real uncertainties, where $M(\zeta) = M^{[0]} + \zeta M^{[\infty]}$

$$\{ \eta^* Q \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \zeta \geq 0} \quad \Leftrightarrow \quad \exists G = -G^* \quad D \succeq 0 : Q \prec \{ M^{[\infty]*} (D + G) M^{[0]} \}^{\mathcal{H}}$$

■ Positive complex uncertainties, where $M(\zeta) = M_0 + \zeta M_\infty$

$$\{ \eta^* Q \eta < 0 \quad \forall M(\zeta) \eta = 0 \} \quad \boxed{\forall \text{Re}(\zeta) \geq 0} \quad \Leftrightarrow \quad \exists D \succeq 0 : Q \prec \{ M^{[\infty]*} D M^{[0]} \}^{\mathcal{H}}$$

- Prove $N^*(j\omega)QN(j\omega) \prec 0$ where $N(j\omega) = \begin{bmatrix} (j\omega - A)^{-1}B \\ I \end{bmatrix}$ for all $\omega \in \mathbb{R}$

- Equivalent to $\{ \eta^* Q \eta < 0 \quad \forall \begin{bmatrix} j\omega - A & -B \end{bmatrix} \eta = 0 \} \quad \forall \omega$

- ▲ S-variable result: $\exists G = -G^* : Q \prec \left\{ \begin{bmatrix} -jI \\ 0 \end{bmatrix} G \begin{bmatrix} -A & -B \end{bmatrix} \right\}^{\mathcal{H}}$

- ▲ Exactly identical to KYP lemma: $\exists P = P^* (= -jG) : Q + \begin{bmatrix} A^*P + PA & PB \\ B^*P & 0 \end{bmatrix} \prec 0$

- Encourages to re-examine the central control results with the S-variable / descriptor viewpoint

- At the expense of increasing the size of π , uncertainties can be separated from design variables

$$\begin{bmatrix} E_x & E_\pi & A & B \\ 0 & KF_\pi & KC & KD - I \end{bmatrix} \begin{pmatrix} \dot{x} \\ \pi \\ x \\ u \end{pmatrix} = \begin{bmatrix} (1 - \zeta)M^{[0]} + \zeta M^{[1]} \\ KM_2 + M_3 \end{bmatrix} \eta = 0 \quad \zeta \in [0 \ 1]$$

- S-Variable robust stability analysis condition: $\exists P^{[v]} \succ 0, S, S^{[v]}$ such that

$$Q(P^{[v]}) \prec \left\{ SM^{[v]} + S^{[v]}(KM_2 + M_3) \right\} \quad v = 0, 1$$

[Sadabadi and Peaucelle, 2016]

$$\begin{bmatrix} E_x & E_\pi & A & B \\ 0 & KF_\pi & KC & KD - I \end{bmatrix} \eta = \begin{bmatrix} (1 - \zeta)M^{[0]} + \zeta M^{[1]} \\ KM_2 + M_3 \end{bmatrix} \eta = 0 \quad \zeta \in [0 \ 1]$$

■ Heuristic robust design condition: choose $K_\pi^{[v]}$ and $K_x^{[v]}$ such that the following 2 systems are stable

$$\begin{bmatrix} E_x^{[v]} & E_\pi^{[v]} & A^{[v]} & B^{[v]} \\ 0 & K_\pi^{[v]} & K_x^{[v]} & -I \end{bmatrix} \eta = \begin{bmatrix} M^{[v]} \\ M_4^{[v]} \end{bmatrix} \eta = 0 \quad v = 0, 1$$

any solution $K = V^{-1}W$ of the following LMIs robustly stabilizes the uncertain plant

$$Q(P^{[v]}) \prec \left\{ SM^{[v]} + M_4^{[v]*} (WM_2 + VM_3) \right\}^{\mathcal{H}} \quad v = 0, 1$$

▼ Good/Best choice of the full information feedback gains $K_\pi^{[v]}$ and $K_x^{[v]}$?

- Choose full-information feedback $K_\pi^{[v]}$, $K_x^{[v]}$ such that the following 2 systems are stable ?

$$\begin{bmatrix} E_x^{[v]} & E_\pi^{[v]} + B^{[v]}K_\pi^{[v]} & A^{[v]} + B^{[v]}K_x^{[v]} \end{bmatrix} \hat{\eta} = 0 \quad v = 0, 1$$

- and probably some more constraints (to be determined)

- Possible elegant solution in [Peaucelle et al., 2024], solve

$$\hat{Q}(R^{[v]}) \prec \left\{ \hat{M}^* \begin{bmatrix} E_x^{[v]} U_x^{[v]} & E_\pi^{[v]} U_\pi^{[v]} + B^{[v]} W_\pi^{[v]} & A^{[v]} U_x^{[v]} + B^{[v]} W_x^{[v]} \end{bmatrix} \right\}^{\mathcal{H}} \quad v = 0, 1$$

where $\hat{M} \hat{\eta} = 0$ describes a stable target system

and get $K_\pi^{[v]} = W_\pi^{[v]}(U_\pi^{[v]})^{-1}$, $K_x^{[v]} = W_x^{[v]}(U_x^{[v]})^{-1}$.

- Thank you for the good discussions and ideas!
- Looking forward for more collaborative results!



Aizerman, M. and Gantmakher, F. (1964).

Absolute Stability of Regulator Systems by , published by the Soviet Academy of Sciences in 1963.
Soviet Academy of Sciences.



Ebihara, Y., Peaucelle, D., and Arzelier, D. (2015).

S-Variable Approach to LMI-based Robust Control.
Communications and Control Engineering. Springer.







Peaucelle, D. (2023).

Exploring robust structured static output feedback design.
WUDS23.



Peaucelle, D., Arzelier, D., Bachelier, O., and Bernussou, J. (2000).

A new robust D-stability condition for real convex polytopic uncertainty.
Systems & Control Letters, 40(1):21–30.

-  Peaucelle, D., Ebihara, Y., and Hosoe, Y. (2024).
About an alternative s -variable condition for state-feedback design.
In European Control Conference, Stockholm.
-  Peaucelle, D. and Sato, M. (2009).
LMI tests for positive definite polynomials: Slack variable approach.
IEEE Trans. on Automat. Control, 54(4):886 – 891.
-  Sadabadi, M. and Peaucelle, D. (2016).
From static output feedback to structured robust static output feedback: A survey.
Annual Reviews in Control, 42:11–26.
-  Yakubovitch, V. (1971).
The S -procedure in nonlinear control theory.
Vestnik Leningrad University, pages 62–77.