

# Comparison of AlGaN/GaN High Electron Mobility Transistors grown by MOVPE on 3C-SiC/Si(111), Si(111) and 6H-SiC for RF applications

Marie Lesecq, Éric Frayssinet, Marc Portail, Micka Bah, Nicolas Defrance, Thi Huong Ngo, Mahmoud Abou Daher, Ali Abboud, Yassine Fouzi, Marcin Zielinski, et al.

## ► To cite this version:

Marie Lesecq, Éric Frayssinet, Marc Portail, Micka Bah, Nicolas Defrance, et al.. Comparison of AlGaN/GaN High Electron Mobility Transistors grown by MOVPE on 3C-SiC/Si(111), Si(111) and 6H-SiC for RF applications. International Workshop on Nitride Semi-conductors, IWN 2022, Oct 2022, Berlin, Germany. hal-04037282

## HAL Id: hal-04037282 https://hal.science/hal-04037282v1

Submitted on 6 Feb 2024

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

### Comparison of AlGaN/GaN High Electron Mobility Transistors grown by MOVPE on 3C-SiC/Si(111), Si(111) and 6H-SiC for RF applications

Marie Lesecq<sup>1</sup>, Eric Frayssinet<sup>2</sup>, Marc Portail<sup>2</sup>, Micka Bah<sup>3</sup>, Nicolas Defrance<sup>1</sup>, Thi Huong Ngo<sup>2</sup>, Mahmoud Abou Daher<sup>1</sup>, Ali Abboud<sup>1</sup>, Yassine Fouzi<sup>1</sup>, Marcin Zielinski<sup>4</sup>, Daniel Alquier<sup>3</sup>, Jean-Claude De Jaeger<sup>1</sup>, <u>Yvon Cordier<sup>2</sup></u>\*

<sup>1</sup>Univ. Lille, CNRS, Centrale Lille, Univ. Polytechnique Hauts-de-France, UMR 8520 – IEMN-Institut d'Electronique de Microélectronique et de Nanotechnologie, F-59000, Lille, France <sup>2</sup>Université Côte d'Azur, CNRS, CRHEA, rue B.Grégory, 06560 Valbonne, France <sup>3</sup>GREMAN, Université de Tours, INSA Centre Val de Loire, 37071 Tours, France <sup>4</sup>NOVASiC, Savoie Technolac, 73370 Le Bourget-du-Lac, France \*email: yvon.cordier@crhea.cnrs.fr

In spite of their outstanding performances for microwave power applications, transistors based on GaN-on-SiC [1] suffer from the lower availability and higher cost of the substrate compared to Silicon ones permitting also to get GaN devices interesting high frequency performances [2]. However, difficulties remain to grow high crystal quality and crack-free RF compatible GaN based epilayers on Silicon. More, the growth parameters of the AlN nucleation layer of High Electron Mobility Transistor (HEMT) structures strongly influence the propagation losses due to the risk of diffusion of Al and/or Ga into the Si substrate [3-4]. It has been reported that the use of 3C-SiC intermediate layer as a template for the growth of AlGaN/GaN HEMT heterostructures on Si substrate limits the risks of cracks generation, enhances the crystal quality of the GaN film [5] and limits the degradation of Silicon substrate resistivity permitting to preserve low RF propagation losses [6]. RF performances were reported on MOCVD grown AlGaN/GaN HEMTs using an ultrathin 3C-SiC intermediate layer. A current gain cutoff frequency (f<sub>T</sub>) of 176 GHz and a maximum oscillation frequency (f<sub>max</sub>) of 70 GHz were obtained on a 80 nm-rectangular gate length device [7]. But the thickening of the 3C-SiC intermediate layer seems suitable to improve the thermal dissipation, crystal quality, RF propagation losses and device performance. In this work, GaN epilayers were grown by MOVPE on a 0.8 µm thick 3C-SiC layer on Si(111) substrate having 5 kOhm.cm resistivity, and they were compared to ones grown directly on Silicon and 6H-SiC substrates. On 3C-SiC/Si, the HEMT structure exhibits a two-dimensional electron gas with a mobility higher to 2000 cm<sup>2</sup>/V.s and a sheet resistance of 392  $\Omega$ . Low RF losses of 0.4 dB/mm are obtained at 40 GHz as a result of a highly resistive interface with Silicon. More, short gate transistors were fabricated using e-beam lithography. In spite of ohmic contact resistance of 0.6  $\Omega$ .mm, a saturated current density of 0.7 A/mm is reached at a gate bias of +1V with a transconductance peak superior to 250 mS/mm for 75 nm T-shaped gate transistors. For the first time, a device with transition frequencies f<sub>T</sub>/f<sub>max</sub> of 60/98 GHz on such thick 3C-SiC template is reported, only 10 GHz behind the device we fabricated on bulk 6H-SiC, showing the capability of this new cost effective route for high frequency power applications.

#### References

[1] K. Harrouche et al, Journal of the Electron Devices Society, Vol.7, 1145, 2019.

- [2] P. Cui et al, Applied Physics Express 12, 104001, 2019.
- [3] S. Chang et al, Semiconductor Science and Technology, Vol.35, 035029, 2020.
- [4] M. Bah et al, Scientific Reports 10, 14166, 2020.
- [5] S. Leone et al, Journal of Applied Physics 125, 235701, 2019.
- [6] E. Frayssinet et al, Physica Status Solidi A 217, 190060, 2020.
- [7] W. Jatal et al, IEEE Electron Device Letters 36, 123, 2015.

#### **Supplementary information**




Figure 1: (left) Cross section picture of the HEMT structure grown on 3C-SiC/Si; (right) Top: scanning spreading resistance microscopy (SSRM) showing the resistivity drop at AlN/Si interface. Bottom: absence of resistivity drop at AlN/3C-SiC and 3C-SiC/Si interfaces.

Grown structure	Substrate resistivity [ohm.cm]	Losses at 40 GHz [dB/mm]
GaN on Si(111)	> 5000	1.2
GaN on 3C-SiC/Si(111)	> 5000	0.38
HEMT on 3C-SiC/Si(111)	> 5000	0.41
HEMT on 6H-SiC	semi-insulating	0.25

Table 1. Propagation losses at 40 GHz in the epi-layers grown on Si(111), 3C-SiC/Si templates and 6H-SiC substrate.




Figure 2: DC output characteristics of a 2 x 50  $\mu$ m x 0,075  $\mu$ m gate transistor fabricated on the AlGaN/GaN HEMT heterostructure grown on (a) Si(111), (b) 3C-SiC/Si(111) and (c) 6H-SiC (Vgs=0V to -5V, Vgs steps = -1V). (d) comparison of gains measured on the transistors.