



**HAL**  
open science

# Contrast re-enhancement of Total-Variation regularization jointly with the Douglas-Rachford iterations

Charles-Alban Deledalle, Nicolas Papadakis, Joseph Salmon

► **To cite this version:**

Charles-Alban Deledalle, Nicolas Papadakis, Joseph Salmon. Contrast re-enhancement of Total-Variation regularization jointly with the Douglas-Rachford iterations. Signal Processing with Adaptive Sparse Structured Representations (SPARS'15), Jul 2015, Cambridge, United Kingdom. hal-01187061

**HAL Id: hal-01187061**

**<https://hal.science/hal-01187061>**

Submitted on 26 Aug 2015

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# Contrast re-enhancement of Total-Variation regularization jointly with the Douglas-Rachford iterations

Charles-Alban Deledalle    Nicolas Papadakis  
 CNRS – Université Bordeaux  
 Institut de Mathématiques de Bordeaux, Talence, France  
 Email: firstname.lastname@math.u-bordeaux.fr

Joseph Salmon  
 CNRS LTCI – Télécom ParisTech  
 Institut Mines-Télécom, Paris, France  
 Email: joseph.salmon@telecom-paristech.fr

**Abstract**—Restoration of a piece-wise constant signal can be performed using anisotropic Total-Variation (TV) regularization. Anisotropic TV may capture well discontinuities but suffers from a systematic loss of contrast. This contrast can be re-enhanced in a post-processing step known as least-square refitting. We propose here to jointly estimate the refitting during the Douglas-Rachford iterations used to produce the original TV result. Numerical simulations show that our technique is more robust than the naive post-processing one.

## I. INTRODUCTION

We consider the reconstruction of a 2D signal identified as a vector  $u_0 \in \mathbb{R}^N$  from its noisy observation  $f = \Phi u_0 + w \in \mathbb{R}^P$  with  $w \in \mathbb{R}^P$  a zero-mean noise component and  $\Phi \in \mathbb{R}^{P \times N}$  a linear operator accounting for a loss of information (e.g., low-pass filter). Anisotropic TV regularization writes, for  $\lambda > 0$ , as [1]

$$u^{\text{TV}} \in \underset{u \in \mathbb{R}^N}{\operatorname{argmin}} \frac{1}{2} \|\Phi u - f\|^2 + \lambda \|\nabla u\|_1, \quad (1)$$

with  $\nabla u \in \mathbb{R}^{2N}$  being the concatenation of vertical and horizontal components of the discrete gradient vector field of  $u$ , and  $\|\nabla u\|_1 = \sum_i |(\nabla u)_i|$  being a sparsity promoting term. Anisotropic TV is known to recover piece-wise constant signals. However, even though the discontinuities can be correctly recovered in some cases, the amplitudes of  $u^{\text{TV}}$  are known to suffer from a loss of contrast compared to  $u_0$  [2].

## II. LEAST-SQUARE REFITTING PROBLEM

A simple technique to correct this effect, known as least-square refitting, consists in enhancing the amplitudes of  $u^{\text{TV}}$  while leaving unchanged the set of discontinuities, as

$$\tilde{u}^{\text{TV}} \in \underset{u; \operatorname{supp}(\nabla u) \subset \operatorname{supp}(\nabla u^{\text{TV}})}{\operatorname{argmin}} \|\Phi u - f\|^2 \quad (2)$$

where, for  $x \in \mathbb{R}^{2N}$ ,  $\operatorname{supp}(x) = \{i \in [2N]; |x_i| \neq 0\}$  denotes the support of  $x$ . Post-refitting identifies  $\operatorname{supp}(\nabla u^{\text{TV}})$  and solves (2) [3], typically with a conjugate gradient. However,  $u^{\text{TV}}$  is usually obtained thanks to a converging sequence  $u^k$ , and unfortunately,  $\operatorname{supp}(\nabla u^k)$  can be far from  $\operatorname{supp}(\nabla u^{\text{TV}})$  even though  $u^k$  can be made arbitrarily close to  $u^{\text{TV}}$ . Such erroneous support identifications can lead to results that strongly deviates from the solution  $\tilde{u}^{\text{TV}}$ .

## III. JOINT REFITTING WITH DOUGLAS-RACHFORD

To alleviate this difficulty, we build a sequence  $\tilde{u}^k$  jointly with  $u^k$  that converges towards a solution  $\tilde{u}^{\text{TV}}$ . We consider the Douglas-Rachford sequence  $u^k$  applied to the splitting TV reformulation [4] given by

$$u^{\text{TV}} \in \underset{u \in \mathbb{R}^N}{\operatorname{argmin}} \min_{z \in \mathbb{R}^N \times 2} \frac{1}{2} \|\Phi u - f\|^2 + \lambda \|z\|_1 + \iota_{\{z, u; z = \nabla u\}}(z, u)$$

where  $\iota_S$  is the indicator function of a set  $S$ . This leads to the proposed algorithm given, for  $\tau > 0$  and  $\beta \geq 0$ , by Eq. (3) (see right column). The sequence  $u^k$  is exactly the Douglas-Rachford sequence converging towards a solution  $u^{\text{TV}}$  [5]. Regarding  $\tilde{u}^k$ , we prove the following.

**Theorem 1.** *Let  $\alpha > 0$  be the minimum non zero value of  $|(\nabla u)_i|$ ,  $i \in [2N]$ . For  $0 < \beta < \alpha\lambda$ ,  $\tilde{u}^k$  converges towards a solution  $\tilde{u}^{\text{TV}}$ .*

*Sketch of proof:* As  $u^k$  converges towards a solution  $u^{\text{TV}}$ , for  $k$  large enough, we get after few manipulations and triangle inequalities that

$$\begin{cases} \mu^{k+1} = (\operatorname{Id} + \Delta)^{-1}(2u^k - \mu^k - \operatorname{div}(2z^k - \zeta^k))/2 + \mu^k/2, \\ \tilde{\mu}^{k+1} = (\operatorname{Id} + \Delta)^{-1}(2\tilde{u}^k - \tilde{\mu}^k - \operatorname{div}(2\tilde{z}^k - \tilde{\zeta}^k))/2 + \tilde{\mu}^k/2, \\ \zeta^{k+1} = \nabla \mu^{k+1}, & \tilde{\zeta}^{k+1} = \nabla \tilde{\mu}^{k+1}, \\ u^{k+1} = \mu^{k+1} + \tau \Phi^t (\operatorname{Id} + \tau \Phi \Phi^t)^{-1} (f - \Phi \mu^{k+1}), \\ \tilde{u}^{k+1} = \tilde{\mu}^{k+1} + \tau \Phi^t (\operatorname{Id} + \tau \Phi \Phi^t)^{-1} (f - \Phi \tilde{\mu}^{k+1}), \\ z^{k+1} = \Psi_{\zeta^{k+1}}(\zeta^{k+1}, \lambda), & \tilde{z}^{k+1} = \Pi_{\tilde{\zeta}^{k+1}}(\tilde{\zeta}^{k+1}, \lambda) \end{cases} \quad (3)$$

$$\text{where } \Psi_{\zeta}(\zeta, \lambda)_i = \begin{cases} 0 & \text{if } |\zeta_i| \leq \tau\lambda, \\ \zeta_i - \tau\lambda \operatorname{sign} \zeta_i & \text{otherwise} \end{cases}$$

$$\text{and } \Pi_{\tilde{\zeta}}(\tilde{\zeta}, \lambda)_i = \begin{cases} 0 & \text{if } |\zeta_i| \leq \tau\lambda + \beta, \\ \tilde{\zeta}_i & \text{otherwise.} \end{cases}$$



Fig. 1. Damaged image, result of TV, post-refitting and our joint-refitting.

$\{i; |\zeta_i^k| > \tau\lambda + \beta\} = \operatorname{supp}(\nabla u^{\text{TV}})$  (for the given range of  $\beta$ ). As a result, for  $k$  large enough, the sequence (3) can be rewritten by substituting  $\Pi_{\tilde{\zeta}}(\cdot, \lambda)$  by the projector onto  $\{u; \operatorname{supp}(u) \subset \operatorname{supp}(\nabla u^{\text{TV}})\}$  which is exactly the Douglas-Rachford sequence for the refitting problem (2) which is provably converging towards a solution  $\tilde{u}^{\text{TV}}$  [5].  $\square$

## IV. RESULTS AND DISCUSSION

Figure 1 shows results on an 8bits image damaged by a Gaussian blur of 2px and white noise  $\sigma = 20$ . The parameter  $\beta$  is chosen as the smallest positive value up to machine precision. While TV reduces the contrast, refitting recovers the original amplitudes and keep unchanged the discontinuities. Post-refitting offers comparable results to ours except for suspicious oscillations due to wrong support identification.

Being computing during the Douglas-Rachford iterations, our refitting strategy is free of post-processing steps such as support identification. It is moreover easy to implement and can be used likewise for other  $\ell_1$  analysis penalties. Extensions of this approach for isotropic TV or block sparsity regularizations are under investigation.

## REFERENCES

- [1] L. I. Rudin, S. Osher, and E. Fatemi, “Nonlinear total variation based noise removal algorithms,” *Physica D: Nonlinear Phenomena*, vol. 60, no. 1, pp. 259–268, 1992.
- [2] D. Strong and T. Chan, “Edge-preserving and scale-dependent properties of total variation regularization,” *Inverse problems*, vol. 19, no. 6, p. S165, 2003.
- [3] B. Efron, T. Hastie, I. Johnstone, and R. Tibshirani, “Least angle regression,” *Ann. Statist.*, vol. 32, no. 2, pp. 407–499, 2004.
- [4] P. L. Combettes and J.-C. Pesquet, “A douglas-rachford splitting approach to nonsmooth convex variational signal recovery,” *Selected Topics in Signal Processing, IEEE Journal of*, vol. 1, no. 4, pp. 564–574, 2007.
- [5] J. Douglas and H. Rachford, “On the numerical solution of heat conduction problems in two and three space variables,” *Transactions of the American mathematical Society*, pp. 421–439, 1956.