



HAL
open science

Projected dynamical systems in a complementarity formalism

W.P.M.H. Heemels, J.M. Schumacher, S. Weiland

► **To cite this version:**

W.P.M.H. Heemels, J.M. Schumacher, S. Weiland. Projected dynamical systems in a complementarity formalism. *Operations Research Letters*, 2000, 27 (2), pp.83-91. 10.1016/S0167-6377(00)00042-0 . hal-01660026

HAL Id: hal-01660026

<https://hal.science/hal-01660026>

Submitted on 9 Dec 2017

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Projected dynamical systems in a complementarity formalism

W.P.M.H. Heemels* J.M. Schumacher† S. Weiland‡

May 8, 2000

Abstract

Projected dynamical systems have been introduced by Dupuis and Nagurney as dynamic extensions of variational inequalities. In the systems and control literature, complementarity systems have been studied as input/output dynamical systems whose inputs and outputs are connected through complementarity conditions. We show here that, under mild conditions, projected dynamical systems can be written as complementarity systems.

Keywords: variational inequalities, complementarity, discontinuous dynamical systems, systems theory, optimization.

1 Introduction

In this paper, we connect two classes of discontinuous dynamical systems. One is the class of *projected dynamical systems* introduced by Dupuis and Nagurney [6] and further developed by Nagurney and Zhang [18]. These systems are described by differential equations of the form

$$\dot{x}(t) = \Pi_K(x(t), -F(x(t))), \quad (1)$$

where F is a vector field, K is a closed convex set, and Π_K is a projection operator that prevents the solution from moving outside the constraint set K (cf. section 2 below for a precise definition). These

*Dept. of Electrical Engineering, Eindhoven University of Technology, P.O. Box 513, 5600 MB Eindhoven, The Netherlands, and Dept. of Economics, Tilburg University, E-mail: w.p.m.h.heemels@tue.nl

†CWI, P.O. Box 94079, 1090 GB Amsterdam, The Netherlands, and Dept. of Economics, Tilburg University, E-mail: Hans.Schumacher@cwi.nl

‡Dept. of Electrical Engineering, Eindhoven University of Technology, P.O. Box 513, 5600 MB Eindhoven, The Netherlands, E-mail: s.weiland@tue.nl

systems are used for studying the behaviour of oligopolistic markets, urban transportation networks, traffic networks, international trade, and agricultural and energy markets (spatial price equilibria). Their stationary points can be characterized by means of variational inequalities; one may therefore say that projected dynamical systems provide a dynamic extension of variational inequalities.

We shall compare projected dynamical systems with *complementarity systems*, which may be considered as dynamical extensions of complementarity problems (cf. section 3). Although particular forms of complementarity systems have been used for a long time in the context of specific applications such as electrical networks with ideal diodes (see *e.g.* Van Bokhoven [2]) and mechanical objects subject to unilateral constraints (Lötstedt [15]), the idea of coupling complementarity conditions to a general input/output dynamical system has first been proposed in 1996 by Van der Schaft and Schumacher [24]. Within the general class of dynamical systems that is obtained in this way there is a natural subdivision corresponding to classifications that are used for input/output dynamical systems. In this paper we shall have occasion to use in particular so-called *gradient-type* complementarity systems. To our knowledge this specific class of dynamical systems has not been introduced before in the literature. We note, though, that the class of nonsmooth dynamical systems recently studied by Seeger [27] contains systems that may be considered as reversed-time versions of gradient-type complementarity systems with linear dynamics.

Complementarity systems are nonsmooth dynamical systems; they switch between several dynamical regimes and may show impulsive motions resulting in discontinuities of some system variables. Since complementarity systems are subject to both continuous dynamics and discrete switching, one may also consider them as a subclass of *hybrid dynamical systems* [1, 20, 26]. Because of the nonsmoothness of trajectories, the formulation of a solution concept for complementarity systems is nontrivial; see Van der Schaft and Schumacher [24, 25] and Heemels *et al.* [9, 13]. Questions of (local) existence and uniqueness of solutions have been studied under various assumptions in [13, 24, 25], Heemels *et al.* [10, 12], and Lootsma *et al.* [14]. Analysis of numerical simulation methods based on time-stepping can be found in Çamlıbel *et al.* [3] and [9].

The study of complementarity systems is motivated by a broad range of applications (see Heemels *et al.* [11] for an overview): electrical networks with diodes, mechanical systems subject to unilateral constraints or Coulomb friction, control systems with relays, saturation characteristics or deadzones, variable structure systems, dynamical systems with static piecewise linear relations, hydraulic systems with one-way valves and optimal control problems with state or control constraints.

It is well known that variational inequalities and complementarity problems are closely related; see for instance Harker and Pang [8]. It is therefore reasonable to expect that projected dynamical systems and complementarity systems are also related. In this paper we show that there is indeed a natural relationship. Specializing to the stationary points, we obtain as a corollary the classical result which states that, under mild conditions, variational inequalities may be rewritten as mixed nonlinear complementarity

problems [8, Prop. 2.2]. Moreover, we obtain a proof of existence and uniqueness of solutions of projected dynamical systems that is independent of the original proof by Dupuis and Nagurney [6] and in particular does not use the Skorokhod problem (see Skorokhod [28]). Complementarity systems have already been used extensively in the engineering literature (see for instance [15], Pfeiffer and Glocker [19], and [25]) and the establishment of a relation between the domains of projected dynamical systems and of complementarity systems makes it possible to compare and transfer analytic and computational techniques between the two. It also follows that the interpretation of projected dynamical systems as tatonnement or adjustment processes carries over to a class of complementarity systems.

The following notational conventions and terminology will be used. If k is a positive integer, \bar{k} denotes the set $\{1, \dots, k\}$. For an index set $I \subseteq \bar{k}$, we denote its complement with respect to \bar{k} by $I^c := \{i \in \bar{k} \mid i \notin I\}$. The cardinality of a set I will be denoted by $|I|$. A vector $u \in \mathbb{R}^k$ is said to be nonnegative (nonpositive) if $u_i \geq 0$ ($u_i \leq 0$) for all $i \in \bar{k}$, and in this case we write $u \geq 0$ ($u \leq 0$). Given a matrix $M \in \mathbb{R}^{k \times l}$ and subsets $I \subseteq \bar{k}$ and $J \subseteq \bar{l}$, we denote the submatrix $(M_{ij})_{i \in I, j \in J}$ by M_{IJ} . In case $I = \bar{k}$ we write $M_{\bullet J}$ rather than $M_{\bar{k}J}$, and similarly if $J = \bar{l}$ we use $M_{I\bullet}$. The transpose of a matrix M is denoted by M^\top . In the Euclidean space \mathbb{R}^k the standard inner product is denoted by $\langle \cdot, \cdot \rangle$ and for $u, v \in \mathbb{R}^k$ we write $u \perp v$ if $\langle u, v \rangle = u^\top v = 0$. We denote the restriction of a function $f : [0, T] \rightarrow \mathbb{R}$ to an interval $(a, b) \subseteq [0, T]$ by $f|_{(a,b)}$. A function $f : \mathbb{R}^n \rightarrow \mathbb{R}^p$ will be said to be real-analytic and convex if its component functions $f_i : \mathbb{R}^n \rightarrow \mathbb{R}$ are real-analytic and convex.

2 Projected dynamical systems

In this section we recall the definition of projected dynamical systems (PDS) [6, 18]. The defining ingredients are a closed convex set K , which usually corresponds to the constraint set of a particular application, and a vector field F whose domain contains K . The projected dynamics is described by the equation $\dot{x}(t) = -F(x(t))$ on the interior of K , but on the boundary a modification is applied to prevent the solution from leaving the constraint set.

To be more precise, let a closed and convex set $K \subseteq \mathbb{R}^n$ be given. The cone of inward normals at $x \in K$ is defined by

$$n(x) = \{\gamma \mid \langle \gamma, x - k \rangle \leq 0 \text{ for all } k \in K\}. \quad (2)$$

Note that $n(x) = \{0\}$, when x is contained in the interior of K . Given $x \in K$ and $v \in \mathbb{R}^n$, define the projection of the vector v at x with respect to K by

$$\Pi_K(x, v) = v - \langle v, n^*(x) \rangle n^*(x), \quad (3a)$$

where

$$n^*(x) \in \arg \max_{n \in n(x), \|n\| \leq 1} \langle v, -n \rangle. \quad (3b)$$

Note that $\Pi_K(x, v)$ is well-defined even though $n^*(x)$ may not be uniquely specified by (3b). The *projected dynamical system* $\text{PDS}(F, K)$ corresponding to a closed convex set K and a vector field F on K is defined by

$$\dot{x}(t) = \Pi_K(x(t), -F(x(t))). \quad (4)$$

The ordinary differential equation (4) has a discontinuous right hand side and is therefore not covered by the standard theory of differential equations. The following notion of solution is proposed in [18].

Definition 2.1 [18] An absolutely continuous function $x : [0, T] \rightarrow K$ is a *solution* to $\text{PDS}(F, K)$ on $[0, T]$ with initial state $x_0 \in K$ if $x(0) = x_0$ and (4) holds almost everywhere in $[0, T]$.

The definition (3) of the projection operator Π_K is convenient for the development below. An alternative definition is the following one. For $x \in K$ and $v \in \mathbb{R}^n$ define

$$\Pi_K(x, v) = \lim_{\delta \rightarrow 0} \frac{P_K(x + \delta v) - x}{\delta}, \quad (5)$$

where P_K is the projection operator that assigns to each vector x in \mathbb{R}^n the vector in K that is closest to x in the Euclidean norm $\|\cdot\|$ (i. e. $P_K x = \arg \min_{k \in K} \|x - k\|$). It has been proven by Dupuis [5] that the formulations in (3) and (5) are equivalent when K is convex and compact with nonempty interior. In [6] the same result is stated under the assumption that K is a convex polyhedron (i. e. an intersection of finitely many closed half-spaces).

3 Complementarity systems

A complementarity system may be specified (in “semi-explicit affine form”, see [24]) by functions $f : \mathbb{R}^n \rightarrow \mathbb{R}^n$, $g_i : \mathbb{R}^n \rightarrow \mathbb{R}^n$ and $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$. The defining equations for the complementarity system corresponding to f , g_i and h are

$$\dot{x}(t) = f(x(t)) + \sum_{i=1}^p g_i(x(t)) u_i(t) \quad (6a)$$

$$y(t) = h(x(t)) \quad (6b)$$

$$0 \leq y(t) \perp u(t) \geq 0 \quad (6c)$$

The relation (6c) implies that for all i at least one of the equalities $u_i(t) = 0$ and $y_i(t) = 0$ must be satisfied. Hence, for all times t there exists an index set J such that $u_i(t) = 0$, $i \notin J$ and $y_i(t) = 0$, $i \in J$.

In the engineering literature this index set is sometimes called the *active index set*, *mode* or *discrete state* of the system at time t . The mode may change during the time evolution of the system. The times at which this happens are called *event times*.

In general a complementarity system may not have a continuous solution, even when the defining functions f , g and h are smooth, and so one needs to introduce larger function spaces to define solutions (cf. [12, 13, 24, 25]). Although the solution concept below is not the most general one, it suffices for the purpose of the paper. We need the notion of *right-isolated* sets. A subset \mathcal{E} of \mathbb{R} is said to be right-isolated if for each $t \in \mathcal{E}$ there exists an $\varepsilon > 0$ such that $(t, t + \varepsilon) \cap \mathcal{E} = \emptyset$.

Definition 3.1 A continuous function $x : [0, T] \rightarrow \mathbb{R}^n$ is called a *solution* to (6) with initial state x_0 on the interval $[0, T]$, if $x(0) = x_0$ and there exist a right-isolated set $\mathcal{E} \subset [0, T]$ and two functions $u : [0, T] \rightarrow \mathbb{R}^p$, $y : [0, T] \rightarrow \mathbb{R}^p$ such that for any interval $(a, b) \subseteq [0, T]$ with $(a, b) \cap \mathcal{E} = \emptyset$ the following conditions hold:

1. the restriction $(u, x, y)|_{(a, b)}$ is real-analytic and satisfies (6a–6b) for all $t \in (a, b)$;
2. there exists an index set $J \subseteq \bar{p}$ such that $u_{J^c}(t) = 0$, $y_J(t) = 0$, $u_J(t) \geq 0$ and $y_{J^c}(t) \geq 0$ for all $t \in (a, b)$.

This definition allows solutions that exhibit accumulations of event times (“Zeno solutions”). Since \mathcal{E} is right-isolated, such accumulations only take place forward in time. Note that a similar restriction is not present in Def. 2.1.

By considering several types of dynamics in (6a–6b), one may define several classes of complementarity systems such as *linear* complementarity systems [13, 24] and *Hamiltonian* complementarity systems [24]. For the purpose of this paper we shall be particularly interested in *gradient-type complementarity systems*; these systems are related to the *gradient systems* that have been studied by Van der Schaft [23]. To specify a gradient-type complementarity system, take functions $F : \mathbb{R}^n \rightarrow \mathbb{R}^n$ and $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$. Let the gradients of the component functions $h_i(x)$ of $h(x)$ be denoted by $\nabla h_i(x)$ (taken to be row-vectors) and let $H(x)$ denote the matrix whose i -th row is equal to $\nabla h_i(x)$ (i.e. the Jacobian matrix of h at x). The gradient-type complementarity system GTCS(F, h) is given by the equations

$$\dot{x}(t) = -F(x(t)) + \sum_{i=1}^p [\nabla h_i(x(t))]^\top u_i(t) \quad (7a)$$

$$y(t) = h(x(t)) \quad (7b)$$

$$0 \leq y(t) \perp u(t) \geq 0, \quad (7c)$$

which is a special case of (6). Equation (7a) can compactly be written in terms of the Jacobian H of h as

$$\dot{x}(t) = -F(x(t)) + [H(x(t))]^\top u(t). \quad (8)$$

The above definition makes implicit use of the standard inner product of \mathbb{R}^n , but it would also be possible to use a coordinate-free treatment as in [23]. There is a closer analogy with the gradient systems studied by Van der Schaft when in (7) the function F is defined as the gradient of some potential function. In that case (7) is referred to as a *gradient complementarity system*.

4 Projected dynamical systems as complementarity systems

In this section we consider projected dynamical systems specified by a vector field F and a convex set K , and we provide conditions under which these systems can be rewritten as gradient-type complementarity systems. It will be assumed that the convex set K can be represented by means of finitely many inequalities.

Assumption 4.1 The set K allows a representation in the form

$$K = \{x \in \mathbb{R}^n \mid h(x) \geq 0\} \quad (9)$$

where $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$ is real-analytic and convex.

If h represents K as in (9), we define for $x \in K$ the *active index set* $I(x)$ as

$$I(x) := \{i \in \bar{p} \mid h_i(x) = 0\}. \quad (10)$$

To prevent technical complications that would obscure the main line of reasoning, we shall use the following constraint qualification in conjunction with Assumption 4.1.

Assumption 4.2 For h as in (9) and H the Jacobian of h , the matrix $H_{I(x)^\bullet}(x)$ has full row rank for all $x \in K$.

Concerning the vector field F , we shall use the following assumptions.

Assumption 4.3 The vector field F is real-analytic.

Assumption 4.4 There exists a constant $B \in \mathbb{R}$ such that F satisfies the linear growth condition

$$\|F(x)\| \leq B(1 + \|x\|) \text{ for all } x \in K. \quad (11)$$

Assumption 4.5 There exists a constant $C \in \mathbb{R}$ such that

$$\langle -F(x) + F(y), x - y \rangle \leq C\|x - y\|^2 \text{ for all } x, y \in K. \quad (12)$$

Remark 4.6 Assumption 4.1 implies that K is convex and closed. A characterization of K as in (9) is possible in all applications of projected dynamical systems mentioned in [18]. In [6] it is even assumed that K is a convex polyhedron. Assumptions 4.4 and 4.5 are used in [18] to prove existence and uniqueness of solutions to the projected dynamical system specified by F and K .

The following theorem is the main result of this paper. The theorem will be proved in the next section.

Theorem 4.7 *Let a set $K \subseteq \mathbb{R}^n$, a vector field $F : \mathbb{R}^n \rightarrow \mathbb{R}^n$ and a function $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$ be given such that Assumptions 4.1–4.5 are satisfied. For all initial states $x_0 \in K$, both the projected dynamical system $PDS(F, K)$ and the gradient-type complementarity system $GTCS(F, h)$ have a unique solution defined on $[0, \infty)$. Moreover, these solutions coincide.*

Remark 4.8 It will follow from the proof given below that without Assumption 4.4 the theorem still holds, except that the solutions are not guaranteed to exist on $[0, \infty)$. To be specific, suppose that $[0, T_1)$ is the maximal interval on which a solution can be defined for $PDS(F, K)$. Similarly, let $[0, T_2)$ be the maximal interval for which $GTCS(F, h)$ admits a solution. Then $T := T_1 = T_2 > 0$, both solutions are unique on $[0, T)$, and the solutions are equal to each other.

Remark 4.9 The constraint qualification Assumption 4.2 is introduced here for simplicity. In the literature on complementarity systems, weaker assumptions have been used. Specifically, Lötstedt [15] uses the condition that the Jacobian matrix $H(x)$ should have locally *constant* row rank to prove the existence and uniqueness of solutions to equations representing unilaterally constrained mechanical systems.

Remark 4.10 Thm. 4.7 provides some additional information about the solutions to $PDS(F, K)$. Under the assumptions of the theorem, solutions to projected dynamical system are real-analytic on the open intervals belonging to a set of the form $[0, \infty) \setminus \mathcal{E}$. Moreover, the exceptional set (the set of event times) \mathcal{E} is a right-isolated set.

Remark 4.11 It follows in particular that, under the conditions of Thm. 4.7, the stationary points of the projected dynamical system $PDS(F, K)$ coincide with those of the gradient-type complementarity system $GTCS(F, h)$. When K is a convex polyhedron, the stationary points \bar{x} of $PDS(F, K)$ are given by the variational inequality [18, Lemma 1]

$$\langle F(\bar{x}), x - \bar{x} \rangle \geq 0 \quad \forall x \in K. \quad (13)$$

The stationary points \bar{x} of $GTCS(F, h)$ are given by the mixed nonlinear complementarity problem

$$0 = -F(\bar{x}) + \sum_{i=1}^p [\nabla h_i(\bar{x})]^\top u_i \quad (14a)$$

$$y = h(\bar{x}) \quad (14b)$$

$$0 \leq y \perp u \geq 0. \quad (14c)$$

In this way we recover the well-known result (see for instance [8, Prop.2.2]) that, under a suitable constraint qualification, variational inequalities may be rewritten as mixed nonlinear complementarity problems.

5 Proof of the main result

We start with a characterization of the projection Π_K in terms of a minimization problem. The proof will be given below on the basis of a duality argument.

Theorem 5.1 *Let $K \subset \mathbb{R}^n$ be of the form (9) for a real-analytic and convex function $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$. For all $x \in K$ and $v \in \mathbb{R}^n$, we have*

$$\Pi_K(x, v) = \arg \min_{w \in W(x)} \|w - v\|, \quad (15)$$

where $W(x)$ is the “cone of admissible velocities” given by

$$W(x) = \{w \in \mathbb{R}^n \mid \nabla h_i(x)w \geq 0 \text{ for all } i \in I(x)\} \quad (16)$$

with $I(x)$ specified by (10).

The duality result that we will use to prove Thm. 5.1 is stated in Prop. 5.2 below. The notation C^0 is used to denote the polar cone (see e. g. Rockafellar [21, p. 121]) of a set $C \subseteq \mathbb{R}^n$:

$$C^0 = \{x \in \mathbb{R}^n \mid \langle x, y \rangle \leq 0 \text{ for all } y \in C\}. \quad (17)$$

Proposition 5.2 *Let $W \subseteq \mathbb{R}^n$ be a closed convex cone with nonempty interior and let $v \in \mathbb{R}^n$ be given. Define w^* by*

$$w^* = \arg \min_{w \in W} \|w - v\| \quad (18)$$

and let z^* be such that

$$z^* \in \arg \max_{z \in W^0, \|z\| \leq 1} \langle v, z \rangle. \quad (19)$$

Then

$$w^* = v - \langle v, z^* \rangle z^*. \quad (20)$$

Proof. We apply the Fenchel duality theorem (Luenberger [16, p. 201]) to the convex function $f(w) := \|w - v\|$ defined on $C := \mathbb{R}^n$ and the concave function $g(w) := 0$ defined on $D := W$. One easily computes (cf. for instance [21, Section 12]) that the conjugate sets of C and D are $C^* = \{z \in \mathbb{R}^n \mid \|z\| \leq 1\}$ and

$D^* = -W^0$, and that the conjugate functions of f and g are given by $f^*(z) = \langle v, z \rangle$ for $z \in C^*$ and $g^*(z) = 0$ for $z \in D^*$. From the Fenchel duality theorem, we therefore have

$$\min_{w \in W} \|w - v\| = \max_{z \in W^0, \|z\| \leq 1} \langle v, z \rangle. \quad (21)$$

Now, suppose first that $\min_{w \in W} \|w - v\| > 0$; then $\|z^*\| = 1$. In this case, there exists a real number $\alpha \geq 0$ such that $w^* - v = -\alpha z^*$ [16, p. 136]. We have $-\alpha = -\|\alpha z^*\| = -\|w^* - v\| = -\langle v, z^* \rangle$ by (21); this proves (20). Next, suppose that $\min_{w \in W} \|w - v\| = 0$. Then $v \in W$ and hence $w^* = v$. We have $\max_{z \in W^0, \|z\| \leq 1} \langle v, z \rangle = 0$, so that $\langle v, z^* \rangle = 0$ and consequently equation (20) is also correct in this case. \square

Remark 5.3 The proof implies that $\langle w^*, z^* \rangle = 0$. Together with the conditions $w^* \in W$, $z^* \in W^0$, and $v = w^* + \langle v, z^* \rangle z^*$, this shows that $\langle v, z^* \rangle z^*$ is actually the projection $P_{W^0} v$ of v onto the cone W^0 (Moreau [17, p. 238]).

Proof of Thm. 5.1 Fix an arbitrary $x \in K$. From [21, Cor. 23.7.1 and 23.8.1] it follows that the cone of inward normals of K at x , denoted by $n(x)$, and the cone of inward normals of $W(x)$ at 0, denoted by $n_{W(x)}(0)$ satisfy

$$n(x) = n_{W(x)}(0) = \left\{ \gamma \in \mathbb{R}^n \mid \gamma = \sum_{i \in I(x)} [\nabla h_i(x)]^\top \lambda_i \text{ for certain } \lambda_i \geq 0 \right\}. \quad (22)$$

By definition of the cone of inward normals and the polar cone (see (2) and (17)), $n_{W(x)}(0)$ is equal to $-W(x)^0$. Hence, $n(x) = -W(x)^0$. The claim of the theorem now follows by applying Prop. 5.2 to $W = W(x)$ and using that $W^0 = -n(x)$. \square

Next we establish a connection to a linear complementarity problem (LCP). See Cottle *et al.* [4] for an extensive treatment of LCPs.

Theorem 5.4 *Let a subset K of \mathbb{R}^n be of the form (9) for a real-analytic and convex function $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$. Fix $x \in K$. Let H be the Jacobian matrix of h at x , and let $I := I(x) = \{i \mid h_i(x) = 0\}$ be the active index set. Then we have*

$$\Pi_K(x, v) = v + H_{I^\bullet}^\top u \quad (23a)$$

where the vector $u \in \mathbb{R}^{|I|}$ solves the LCP

$$0 \leq u \perp H_{I^\bullet} v + H_{I^\bullet} [H_{I^\bullet}]^\top u \geq 0. \quad (23b)$$

Proof. By Thm. 5.1, the vector $\Pi_K(x, v)$ is the projection of v onto the cone $W(x)$ defined in (16). In terms of the notation introduced in the statement of the theorem, we have

$$W(x) = \{w \in \mathbb{R}^n \mid H_{I^\bullet} w \geq 0\}. \quad (24)$$

The fact that the projection onto this cone can be found from (23) is well-known; one may for instance use the Kuhn-Tucker conditions. An alternative approach is to use the result by Moreau [17] which states that in order to compute the projection of a vector v in a Hilbert space on a closed cone W , it is enough to find w and w^0 such that $v = w + w^0$, $w \in W$, $w^0 \in W^0$, and $w \perp w^0$; the projection $P_W v$ is then given by w . In our case $W(x)$ is given by (24) so that the polar cone $W^0(x)$ can be written as (see *e.g.* the proof of Thm. 5.1)

$$W^0(x) = \{w^0 \in \mathbb{R}^n \mid w^0 = -[H_{I_\bullet}]^\top u \text{ for some } u \geq 0\}. \quad (25)$$

Therefore the three conditions of the LCP (23b) are exactly the conditions that ensure, by Moreau's theorem, that $\Pi_K(x, v)$ is given by (23). Note in particular that the condition $[H_{I_\bullet}]^\top u \perp v + [H_{I_\bullet}]^\top u$ is equivalent to $u \perp H_{I_\bullet} v + H_{I_\bullet} [H_{I_\bullet}]^\top u$. \square

The discussion so far may be summarized as follows.

Corollary 5.5 *A function $x : [0, T] \rightarrow \mathbb{R}^n$ is a solution to the projected dynamical system (4) if and only if there exists a locally integrable function $u : [0, T] \rightarrow \mathbb{R}^p$ such that, with $I(x)$ the active index set as in (10) and $H(x)$ the Jacobian matrix of h at $x \in K$, one has for almost all $t \in [0, T]$:*

$$\dot{x}(t) = -F(x(t)) + [H_{I(x(t))_\bullet}(x(t))]^\top u_{I(x(t))}(t) \quad (26a)$$

$$u_{I(x(t))^c}(t) = 0 \quad (26b)$$

$$0 \leq u_{I(x(t))}(t) \perp -H_{I(x(t))_\bullet}(x(t))F(x(t)) + H_{I(x(t))_\bullet}(x(t))[H_{I(x(t))_\bullet}(x(t))]^\top u_{I(x(t))}(t) \geq 0. \quad (26c)$$

In the proof of the main theorem we shall use the following result, which can easily be derived from Thm. 3.2 in [25]. The quoted theorem gives a local existence and uniqueness result for complementarity systems of the form (6).

Theorem 5.6 *Let real-analytic functions $F : \mathbb{R}^n \rightarrow \mathbb{R}^n$ and $h : \mathbb{R}^n \rightarrow \mathbb{R}^p$ be given. Take $x_0 \in \mathbb{R}^n$ such that $h(x_0) \geq 0$. If Assumption 4.2 is satisfied, then there exists an $\varepsilon > 0$ such that GTCS(F, h) has a solution x on $[0, \varepsilon)$ with initial condition x_0 . Moreover, this solution is unique.*

Proof. Define $I = I(x_0)$ as in (10) and apply Thm. 3.2 in [25] to the system GTCS(F, h_I), *i.e.* $\dot{x}(t) = -F(x(t)) + [H_{I_\bullet}(x(t))]^\top u_I(t)$ and $0 \leq h_I(x(t)) \perp u_I(t) \geq 0$ with $I = I(x_0)$. Since $h_i(x_0) > 0$ for $i \notin I(x_0)$, it is clear that continuous solutions to GTCS(F, h_I) with initial state x_0 are solutions to GTCS(F, h) for sufficiently small t , and vice versa.

Note that $H_{I_\bullet}(x_0)[H_{I_\bullet}(x_0)]^\top$ is positive definite due to Assumption 4.2 and hence, is also a P-matrix (*i.e.* has only positive principal minors) [4, Thm. 3.1.6 and Thm. 3.3.7]. Consequently, Thm. 3.2 in [25]

applies to $\text{GTCS}(F, h_I)$ and the result follows. \square

Now we are in a position to prove the main result of this paper.

Proof of Thm. 4.7 Take $x_0 \in K$. According to Theorem 5.6 there exists a real-analytic triple (u, x, y) that satisfies (7) on $[0, \varepsilon)$. In particular, there exists an index set $J \subseteq \bar{p}$ such that $y_J(t) = 0$ and $u_{J^c}(t) = 0$ for all $t \in [0, \varepsilon)$.

We now want to show that the trajectory x that has been defined in this way on $[0, \varepsilon)$ is also a solution to $\text{PDS}(F, K)$ on $[0, \varepsilon)$. It is immediately clear that (26a) is satisfied because it is just another way of writing (8). For $x \in K$, define $I(x)$ as in (10). From the fact that $y_J(t) = 0$ on $[0, \varepsilon)$ it follows that $J \subseteq I(x(t))$ for $t \in [0, \varepsilon)$. Therefore $I(x(t))^c \subseteq J^c$ and so $u_{I(x(t))^c}(t) = 0$ for $t \in [0, \varepsilon)$. Hence, (26b) is satisfied. It remains to show that $u_{I(x(t))}(t)$ satisfies the LCP (26c) on $(0, \varepsilon)$. It is clear from (7c) that the inequality $u_{I(x(t))}(t) \geq 0$ is satisfied on $(0, \varepsilon)$. For $t \in (0, \varepsilon)$, we have

$$0 = \dot{y}_J(t) = -H_{J^\bullet}(x(t))F(x(t)) + H_{J^\bullet}(x(t))[H_{J^\bullet}(x(t))]^\top u_J(t). \quad (27)$$

Dropping all arguments now to lighten the notation, we have from $u_{J^c} = 0$ and $J \subseteq I$ that

$$(H_{I^\bullet}[H_{I^\bullet}]^\top u_I)_J = H_{J^\bullet}[H_{J^\bullet}]^\top u_J. \quad (28)$$

Since obviously $(H_{I^\bullet}F)_J = H_{J^\bullet}F$, it follows from (27) and from $u_{J^c} = 0$ that the orthogonality condition in (26c) holds. The final inequality in (26c) follows by expressing $\dot{y}_i(t)$ similarly to (27), and noting that $\dot{y}_i(t) \geq 0$ whenever $y_i(t) = 0$ (*i.e.* whenever $i \in I(x(t))$), because otherwise the inequality $y_i(t) \geq 0$ on $[0, \varepsilon)$ would be violated.

If the limit $\lim_{t \uparrow \varepsilon} x(t) =: x(\varepsilon)$ exists, the existence of a solution to (7) starting from $x(\varepsilon)$ on $[\varepsilon, \varepsilon + \varepsilon_1)$ for some $\varepsilon_1 > 0$ follows from Thm. 5.6. Hence, we have a solution x to (7) on $[0, \varepsilon + \varepsilon_1)$ in the sense of Definition 3.1. In the same way as above, it can be shown that x is a solution of $\text{PDS}(F, K)$ on $[0, \varepsilon + \varepsilon_1)$.

We now have to show that actually a solution to $\text{GTCS}(F, h)$ can be constructed on all of $[0, \infty)$. In principle it might happen that the above construction only leads to a solution on some interval $[0, T)$ with $T < \infty$. To proceed by contradiction, assume that we are in such a situation. The following estimates hold for $0 \leq t \leq T$:

$$\begin{aligned} \|x(t)\| &\leq \|x_0\| + \int_0^t \|\Pi_K(x(\tau), -F(x(\tau)))\| d\tau \\ &\leq \|x_0\| + \int_0^t \|F(x(\tau))\| d\tau \\ &\leq \|x_0\| + BT + B \int_0^t \|x(\tau)\| d\tau. \end{aligned}$$

The second step follows easily from the definition of Π_K (see [18, Eq. (2.19)] or use the orthogonality mentioned in Remark 5.3) and the third inequality is a consequence of (11). Using Gronwall's lemma we

see from this that $x(\cdot)$ is bounded on $[0, T)$; say $\|x(t)\| \leq M$ for $t \in [0, T)$ for some constant $M > 0$. It follows in particular that no “finite escape time” can occur. Moreover, it follows that the solution x is Lipschitz continuous and hence uniformly continuous on $[0, T)$. Indeed, for $0 \leq t < s < T$ we have

$$\begin{aligned} \|x(t) - x(s)\| &\leq \int_t^s \|\Pi_K(x(\tau), -F(x(\tau)))\| d\tau \\ &\leq \int_t^s \|F(x(\tau))\| d\tau \\ &\leq B \int_t^s (1 + \|x(\tau)\|) d\tau \\ &\leq B(1 + M)(s - t). \end{aligned}$$

By a standard result in analysis (see for instance Rudin [22, Exc.4.13]) this implies that the limit $x(T) := \lim_{t \uparrow T} x(t)$ exists. Since by continuity arguments $h(x(T)) \geq 0$, continuation is possible beyond T according to Thm.5.6, and we have reached a contradiction. Therefore, it follows that there is a unique solution of the gradient-type complementarity system GTCS(F, h) on $[0, \infty)$ which is also a solution of the projected dynamical system PDS(F, K). The uniqueness of solutions to PDS(F, K) follows from Assumption 4.5 as in [18, p.33]. \square

Remark 5.7 The existence of solutions to PDS(F, K) on $[0, \infty)$ is shown in [18] by a method based on the Skorokhod Problem [28]. The proof above provides an alternative argument. In fact the proof shows that Assumptions 4.1–4.3 are sufficient for *local* existence of solutions to PDS(F, K). With the additional Assumption 4.4, one can prove existence on $[0, \infty)$. The argument to prove uniqueness uses Assumption 4.5 and is essentially due to Filippov [7].

6 Conclusions

We have shown that, under mild conditions, projected dynamical systems can be rewritten as gradient-type complementarity systems. This result may be looked at as a dynamic version of the well known fact that, under suitable conditions, variational inequalities may be rewritten as mixed nonlinear complementarity problems. The class of gradient-type complementarity systems is a subclass of the class of complementarity systems which has received a considerable amount of attention in the engineering and applied physics literature. The establishment of a connection between the domains of projected dynamical systems and complementarity systems facilitates the transfer of techniques from one domain to the other. As an interesting bonus, we have obtained a new, and in the authors’ opinion more direct, proof for the existence of solutions to projected dynamical systems.

References

- [1] P.J. Antsaklis and A. Nerode (guest eds.). Special issue on hybrid control systems. *IEEE Transactions on Automatic Control*, 43(4), 1998.
- [2] W.M.G. van Bokhoven. *Piecewise Linear Modelling and Analysis*. Kluwer, Deventer, the Netherlands, 1981.
- [3] M.K. Çamlıbel, W.P.M.H. Heemels, and J.M. Schumacher. Dynamical analysis of linear passive networks with ideal diodes. Part II: consistency of a time-stepping method. Technical Report 00 I/03, Eindhoven University of Technology, Dept. of Electrical Engineering, Measurement and Control Systems, Eindhoven, The Netherlands, 2000.
- [4] R.W. Cottle, J.-S. Pang, and R.E. Stone. *The Linear Complementarity Problem*. Academic Press, Boston, 1992.
- [5] P. Dupuis. Large deviations analysis of reflected diffusions and constrained stochastic approximation algorithms in convex sets. *Stochastics*, 21:63–96, 1987.
- [6] P. Dupuis and A. Nagurney. Dynamical systems and variational inequalities. *Annals of Operations Research*, 44:9–42, 1993.
- [7] A. F. Filippov. Differential equations with discontinuous right-hand side. *Matemat. Sbornik.*, 51:99–128, 1960. In Russian. English translation: *Am. Math. Soc. Transl.* 62 (1964).
- [8] P. T. Harker and J.-S. Pang. Finite-dimensional variational inequality and nonlinear complementarity problems: a survey of theory, algorithms and applications. *Math. Progr. Ser. B*, 48:161–220, 1990.
- [9] W.P.M.H. Heemels. *Linear complementarity systems: a study in hybrid dynamics*. Ph.D. dissertation Eindhoven University of Technology, Dept. of Electrical Engineering, Eindhoven, The Netherlands, 1999.
- [10] W.P.M.H. Heemels, M.K. Çamlıbel, and J.M. Schumacher. Dynamical analysis of linear passive networks with ideal diodes. Part I: well-posedness. Technical Report 00 I/02, Eindhoven University of Technology, Dept. of Electrical Engineering, Measurement and Control Systems, Eindhoven, The Netherlands, 2000.
- [11] W.P.M.H. Heemels, J.M. Schumacher, and S. Weiland. Applications of complementarity systems. In *Proceedings of the European Control Conference in Karlsruhe (Germany)*, 1999.
- [12] W.P.M.H. Heemels, J.M. Schumacher, and S. Weiland. The rational complementarity problem. *Linear Algebra and its Applications*, 294(1-3):93–135, 1999.
- [13] W.P.M.H. Heemels, J.M. Schumacher, and S. Weiland. Linear complementarity systems. *SIAM Journal on Applied Mathematics*, 60(4):1234–1269, 2000.

- [14] Y.J. Lootsma, A.J. van der Schaft, and M.K. Çamlıbel. Uniqueness of solutions of relay systems. *Automatica*, 35(3):467–478, 1999.
- [15] P. Lötstedt. Mechanical systems of rigid bodies subject to unilateral constraints. *SIAM Journal on Applied Mathematics*, 42:281–296, 1982.
- [16] D.G. Luenberger. *Optimization by Vector Space Methods*. Wiley, Chichester, 1969.
- [17] J.J. Moreau. Décomposition orthogonale d’un espace hilbertien selon deux cônes mutuellement polaires. *C.R. Académie des Sciences Paris*, 255:238–240, 1962.
- [18] A. Nagurney and D. Zhang. *Projected Dynamical Systems and Variational Inequalities with Applications*. Kluwer, Dordrecht, 1996.
- [19] F. Pfeiffer and C. Glocker. *Multibody Dynamics with Unilateral Contacts*. Wiley, Chichester, 1996.
- [20] A. Pnueli and J. Sifakis (guest eds.). Special issue on hybrid systems. *Theoretical Computer Science* 138, 1995.
- [21] R.T. Rockafellar. *Convex Analysis*. Princeton University Press, 1970.
- [22] W. Rudin. *Principles of Mathematical Analysis*. McGraw-Hill, New York, 1976.
- [23] A.J. van der Schaft. *System Theoretic Descriptions of Physical Systems*. CWI Tract 3. CWI, Amsterdam, 1984.
- [24] A.J. van der Schaft and J.M. Schumacher. The complementary-slackness class of hybrid systems. *Mathematics of Control, Signals and Systems*, 9:266–301, 1996.
- [25] A.J. van der Schaft and J.M. Schumacher. Complementarity modelling of hybrid systems. *IEEE Transactions on Automatic Control*, 43:483–490, 1998.
- [26] A.J. van der Schaft and J.M. Schumacher. *An introduction to hybrid dynamical systems*, volume 251 of *Lecture Notes in Control and Information Sciences*. Springer, London, 2000.
- [27] A. Seeger. Eigenvalue analysis of equilibrium processes defined by linear complementarity conditions. *Linear Algebra and its Applications*, 292:1–14, 1999.
- [28] A.V. Skorokhod. Stochastic equations for diffusions in a bounded region. *Theory of Probability and its Applications*, 6:264–274, 1961.