



HAL
open science

Power Edge Set and Zero Forcing Set Remain Difficult in Cubic Graphs

Pierre Cazals, Benoit Darties, Annie Chateau, Rodolphe Giroudeau, Mathias
Weller

► **To cite this version:**

Pierre Cazals, Benoit Darties, Annie Chateau, Rodolphe Giroudeau, Mathias Weller. Power Edge Set and Zero Forcing Set Remain Difficult in Cubic Graphs. IWOCA 2019 - 30th International Workshop on Combinatorial Algorithms, Jul 2019, Pisa, Italy. pp.122-135, 10.1007/978-3-030-25005-8_11 . hal-02359076

HAL Id: hal-02359076

<https://hal.science/hal-02359076>

Submitted on 9 Jun 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution 4.0 International License

Power Edge Set and Zero Forcing Set remain difficult in cubic graphs

P. Cazals¹ and B. Darties² and A. Chateau^{1,4} and R. Giroudeau¹ and M. Weller³

¹ LIRMM - CNRS UMR 5506 - Univ. de Montpellier, France

² Le2i FRE2005, CNRS, Arts et Métiers, Univ. Bourgogne Franche-Comté

³ CNRS - LIGM - Univ. Marne-La-Vallée, France

⁴ IBC - Montpellier, France

{chateau,giroudeau}@lirmm.fr, benoit.darties@u-bourgogne.fr,
mathias.weller@u-pem.fr

Abstract. This paper presents new complexity and non-approximation results concerning two color propagation problems, namely POWER EDGE SET and ZERO FORCING SET. We focus on cubic graphs, exploiting their structural properties to improve and refine previous results. We also give hardness results for parameterized precolored versions of these problems. Finally, we give a polynomial-time algorithm for ZERO FORCING SET in proper interval graphs.

keywords : Synchronphasor, Power Edge Set, Zero Forcing Set, Complexity

1 Introduction

Motivation. In power networks, synchronphasors are time-synchronized numbers that represent both the magnitude and phase angle of the sine waves on network links. A Phasor Measurement Unit (PMU) is an expensive measuring device used to continuously collect the voltage and phase angle of a single station and the electrical lines connected to it. The problem of minimizing the number of PMUs to place on a network for complete network monitoring is an important challenge for operators and has gained a considerable attention over the past decade [4,7,8,11,12,14,16,18,21,23,26]. The problem is known as POWER DOMINATING SET [26] and we state it below. We model the network as a graph $G = (V, E)$ with $|V| =: n$ and $|E| =: m$. We denote the set of vertices and edges of G by $V(G)$ and $E(G)$, respectively. We let $N_G(v)$ denote the set of neighbors of $v \in V$ in G and $d_G(v) = |N_G(v)|$ its degree in G . Further, we let $N_G[v] = N_G(v) \cup \{v\}$ denote the *closed* neighborhood of v in G , and we let $G[W]$ denote the subgraph of G *induced* by vertices $W \subseteq V(G)$. The problem is described through *monitoring* of nodes of the network, corresponding to monitoring vertices $V(G)$ by PMUs, propagated using the following rules.

RULE R_1 *: A vertex v of G on which a PMU is placed will be called a *monitored* vertex, and all its neighbors vertices $N_G(v)$ automatically become monitored.

RULE R_2 : if all but one neighbor of a monitored vertex are monitored, then this unmonitored vertex will become monitored as well.

Letting $\Gamma_P(G)$ denote the minimum number of PMUs to place on vertices to obtain a full monitoring of the network (using RULE R_2), the decision version of the problem is described as follows:

POWER DOMINATING SET (PDS)

Input: a graph $G = (V, E)$ and some $k \in \mathbb{N}$

Question: Is $\Gamma_P(G) \leq k$?

POWER DOMINATING SET is \mathcal{NP} -complete in general graphs [14]. A large amount of literature is devoted to this problem, describing a wide range of approaches, either exact such as integer linear programming [11] or branch-and-cut [21], or heuristic, such as greedy algorithms [16], approximations [4] or genetic algorithms [18]. The problem has also been shown to be polynomial-time solvable on grids [7], but \mathcal{NP} -complete in unit-disk graphs [23].

In this paper, we consider two variants of the problem, called POWER EDGE SET (PES) [25,24] and ZERO FORCING SET (ZFS) [3], which respectively consist in placing PMUs on the *links*, and reducing the monitoring range of a PMU placed on a node. This leads us to replace RULE R_1^* in each of these problems as follows (RULE R_2 remains unchanged):

RULE R_1 (PES): two endpoints of an edge bearing a PMU are monitored.

RULE R_1 (ZFS): only the node bearing a PMU is monitored.

We let $pes(G)$ and $zfs(G)$ denote the minimum number of PMUs to place on the edges, resp. nodes, of G to entirely monitor G . Both PES and ZFS can be seen as a problem of color propagation with colors 0 (white) and 1 (black), respectively designating the states *not monitored* and *monitored* of a vertex of G . As input to PES or ZFS, we will consider a connected graph $G = (V, E)$. For each vertex $v \in V$, let $c(v)$ be the color assigned to v (we abbreviate $\bigcup_{v \in X} c(v) =: c(X)$). Before placing the PMUs, we have $c(V) = \{0\}$ and the aim is to obtain $c(V) = \{1\}$ using RULE R_1 and RULE R_2 while minimizing the number of PMUs. See Figure 1 and Figure 2 for detailed examples illustrating the differences between PES and ZFS.

POWER EDGE SET (PES)

Input: a graph G , some $k \in \mathbb{N}$

Question: Is $pes(G) \leq k$?

ZERO FORCING SET (ZFS)

Input: a graph G , some $k \in \mathbb{N}$

Question: Is $zfs(G) \leq k$?

Related work & our results. Assigning a minimum number of PMUs to monitor the whole network is known to be \mathcal{NP} -hard in general for both PES and ZFS. For the former, preliminary complexity result and a lower bound on approximation of $1.12 - \epsilon$ with $\epsilon > 0$ have been shown by Toubaline et al. [24]. They also present a linear-time algorithm on trees by reduction to PATH COVER. Poirion et al. [20] propose a linear program with binary variables indexed by the necessary iterations using propagation RULE R_1 and RULE R_2 . Recently, inapproximability results have been proposed on special graph classes such as planar or bipartite graphs [5].

In this work, we develop hardness results on complexity and approximation for special cases of POWER EDGE SET and ZERO FORCING SET.




Fig. 1. PMU propagation on PES problem: before any PMU placement, all vertices are white (Figure 1a). A PMU on $\{b, c\}$ induces $c(b) = c(c) = 1$ (black) by RULE R_1 (Figure 1b). By applying RULE R_2 on b , we obtain $c(a) = 1$ (Figure 1c). Then RULE R_2 on a induces $c(d) = 1$ (Figure 1d), and RULE R_2 on c or d induces $c(e) = 1$ (Figure 1e). A second PMU is required to obtain a complete coloring. Placing a PMU on $\{e, f\}$ gives us $c(f) = 1$ by RULE R_1 (Figure 1f). Finally, RULE R_2 on e induces $c(g) = 1$ (Figure 1g). The set of edges where PMUs have been placed is $S = \{bc, ef\}$, giving (b, c, a, d, e, f, g) as a valid order for G .




Fig. 2. PMU propagation on ZFS problem: before any PMU placement, all vertices are white (Figure 2a). Placing one PMU on $\{b\}$ allows to monitor it. (Figure 2b). Placing a second PMU on $\{c\}$ allows to monitor it (Figure 2c), and now we can apply RULE R_2 on b , to obtain $c(a) = 1$ (Figure 2d). Then RULE R_2 on a induces $c(d) = 1$ (Figure 2e), and RULE R_2 on c or d induces $c(e) = 1$ (Figure 2f). A third PMU is required to obtain a complete coloring. For example, placing a PMU on f (Figure 2g) allows to apply RULE R_2 on e to obtain $c(g) = 1$ (Figure 2h).

Preliminaries. In the following, we will consider a total order σ of vertices of a graph G as a sequence (v_1, v_2, \dots) such that v_i occurs before v_j in the sequence if and only if $v_i <_\sigma v_j$.

Definition 1 (valid order). Let $G = (V, E)$ be a graph, let $S \subseteq E$ (resp. $S \subseteq V$), and let σ be a total order of V , such that for each $v \in V(G)$, there is an edge incident to v in S (resp. $v \in S$) or there is a vertex $u \in N_G(v)$ which verifies $N_G[u] \leq_\sigma v$. Then, $<_\sigma$ is called valid for S .

Given a graph $G = (V, E)$, any set $S \subseteq V$ (or $S \subseteq E$) such that repeated application of RULE R_1 (ZFS) (or RULE R_1 (PES)) and RULE R_2 leads to G being completely monitored is called a *zero forcing set* (or *power edge set*). Using Definition 1, we can formally define the propagation process in G . For instance, in Figure 1, a valid order for $S = \{bc, ef\}$ is (b, c, a, d, e, f, g) .

Observation 1 Let $G = (V, E)$ be a graph and let $S \subseteq E$ (resp. $S \subseteq V$). Then, S is a power edge set (res. a zero forcing set) if and only if there is a valid order σ on G , with respect to S .

Note that, for a graph $G = (V, E)$, any set $S \subseteq E$ is a power edge set if and only if $\bigcup_{e \in S} e$ is a zero forcing set for G . It is therefore natural to unambiguously also call such an edge set *zero forcing set*.

Finally, we call a vertex v *propagating to* $x \in N_G(v)$ if $c(x) = 0$ and for all $y \in N_G[v] \setminus \{x\}$, we have $c(y) = 1$. Note that each maximal clique of G can contain at most one propagating vertex.

Lemma 1. Let $G = (V, E)$ be a graph, let S be a zero forcing set of G , and let $\mathcal{C} := \{C_1, \dots, C_c\}$ be a set of maximal cliques in G covering E . Then $|V \setminus S| \leq c$.

Proof. Let σ be a valid order for S . We show that each C_i contains at most one edge uv such that $v \notin S$ and $N_G[u] \leq_\sigma v$. Since \mathcal{C} covers E , this implies $|V \setminus S| \leq |\mathcal{C}| = c$. Let $C \in \mathcal{C}$ and let C contain an edge uv such that $N_G[u] \leq_\sigma v$ and $v \notin S$. Then, $C \subseteq N_G[u]$, implying $C \leq_\sigma v$. Thus, v is the last vertex of C with respect to σ and this vertex is *unique*. \square

2 Classical Hardness

Most results presented in this section rely on reductions from graph problems using gadgets for vertices or edges of the original instance. We model the propagation process using the notion of valid order with respect to the solution set, whatever the nature of it: set of edges for PES, of vertices for ZFS.

We present new lower bounds for POWER EDGE SET that hold even in the very restricted case that G is cubic (*i.e.* all vertices in G have degree three). Previous results show that the problem is \mathcal{NP} -complete even if G is a subgraph of the grid with bounded degree at most three [5]. In this paper, we show the problem remains \mathcal{NP} -complete if G is cubic and planar. The proof is done by




Fig. 3. The gadget H_v for a vertex v .

reduction from VERTEX COVER (see below) on 3-regular, planar graphs, which is \mathcal{NP} -complete [10] but admits a PTAS [1], and a $3/2$ -approximation [2].

VERTEX COVER (VC)

Input: a graph $G = (V, E)$, some $k \in \mathbb{N}$.

Question: Is there a size- k set $S \subseteq V$ covering E , i.e. $\forall e \in E \ e \cap S \neq \emptyset$?

Construction 1 For a given cubic planar graph $G = (V, E)$ with n vertices, we construct a graph G' as follows:

- For each $v \in V$, construct H_v (see Figure 3).
- For each $v \in V$ with $N_G(v) = \{x, y, z\}$, connect H_x to H_v with the edge v_1x_1 , H_y to H_v with v_2y_2 and H_z to H_v with v_0z_0 .

The graph G' is clearly cubic and planar and Construction 4 is applied in polynomial time. The construction is linear in n and k .

Lemma 2. *The gadget H_v needs at least one PMU to be fully colored: if x_1 , y_2 and z_0 are propagating respectively to v_1 , v_2 and v_0 , then one PMU is sufficient; otherwise two PMUs are needed to fully color H_v .*

Proof. First, if x_1 , y_2 and z_0 are propagating respectively to v_1 , v_2 and v_0 , then, after application of RULE R_2 , $c(v_0) = c(v_1) = c(v_2) = 1$. Thus this is the beginning of a valid order: $(v_0, v_1, v_2, v_3, v_5, v_4, v_6, v_7, v_{12}, v_9, v_{10})$. There is no more possible propagation, it is necessary to assign a new PMU. If we place it on the edge $v_{14}v_{16}$, the remainder of a valid order for H_v is: $(v_{14}, v_{16}, v_{11}, v_8, v_{13}, v_{15}, v_{16})$.

Second, we show that H_v may be colored by two PMUs in every case. If PMUs are assigned to the edges $v_{11}v_{13}$ and $v_{15}v_{16}$, we the following order is valid: $(v_{11}, v_{13}, v_{15}, v_{16}, v_7, v_8, v_9, v_{14}, v_4, v_6, v_{10}, v_3, v_{12}, v_3, v_{12}, v_1, v_2, v_5, v_0)$.

Third, we show that even if x_1 and z_0 are propagating to respectively v_1 and v_0 , and y_2 is not, we need two PMUs to color H_v (the argument for $(x_1$ and $y_2)$ and $(y_2$ and $z_0)$ is symmetric). The beginning of the propagation is given by the following order: (v_0, v_1, v_3, v_5) . There is no more possible propagation, therefore

we have to put one more PMU. As more than two uncolored vertices remain, so we have to initiate propagation with this PMU. So the potential edges are v_6v_{12} , v_4v_2 , v_6v_9 or $v_{10}v_{12}$. By exhaustive search, we find that it is impossible to color H_v with only PMU on any one of these edges. \square

Theorem 1. POWER EDGE SET *remains \mathcal{NP} -complete on planar cubic graphs.*

Proof. Let G' be the graph obtained by using [Construction 4](#) on $G = (V, E)$, a cubic planar graph. We show that G has a size- k vertex cover iff POWER EDGE SET has a solution of size $n + k$ on G' . Clearly, POWER EDGE SET is in \mathcal{NP} .

“ \Rightarrow ”: With a size- k vertex cover S for G , we build a power edge set S' for G' :

$$S' := \bigcup_{v \in S} \{v_{11}v_{16}, v_{13}v_{15}\} \cup \bigcup_{v \in V \setminus S} \{v_{14}v_{16}\}$$

Then, $|S'| = n + k$ and, by [Lemma 2](#), all vertices of G' are colored by S' .

“ \Leftarrow ”: Suppose that G' is colored with $n + k$ PMUs. By [Lemma 2](#), there is at least one PMU on each gadget. Further, if a gadget H_v is colored with a single PMU, then every H_x with $x \in N_G(v)$ is colored with two PMUs inside (by [Lemma 2](#)). Then, $\{v \mid H_v \text{ admits two PMUs}\}$ is a vertex cover for G . \square

3 Parameterized Hardness

In what follows, we introduce parameterized versions of our problems and recall the notion of parameterized reduction. Using known results for DOMINATING SET, we deduce hardness results for POWER EDGE SET and ZERO FORCING SET. First, we recall the parameterized DOMINATING SET problem.

DOMINATING SET (DS)

Input: a graph $G = (V, E)$, some $k \in \mathbb{N}^*$

Question: Does G have a size- k dominating set?

Parameter: k

We obtain hardness results for a restricted version of our problems, when a precoloring exists on a particular set of vertices.

PRECOLORED ZERO FORCING SET/PRECOLORED POWER EDGE SET

Input: a graph $G = (V, E)$, a set $B \subseteq V$, some $c : V \rightarrow \{0, 1\}$ with $c^{-1}(1) = B$, and an integer k

Question: Is there a set $S' \subseteq V$ (resp. $S' \subseteq E$) of size k such that $B \cup S'$ (resp. $B \cup \bigcup_{e \in S'} e$) is a zero forcing set for G ?

Parameter: k

We prove the hardness using a parameterized reduction from DOMINATING SET. First, we introduce a gadget which allows to propagate a coloration, but only in one direction. It is called "check-valve".




Fig. 4. The check-valve $C_{x,y}$

Definition 2 (Check-valve). A check-valve $C_{x,y}$ from x to y is a graph $G = (V, E)$, with $V = \{x, y, x_1, x_2, x_3, x_4\}$ and $E = \{xx_1, xx_2, x_1x_3, x_1x_4, x_2x_4, x_3y, x_4y\}$, with a coloring function $c : V \rightarrow \mathbb{N}$, such that $c(x) = c(x_1) = 1$ and all other vertices are colored by 0. A check-valve $C_{x,y}$ is illustrated on Figure 4.

Observation 2 Let $C_{x,y}$ be a check-valve inserted between two vertices a and b , depicted by Figure 4. Then:

1. If $c(a) = 1$ then $c(b) = 1$ after exhaustive application of RULE R_2 .
2. If $c(b) = 1$, and $c(a) = 0$, then $c(a)$ is still 0 after exhaustive application of RULE R_2 , and it is necessary to add a PMU in order to have $c(a) = 1$.

Construction 2 Let xy be an edge such that $c(x) = 1$ and $c(y) = 0$, we construct the gadget C_{xy} : we add vertices x_1, x_2, x_3 and x_4 and we add edges $xx_1, x_1x_2, x_3y, yx_4, x_4x_2$ et x_2x . Notice that xy is deleted.

Construction 3 For given $G = (V, E)$, construct $G' = (V', E')$ as follows:

1. For all $x \in V$, build J_x depicted in Figure 5, containing a core graph $(\{E_x, R_x, V_x, x_1, x_2, x_3, x_4\}, \{E_x x_3, E_x x_4, E_x V_x, x_1 x_3, x_2 x_4, R_x x_1, R_x x_2, R_x V_x\})$ with precolored vertices V_x, x_3 and x_4 , and outgoing check-valves: $d_G(x)$ many $C_{x_{v_i}^1, x_{v_i}^2}$ connected to E_x , and n many $C_{x_{s_i}^1, x_{s_i}^2}$ connected to R_x .
2. For all $v_i \in N(x)$, add edges $x_{v_i}^2 R_{v_i}$ with $x_{v_i}^2 \in J_x$ and $R_{v_i} \in J_{v_i}$.
3. For all $s_i \in V$, add edges $x_{s_i}^2 V_{s_1}$ with $x_{s_i}^2 \in J_x$ and $V_{s_1} \in J_{s_i}$.

Lemma 3. For all $x \in V$, if $c(E_x) = 1$ then, after exhaustive application of RULE R_2 , $c(J_x) = 1$ and $c(R_v) = 1$ for all $v \in N(x)$.

Proof. If $V = \{s_1, \dots, s_n\}$ and $N(x) = \{v_1, \dots, v_t\}$, then the following sequence is a valid order: $(E_x, x_1, x_2, R_x, x_{s_1}^2, \dots, x_{s_n}^2, x_{v_1}^2, \dots, x_{v_t}^2, R_{v_1}, \dots, R_{v_t})$. \square

Lemma 4. Let $c(R_x) = 1$ for all $x \in V$. Then, after exhaustive application of RULE R_2 , G' becomes fully colored.

Proof. Clearly, all vertices in $N(V_x) \setminus \{E_x\}$ are colored by R_x for all $x \in V$. Then, E_x is colored by V_x . By Lemma 3, $c(E_x) = 1$ leads to J_x being fully colored. As $V' = \bigcup_{z \in V} V(J_z)$, G' becomes fully colored. \square

Theorem 2. PRECOLORED ZERO FORCING SET and PRECOLORED POWER EDGE SET are $W[2]$ -hard wrt. the solution size k .




Fig. 5. The gadget J_x for a vertex x . Note that for sake of clarity, some external vertices have been duplicated. Indeed, $\{R_{v_1}, \dots, R_{v_t}\}$, where v_1, \dots, v_t are neighbors of x , is included in $\{R_{s_1}, \dots, R_{s_n}\}$.

The proof is really similar for both problems, thus we only mention the minor changes for PRECOLORED POWER EDGE SET between parenthesis.

Proof. Let $G = (V, E)$ be a graph and let G' the product of **Construction 3** on G . We show that G has a size- k dominating set if and only if G' has a size- k zero forcing set (power edge set).

“ \Rightarrow ”: Let S be a size- k dominating set for G . A size- k zero forcing set S' for G' is obtained as follows: for all $x \in S$, we place a PMU on E_x , (resp. $E_x x_4$). By **Lemma 3** and **Lemma 4**, G' is fully colored after applying **RULE R_2** exhaustively.

“ \Leftarrow ”: Let S' be a zero forcing set of size k for G' . Let S be the set of vertices $x \in V(G)$ such that J_x has at least one vertex, resp. one edge, in S' (for each $x, y \in V$, if there is a PMU on the edge $E_x R_y$ or $R_x V_y$ it counts as an edge of J_x). Suppose that S is not a dominating set for G . So, there is some $y \in V$ such that no $u \in V(J_y)$ is in S' and no $v \in V(J_x)$ is in S' for any $x \in N(y)$. (for PES, there is some $y \in V$ such that no $u_1 u_2 \in E(J_y)$ is in S' and no $v_1 v_2 \in E(J_x)$ is in S' for any $x \in N(y)$). Since J_y is fully colored, this coloration comes from a vertex (resp. an edge) outside of J_y . Four cases have to be considered:

Case 1: There is some $v_i \in N(y)$ such that $c(y_{v_i}^2) = 1$ for $y_{v_i}^2 \in J_y$ and this coloration comes from $R_{v_i} \in J_{v_i}$. By **Observation 2**, we have $c(E_y) = 1$ only if at least one PMU is assigned on the check-valve.

Case 2: There is some $s_i \in V$ such that $c(y_{s_i}^2) = 1, \in J_y$, and this coloration comes from $V_{s_i} \in J_{s_i}$. By **Observation 2**, for R_y to be colored, at least one PMU has to be assigned to the check-valve.

Case 3: V_y be a propagator. But then, S' is not zero forcing since $c(E_y) = 0$ and $c(R_y) = 0$ and they are in $N(y)$.

Case 4: There is some $v_i \in N(y)$ such that a coloration happens on $R_y \in J_y$ from $E_{v_i} \in J_{v_i}$. Then, either there is some $t \in J_{v_i} \cap S$ and so S is a dominating set, or no PMU is assigned on J_{v_i} , but we already know that E_{v_i} cannot be

colored (see Case 1). Consequently, if $c(E_{v_i}) = 1$ then $c(w) = 1$ for some $w \in J_{v_i}$ contradicting S not being a dominating set.

Thus S is a dominating set of G . Further, [Construction 3](#) can be carried out in polynomial time and $|S| = |S'|$, yielding the desired result. \square

4 Hardness according to other complexity hypotheses

4.1 Lower Bounds for Exact and \mathcal{FPT} Algorithms

In this section, we propose some negative results for POWER EDGE SET concerning subexponential-time and parameterized algorithms under \mathcal{ETH} (see [\[15\]](#)).

Since the polynomial-time transformation given in [Theorem 1](#) is linear in the number of vertices and VERTEX COVER does not admit a $2^{o(\sqrt{n})}$ -time algorithm, even on 3-regular, planar graphs, there is also no $2^{o(\sqrt{n})}$ -time algorithm for POWER EDGE SET in cubic planar graphs.

Moreover, since $k \leq n$, a $2^{o(k)}n^c$ -time algorithm directly implies a $2^{o(n)}$ -time algorithm for VERTEX COVER. However, we know VERTEX COVER does not admit such an algorithm (even in the planar case) unless the \mathcal{ETH} fails [\[17\]](#). Therefore, we obtain the following results.

Corollary 1. *Assuming \mathcal{ETH} , POWER EDGE SET does not admit a $2^{o(\sqrt{n})}$ -time algorithm, even in planar cubic graphs, nor a $2^{o(k)}n^{O(1)}$ -time algorithm, even on planar graphs.*

Based on the previous complexity result, it is clear that POWER EDGE SET parameterized by Δ (the maximum degree of the graph) is not in \mathcal{XP} .

4.2 Hardness according to \mathcal{UGC}

In the following, we propose an L -reduction from VERTEX COVER in 3-uniform hypergraphs. An L -reduction (see [\[19\]](#)) between problems Π and Π' is defined as follows: let $f : \Pi \rightarrow \Pi'$ and g be polynomial-time computable functions such that, for all $x \in \Pi$ and each feasible solution y' for $f(x)$, $g(y')$ is a feasible solution for x . Moreover, there are constants $\alpha_1, \alpha_2 > 0$ such that:

1. $OPT_{\Pi'}(f(x)) \leq \alpha_1 OPT_{\Pi}(x)$ and
2. $|val_{\Pi}(g(y')) - OPT_{\Pi}(x)| \leq \alpha_2 |val_{\Pi'}(y') - OPT_{\Pi'}(f(x))|$.

Even on 3-uniform graphs, VERTEX COVER is hard to approximate within a factor less than $2 - \epsilon$ for all $\epsilon > 0$ (assuming $P \neq \mathcal{NP}$), even if each vertex appears in at most three edges [\[6\]](#). It is also hard to approximate within a factor less than $3 - \epsilon$ for all $\epsilon > 0$ (assuming \mathcal{UGC}) [\[22\]](#).

Construction 4 *Let $G = (V, E)$ be a cubic planar hypergraph. Build G' by*

- for each $v \in V$ constructing the gadget H_v (see [Figure 3](#)),
- for each $xyz \in E$ constructing the gadget J_{xyz} (see [Figure 6](#)), and
- for each $e = xyz \in E$ connecting J_{xyz} to H_x (resp. H_y, H_z) by the edge e_0x_0 (resp. e_1y_1, e_2z_2).




Fig. 6. The gadget J_{xyz} for an edge xyz .

Note that $x_i \neq y_i$ for all i but, for distinct i and j , x_i can be equal to x_j or y_j .

Lemma 5. *The gadget J_{xyz} may be colored with only one PMU if at least one among x_1 , y_2 or z_0 is propagating to respectively e_1 , e_2 or e_0 . Further, any zero forcing set contains a vertex of J_{xyz} .*

Proof. By symmetry, we assume w.l.o.g. that x_1 is propagating to e_1 . First, assigning a PMU to e_3e_6 we get the following valid order: $(e_1, e_3, e_6, e_4, e_0, e_5, e_2)$. Second, even if e_0 , e_1 and e_2 are colored by propagation from outside J_{xyz} , the propagation stops unless a PMU is assigned to an edge of J_{xyz} . \square

Theorem 3. *Under UGC, POWER EDGE SET on cubic graphs cannot be approximated to within a factor better than $13/11$*

Proof. Let G' be the result of applying Figure 4 to a hypergraph $G = (V, E)$. We show that G has a size- k vertex cover iff POWER EDGE SET has a solution of size $k + 2n$ on G' .

“ \Rightarrow ”: Let S be a size- k vertex cover for G . We build a solution S' for G' :

$$S' := \bigcup_{v \in S} (\{v_{11}v_{16}\} \cup \{v_{13}v_{15}\}) \cup \bigcup_{v \in V \setminus S} \{v_{14}v_{16}\} \cup \bigcup_{xzy \in E} \begin{cases} \{e_3e_6\} & \text{if } x \in S \\ \{e_4e_6\} & \text{if } y \in S \\ \{e_5e_6\} & \text{if } z \in S \end{cases}$$

By Lemma 5, S' is a power edge set for G' and $|S'| = k + 2n$.

“ \Leftarrow ”: Assume that G' possesses $2n+k$ PMUs such that all vertices are colored. Lemma 2 and Lemma 5 state that it is impossible to color a gadget without any PMU inside, so there is at least one PMU on each gadget H and J . If there is more than one PMU on a gadget J , we count it as if it is inside any adjacent gadget H . If a gadget H_v is colored by a single PMU, it means that, for each hyperedge containing v , there is at least one H_x with x in this hyper-edge, which counts two PMUs. Thus, $X := \{v \mid H_v \text{ admits two PMUs}\}$ is a vertex-cover. Suppose that more than k gadgets have at least two PMUs. Then, there is at least one gadget without any PMU, contradicting Lemma 5. Thus, $|S| \leq k$.

Finally, to show that Figure 4 is an L -reduction, let f be a function transforming any 3-uniform instance I of VERTEX COVER into an instance I' of POWER EDGE SET as above, let S' be any feasible solution for I' , and let g be the function that transforms S' into a solution S that contains one or two edges per gadget H_v and one per gadget J_{xyz} , and then outputs the set of vertices




Fig. 7. An interval graph (7a), with its interval representation (7b), a perfect path decomposition of this graph (7c) and its bag partition according to Definition 4 (7d).

v for which S assigns two PMUs to H_v . First, the above argument shows that $g(S')$ is a feasible solution for I' .

Second, by construction, $OPT(I') = OPT(I) + n + m$. Let S be a solution to I . Then, we have $m \leq \sum_{v \in S} d_G(v)$, and $d_G(v) \leq 3$. We obtain $m \leq 3OPT(I)$ as $|S| = OPT(I)$. Moreover, $m \leq n$. Since each vertex of I appears in at most three hyperedges of I , at least one in seven vertices has to be in a vertex cover of G , implying $n/7 \leq OPT(I)$. Thus, $OPT(I') \leq 11OPT(I)$

Third, by construction of g , we have

$$val(g(S')) \leq val(S') - n - m \leq val(S') - OPT(I') + OPT(I)$$

Thus, we constructed an L -reduction with $\alpha_1 = 11$ and $\alpha_2 = 1$.

Assuming UGC , VERTEX COVER on 3-uniform hypergraphs is hard to approximate to a factor $3 - \epsilon$ [22], thus yielding to the desired result:

$$\begin{aligned} |S'| &\geq |g(S')| + OPT(I') - OPT(I) \\ &\geq (3 - \epsilon)OPT(I) + OPT(I') - OPT(I) \\ &\geq 13/11OPT(I') \end{aligned} \quad \square$$

5 ZFS on Proper Interval Graphs

Preliminaries. A graph G is an *interval graph* if it is the intersection graph of a family of intervals on the real line. Each interval is represented by a vertex of G and an intersection between two intervals is represented by an edge between the corresponding vertices (see Figure 7). G is called *proper interval* if it has an interval representation in which no interval is properly contained in another. In the following, we use perfect path decompositions to solve POWER EDGE SET on proper interval graphs.

Definition 3. A path decomposition \mathcal{D} of a graph $G = (V, E)$ is a sequence $(X_i)_{i=1 \dots \ell}$ of subsets of V (called bags), verifying the following properties:

(a) for each $xy \in E$, there is some X_i with $x, y \in X_i$ (each edge is in a bag),
(b) for $i \leq j \leq k$, $X_i \cap X_k \subseteq X_j$ (bags containing any $v \in V$ are consecutive).
 \mathfrak{D} is called perfect if the number of bags and their sizes are minimal under (a) and (b). The pathwidth of \mathfrak{D} is the size of the largest X_i minus one.

Lemma 6. If G is connected, then $X_i \cap X_{i-1} \neq \emptyset$ for all $i > 1$.

Proof. Towards a contradiction, assume that $X_i \cap X_{i-1} = \emptyset$. Then, by Definition 3(b), $A := \bigcup_{1 \leq k \leq i-1} X_k$ and $B := \bigcup_{i \leq l} X_l$ are disjoint. Since G is connected, there is an edge xy between A and B , but no bag contains both x and y , contradicting Definition 3(a). \square


Lemma 7. Let G be an interval graph. A perfect path decomposition \mathfrak{D} of G can be computed in linear time and each bag of \mathfrak{D} is a maximal clique in G .

Proof. Being an interval graph, G admits a linear order of its maximal cliques such that, for each vertex v , all maximal cliques containing v are consecutive [9] and this order can be computed in $O(n + m)$ time [13]. Such a ‘‘clique path’’ naturally corresponds to a perfect path decomposition and we know that vertices of each bags induce maximal cliques. In a clique path, the size and the number of bags are minimal. \square

The Algorithm. In the following, G is a connected proper interval graph and $\mathfrak{D} = (X_1, \dots, X_\ell)$ is a perfect path decomposition of G . We show that it is possible to apply RULE R_2 once per maximal clique X_i in interval graphs. The central concept is a partition of the bags of \mathfrak{D} into four sets.

Definition 4 (Bag partition, see Figure 7). Let X_i be a bag in a perfect path decomposition of an interval graph.

- IO (Inside Only) is the set $X_i \setminus (X_{i-1} \cup X_{i+1})$.
- LO (Left Only) is the set $X_i \cap X_{i-1} \setminus X_{i+1}$.
- RO (Right Only) is the set $X_i \cap X_{i+1} \setminus X_{i-1}$.
- LR (Left Right), contains all remaining vertices of X_i .



Note that $RO(X_i)$ and $RO(X_j)$ are disjoint for $i \neq j$. Further, since G is proper interval, $RO(X_i) \neq \emptyset$ for all $i < \ell$. Our algorithm will simply choose any vertex of $RO(X_i) \cup IO(X_i)$ for all i . This can clearly be done in linear time and we show that it is correct and optimal.

Lemma 8. Let G be a connected interval graph and let $\mathfrak{D} = (X_1, \dots, X_\ell)$ be a perfect path decomposition of G . Let \bar{S} be a set intersecting each $RO(X_i)$ for all $1 \leq i < \ell$ in exactly one vertex and intersecting $IO(X_\ell)$ in exactly one vertex. Then, $S := V \setminus \bar{S}$ is an optimal zero forcing set for G .

Proof. For each i , let x_i be the i^{th} vertex of \bar{S} , that is, $\bar{S} \cap (RO(X_i) \cup IO(X_i)) = \{x_i\}$ for each $X_i \in \mathfrak{D}$. We show that the order σ consisting of S in any order followed by (x_1, \dots, x_ℓ) is valid for S . To this end, let $1 \leq j < \ell$. Note that $IO(X_j) \cup LO(X_j) = ((X_j \setminus X_{j+1}) \cap X_{j-1}) \cup ((X_j \setminus X_{j+1}) \setminus X_{j+1}) = X_j \setminus X_{j+1}$. Thus, there is some $u \in IO(X_j) \cup LO(X_j)$ as otherwise, $X_j \subseteq X_{j+1}$ contradicting

\mathfrak{D} being perfect. Towards a contradiction, assume $N_G[u] \not\leq_{\sigma} x_j$, that is, there is some $v \in N_G[u]$ with $x_j <_{\sigma} v$. By construction of σ , there is a $k > j$ such that $v = x_k$. By construction of \overline{S} , we have $x_k \in IO(X_k) \cup RO(X_k)$, implying $x_k \notin X_{k-1}$ by definition of RO and IO . Further, since ux_k is an edge of G , there is a bag X_i containing both u and x_k and, since $u \in IO(X_j) \cup LO(X_j)$ we know $i \leq j$. But then, x_k occurs in X_i , not in X_{k-1} but again in X_k , contradicting \mathfrak{D} being perfect. It remains to treat x_{ℓ} , but since x_{ℓ} is the last vertex of σ , $N_G[u] \leq_{\sigma} x_{\ell}$ for all $u \in N_G(x_{\ell})$.

Finally, optimality of S is implied by Lemma 1 as $|\overline{S}| = |\mathfrak{D}|$. \square

Theorem 4. ZERO FORCING SET is solvable in $O(n + m)$ time on proper interval graphs.

6 Conclusion and perspectives

In this article, we investigated POWER EDGE SET and ZERO FORCING SET from the point of view of computational complexity. We obtained a series of negative results, refining the previous hardness results and excluding certain exact algorithms. On the positive side, we give a linear-time algorithm in case the input is a proper interval graph. Further research will be focused on developing efficient polynomial-time approximation algorithms, as well as considering more special cases and structural parameterizations.

References

1. Baker, B.: Approximation Algorithms for NP-Complete Problems on Planar Graphs. *Journal of ACM* **41**(1), 153–180 (1994)
2. Bar-Yehuda, R., Even, S.: On Approximating a Vertex Cover for Planar Graphs. In: *Proceedings of the 14th Annual ACM Symposium on Theory of Computing*, May 5-7, 1982, San Francisco, California, USA. pp. 303–309 (1982)
3. Barioli, F., Barrett, W., Butler, S., Cioabă, S.M., Cvetković, D., Fallat, S.M., Godsil, C., Haemers, W., Hoghen, L., Mikkelsen, R., et al.: Zero forcing sets and the minimum rank of graphs. *Linear Algebra and its Applications* **428** (2008)
4. Cheng, X., Huang, X., Li, D., Wu, W., Du, D.: A polynomial-time approximation scheme for the minimum-connected dominating set in ad hoc wireless networks. *Networks* **42**(4), 202–208 (2003)
5. Darties, B., Chateau, A., Giroudeau, R., Weller, M.: Complexity and lowers bounds for power edge set problem. *accepted Journal of Discrete Algorithms* (2018)
6. Dinur, I., Guruswami, V., Khot, S., Regev, O.: A new multilayered PCP and the hardness of hypergraph vertex cover. *SIAM Journal on Computing* **34**(5), 1129–1146 (2005)
7. Dorfling, M., Henning, M.A.: A note on power domination in grid graphs. *Discrete Applied Mathematics* **154**(6), 1023 – 1027 (2006)
8. Fan, N., Watson, J.: Solving the Connected Dominating Set Problem and Power Dominating Set Problem by Integer Programming, pp. 371–383. Springer Berlin Heidelberg, Berlin, Heidelberg (2012)

9. Fulkerson, D.R., Gross, O.A.: Incidence matrices and interval graphs. *Pacific J. Math.* **15**(3), 835–855 (1965), <https://projecteuclid.org:443/euclid.pjm/1102995572>
10. Garey, M.R., Johnson, D.S.: *Computers and Intractability: A Guide to the Theory of NP-Completeness*. W. H. Freeman & Co., New York, NY, USA (1979)
11. Gou, B.: Generalized integer linear programming formulation for optimal pmu placement. *IEEE Transactions on Power Systems* **23**(3), 1099–1104 (2008)
12. Guo, J., Niedermeier, R., Raible, D.: Improved algorithms and complexity results for power domination in graphs. *Algorithmica* **52**(2), 177–202 (2008)
13. Habib, M., McConnell, R.M., Paul, C., Viennot, L.: Lex-bfs and partition refinement, with applications to transitive orientation, interval graph recognition and consecutive ones testing. *Theoretical Computer Sciences* **234**(1-2), 59–84 (2000)
14. Haynes, T.W., Hedetniemi, S.M., Hedetniemi, S.T., Henning, M.A.: Domination in graphs applied to electric power networks. *SIAM Journal on Discrete Mathematics* **15**(4), 519–529 (2002)
15. Impagliazzo, R., Paturi, R., Zane, F.: Which Problems Have Strongly Exponential Complexity? *Journal of Computer and System Sciences* **63**(4), 512–530 (2001)
16. Li, Y., Thai, M.T., Wang, F., Yi, C., Wan, P., Du, D.: On greedy construction of connected dominating sets in wireless networks. *Wireless Communications and Mobile Computing* **5**(8), 927–932 (2005)
17. Lokshtanov, D., Marx, D., Saurabh, S.: Lower bounds based on the Exponential Time Hypothesis. *Bulletin of the EATCS* **105**, 41–72 (2011)
18. Milosevic, B., Begovic, M.: Nondominated sorting genetic algorithm for optimal phasor measurement placement. *IEEE Power Engineering Review* **22**(12), 61–61 (2002)
19. Papadimitriou, C., Yannakakis, M.: Optimization, approximation, and complexity classes. *J. Comput. Syst. Sci.* **43**(3), 425–440 (1991)
20. Poirion, P., Toubaline, S., D’Ambrosio, C., Liberti, L.: The power edge set problem. *Networks* **68**(2), 104–120 (2016)
21. Simonetti, L., Salles da Cunha, A., Lucena, A.: The Minimum Connected Dominating Set Problem: Formulation, Valid Inequalities and a Branch-and-Cut Algorithm, pp. 162–169. Springer Berlin Heidelberg, Berlin, Heidelberg (2011)
22. Subhash, K., Oded, R.: Vertex cover might be hard to approximate to within $2 - \epsilon$. In: *Computational Complexity, 2003. Proceedings. 18th IEEE Annual Conference on*. pp. 379–386. IEEE (2003)
23. Thai, M.T., Du, D.Z.: Connected dominating sets in disk graphs with bidirectional links. *IEEE Communications Letters* **10**(3), 138–140 (Mar 2006)
24. Toubaline, S., D’Ambrosio, C., Liberti, L., Poirion, P., Schieber, B., Shachnai, H.: Complexity and inapproximability results for the power edge set problem. *Journal of Combinatorial Optimization* **35**(3), 895–905 (2018)
25. Toubaline, S., Poirion, P., D’Ambrosio, C., Liberti, L.: Observing the State of a Smart Grid Using Bilevel Programming, pp. 364–376. Springer International Publishing, Cham (2015)
26. Yuill, W., Edwards, A., Chowdhury, S., Chowdhury, S.P.: Optimal pmu placement: A comprehensive literature review. In: *2011 IEEE Power and Energy Society General Meeting*. pp. 1–8 (July 2011)