



HAL
open science

INHARMONICITY OF A TRUMPET WITH A VARIABLE DEPTH MOUTHPIECE

Robin Tournemenne, Jean-François Petiot, Joel Gilbert

► **To cite this version:**

Robin Tournemenne, Jean-François Petiot, Joel Gilbert. INHARMONICITY OF A TRUMPET WITH A VARIABLE DEPTH MOUTHPIECE. Vienna Talk 2015 on Music Acoustics, Sep 2015, Vienna, Austria. hal-02587854

HAL Id: hal-02587854

<https://hal.science/hal-02587854>

Submitted on 15 May 2020


HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

INHARMONICITY OF A TRUMPET WITH A VARIABLE DEPTH MOUTHPIECE

Robin TOURNEMENNE - Jean-François PETIOT
 IRCyN - UMR CNRS 6597 - Ecole Centrale de Nantes,
 1, rue de la Noë 44321 NANTES Cedex 03, France

Joël GILBERT
 LAUM - UMR CNRS 6613 - Av. O. Messiaen
 72085 Le Mans Cedex 9, France



3 INVESTIGATION METHODS


Resonance frequencies of the INPUT IMPEDANCE

- Measurement of the input impedance Z_{in} for one given depth ($x=0$).
- Extrapolation of the input impedance for different depths by impedance calculation (addition of a cylinder of length x with the transmission line formalism)
- Extraction of the resonances frequencies of the impedance, for different mouthpiece depths

Playing frequencies of SIMULATED SOUNDS

- Simulation in the frequency domain with the harmonic balance technique:

$$p(t) = \sum_{n=1}^N A_n \cos(2\pi j_n F_n t + \phi_n)$$



- 4 Fingerings: D₀ D₁ D₂ D₂₃
- 5 Regimes: R2 to R6
- 30 Mouthpiece positions (discretization of x)
- 300 virtual "embouchures"

Playing frequency of a note averaged on the different embouchures

Playing frequencies of RECORDED SOUNDS

- Trumpet with the variable mouthpiece played by a musician
- Extraction of the playing frequencies of the sounds

- 4 Fingerings: D₀ D₁ D₂ D₂₃
- 5 Regimes: R2 to R6
- 3 Mouthpiece positions: $x=0\text{mm}$, 1.5mm and 3mm
- 3 repetitions

Playing frequency of a note averaged on the 3 repetitions

OBJECTIVE

Study of the agreement between the playing frequencies of the recorded sounds, the playing frequencies of the simulated sounds, the resonance frequencies of the impedance

⇒ Toward a prediction of the intonation


ESTIMATION OF THE INHARMONICITY: The Equivalent Fundamental Pitch (EFP)

- Choice of a reference $f(ref)$: 4th regime of the fingering D₀ (tuning note)
- EFP of each note (cent):



$$EFP(i) = 1200 \log_2 \left(\frac{f(i)/i}{f(ref)/ref} \right)$$

- Proposition of an estimator of the global intonation for the whole trumpet

$$Intonation_{estim} = \sum_{j \in \{fingerings\}} \sum_{i \in \{regimes\}} |EFP_{ij}|$$



RESULTS



Evolution of the EFPs and the Intonation according to the mouthpiece depth x for different regimes (R2 to R6), for fingering D₀ only (left) and fingerings D₀, D₁, D₂, D₂₃ (right)

CONCLUSIONS

- For Fingering D₀: noticeable similarities in the global behaviour for the 3 methods:
 - The general evolution trends of the EFPs for the different regimes are consistent (except for regime 3 for the impedance)
 - The absolute values of the EFPs are consistent (except for regime 2 and the simulations)
 - Influence of the virtual embouchure on the simulated sounds. Necessity of a method to select the embouchures
- For all the fingerings
 - The precision of the intonation predictions remains low with the impedance. Results in progress for the simulations...