

Thermal Thin Shell Approximation for 3D Finite Element Quench Simulation of Insulated HTS Coils

Erik Schnaubelt, Mariusz Wozniak, Sebastian Schöps

▶ To cite this version:

Erik Schnaubelt, Mariusz Wozniak, Sebastian Schöps. Thermal Thin Shell Approximation for 3D Finite Element Quench Simulation of Insulated HTS Coils. 8th International Workshop on Numerical Modelling of High Temperature Superconductors (HTS 2022), Kévin Berger (Université de Lorraine - GREEN), Jun 2022, Nancy, France. hal-03791298

HAL Id: hal-03791298 https://hal.science/hal-03791298v1

Submitted on 29 Sep 2022

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Thermal Thin Shell Approximation for 3D Finite Element Quench Simulation of Insulated HTS Coils

Erik Schnaubelt CERN Geneva, Switzerland Technische Universität Darmstadt Darmstadt, Germany erik.schnaubelt@cern.ch Mariusz Wozniak CERN Geneva, Switzerland mariusz.wozniak@cern.ch Sebastian Schöps Technische Universität Darmstadt Darmstadt, Germany sebastian.schoeps@tu-darmstadt.de

Abstract—Insulation layers in superconducting coils often exhibit high aspect ratios which can lead to unfavorable meshes, either because of a high number of degrees of freedom or deformed mesh elements. To avoid this issue, this work proposes to collapse thin insulation layers of insulated high-temperature superconducting coils into a surface using a thin shell approximation. This approach is beneficial for three-dimensional finite element method based quench simulations of coils made with hightemperature superconducting tapes.

Keywords—thin shell approximation, quench simulation, HTS solenoid, finite element method, insulation layer

I. INTRODUCTION AND PROBLEM DEFINITION

In order to study the quench behavior of superconducting coils, appropriate numerical tools are needed. When using the finite element (FE) method, the high aspect ratio of thin sheets such as insulation layers can lead to numerical difficulties [1] and suitable methods to deal with this problem are essential.

Let us consider a three-dimensional (3D) adiabatic hightemperature superconducting (HTS) solenoid $\Omega = \Omega_t \cup \Omega_i$, consisting of a homogenized HTS tape Ω_t and a thin insulation layer Ω_i (see Fig. 1). To analyze the thermal behavior, we solve the heat equation to find the temperature T such that

$$\nabla \cdot (\kappa \nabla T) + \rho C_{\mathbf{p}} \partial_t T = Q \qquad \text{in } \Omega, \qquad (1)$$

$$\vec{n}_{\Omega} \cdot (\kappa \nabla T) = 0$$
 on $\partial \Omega$, (2)

where κ denotes the thermal conductivity, ρ the mass density, $C_{\rm p}$ the heat capacity, Q a heat source (e.g., given by Joule losses) and \vec{n}_{Ω} the unit vector normal to $\partial\Omega$.

By multiplying (1) with a test function T', integration over the computational domain and partial integration, the weak problem is to find $T \in H^1(\Omega)$ such that

$$(\kappa \,\nabla \,T, \nabla \,T')_{\Omega} + (\rho \,C_{\mathbf{p}} \,\partial_t T, T')_{\Omega} = (Q, T')_{\Omega} \,\,\forall T' \in \mathrm{H}^1(\Omega),$$

This work has been sponsored by the Wolfgang Gentner Programme of the German Federal Ministry of Education and Research (grant no. 13E18CHA) and by the Graduate School CE within the Centre for Computational Engineering at Technische Universität Darmstadt.



Fig. 1. Top view: in the proposed approach, the thin insulation layer in an HTS solenoid (left) marked by a dashed line is collapsed into a surface (right).



Fig. 2. Top view: virtual discretization of the insulation layer Ω_i into slabs.

where $H^1(\Omega)$ is the space of square integrable functions with square integrable weak gradient in Ω and $(\vec{a}, \vec{a}')_{\Omega}$ denotes the volume integral of the scalar product of \vec{a} and \vec{a}' in Ω .

II. THIN SHELL APPROXIMATION

The insulation layer Ω_i is collapsed into a surface Γ in the middle of the original layer (see Fig. 1) [2]. In order to model the temperature difference between the two sides of Γ , two copies Γ^+ and Γ^- of Γ at the same position allowing independent temperatures T^- and T^+ that represent the temperature on the two sides of the shell are introduced. As a consequence, the weak formulation now contains an additional surface integral, i.e.,

$$(\kappa \nabla T, \nabla T')_{\Omega_{t}} + (\rho C_{p} \partial_{t} T, T')_{\Omega_{t}} + \langle [\vec{n} \cdot \kappa \nabla T], T' \rangle_{\Gamma} = (Q, T')_{\Omega_{t}} \quad \forall T' \in \mathrm{H}^{1}(\Omega),$$
(3)

where $\langle \vec{a}, \vec{a}' \rangle_{\Gamma}$ denotes the surface integral of the scalar product of \vec{a} and \vec{a}' over Γ , $[b] := b|_{\Gamma^+} - b|_{\Gamma^-}$ denotes the jump of b from Γ^- to Γ^+ and $\vec{n} = \vec{n}^+ = -\vec{n}^-$ is the unit vector normal to the thin shell (see Fig. 2). Following the ideas proposed in [2] for the computation of magnetic fields using a thin shell approximation, the surface terms are now used for a virtual discretization of the heat equation in Ω_i which is split into N slabs $\hat{\Omega}_i^{(k)} := \Gamma \times [w_{k-1}, w_k]$ (see Fig. 2) for k = 1, ..., N. Here, a local coordinate system $(\vec{u}, \vec{v}, \vec{w})$ is used with (\vec{u}, \vec{v}) oriented along the tangential and \vec{w} oriented along the normal direction of Γ . Then, we have

$$\langle [\vec{n} \cdot \kappa \nabla T], T' \rangle_{\Gamma}$$

= $(\kappa \nabla T, \nabla T')_{\hat{\Omega}_{i}} + (\rho C_{p} \partial_{t}T, T')_{\hat{\Omega}_{i}}$ (4)
= $\sum_{k=1}^{N} (\kappa \nabla T, \nabla T')_{\hat{\Omega}_{i}} + \sum_{k=1}^{N} (\rho C_{p} \partial_{t}T, T')_{\hat{\Omega}_{i}}.$

For example, using first-order Lagrange basis functions

$$N_{k-1}(w) = \frac{w_k - w}{w_k - w_{k-1}}$$
 and $N_k(w) = \frac{w - w_{k-1}}{w_k - w_{k-1}}$,

a one-dimensional discretization of T along the normal direction \vec{w} is assumed as

$$T|_{\hat{\Omega}_{i}^{(k)}}(u,v,w,t) = \sum_{j=k-1}^{k} T_{j}(u,v,t)N_{j}(w),$$

where $T_j := T|_{\Gamma_j}$. Using the same ansatz for the test function T' subsequently leads to a decomposition of the last line of (4) into surface integrals over Γ_k and one-dimensional (1D) finite element matrices along w. For example, it follows that

$$(\rho C_{\mathbf{p}} \partial_t T, T')_{\hat{\Omega}_{\mathbf{i}}} = \sum_{k=1}^{N} \sum_{j=k-1}^{k} \langle \partial_t T_j, T'_l \rangle_{\Gamma_j} \cdot M^{(k)}_{lj,C_{\mathbf{V}}}$$
(5)

for l = k - 1, k and the 1D FE mass matrix

$$M_{lj,C_{\mathbf{V}}}^{(k)} := \int_{w_{k-1}}^{w_k} \rho \, C_p N_l \, N_j \, \mathrm{d}w. \tag{6}$$

The remaining term in (4) yields similar results. These integrals can be evaluated without the need for a volumetric mesh representation of Ω_i while still allowing to consider multilayered domains Ω_i by increasing the number of slabs N.

III. NUMERICAL EXPERIMENTS

The thin shell formulation has been implemented in the open-source FE framework GetDP [3] relying on Gmsh [4] for mesh creation. As before mentioned, this work proposes to use the latter formulation for efficient 3D FE quench simulations of HTS tape solenoids avoiding the cumbersome meshing of thin layers. For illustration, the heat distribution in a pancake coil resulting from the diffusion of a thermal hot spot leading to localized Joule heating is shown in Fig. 3. Good agreement

between the results for a meshed insulation layer and the thin shell approach can be observed.

The proposed method will be compared to FE analysis with its counterpart with meshed insulation layers in terms of accuracy, efficiency and robustness. To enable comprehensive quench simulations, a weak coupling of the thermal thin shell approach and magnetic field computation will be discussed, in order to include Joule heating and the dependency of material properties (e.g., the critical temperature) on the magnetic field.



Fig. 3. 3D temperature distribution of diffusing hot spot in a small solenoid of four turns for meshed insulation layer (left) and thin shell insulation (right).

ACKNOWLEDGMENT

The authors would like to thank Bruno de Sousa Alves (formerly École Polytechnique de Montréal), Christophe Geuzaine, Julien Dular, Benoît Vanderheyden (all Université de Liège) and Nicolas Marsic (TU Darmstadt) for the fruitful discussions on simulation of superconductors.

REFERENCES

- J. Driesen, R. Belmans, and K. Hameyer, "Finite-element modeling of thermal contact resistances and insulation layers in electrical machines," *IEEE Transactions on Industry Applications*, vol. 37, no. 1, pp. 15–20, 2001.
- [2] B. de Sousa Alves, V. Lahtinen, M. Laforest, and F. Sirois, "Thin-shell approach for modeling superconducting tapes in the h-φ finite-element formulation," *Superconductor Science and Technology*, vol. 35, no. 2, p. 024 001, Dec. 2021.
- [3] P. Dular, C. Geuzaine, F. Henrotte, and W. Legros, "A general environment for the treatment of discrete problems and its application to the finite element method," *IEEE Transactions on Magnetics*, vol. 34, no. 5, pp. 3395–3398, Sep. 1998.
- [4] C. Geuzaine and J.-F. Remacle, "Gmsh: A 3-D finite element mesh generator with built-in pre- and postprocessing facilities," vol. 79, pp. 1309–1331, 2009.