



HAL
open science

End-to-end learning of dynamical systems with the Mori-Zwanzig formalism

Thibault Monsel, Lionel Mathelin, Onofrio Semeraro, Guillaume Charpiat

► **To cite this version:**

Thibault Monsel, Lionel Mathelin, Onofrio Semeraro, Guillaume Charpiat. End-to-end learning of dynamical systems with the Mori-Zwanzig formalism. CSE 2023 - SIAM Computational Science and Engineering, Feb 2023, Amsterdam, Netherlands. hal-04406551

HAL Id: hal-04406551

<https://hal.science/hal-04406551>

Submitted on 19 Jan 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

END-TO-END LEARNING OF DYNAMICAL SYSTEMS WITH THE MORI-ZWANZIG FORMALISM

T. MONSEL ¹, O. SEMERARO ¹, L. MATHELIN ¹, G. CHARPIAT ^{1,2}

¹LISN, Université de Paris-Saclay, 91400 Orsay, France

²INRIA, 91400 Saclay, France

March 6, 2023



- 1 Introduction
- 2 The Mori-Zwanzig (MZ) formalism
 - Derivation of the MZ equation
 - Modelling possibilities
 - Examples
- 3 Applying Delay Differential Equations to MZ

Introduction

Modelling dynamical systems into the age of DL

- Experimental data is often noisy, corrupted and does not account for the system's full state.
- Generally, partially observed states cannot reconstruct its own dynamics but ...
- ... With historical values of such a partial state, it can be done (Takens theorem).




Figure: Lorenz system




Figure: Delay coordinate embedding $h_t = [x_t, x_{t-\tau}, x_{t-2\tau}]$

Introduction

Modelling partially observed dynamical systems into the age of Deep Learning (DL)

- Latent variables enhance model expressivity but ...
- these black box models (RNN, LSTM ...) lack interpretability, robustness guarantees and insights into the structure of the dynamics.

$$\mathbf{h}_{t+1} = f_{\theta_t}(\mathbf{h}_t, \mathbf{x}_t)$$




Figure: Example of RNN

Introduction

Modelling dynamical systems into the age of Deep Learning (DL)

Neural Ordinary Differential Equations (NODEs)¹ is a **natural way** of modelling a dynamical system since NODE is a continuous equivalent ResNets (to be precise Leaky RNN):

$$\mathbf{x}_{t+1} = \mathbf{x}_t + f_{\theta}(\mathbf{x}_t, t)$$
$$\frac{d\mathbf{x}(t)}{dt} = f_{\theta}(\mathbf{x}(t), t)$$

More often than not :

- Experiments are done with the full state $\mathbf{x}(t)$.
- Partially observed states coupled with non physical latent variables to reconstruct the dynamics (i.e. Augmented NODEs², LSTM ...).

Ideally what we want :

- a DL framework with a principled sound structure.

Mori-Zwanzig (MZ) formalism provides a rigorously grounded theory for our needs.

¹R Chen et al. *Neural ordinary differential equations*. 2018.

²E. Dupont et al. *Augmented Neural ODEs*. 2019.

The Mori-Zwanzig Formalism

Coping with partially observed systems

- It allows to derive **exact** evolution equations for **coarse-grained quantities** of interest from high-dimensional systems.
- If we consider a nonlinear system evolving on a smooth manifold $\mathcal{S} = \mathbb{R}^n$.

$$\frac{dx}{dt} = F(x), \quad x(0) = x_0$$

- The system is seen through the lens of the observables; $\forall i, g_i : \mathcal{S} \rightarrow \mathbb{C}$, that obey³:

$$\mathcal{L}g_i(x) = F(x) \cdot \nabla g_i(x)$$

where \mathcal{L} is the Liouville operator

³Liouville operator Linked to the Koopman operator $\mathcal{K}(t,s) = e^{(t-s)\mathcal{L}}$

The Mori-Zwanzig Equation

Coping with partially observed systems

By concatenating the observables g_i , $\mathbf{g} = [g_0, \dots, g_n]$, we get the MZ equation^{4,5,6}:

$$\frac{\partial}{\partial t} \mathbf{g}(x, t) = \underbrace{M(\mathbf{g}(x, t))}_{\text{Markov term}} + \underbrace{F(x, t)}_{\text{Noise term}} - \underbrace{\int_0^t K(\mathbf{g}(x, t-s), s) ds}_{\text{Memory term}}$$

where

$$M(\mathbf{g}(x, t)) = e^{t\mathcal{L}} \mathcal{P} \mathcal{L} \mathbf{g}(x)$$

$$F(x, t) = e^{t\mathcal{Q}\mathcal{L}} \mathcal{Q} \mathcal{L} \mathbf{g}(x)$$

$$K(\mathbf{g}(x, t-s), s) = -e^{(t-s)\mathcal{L}} \mathcal{P} \mathcal{L} e^{s\mathcal{Q}\mathcal{L}} \mathcal{Q} \mathcal{L} \mathbf{g}(x)$$

with \mathcal{P} a projector operator and its orthogonal $\mathcal{Q} = \mathcal{I} - \mathcal{P}$

⁴Y. Zhu. *Mori-Zwanzig equation: Theory and Applications*. 2019.

⁵H. Mori. *A Continued-Fraction Representation of the Time-Correlation Functions*. 1965.

⁶R. Zwanzig. *Approximate Eigenfunctions of the Liouville Operator in Classical Many-Body Systems*. 1966.

The Mori-Zwanzig Equation

Coping with partially observed systems

Several ways are possible to cancel the noise term $F(x, t)$ in the MZ equation. With $F(x, t) = 0$, we get :

$$\frac{\partial}{\partial t} \mathbf{g}(x, t) = \underbrace{M(\mathbf{g}(x, t))}_{\text{Markov term}} - \underbrace{\int_0^t K(\mathbf{g}(x, t-s), s) ds}_{\mathbf{y}(x, t) = \text{Memory term}}$$

Additionally, we can rewrite the MZ equation as coupled PDEs⁷:

$$\begin{cases} \frac{\partial}{\partial t} \mathbf{g}(x, t) = M(\mathbf{g}(x, t)) + \mathbf{y}(x, t) \\ \frac{\partial}{\partial t} \mathbf{y}(x, t) = K(\mathbf{g}(x, t), 0) - \int_0^t \partial_2 K(\mathbf{g}(x, t-s), s) ds \end{cases}$$


On-going theoretical link of MZ with Deep Learning theory⁸.

⁷ ∂_2 refers to the partial derivative with respect to the second argument

⁸D. Venturi et al. *The Mori-Zwanzig formulation of deep learning*. 2022.

Modelling possibilities with MZ

An overview



Practical example of MZ

Linear systems

$$X'(t) = AX(t)$$

$$A = \begin{bmatrix} A_{rr} & A_{ru} \\ A_{ur} & A_{uu} \end{bmatrix}, \quad X = \begin{bmatrix} X_r \\ X_u \end{bmatrix}$$

$$\mathcal{P}A = A_{rr}, \quad \mathcal{Q}A = A_{uu}$$

The MZ equation applied to the resolved variables $X_r(t)$ gives

$$X_r'(t) = A_{rr}X_r(t) + A_{ru} \int_0^t e^{(t-s)A_{uu}} A_{ur} X_r(s) ds + \underbrace{A_{ru} e^{tA_{uu}} X_u(0)}_{X_u(0) := \mathbf{0}}$$

Practical example of MZ

Harmonic Oscillator

An harmonic oscillator dynamic is specified by

$$\ddot{x} + \frac{1}{\tau}\dot{x} + \omega_0^2 x = 0$$

than can be rewritten in matrix form as

$$A = \begin{bmatrix} 0 & 1 \\ -\omega_0^2 & -\frac{1}{\tau} \end{bmatrix} \quad X = \begin{bmatrix} x \\ \dot{x} \end{bmatrix}$$

If only the velocity $g = \dot{x}$ is observed then we get :

$$\begin{cases} \frac{dg(t)}{dt} = -\frac{1}{\tau}g(t) + y(t) \\ \frac{dy(t)}{dt} = -\omega_0^2 g(t) \end{cases}$$

Analytical

$$\begin{cases} \frac{dg(t)}{dt} = f_{\theta_1}(g(t), t) + y(t) \\ \frac{dy(t)}{dt} = f_{\theta_2}(g(t), t) \end{cases}$$

DL-based

Practical example of MZ

Harmonic Oscillator




Figure: Analytical derivation of quantities of interest \dot{x}




Figure: NODEs estimation of Markov and memory terms

Neural Network based DDEs

Applied to MZ equation

- Modelling partially observed dynamics with DDEs is a compromise between an ODE and IDE model for the memory term's dynamic $\mathbf{y}(x, t)$.
- Therefore, our MZ equation modelling is :

$$\begin{cases} \frac{\partial}{\partial t} \mathbf{g}(x, t) = M_{\theta}(\mathbf{g}(x, t)) + \mathbf{y}(x, t) \\ \frac{\partial}{\partial t} \mathbf{y}(x, t) = f_{\theta}(\mathbf{g}(x, t), \mathbf{g}(x, t - \tau_1), \dots, \mathbf{g}(x, t - \tau_n), t) \end{cases}$$

- A DDE approach can also be justified by Takens theorem.
- **So far, our work focuses on neural-network based DDE implementation since no tool is available. DDE solver was implemented with autodifferentiation software JAX.**

Neural Network based DDEs

Validating the DDE approach

Mackey-Glass system ($\beta = 0.25$, $n = 10$, $\tau = 10$ and $\gamma = 0.1$):

$$\dot{x}(t) = \beta \frac{x(t-\tau)}{1 + x(t-\tau)^n} - \gamma x(t)$$




Figure: DL model $\dot{x}(t) = f_{\theta}(x(t), x(t-\tau))$ testset predictions

Neural Network based DDEs

Practical Example : Van der Pol oscillator

- Stiff Van der Pol oscillator ($\mu = 2$) : $\ddot{x} + \mu(1 - x^2)\dot{x} + x = 0$
- If only the velocity $g = \dot{x}$ is observed then no obvious analytical form is given. Moreover, the current NODE approach for linear system fails




Figure: Results for the same MZ structure used in linear systems for Van der Pol

$$\begin{cases} \frac{dg(t)}{dt} = f_{\theta_1}(g(t), t) + y(t) \\ \frac{dy(t)}{dt} = f_{\theta_2}(g(t), t) \end{cases}$$

Conclusion

DL-based MZ formalism is underway for modelling partially observed systems because:

- Deep Learning based theory for MZ.
- Theoretically and empirically sound results for linear systems.
- Neural networks based DDEs are now possible with known delays.
- Tool developed with be used for MZ modelling.

References I

- [1] R Chen et al. *Neural ordinary differential equations*. 2018.
- [2] E. Dupont et al. *Augmented Neural ODEs*. 2019.
- [3] Y. Zhu. *Mori-Zwanzig equation: Theory and Applications*. 2019.
- [4] H. Mori. *A Continued-Fraction Representation of the Time-Correlation Functions*. 1965.
- [5] R. Zwanzig. *Approximate Eigenfunctions of the Liouville Operator in Classical Many-Body Systems*. 1966.
- [6] D. Venturi et al. *The Mori-Zwanzig formulation of deep learning*. 2022.